

Conditions on using HP regulatory approvals:

- A. Customer must ensure that its product (the “CUSTOMER Product”) is electrically identical to Broadcom’s reference designs. Customer acknowledges that any modifications to Broadcom’s reference designs may invalidate regulatory approvals in relation to the CUSTOMER Product, or may necessitate notifications to the relevant regulatory authorities.
- B. Customer is responsible for ensuring that antennas used with the product are of the same type, with same or lower gains as approved and providing antenna reports to Broadcom.
- C. Customer is responsible for regression testing to accommodate changes to Broadcom’s reference designs, new antennas, and portable RF exposure safety testing/approvals.
- D. Appropriate labels must be affixed to the CUSTOMER Product that comply with applicable regulations in all respects.
- E. The Broadcom radio is approved as a client/slave device; to ensure compliance with local regulations, the device should be set to the country domain in which the access point is installed.
- F. A user’s manual or instruction manual must be included with the customer product that contains the text as required by applicable law. Without limitation of the foregoing, an example (for illustration purposes only) of possible text to include is set forth below:

1. USA—Federal Communications Commission (FCC)

FCC COMPLIANCE STATEMENT:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

INFORMATION TO USER:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy. If not installed and used in accordance with the instructions, it may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by tuning the equipment off and on, the

OEM Installation Guidance Document
 For HP SDGOB-1506
 FCC ID: B94SDGOB1506; IC: 466D-SDGOB1506

user is encouraged to try and correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the distance between the equipment and the receiver.
- Connect the equipment to outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

System integrators must include the FCC ID on the end product.

No.	Antenna Manufacturer	Antenna Type	Model	Peak gain @ 2.4GHz (dBi)	Peak gain @ 5GHz (dBi)	Internal Reference
1	HP	802.11bgn WLAN Antenna	WLAN 2.4/5 GHz Antenna Data Sheet for Ulysses Family	2.5	3.5	Spectra trace antenna
2	Yageo/Phicomp	802.11bgn WLAN Antenna	ANTX300P002B24553	0.7	1.9	External antenna

FCC Radio-Frequency Exposure & Approval Conditions:

1. For Mobile applications, a separation distance of at least 20 cm must be maintained between the antenna of this device and all persons. This device must not be co-located or operating in conjunction with any other antenna or transmitter.
2. The antenna(s) used for this transmitter must not be collocated or operating in conjunction with any other antenna or transmitter within a host device, except in accordance with FCC multi-transmitter product procedures.
3. Only those antennas with same type and lesser gain filed under this FCC ID number can be used with this device.
4. The regulatory label on the final system must include the statement: "Contains FCC ID: B94SDGOB1506 "or using electronic labeling method as documented in KDB 784748.
5. The final system integrator must ensure there is no instruction provided in the user manual or customer documentation indicating how to install or remove the transmitter module except such device has implemented two-ways authentication between module and the host system.

OEM Installation Guidance Document
For HP SDGOB-1506
FCC ID: B94SDGOB1506; IC: 466D-SDGOB1506

6. The final host manual shall include the following regulatory statement:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy. If not installed and used in accordance with the instructions, it may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by tuning the equipment off and on, the user is encouraged to try and correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the distance between the equipment and the receiver.
- Connect the equipment to outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

2. Canada - Industry Canada (IC)

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

French:

Cet appareil est conforme avec Industrie Canada exempts de licence standard RSS (s). L'utilisation de ce dispositif est autorisée seulement aux conditions suivantes : (1) il ne doit pas produire de brouillage et (2) l'utilisateur du dispositif doit être prêt à accepter tout brouillage radioélectrique reçu, même si ce brouillage est susceptible de compromettre le fonctionnement du dispositif.

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

OEM Installation Guidance Document
 For HP SDGOB-1506
 FCC ID: B94SDGOB1506; IC: 466D-SDGOB1506

French:

Sous la réglementation d'Industrie Canada, ce transmetteur radio ne peut fonctionner en utilisant une antenne d'un type et un maximum (ou moins) gain approuvées pour l'émetteur par Industrie Canada. Pour réduire le risque d'interférence aux autres utilisateurs, le type d'antenne et son gain doivent être choisis de manière que la puissance isotrope rayonnée équivalente (PIRE) ne dépasse pas ce qui est nécessaire pour une communication réussie.

This radio transmitter, IC ID: 466D-SDGOB1506, has been approved by Industry Canada to operate with the onboard antenna or a detachable WLAN antenna with a maximum gain listed below. The required antenna impedance is 50 ohms.

French:

Cet émetteur radio, IC ID: 466D-SDGOB1506, a été approuvé par Industrie Canada pour fonctionner avec l'antenne intégrée ou une antenne amovible PIFA avec un gain maximum de ci-dessous. L'impédance d'antenne requise est de 50 ohms.

No.	Antenna Manufacturer	Antenna Type	Model	Peak gain @ 2.4GHz (dBi)	Peak gain @ 5GHz (dBi)	Internal Reference
1	HP	802.11bgn WLAN Antenna	WLAN 2.4/5 GHz Antenna Data Sheet for Ulysses Family	2.5	3.5	Spectra trace antenna
2	Yageo/ Phicomp	802.11bgn WLAN Antenna	ANTX300P002B24553	0.7	1.9	External antenna

Caution: Exposure to Radio Frequency Radiation.

To comply with RSS 102 RF exposure compliance requirements, for mobile configurations, a separation distance of at least 20 cm must be maintained between the antenna of this device and all persons. This device must not be co-located or operating in conjunction with any other antenna or transmitter.

Pour se conformer aux exigences de conformité 102 RSS RF exposition, pour des configurations mobiles, une distance de séparation d'au moins 20 cm doit être maintenue entre l'antenne de cet appareil et toutes les personnes. Cet appareil ne doit pas être co-localisés ou fonctionnant en conjonction avec une autre antenne ou transmetteur.

System integrators must include a label with “Contains IC: 466D-SDGOB1506” on the end product. Industry Canada user statements should be provided in both English and French, at the time each product is offered for sale or lease in Canada.

OEM Installation Guidance Document
For HP SDGOB-1506
FCC ID: B94SDGOB1506; IC: 466D-SDGOB1506

Les intégrateurs de systèmes doivent comporter une étiquette avec "Contient IC: 466D-SDGOB1506" sur le produit final. Comptes d'utilisateur d'Industrie Canada devraient être fournis en anglais et en français, au moment où chaque produit est offert à la vente ou la location au Canada.

As per RSS-247, Issue 1, Section 6.4(5):

Operation in the 5150-5250MHz is for indoor use only to reduce the potential for harmful interference to co-channel mobile satellite systems

Users should be advised that high-power radars are allocated as primary users (i.e. priority users) of the bands 5250-5350MHz and 5650-5850MHz and that these radars could cause interference and/or damage to LE-LAN devices.

French :

Comme par RSS-247, Issue 1, Section 6.4 (5):

Opération dans le 5150-5250MHz est pour usage intérieur seulement de réduire le risque d'interférences nuisibles à la co-canal systèmes mobiles par satellite

Utilisateurs estimé qu'il devrait être radars à haute puissance sont désignés comme utilisateurs principaux (c. utilisateurs prioritaires) des bandes 5250-5350MHz et 5650-5850MHz Ces radars et qui pourraient provoquer des interférences et / ou endommager les appareils LE-LAN.

3. Europe - EU Restrictions

This equipment needs to be marked with the **CE2155**  and can be used throughout the European community.

Operation in the 5150-5350MHz band is limited to indoor use.

Caution: Exposure to Radio Frequency Radiation.

To comply with RF exposure compliance requirements, for mobile configurations, a separation distance of at least 20 cm must be maintained between the antenna of this device and all persons.

Czech:

User's Manual in Czech language and a statement of conformity with Directive 1999/5/EC in Czech language must be enclosed to each product.

Italy:

For private use, a general authorisation is required if WAS/RLAN's are used outside own premises. For public use, a general authorisation is required

Note for system integrators:

- The module is tested to comply with the requirement of the R&TTE Directive. System integrators are responsible for compliance of the final device with the R&TTE Directive.
- Packaging: CE Marking must also be on the outer packaging of the product. The outer packaging must also provide an indication as to where the device is intended to be used and OR conversely, where there may be restrictions for use.

4. Taiwan - NCC Statement to be included in the user guide

Statement- For general products

低功率電波輻射性電機管理辦法

第十二條經型式認證合格之低功率射頻電機，非經許可，公司、商號或使用者均不得擅自變更頻率、加大功率或變更原設計之特性及功能。

第十四條低功率射頻電機之使用不得影響飛航安全及干擾合法通信；經發現有干擾現象時，應立即停用，並改善至無干擾時方得繼續使用。前項合法通信，指依電信規定作業之無線電信。低功率射頻電機須忍受合法通信或工業、科學及醫療用電波輻射性電機設備之干擾。

Translation:

Article 12

Without permission, any company, firm or user shall not alter the frequency, increase the power, or change the characteristics and functions of the original design of the certified lower power frequency electric machinery.

Article 14

The application of low power frequency electric machineries shall not affect the navigation safety nor interfere a legal communication, if an interference is found, the service will be suspended until improvement is made and the interference no longer exists.

The foregoing legal communication refers to the wireless telecommunication operated according to the telecommunications laws and regulations.

The low power frequency electric machinery should be able to tolerate the interference of the electric wave radiation electric machineries and equipments for legal communications or industrial and scientific applications.

Appendix:

模組認證合格標籤 (ID):

“ CCXXxxLPyyyZz ”

如果使用本模組之平台,無法在外部看見審驗合格標籤時,應在該平台的外部明顯標示

“內含射頻模組  CCXXxxLPyyyZz” .

5. Korea

Include the following statement either on the label or in the User Guide.

"당해 무선설비가 전파혼신 가능성이 있으므로 인명안전과 관련된 서비스는 할 수 없음"

6. Argentina

The current approval is in the name of Broadcom's local representative. It may be necessary to obtain regulatory approval in the name of the local distributor or importer. We suggest manufacturers check with their local distributors and importers in Argentina.

7. Brazil - Anatel

Before using Broadcom Anatel approvals,

1. PC- OEM must make arrangement for its local offices or distributors to provide maintenance, technical assistance or replace any faulty products sold in Brazil.
2. All warranty services will be provided by the distributors or PC-OEM sales support in Brazil. An official agreement stating warranty responsibilities must be signed and made available to Broadcom.

Interference statement to be included in the Users Guide

"Este equipamento opera em caráter secundário, isto é, não tem direito a proteção contra interferência prejudicial, mesmo de estações do mesmo tipo, e não pode causar interferência a sistemas operando em caráter primário."

Translation:

OEM Installation Guidance Document
For HP SDGOB-1506
FCC ID: B94SDGOB1506; IC: 466D-SDGOB1506

"This equipment operates in secondary character. It can be affected by harmful interference. However, it cannot cause interference to systems operating in primary character."

8. South Africa – ICASA

PC-OEMs must make arrangement for importers to supply spare parts and carry out repairs in South Africa.

9. Indonesia – POSTEL, Kenya – CCK, Nepal - NTA

PC-OEMs must make arrangement for importers to provide product warranty and after sales services.

10. Mexico

PC-OEMs must make arrangement for importers to provide User Manual in Spanish in Mexico.

The User Manual must feature the following mandatory statement:

“La operación de este equipo está sujeta a las siguientes dos condiciones: (1) es posible que este equipo o dispositivo no cause interferencia perjudicial y (2) este equipo o dispositivo debe aceptar cualquier interferencia, incluyendo la que pueda causar su operación no deseada.”

Translation:

The operation of this device is subject to the following two conditions:

- (1) this equipment or device must not cause harmful interference and
- (2) this equipment or device must accept any interference, including interference which could otherwise cause its undesired operation.

12. CB Certifications

PC-OEMs must provide User Guides in the language suitable for the countries when shipping products to countries listed in the CB reports.

13. Moldova- Labeling to be included

Proper Marking must be included on each certified unit shipping into Moldova,

14. Japan - MIC

Radio devices using 5.15-5.35GHz bands are restricted to indoor use only.