

## FCC 47 CFR MPE REPORT

DONGGUAN ALLLIKE ELECTRONIC CO., LTD

Bluetooth Rock Speakers

Model Number: ITSBO-513PS10

Additional Model: ITSBO-513P10, ITSBO-358PS10

FCC ID: BUQBR9091P10

Prepared for:	DONGGUAN ALLLIKE ELECTRONIC CO., LTD
	CHUANCHENG DEVELOPMENT DISTRICT MAYONG TOWN,
	DONGGUAN GUANGDONG, China
Prepared By:	EST Technology Co., Ltd.
	Chilingxiang, Qishantou, Santun, Houjie, Dongguan, Guangdong, China
	Tel: 86-769-83081888-808

Report Number:	ESTE-R1801040
Date of Test:	Dec. 26, 2017~Jan. 10, 2018
Date of Report:	Jan. 13, 2018

## Maximum Permissible Exposure

### 1、Applicable Standard

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure. In accordance with 47 CFR FCC Part 2 Subpart J, section 2.1091 this device has been defined as a mobile device whereby a distance of 0.2m normally can be maintained between the user and the device.

### (a)、Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f)*	6
30-300	61.4	0.163	1.0	6
300-1500			F/300	6
1500-10000			5	6

### (b)、Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500			F/1500	30
1500-10000			1.0	30

Note: f=frequency in MHz; \*Plane-wave equivalent power density

### 2、MPE Calculation Method

$$E \text{ (V/m)} = (30 * P * G) / (0.5 * d)$$

$$\text{Power Density: } Pd \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric Field (V/m)

P = Peak RF output Power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$Pd = (30 * P * G) / (377 * d^2)$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained

### 3、Conducted Power Result

Mode	Frequency (MHz)	Peak output power (dBm)	Peak output power (mW)	Target power ( dBm )	Antenna gain	
					(dBi)	(Linear)
GFSK	2402	-0.528	0.886	-1±1	0	1.000
	2441	-0.697	0.852	-1±1	0	1.000
	2480	-2.083	0.619	-3±1	0	1.000
8-DPSK	2402	-0.740	0.843	-1±1	0	1.000
	2441	-0.932	0.807	-1±1	0	1.000
	2480	-2.241	0.597	-3±1	0	1.000

#### 4、Calculated Result and Limit

Mode	Target power (dBm)	Antenna gain		Power Density (S) (mW /cm <sup>2</sup> )	Limited of Power Density (S) (mW /cm <sup>2</sup> )	Test Result
		(dBi)	(Linear)			
GFSK	0	0	1.000	<b>0.00020</b>	1	Compiles
8-DPSK	0	0	1.000	<b>0.00020</b>	1	Compiles