

Table 5-1: Conducted Spurious Emissions – VRM; 764.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1528.025	4.5	76.7	53.0	-23.7
2292.038	5.5	81.8	53.0	-28.8
3056.05	2.3	101.5	53.0	-48.5
3820.063	3	89.9	53.0	-36.9
4584.075	2.4	113.3	53.0	-60.3
5348.088	14.4	94.3	53.0	-41.3
6112.1	1	114.2	53.0	-61.2
6876.113	2.5	106.7	53.0	-53.7
7640.125	0.7	110.0	53.0	-57.0

Table 5-2: Conducted Spurious Emissions – VRM; 775.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1551.975	3.5	78.3	53.0	-25.3
2327.963	5.2	79.4	53.0	-26.4
3103.95	0.5	104.9	53.0	-51.9
3879.938	0.8	92.6	53.0	-39.6
4655.925	2.5	106.3	53.0	-53.3
5431.913	11.8	96.4	53.0	-43.4
6207.9	0.3	105.6	53.0	-52.6
6983.888	1.5	105.1	53.0	-52.1
7759.875	2.9	103.8	53.0	-50.8

Table 5-3: Conducted Spurious Emissions – VRM; 794.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1588.025	5.7	75.7	52.9	-22.8
2382.038	0.3	81.5	52.9	-28.6
3176.05	1.0	107.3	52.9	-54.4
3970.063	0.5	92.8	52.9	-39.9
4764.075	4.8	104.4	52.9	-51.5
5558.088	4.5	104.6	52.9	-51.7
6352.1	1.1	108.2	52.9	-55.3
7146.113	2.0	105.7	52.9	-52.8
7940.125	4.5	101.7	52.9	-48.8

Table 5-4: Conducted Spurious Emissions – VRM; 805.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1611.975	1.9	77.8	53.0	-24.8
2417.963	6.4	79.2	53.0	-26.2
3223.95	3.8	104.5	53.0	-51.5
4029.938	1.7	97.2	53.0	-44.2
4835.925	6	102.7	53.0	-49.7
5641.913	37.6	71.6	53.0	-18.6
6447.9	5.7	103.3	53.0	-50.3
7253.888	10.3	96.8	53.0	-43.8
8059.875	4.1	102.2	53.0	-49.2

Table 5-5: Conducted Spurious Emissions – VRM; 806.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1612.025	1.9	78.4	53.0	-25.4
2418.038	6.4	79.0	53.0	-26.0
3224.05	3.8	104.8	53.0	-51.8
4030.063	1.7	96.9	53.0	-43.9
4836.075	6	102.7	53.0	-49.7
5642.088	37.6	71.2	53.0	-18.2
6448.1	5.7	103.1	53.0	-50.1
7254.113	10.3	95.9	53.0	-42.9
8060.125	4.1	102.4	53.0	-49.4

Table 5-6: Conducted Spurious Emissions – VRM; 823.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1647.975	2.9	80.1	53.2	-26.9
2471.963	2.4	87.3	53.2	-34.1
3295.95	4.4	104.2	53.2	-51.0
4119.938	2.2	99.3	53.2	-46.1
4943.925	2.8	105.6	53.2	-52.4
5767.913	7.6	101.7	53.2	-48.5
6591.9	5.8	100.6	53.2	-47.4
7415.888	4.1	99.3	53.2	-46.1
8239.875	7.8	98.8	53.2	-45.6

Table 5-7: Conducted Spurious Emissions – VRM; 851.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1702.025	2.7	78.7	53.0	-25.6
2553.038	4.3	78.6	53.0	-25.5
3404.05	2.9	105.7	53.0	-52.6
4255.063	2	100.4	53.0	-47.3
5106.075	3.1	91.8	53.0	-38.7
5957.088	8.8	92.0	53.0	-38.9
6808.1	29.8	68.4	53.0	-15.3
7659.113	4.8	96.6	53.0	-43.5
8510.125	16.2	79.7	53.0	-26.6

Table 5-8: Conducted Spurious Emissions – VRM; 868.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1737.975	5.3	77.2	53.0	-24.1
2606.963	5.6	72.3	53.0	-19.2
3475.95	3.4	100.0	53.0	-46.9
4344.938	3.2	95.5	53.0	-42.4
5213.925	3	105.3	53.0	-52.2
6082.913	7.7	99.2	53.0	-46.1
6951.9	14.3	90.8	53.0	-37.7
7820.888	4.3	100.8	53.0	-47.7
8689.875	24.1	77.3	53.0	-24.2

Table 5-9: Conducted Spurious Emissions – VRM; 794.0125 MHz; OTP mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1588.025	5.7	76.4	52.9	-23.5
2382.038	0.3	84.8	52.9	-31.9
3176.05	1.0	107.0	52.9	-54.1
3970.063	0.5	93.6	52.9	-40.7
4764.075	4.8	104.1	52.9	-51.2
5558.088	4.5	104.7	52.9	-51.8
6352.1	1.1	108.1	52.9	-55.2
7146.113	2.0	105.8	52.9	-52.9
7940.125	4.5	102.3	52.9	-49.4

Table 5-10: Conducted Spurious Emissions – VRM; 805.9875 MHZ; OTP mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1611.975	1.9	78.7	52.8	-25.9
2417.963	6.4	79.6	52.8	-26.8
3223.95	3.8	104.7	52.8	-51.9
4029.938	1.7	98.0	52.8	-45.2
4835.925	6	103.1	52.8	-50.3
5641.913	37.6	71.1	52.8	-18.3
6447.9	5.7	103.6	52.8	-50.8
7253.888	10.3	94.1	52.8	-41.3
8059.875	4.1	99.6	52.8	-46.8

Table 5-11: Conducted Spurious Emissions – VRM; 806.0125 MHZ; OTP mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1612.025	1.9	78.1	53.3	-24.8
2418.038	6.4	79.9	53.3	-26.6
3224.05	3.8	104.4	53.3	-51.1
4030.063	1.7	96.0	53.3	-42.7
4836.075	6	103.3	53.3	-50.0
5642.088	37.6	71.4	53.3	-18.1
6448.1	5.7	103.9	53.3	-50.6
7254.113	10.3	96.9	53.3	-43.7
8060.125	4.1	102.9	53.3	-49.6

Table 5-12: Conducted Spurious Emissions – VRM; 823.9875 MHZ; OTP mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1647.975	2.9	78.6	52.9	-25.7
2471.963	2.4	85.4	52.9	-32.5
3295.95	4.4	104.3	52.9	-51.4
4119.938	2.2	97.7	52.9	-44.8
4943.925	2.8	106.2	52.9	-53.3
5767.913	7.6	101.6	52.9	-48.7
6591.9	5.8	101.3	52.9	-48.4
7415.888	4.1	97.3	52.9	-44.4
8239.875	7.8	96.0	52.9	-43.1

Table 5-13: Conducted Spurious Emissions – VRM; 806.0125 MHz; EDACS mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1612.025	1.9	78.1	53.2	-24.9
2418.038	6.4	78.1	53.2	-24.9
3224.05	3.8	105.0	53.2	-51.8
4030.063	1.7	95.7	53.2	-42.5
4836.075	6	103.0	53.2	-49.8
5642.088	37.6	71.2	53.2	-18.0
6448.1	5.7	103.3	53.2	-50.1
7254.113	10.3	97.2	53.2	-44.0
8060.125	4.1	102.6	53.2	-49.4

Table 5-14: Conducted Spurious Emissions – VRM; 823.9875 MHz; EDACS mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1647.975	2.9	78.9	53.1	-25.8
2471.963	2.4	85.9	53.1	-32.8
3295.95	4.4	104.2	53.1	-51.1
4119.938	2.2	98.0	53.1	-44.9
4943.925	2.8	106.2	53.1	-53.1
5767.913	7.6	101.5	53.1	-48.4
6591.9	5.8	101.7	53.1	-48.6
7415.888	4.1	98.1	53.1	-45.0
8239.875	7.8	99.6	53.1	-46.5

Table 5-15: Conducted Spurious Emissions – VRM; 851.0125 MHz; EDACS mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1702.025	2.7	78.7	53.0	-25.7
2553.038	4.3	78.2	53.0	-25.2
3404.05	2.9	105.9	53.0	-52.9
4255.063	2	99.4	53.0	-46.4
5106.075	3.1	91.1	53.0	-38.1
5957.088	8.8	90.5	53.0	-37.5
6808.1	29.8	67.3	53.0	-14.3
7659.113	4.8	96.5	53.0	-43.5
8510.125	16.2	79.8	53.0	-26.8

Table 5-16: Conducted Spurious Emissions – VRM; 868.9875 MHz; EDACS mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1737.975	5.3	77.4	53.0	-24.4
2606.963	5.6	71.8	53.0	-18.8
3475.95	3.4	99.4	53.0	-46.4
4344.938	3.2	94.7	53.0	-41.7
5213.925	3	105.9	53.0	-52.9
6082.913	7.7	98.1	53.0	-45.1
6951.9	14.3	89.3	53.0	-36.3
7820.888	4.3	101.4	53.0	-48.4
8689.875	24.1	75.8	53.0	-22.8

Table 5-17: Conducted Spurious Emissions – VRM; 764.0125 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1528.025	4.5	77.8	53.0	-24.8
2292.038	5.5	83.3	53.0	-30.3
3056.05	2.3	101.7	53.0	-48.7
3820.063	3	89.9	53.0	-36.9
4584.075	2.4	106.6	53.0	-53.6
5348.088	14.4	93.6	53.0	-40.6
6112.1	1	107.9	53.0	-54.9
6876.113	2.5	104.3	53.0	-51.3
7640.125	0.7	106.0	53.0	-53.0

Table 5-18: Conducted Spurious Emissions – VRM; 775.9875 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1551.975	3.5	79.9	53.0	-26.9
2327.963	5.2	78.0	53.0	-25.0
3103.95	0.5	106.3	53.0	-53.3
3879.938	0.8	94.1	53.0	-41.1
4655.925	2.5	107.3	53.0	-54.3
5431.913	11.8	96.6	53.0	-43.6
6207.9	0.3	106.1	53.0	-53.1
6983.888	1.5	105.5	53.0	-52.5
7759.875	2.9	104.4	53.0	-51.4

Table 5-19: Conducted Spurious Emissions – VRM; 794.0125 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1588.025	5.7	76.2	52.8	-23.4
2382.038	0.3	82.1	52.8	-29.3
3176.05	1.0	106.9	52.8	-54.1
3970.063	0.5	93.0	52.8	-40.2
4764.075	4.8	104.2	52.8	-51.4
5558.088	4.5	104.7	52.8	-51.9
6352.1	1.1	107.9	52.8	-55.1
7146.113	2.0	104.8	52.8	-52.0
7940.125	4.5	101.7	52.8	-48.9

Table 5-20: Conducted Spurious Emissions – VRM; 805.9875 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1611.975	1.9	78.8	52.9	-25.9
2417.963	6.4	76.4	52.9	-23.5
3223.95	3.8	104.5	52.9	-51.6
4029.938	1.7	96.7	52.9	-43.8
4835.925	6	102.9	52.9	-50.0
5641.913	37.6	71.3	52.9	-18.4
6447.9	5.7	102.9	52.9	-50.0
7253.888	10.3	97.1	52.9	-44.2
8059.875	4.1	102.8	52.9	-49.9

Table 5-21: Conducted Spurious Emissions – VRM; 806.0125 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1612.025	1.9	78.0	53.2	-24.8
2418.038	6.4	76.3	53.2	-23.1
3224.05	3.8	104.7	53.2	-51.5
4030.063	1.7	95.9	53.2	-42.7
4836.075	6	103.2	53.2	-50.0
5642.088	37.6	71.5	53.2	-18.3
6448.1	5.7	103.7	53.2	-50.5
7254.113	10.3	96.7	53.2	-43.5
8060.125	4.1	100.6	53.2	-47.4

Table 5-22: Conducted Spurious Emissions – VRM; 823.9875 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1647.975	2.9	78.8	53.0	-25.7
2471.963	2.4	83.7	53.0	-30.6
3295.95	4.4	104.0	53.0	-50.9
4119.938	2.2	98.3	53.0	-45.2
4943.925	2.8	106.3	53.0	-53.2
5767.913	7.6	102.0	53.0	-48.9
6591.9	5.8	101.7	53.0	-48.6
7415.888	4.1	97.8	53.0	-44.7
8239.875	7.8	99.1	53.0	-46.0

Table 5-23: Conducted Spurious Emissions – VRM; 851.0125 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1702.025	2.7	78.9	53.0	-25.9
2553.038	4.3	77.0	53.0	-24.0
3404.05	2.9	105.6	53.0	-52.6
4255.063	2	99.1	53.0	-46.1
5106.075	3.1	92.1	53.0	-39.1
5957.088	8.8	91.6	53.0	-38.6
6808.1	29.8	66.8	53.0	-13.8
7659.113	4.8	96.0	53.0	-43.0
8510.125	16.2	79.1	53.0	-26.1

Table 5-24: Conducted Spurious Emissions – VRM; 868.9875 MHz; OCF mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1737.975	5.3	77.3	53.0	-24.3
2606.963	5.6	71.7	53.0	-18.7
3475.95	3.4	99.7	53.0	-46.7
4344.938	3.2	94.6	53.0	-41.6
5213.925	3	103.2	53.0	-50.2
6082.913	7.7	98.7	53.0	-45.7
6951.9	14.3	89.4	53.0	-36.4
7820.888	4.3	98.8	53.0	-45.8
8689.875	24.1	76.0	53.0	-23.0

Table 5-25: Conducted Spurious Emissions – VRB; 764.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1528.025	4.5	81.3	47.9	-33.4
2292.038	5.5	89.0	47.9	-41.1
3056.05	2.3	101.5	47.9	-53.6
3820.063	3	97.8	47.9	-49.9
4584.075	2.4	101.6	47.9	-53.7
5348.088	14.4	89.6	47.9	-41.7
6112.1	1	103.0	47.9	-55.1
6876.113	2.5	99.8	47.9	-51.9
7640.125	0.7	101.2	47.9	-53.3

Table 5-26: Conducted Spurious Emissions – VRB; 775.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1551.975	3.5	84.2	47.9	-36.3
2327.963	5.2	86.1	47.9	-38.2
3103.95	0.5	103.1	47.9	-55.2
3879.938	0.8	100.5	47.9	-52.6
4655.925	2.5	101.6	47.9	-53.7
5431.913	11.8	92.3	47.9	-44.4
6207.9	0.3	103.7	47.9	-55.8
6983.888	1.5	101.0	47.9	-53.1
7759.875	2.9	99.5	47.9	-51.6

Table 5-27: Conducted Spurious Emissions – VRB; 851.0125 MHz; P25 mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1702.025	2.7	83.6	47.6	-36.0
2553.038	4.3	82.7	47.6	-35.1
3404.05	2.9	101.2	47.6	-53.6
4255.063	2	101.8	47.6	-54.2
5106.075	3.1	100.8	47.6	-53.2
5957.088	8.8	94.7	47.6	-47.1
6808.1	29.8	72.0	47.6	-24.4
7659.113	4.8	95.2	47.6	-47.6
8510.125	16.2	85.3	47.6	-37.7

Table 5-28: Conducted Spurious Emissions – VRB; 868.9875 MHz; P25 mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1737.975	5.3	81.9	47.8	-34.1
2606.963	5.6	77.2	47.8	-29.5
3475.95	3.4	100.4	47.8	-52.7
4344.938	3.2	99.6	47.8	-51.9
5213.925	3	100.5	47.8	-52.8
6082.913	7.7	96.0	47.8	-48.3
6951.9	14.3	87.3	47.8	-39.6
7820.888	4.3	97.5	47.8	-49.8
8689.875	24.1	77.3	47.8	-29.6

Table 5-29: Conducted Spurious Emissions – VRB; 764.0125 MHz; OTP mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1528.025	4.5	82.4	47.6	-34.7
2292.038	5.5	89.2	47.6	-41.5
3056.05	2.3	101.3	47.6	-53.6
3820.063	3	98.6	47.6	-50.9
4584.075	2.4	101.4	47.6	-53.7
5348.088	14.4	89.2	47.6	-41.5
6112.1	1	103.0	47.6	-55.3
6876.113	2.5	99.8	47.6	-52.1
7640.125	0.7	101.4	47.6	-53.7

Table 5-30: Conducted Spurious Emissions – VRB; 775.9875 MHz; OTP mode; High Power

Limit = $43 + 10 \log(47.1) = 60.1$ dBc

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1551.975	3.5	84.1	47.6	-36.5
2327.963	5.2	87.2	47.6	-39.6
3103.95	0.5	103.4	47.6	-55.8
3879.938	0.8	101.1	47.6	-53.5
4655.925	2.5	101.4	47.6	-53.8
5431.913	11.8	92.0	47.6	-44.4
6207.9	0.3	103.4	47.6	-55.8
6983.888	1.5	100.5	47.6	-52.9
7759.875	2.9	98.9	47.6	-51.3

Table 5-31: Conducted Spurious Emissions – VRB; 851.0125 MHZ; OTP mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1702.025	2.7	83.7	47.8	-35.9
2553.038	4.3	82.1	47.8	-34.3
3404.05	2.9	101.1	47.8	-53.3
4255.063	2	102.1	47.8	-54.3
5106.075	3.1	100.9	47.8	-53.1
5957.088	8.8	95.3	47.8	-47.5
6808.1	29.8	72.3	47.8	-24.5
7659.113	4.8	96.8	47.8	-49.0
8510.125	16.2	85.6	47.8	-37.8

Table 5-32: Conducted Spurious Emissions – VRB; 868.9875 MHZ; OTP mode; High Power

Limit = $43 + 10 \log (47.1) = 60.1 \text{ dBc}$

Frequency (MHz)	Notch/cable loss (dB)	Level (dBc)	Limit (dBc)	Margin(dB)
1737.975	5.3	81.9	47.9	-34.0
2606.963	5.6	76.9	47.9	-29.0
3475.95	3.4	100.7	47.9	-52.8
4344.938	3.2	99.9	47.9	-52.0
5213.925	3	101.0	47.9	-53.1
6082.913	7.7	96.0	47.9	-48.1
6951.9	14.3	88.2	47.9	-40.3
7820.888	4.3	96.9	47.9	-49.0
8689.875	24.1	77.7	47.9	-29.8

Table 5-33: Test Equipment for Testing Conducted Spurious Emissions

RTL Asset #	Manufacturer	Model	Part Type	Serial Number	Calibration Due
901215	Hewlett Packard	8596EM	EMC Analyzer (9 kHz - 12.8 GHz)	3826A00144	10/16/07
901396	MCE Weinschel	48-40-34	Attenuator, 40 dB, DC-18 GHz, 100 W	93453	1/13/09
901424	Insulated Wire Inc.	KPS-1503-360-KPS	RF cable 36"	NA	1/23/07

Test Personnel:

Daniel Biggs		January 4, 2007
Test Technician/Engineer	Signature	Date Of Test