



A D T

# RF EXPOSURE REPORT

**REPORT NO.:** SA121002C09

**MODEL NO.:** BTD 800 USB

**FCC ID:** DMOCBBSKE

**RECEIVED:** Oct. 02, 2012

**TESTED:** Oct. 15 ~ Oct. 22, 2012

**ISSUED:** Oct. 24, 2012

**APPLICANT:** Sennheiser Electronic Corp (NY)

**ADDRESS:** 1 Enterprise Drive Old Lyme, Connecticut 06371  
United States

**ISSUED BY:** Bureau Veritas Consumer Products Services  
(H.K.) Ltd., Taoyuan Branch

**LAB ADDRESS:** No. 47, 14th Ling, Chia Pau Vil., Lin Kou Dist.,  
New Taipei City, Taiwan, R.O.C.

**TEST LOCATION:** No. 19, Hwa Ya 2nd Rd, Wen Hwa Tsuen, Kwei  
Shan Hsiang, Taoyuan Hsien 333, Taiwan, R.O.C.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification.

## Table of Contents

|                                        |   |
|----------------------------------------|---|
| RELEASE CONTROL RECORD .....           | 3 |
| 1. CERTIFICATION .....                 | 4 |
| 2. EVALUATION RESULT .....             | 5 |
| 3. SAR TEST EXCLUSION THRESHOLDS ..... | 6 |
| 4. CONCLUSION .....                    | 6 |



A D T

## RELEASE CONTROL RECORD

| ISSUE NO.   | REASON FOR CHANGE | DATE ISSUED   |
|-------------|-------------------|---------------|
| SA121002C09 | Original release. | Oct. 24, 2012 |

## 1. CERTIFICATION

**PRODUCT:** Bluetooth USB dongle  
**MODEL NO.:** BTD 800 USB  
**BRAND:** SENNHEISER  
**APPLICANT:** Sennheiser Electronic Corp (NY)  
**TESTED:** Oct. 15 ~ Oct. 22, 2012  
**TEST SAMPLE:** ENGINEERING SAMPLE  
**STANDARDS:** **FCC Part 2 (Section 2.1093)**  
**FCC OET Bulletin 65, Supplement C (01-01)**  
IEEE C95.1

The above equipment (model: BTD 800 USB) has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

**PREPARED BY :** Sun Li , **DATE :** Oct. 24, 2012  
Suntee Liu / Specialist

**APPROVED BY :** Ken Liu , **DATE :** Oct. 24, 2012  
Ken Liu / Manager

## 2. EVALUATION RESULT

### Following FCC KDB 447498 D01 “General SAR test exclusion guidance”

The corresponding SAR Exclusion Threshold condition, listed below:

- 1) The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances  $\leq 50$  mm are determined by:  

$$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0 \text{ for 1-g SAR and } \leq 7.5 \text{ for 10-g extremity SAR, 16 where}$$
  - $f(\text{GHz})$  is the RF channel transmit frequency in GHz.
  - Power and distance are rounded to the nearest mW and mm before calculation.
  - The result is rounded to one decimal place for comparison. The test exclusions are applicable only when the minimum test separation distance is  $\leq 50$  mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is  $< 5$  mm, a distance of 5 mm is applied to determine SAR test exclusion.
- 2) At 100 MHz to 6 GHz and for test separation distances  $> 50$  mm, the SAR test exclusion threshold is determined according to the following:
  - a) [Threshold at 50 mm in step 1) + (test separation distance - 50mm) · (  $f(\text{MHz})/150$ )] mW, at 100MHz to 1500 MHz
  - b) [Threshold at 50 mm in step 1) + (test separation distance - 50 mm) · 10] mW at  $> 1500$  MHz and  $\leq 6$  GHz
- 3) At frequencies below 100 MHz, the following may be considered for SAR test exclusion.
  - a) The threshold at the corresponding test separation distance at 100 MHz in step 2) is multiplied by  $[1 + \log(100/f(\text{MHz}))]$  for test separation distances  $> 50$  mm and  $< 200$  mm.
  - b) The threshold determined by the equation in a) for 50 mm and 100 MHz is multiplied by  $\frac{1}{2}$  for test separation distances  $\leq 50$  mm.
  - c) SAR measurement procedures are not established below 100 MHz. When SAR test exclusion cannot be applied, a KDB inquiry is required to determine SAR evaluation requirements for any test results to be acceptable.

### 3. SAR TEST EXCLUSION THRESHOLDS

Maximum measured transmitter power:

| Frequency (GHz)  | Max. Power (mW) | Min. test separation distance (mm) | SAR test exclusion calculation value <sup>(NOTE 2)</sup> | 1-g extremity SAR test exclusion thresholds | Result |
|------------------|-----------------|------------------------------------|----------------------------------------------------------|---------------------------------------------|--------|
| Bluetooth EDR    | 9.594           | 5                                  | 2.973                                                    | 3                                           | Pass   |
| Bluetooth LE 4.0 | 7.870           | 5                                  | 2.438                                                    | 3                                           | Pass   |

**NOTE:** 1. The antenna type is printed antenna with -1.33dBi gain.  
2. Calculate SAR test exclusion thresholds from condition “1” formulas.

### 4. CONCLUSION

Since Source-base time average power is below SAR test exclusion power thresholds, the SAR evaluation is not required.