



RF EXPOSURE REPORT

REPORT NO.: SA940802A11

MODEL NO.: VGP-BMS30

ACCORDING: FCC Guidelines for Human Exposure
IEEE C95.1

APPLICANT : PRIMAX ELECTRONICS LTD.

ADDRESS : No. 669, Ruey Kuang Road, Neihu, Taipei, Taiwan.
R.O.C.

ISSUED BY : Advance Data Technology Corporation

LAB ADDRESS : No. 47, 14th Ling, Chia Pau Tsuen, Lin Kou Hsiang
244, Taipei Hsien, Taiwan, R.O.C.



RF Exposure Measurement

1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

| Frequency Range (MHz) | Electric Field Strength (V/m) | Magnetic Field Strength (A/m) | Power Density (mW/cm ²) | Average Time (minutes) |
|---|-------------------------------|-------------------------------|-------------------------------------|------------------------|
| (A)Limits For Occupational / Control Exposures | | | | |
| 300-1500 | ... | ... | F/300 | 6 |
| 1500-100,000 | ... | ... | 5 | 6 |
| (B)Limits For General Population / Uncontrolled Exposure | | | | |
| 300-1500 | ... | ... | F/1500 | 6 |
| 1500-100,000 | ... | ... | 1.0 | 30 |

F = Frequency in MHz



3. Friis Formula

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm

If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref.: David K. Cheng, *Field and Wave Electromagnetics*, Second Edition,
Page 640, Eq. (11-133).

4. EUT Operating condition

The software provided by manufacturer enabled the EUT to transmit data at lowest, middle and highest channel individually.



5. Conclusion

No Evaluation Required if power is below this threshold:

| F(GHz) | | mW |
|--------|-------|-------|
| Low | 2.402 | 24.58 |
| High | 2.480 | |

Maximum measured transmitter power:

| | Pout (dBm) | Pout (mW) |
|-----------------|------------|-----------|
| Conducted Power | 2.74 | 1.879 |
| EIRP Power | -0.30 | 0.933 |

***Note:** The antenna is Inverted-F antenna with -3.04 dBi gain

Threshold for no SAR evaluation is 24.58mW

Transmitter power is 1.879mW

Conclusion: No SAR evaluation required since Transmitter Pout is below FCC threshold