

---

## FCC 47 CFR MPE REPORT

Guangzhou Panyu Juda Car Audio Equipment Co.,Ltd.

BLUETOOTH SPEAKER

Model Number: Sound Piece

FCC ID: ESX-BL5602

Prepared for : Guangzhou Panyu Juda Car Audio Equipment Co.,Ltd.  
Vtrek Dewei Industrial Garden, Shibei Industrial Road, Dashi  
Town, Panyu Borough, Guangzhou City , Guangdong Province,  
China

Prepared By : EST Technology Co., Ltd.  
Santun(guantai Road), Houjie Town, DongGuan City,  
GuangDong, China.

Tel: 86-769-83081888-808

Report Number: ESTE-R1508057  
Date of Test : August 13,2015~ August 31, 2015  
Date of Report : September 01, 2015

## Maximum Permissible Exposure

### 1、Applicable Standard

Systems operating under the provisions of this section shall be operated in a manner that ensures that the public is not exposed to radio frequency energy level in excess limit for maximum permissible exposure. In accordance with 47 CFR FCC Part 2 Subpart J, section 2.1091 this device has been defined as a mobile device whereby a distance of 0.2m normally can be maintained between the user and the device.

### (a)、Limits for Occupational / Controlled Exposure

Frequency Range (MHz)	Electric Field Strength E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-3.0	614	1.63	(100)*	6
3.0-30	1842/f	4.89/f	(900/f)*	6
30-300	61.4	0.163	1.0	6
300-1500			F/300	6
1500-10000			5	6

### (b)、Limits for General Population / Uncontrolled Exposure

Frequency Range (MHz)	Electric Field Strength E) (V/m)	Magnetic Field Strength (H) (A/m)	Power Density (S) (mW/cm <sup>2</sup> )	Averaging Times   E   2 ,   H   2 or S (minutes)
0.3-1.34	614	1.63	(100)*	30
1.34-30	824/f	2.19/f	(180/f)*	30
30-300	27.5	0.073	0.2	30
300-1500			F/1500	30
1500-10000			1.0	30

Note: f=frequency in MHz; \*Plane-wave equivalent power density

### 2、MPE Calculation Method

$$E \text{ (V/m)} = (30 * P * G) / 0.5/d \quad \text{Power Density: } Pd \text{ (W/m}^2\text{)} = E^2 / 377$$

E = Electric Field (V/m)

P = Peak RF output Power (W)

G = EUT Antenna numeric gain (numeric)

d = Separation distance between radiator and human body (m)

The formula can be changed to

$$Pd = (30 * P * G) / (377 * d^2)$$

From the peak EUT RF output power, the minimum mobile separation distance, d=0.2m, as well as the gain of the used antenna, the RF power density can be obtained



### 3、Calculated Result and Limit

Model	Frequency (MHz)	Peak output power (dBm)	Peak output power (mW)	Antenna gain		Target power ( dBm )	Power Density (S) (mW/cm2)	Limited of Power Density (S) (mW/cm2)	Test Result
				(dBi)	(Linear)				
BT 4.0-BLE	2402	3.80	2.400	0	1	<b>4±1</b>	<b>0.00063</b>	1	Compiles
	2440	4.32	2.704	0	1	<b>4±1</b>	<b>0.00063</b>	1	Compiles
GFSK	2480	4.88	3.076	0	1	<b>4±1</b>	<b>0.00063</b>	1	Compiles

