

TABLE OF CONTENTS LIST

APPLICANT: KA WAH MANUFACTORY LTD.

FCC ID: F5J604225T

TEST REPORT CONTAINING:

PAGE 1.....TEST PROCEDURE  
PAGE 2.....TEST PROCEDURE CONTD. & CIRCUIT DESCRIPTION  
PAGE 3.....RADIATION INTERFERENCE TEST DATA  
PAGE 4.....OCCUPIED BANDWIDTH TEST DATA

EXHIBITS CONTAINING:

EXHIBIT 1.....POWER OF ATTORNEY LETTER  
EXHIBIT 2.....BLOCK DIAGRAM  
EXHIBIT 3.....SCHEMATIC  
EXHIBIT 4.....PARTS LIST  
EXHIBIT 5A-5B.....INSTRUCTION MANUAL  
EXHIBIT 6.....SAMPLE OF FCC ID LABEL  
EXHIBIT 7.....LOCATION OF FCC ID LABEL  
EXHIBIT 8.....EXTERNAL PHOTO - FRONT VIEW  
EXHIBIT 9.....EXTERNAL PHOTO - REAR VIEW  
EXHIBIT 10.....INTERNAL PHOTO - COMPONENT SIDE  
EXHIBIT 11.....INTERNAL PHOTO - COPPER SIDE  
EXHIBIT 12.....OCCUPIED BANDWIDTH PLOT

APPLICANT: KA WAH MANUFACTORY LTD.

FCC ID: F5J604225T

REPORT #: F:\CUS\K\KAWAH\KAW166H9.RPT

PAGE: TABLE OF CONTENTS LIST

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T

#### TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B - Opt 462, w/ preselector 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B - OPT H02 Cal. 6/26/98
2. Signal Generator, Hewlett Packard 8640B, cal. 10/1/98
3. Eaton Biconical Antenna Model 94455-1  
20-200 MHz Serial No. 0997 Cal. 10/30/98
4. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA-30 10/31/98
5. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 10/30/98
6. Electro-Metric Antennas Model TDA-30/1-4, Cal. 10/15/98
7. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. Cal. 11/19/98
8. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. Cal. 11/19/98
9. Special low loss cable was used above 1 GHz
10. Tenney Temperature Chamber

#### TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution bandwidth was 100KHz and the video bandwidth was 300KHz. The ambient temperature of the UUT was 80oC with a humidity of 76%.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz)	METER READING + ACF = FS
33	20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T  
REPORT #: F:\CUS\K\KAWAH\KAW166H9.RPT  
PAGE #: 1

## TEST PROCEDURES CONTINUED

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The unit under test was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

### CIRCUIT DESCRIPTION:

In the transmit mode the momentary switches B, F, R, & L provide input to the encoder intergrated circuit U2. The output of U2 modulated the RF output stage Q2 by turning on/off the transistor Q3 which is in the emitter of Q2. The crystal controlled oscillator Q1 is coupled to Q2 via C3. From Q2 the signal goes to the double tuned circuit made up of t1, c12 which is connected to the low pass filter C9, L2 C7 & C8 which is in turn connected to the antenna. The RF frequency is determined by the crystal XTAL1.

In the transmit mode the switches B, F, R, & L set the encoding for U2. The output of U2 switches the transistor Q3 on & off to modulate the output signal of Q2, the RF output stage. The crystal oscillator Q1 is connected to Q2 via C3. Q2 is connected to the antenna via the output filter made up of the double tuned circuit T1 and the output filter C9, C7, L2, C6, & L3.

### ANTENNA AND GROUND CIRCUITRY

This unit makes use of a external 5" antenna. The antenna is inductively coupled. This unit is powered from a 9.0V battery.

No ground connection is provided. The unit relies on the ground tract of the printed circuit board.

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T  
REPORT #: F:\CUS\K\KAWAH\KAW166H9.RPT  
PAGE #: 2

APPLICANT: KA WAH MANUFACTORY LTD.

FCC ID: F5J604225T

NAME OF TEST: RADIATION INTERFERENCE

RULES PART NO.: 15.235

REQUIREMENTS: CARRIER FREQUENCY WILL NOT EXCEED 80 dBuV/m AT 3M.  
OUT-OF-BAND EMISSIONS SHALL NOT EXCEED:

30 - 88 MHz	40.0 dBuV/M	MEASURED AT 3 METERS
88 - 216 MHz	43.5 dBuV/M	
216 - 960 MHz	46.0 dBuV/M	
ABOVE 960 MHz	54.0 dBuV/M	

TEST DATA:

EMISSION FREQUENCY MHz	METER READING AT 3 METERS dBuV	COAX LOSS dB	PEAK FIELD STRENGTH dBuV/m@3m			MARGIN dB	ANT. POL.
			ANTENNA CORRECTION FACTOR	dB			
49.86	44.80	0.25	10.99	56.04	23.96	V	
99.70	10.00	0.80	8.39	19.19	24.31	V	
149.60	3.70	0.80	16.90	21.40	22.10	H	
199.40	10.50	0.90	12.66	24.06	19.44	V	
249.30	26.20	1.20	13.35	40.75	5.25	V	
299.20	10.40	1.40	15.65	27.45	18.55	V	
349.00	14.10	1.40	15.52	31.02	14.98	V	
398.90	19.00	1.40	16.97	37.37	8.63	V	
448.70	8.50	1.60	18.12	28.22	17.78	V	
498.60	11.70	1.60	19.27	32.57	13.43	V	
598.30	1.90	1.60	20.09	23.59	22.41	H	

SAMPLE CALCULATION:

$$FSdBuV/m = MR(dBuV) + ACFdB.$$

TEST PROCEDURE: The procedure used was ANSI STANDARD C63.4-1992. The spectrum was scanned from 30 MHz to 1000 MHz. When an emission was found, the table was rotated to produce the maximum signal strength. The antenna was placed in both the horizontal and vertical planes and the worse case emissions were reported. The UUT was tested in 3 orthogonal planes.

TEST RESULTS: THE UNIT DOES MEET THE FCC REQUIREMENTS.

PERFORMED BY: S. S. SANDERS

DATE: APRIL 28, 1999

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T  
REPORT #: F:\CUS\K\KAWAH\KAW166H9.RPT  
PAGE #: 3

APPLICANT: KA WAH MANUFACTORY LTD.

FCC ID: F5J604225T

NAME OF TEST: Occupied Bandwidth

RULES PART NO.: 15.235

REQUIREMENTS: The field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges shall be attenuated at least 26 dB below the level of the unmodulated carrier or to the general limits of 15.209, whichever permits the higher emission levels.

THE GRAPH IN EXHIBIT 12 REPRESENTS THE EMISSIONS TAKEN FOR THE DEVICE.

METHOD OF MEASUREMENT: A small sample of the transmitter output was fed into the spectrum analyzer and the attached plot was taken. The vertical scale is set to -10 dBm per division. The horizontal scale is set to 5 kHz per division.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: S. S. SANDERS DATE: APRIL 28, 1999

APPLICANT: KA WAH MANUFACTORY LTD.  
FCC ID: F5J604225T  
REPORT #: F:\CUS\K\KAWAH\KAW166H9.RPT  
PAGE #: 4