

	Model: 051064S	Test Number: 200117		
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi. dBi = dB gain compared to an isotropic radiator. S = power density in mW/cm <sup>2</sup>			
	Transmitter Output power (dBm)	0.00		
	Transmitter Output power (mW)	1.00		
	Transmitter maximum Output power operating at 100% (Watts)	0.001	Antenna Gain (dBi)	1
	Output Power for 100% duty Cycle operation (Watts)	0.001	Antenna Gain (Numeric)	1.26
Tx Frequency (MHz)	915	Calculation power (Watts)	0.001	$dBd + 2.17 = dBi$
				$dBi - 2.2 = dBd$
Cable Loss (dB)	0.0	Adjusted Power (dBm)	0.0	Antenna Gain (dBd)
				-1.17
				Antenna minus cable (dB)
				1.00
	Calculated ERP (mW)	0.764	EIRP = $Po(dBm) + Gain (dB)$	
	Calculated EIRP (mW)	1.259	Radiated (EIRP) dBm	1.000
	$Power\ density\ (S)\ mW/cm^2 = \frac{EIRP}{4\pi r^2}$ $r\ (cm)\ EIRP\ (mW)$		ERP = EIRP - 2.17 dB	
			Radiated (ERP) dBm	-1.170
	<b>Occupational Limit</b>	FCC radio frequency radiation exposure limits per 1.1310		
f300	mW/cm <sup>2</sup>	Frequency (MHz)	Occupational Limit (mW/cm <sup>2</sup> )	Public Limit (mW/cm <sup>2</sup> )
30.5	W/m <sup>2</sup>	30-300	1	0.2
	<b>General Public Limit</b>	300-1,500	f300	f1500
f1500	mW/cm <sup>2</sup>	1,500-10,000	5	1
6.1	W/m <sup>2</sup>			
	<b>Occupational Limit</b>	IC radio frequency radiation exposure limits per RSS-102		
0.6455f <sup>0.5</sup>	W/m <sup>2</sup>	Frequency (MHz)	Occupational Limit (W/m <sup>2</sup> )	Public Limit (W/m <sup>2</sup> )
24.3	W/m <sup>2</sup>	100-6,000	0.6455f <sup>0.5</sup>	
	<b>General Public Limit</b>	6,000-15,000	50	
0.02619f <sup>0.6834</sup>	W/m <sup>2</sup>	48-300		1.291
2.8	W/m <sup>2</sup>	300-6,000		0.02619f <sup>0.6834</sup>
		6,000-15,000	50	10
f = Transmit Frequency (MHz)			f (MHz) =	915
P <sub>T</sub> = Power Input to Antenna (mW)			P <sub>T</sub> (mW) =	1.0000
Duty cycle (percentage of operation)			% =	100
P <sub>A</sub> = Adjusted Power due to Duty cycle or Cable Loss (mW)			P <sub>A</sub> (mW) =	1.00
G <sub>N</sub> = Numeric Gain of the Antenna			GN (numeric) =	1.26
S <sub>20</sub> = Power Density of device at 20cm (mW/m <sup>2</sup> )		S <sub>20</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>20</sub> ) <sup>2</sup>	S <sub>20</sub> (mW/m <sup>2</sup> ) =	0.00
S <sub>20</sub> = Power Density of device at 20cm (W/m <sup>2</sup> )		S <sub>20</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>20</sub> ) <sup>2</sup>	S <sub>20</sub> (W/m <sup>2</sup> ) =	0.00
S <sub>L</sub> = Power Density Limit (W/m <sup>2</sup> )			S <sub>L</sub> (W/m <sup>2</sup> ) =	2.767
R <sub>C</sub> = Minimum distance to the Radiating Element for Compliance (cm)		R <sub>C</sub> = $\sqrt{(P_A G_N / 4\pi S_L)}$	R <sub>C</sub> (cm) =	0.6
S <sub>C</sub> = Power Density of the device at the Compliance Distance R <sub>C</sub> (W/m <sup>2</sup> )		S <sub>C</sub> =(P <sub>A</sub> G <sub>N</sub> )/(4πR <sub>C</sub> ) <sup>2</sup>	S <sub>C</sub> (W/m <sup>2</sup> ) =	2.77
R <sub>20</sub> = 20cm			R20=	20
	For Compliance with Canada General Population Limits, User Manual must indicate a minimum separation distance of			0.6 cm
	Or in Meters for Compliance with Canada General Population Limits, a minimum separation distance of			0.006 Meters

Rogers Labs, Inc.  
4405 West 259<sup>th</sup> Terrace  
Louisburg, KS 66053  
Phone/Fax: (913) 837-3214  
Revision 1

Transcore  
Model: 051064S, Secure IAG Tag  
Test: 200117  
Test to: 47CFR Parts 2, 90 and RSS-137  
File: 051064S RFExemption

SN: 061003-03 Secure  
FCC ID: FIH051064S  
IC: 1584A-FIH051064S  
Date: February 8, 2020  
Page 1 of 1