

## TABLE OF CONTENTS

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

### TEST REPORT:

PAGE 1.....TEST PROCEDURE  
PAGE 2.....TEST PROCEDURE CONTINUED AND CIRCUIT DESCRIPTION  
PAGE 3.....RADIATION INTERFERENCE TEST DATA  
PAGE 4.....POWERLINE CONDUCTED INTERFERENCE

### EXHIBITS:

EXHIBIT 1.....POWER OF ATTORNEY LETTER  
EXHIBIT 2.....BLOCK DIAGRAM  
EXHIBIT 3.....SCHEMATIC  
EXHIBIT 4A-4B.....PARTS LIST  
EXHIBIT 5A-5B.....USERS MANUAL  
EXHIBIT 6.....SAMPLE OF FCC ID LABEL  
EXHIBIT 7.....FCC ID LABEL LOCATION  
EXHIBIT 8.....EXTERNAL PHOTO-FRONT SIDE  
EXHIBIT 9.....EXTERNAL PHOTO-BACK SIDE  
EXHIBIT 10.....INTERNAL PHOTO-COMPONENT SIDE  
EXHIBIT 11.....INTERNAL PHOTO-COPPER SIDE  
EXHIBIT 12.....POWERLINE CONDUCTED PLOT-LINE 1  
EXHIBIT 13.....POWERLINE CONDUCTED PLOT-LINE 2

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

REPORT #: F:\CUS\B\BESCO\BES179H8.RPT

PAGE #: TABLE OF CONTENTS

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B, with preselector HP 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B OPT H02 Cal. 9/30/97
2. Eaton Biconnical Antenna Model 94455-1 20-200 MHz Serial No. 0997 Cal. 9/17/97
3. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA 25 cal. 5/15/97
4. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 9/24/97
5. Electro-Metric Antennas Model TDS-25-1, TDS-25-2, 9/3/97
6. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. 9/30/97
7. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. 9/30/97

TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution BW was 100KHz and the video bandwidth was 300KHz up to 1.0GHz and RBW was 1.0MHz with a VBW of 3.0MHz above 1.0GHz. The ambient temperature of the UUT was 89.7OF with a humidity of 54 %.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz) METER READING + ACF = FS  
33 20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was &tempc& with a humidity of &humc&.

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

REPORT #: F:\CUS\B\BESCO\BES179H8.RPT

PAGE #: 1

TEST PROCEDURES CONTINUED

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The unit under test was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

RULES: 2.1033(b)(4) CIRCUIT DESCRIPTION

This unit is a super regenerative receiver for a low power security device system. The signal comes in on the antenna to the super regenerative detector Q4. From Q4 the detected signal is fed to the amplifier IC1. From IC1 the signal is fed to the IC2, where the signal decoded and fed into the switches Q2, Q3, Q4 which in turn drive the musical chime.

ANTENNA & GROUND:

This unit uses the a 8 inch long piece of 24AWG wire as an antenna. There is no provision for an external antenna.

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

REPORT #: F:\CUS\B\BESCO\BES179H8.RPT

PAGE #: 2

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

NAME OF TEST: RADIATION INTERFERENCE

RULES PART NO.: 15.109

REQUIREMENTS: 30-88 MHz 40.0 dBuV/m measured at 3 meters  
                   88-216 MHz 43.5 dbuV/m  
                   216-960 MHz 46.0 dbuV/m  
                   ABOVE 960 MHz 54.0 dbuV/m

TEST DATA:

TUNED FREQ. MHz	EMISSION FREQUENCY MHz	METER READING @ 3m	COAX		FIELD		
			dBuV	dB	A.C.F. dB	dBuV/m@3m	MARGIN dB
299.82	294.20	11.40	1.40	15.33	28.13	17.87	V
299.82	295.22	12.90	1.40	15.39	29.69	16.31	V
299.82	296.76	15.40	1.40	15.49	32.29	13.71	H
299.82	298.42	14.10	1.40	15.60	31.10	14.90	H
299.82	299.82	27.70	1.40	15.69	44.79	1.21	V
299.82	301.70	9.40	1.40	15.64	26.44	19.56	H
299.82	303.46	7.40	1.40	15.58	24.38	21.62	H

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD C63.4-1992. The spectrum was scanned from 30 MHz to at 2 GHz. The spectrum analyzer was as specified in ANSI STANDARD C63.4-1992. The receiver was put into a coherent mode.

- 1) Resolution bandwidth 100 kHz to 1 GHz and 1 MHz above 1 GHz
- 2) Frequency scan per division 1 MHz/division
- 3) Scan time was set to 20 mS/division
- 4) A preselecltor was a part of the spectrum analyzer system for the frequency range.
- 5) A weak, on frequency signal was used to place the receiver in the coherent mode.
- 6) The line spectrum of pulse analysis was used.

SAMPLE CALCULATION:

$$FSdBuV/m = MR(dBuV) + ACFdB.$$

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: S. S. SANDERS

DATE TESTED: 6/24/98

APPLICANT: BESCO ELECTRONIC MANUFACTURING CO. LTD.  
                   FCC ID: GXKBS3220RX  
                   REPORT #: F:\CUS\B\BESCO\BES179H8.RPT  
                   PAGE #: 3

APPLICANT: BESCO ELECTRONICS MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

NAME OF TEST: POWER LINE CONDUCTED INTERFERENCE

RULES PART NUMBER: 15.107

MINIMUM REQUIREMENTS:	FREQUENCY	LEVEL
	MHz	uV
	0.450-30	250

TEST PROCEDURE: ANSI STANDARD C63.4-1992

THE HIGHEST EMISSION READ FOR LINE 1 WAS 15.117 uV @ 1.16 MHz.

THE HIGHEST EMISSION READ FOR LINE 2 WAS 21.109 uV @ 800 kHz.

THE PLOTS IN EXHIBITS 12-13 REPRESENT THE EMISSIONS READ FOR POWERLINE CONDUCTED FOR THIS DEVICE.

TEST RESULTS: Both lines were observed. The measurements indicate that the unit PASS appear to meet the FCC requirements for this class of equipment.

PERFORMED BY: \_\_\_\_\_ DATE: 6/24/98

APPLICANT: BESCO ELECTRONICS MANUFACTURING CO. LTD.

FCC ID: GXKBS3220RX

REPORT #: F:\CUS\B\BESCO\BES179H8.RPT

PAGE #: 4