

RF Exposure Report

(Part 0: SAR Char Evaluation)

APPLICANT : Motorola Mobility LLC
EQUIPMENT : Mobile Cellular Phone
BRAND NAME : Motorola
MODEL NAME : XT2551-1, XT2551-2, XT2551-6
FCC ID : IHDT56AU1
STANDARD : FCC 47 CFR PART 2 (2.1093)

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures given in 47 CFR Part 2.1093 and FCC KDB and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.



Approved by: Si Zhang

Sporton International Inc. (Kunshan)

No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China



Table of Contents

1. Introduction	4
2. Product Description	5
3. SAR Characterization.....	7
3.1 SAR design target and uncertainty.....	7
3.2 SAR Char Table	8



History of this test report

Report No.	Version	Description	Issued Date
FA4N2802D	01	Initial issue of report	Jan. 13, 2025
FA4N2802D	02	Updated Plimit table This report is an update version, replacing the report issued on Jan. 13, 2025.	Feb. 11, 2025



1. Introduction

For Open Mode

Qualcomm® Smart Transmit™ 5.0 of Smart Transmit (GEN2) Feature operates based on pre-defined sub6 antenna groups (AG). This Device is enabled with the Qualcomm® Smart Transmit Gen2 feature. The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN and WLAN/BT transmitter to ensure the product in compliance with RF exposure limit over a defined time window. To control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Smart Transmit cannot operate without SAR characterization at the device level beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. SAR char will be entered via the Embedded File System (EFS) version 23 to enable the Smart Transmit Gen2 Feature.

For Close Mode

The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN and WLAN/BT transmitter to ensure the product in compliance with RF exposure limit over a defined time window. To control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Smart Transmit cannot operate without SAR characterization at the device level beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. SAR char will be entered via the Embedded File System (EFS) version 23 to enable the Smart Transmit Gen1 Feature.

Terminologies in this report

P_{limit}	The time-averaged RF power which corresponds to SAR_design_target.
P_{max}	Maximum target power level
SAR_design_target:	The design target for SAR compliance. It should be less than regulatory power density limit to account for all device design related uncertainty.
SAR char	P_{limit} for all the technologies/bands for all applicable DSI



2. Product Description

Product Feature & Specification	
Equipment Name	Mobile Cellular Phone
Brand Name	Motorola
Model Name	XT2551-1, XT2551-2, XT2551-6
FCC ID	IHDT56AU1
Wireless Technology and Frequency Range	GSM850: 824 MHz ~ 849 MHz GSM1900: 1850MHz ~ 1910MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 14: 788 MHz ~ 798 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 25: 1850 MHz ~ 1915 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 30: 2305 MHz ~ 2315 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 42: 3450 MHz ~ 3600 MHz LTE Band 43: 3600 MHz ~ 3700 MHz LTE Band 48: 3550 MHz ~ 3700 MHz LTE Band 66: 1710 MHz ~ 1780 MHz LTE Band 71: 663 MHz ~ 698 MHz 5G NR n2 : 1850 MHz ~ 1910 MHz 5G NR n5 : 824 MHz ~ 849 MHz 5G NR n7 : 2500 MHz ~ 2570 MHz 5G NR n12 : 699 MHz ~ 716 MHz 5G NR n14 : 788 MHz ~ 798 MHz 5G NR n25 : 1850 MHz ~ 1915 MHz 5G NR n26 : 814 MHz ~ 849 MHz 5G NR n30 : 2305 MHz ~ 2315 MHz 5G NR n38 : 2570 MHz ~ 2620 MHz 5G NR n41 : 2496 MHz ~ 2690 MHz 5G NR n48 : 3550 MHz ~ 3700 MHz 5G NR n66 : 1710 MHz ~ 1780 MHz 5G NR n70 : 1695 MHz ~ 1710 MHz 5G NR n71 : 663 MHz ~ 698 MHz 5G NR n77: 3700 MHz ~ 3980 MHz, 3450MHz ~ 3550MHz 5G NR n78: 3700 MHz ~ 3800 MHz, 3450MHz ~ 3550MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz WLAN 6GHz U-NII 5: 5925 MHz ~ 6425 MHz WLAN 6GHz U-NII 6: 6425 MHz ~ 6525 MHz WLAN 6GHz U-NII 7: 6525 MHz ~ 6875 MHz WLAN 6GHz U-NII 8: 6875 MHz ~ 7125 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC : 13.56 MHz WPT: 115 KHz ~ 145 KHz UWB: 6489.6MHz & 7987.2MHz
Mode	GSM/GPRS/EGPRS RMC/AMR 12.2Kbps HSDPA/HSUPA DC-HSDPA



	HSPA+ (16QAM uplink is not supported) LTE: QPSK, 16QAM, 64QAM, 256QAM 5G NR: DFT-s-OFDM/CP-OFDM, Pi/2 BPSK/QPSK/16QAM/64QAM/256QAM WLAN 2.4GHz 802.11b/g/n HT20/HT40 WLAN 2.4GHz 802.11ax HE20/HE40 WLAN 2.4GHz 802.11be EHT20/EHT40 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac VHT20/VHT40/VHT80/VHT160 WLAN 5GHz 802.11ax HE20/HE40/HE80/HE160 WLAN 5GHz 802.11be EHT20/EHT40/EHT80/EHT160 WLAN 6GHz 802.11a/ax HE20/HE40/HE80/HE160 WLAN 6GHz 802.11be EHT20/EHT40/EHT80/EHT160/EHT320 Bluetooth BR/EDR/LE NFC: ASK WPT: ASK UWB: BPM-BPSK
--	--

3. SAR Characterization

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at WWAN and WLAN/BT bands. It will then be used as input for Smart Transmit to control and manage RF exposure for WWAN and WLAN/BT bands.

3.1 SAR design target and uncertainty

SAR design Target:

Exposure Condition	Measure Distance	SAR (W/kg)
		WWAN 2/3/4/5G
Body Worn (1g)	5 mm	1.03
Hotspot (1g)	5 mm	1.03
Head (1g)	touch&tilt 15deg	1.03
Extremity (10g)	0 mm	2.55

Exposure Condition	Measure Distance	SAR (W/kg)
		WLAN MIMO/BT
Body Worn (1g)	5 mm	0.915
Hotspot (1g)	5 mm	0.915
Head (1g)	touch&tilt 15deg	0.915
Extremity (10g)	0 mm	2.271

Antenna Group:

Antenna Group 0 (AG0)	ANT2 & ANT3 & ANT4 & ANT5 & ANT6 & ANT7& ANT8
Antenna Group 1 (AG1)	ANT0 & ANT1

Uncertainty:

Item	Uncertainty dB (k=2)
Total uncertainty	1.5

To account for total uncertainty, SAR_design_target should be determined as:

$$SAR_{design_target} < SAR_{regulatory_limit} \times 10^{\frac{-total\ uncertainty}{10}}$$

**3.2 SAR Char Table**

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at WWAN and WLAN/BT bands. It will then be used as input for Smart Transmit to control and manage RF exposure for WWAN and WLAN/BT bands.

<P_{limit} for supported technologies and bands (P_{limit} in EFS file)>

Band	Antenna	Head DSI 2	Body-Worn open DSI 3	Hotspot open DSI 7	Extremity open DSI 6	Body-Worn close DSI 10	Hotspot close DSI 11	Sensor off open/close DSI 4	Pmax*
GSM850	Ant 0	33.1	26.5	26.5	23.7	28.5	28.5	23.7	23.7
GSM850	Ant 1	29.5	26.5	26.5	23.7	27.1	27.1	23.7	23.7
GSM1900	Ant 2	18.2	22.0	17.9	23.2	21.6	17.8	21.5	21.5
GSM1900	Ant 0	34.8	28.4	25.2	21.2	26.4	24.3	21.2	21.2
WCDMA II	Ant 2	18.1	20.0	17.4	22.2	21.1	17.5	23.0	23.0
WCDMA II	Ant 0	32.6	23.0	21.9	23.6	25.7	24.4	23.0	23.0
WCDMA IV	Ant 2	17.9	19.2	17.1	21.8	23.2	19.3	23.0	23.0
WCDMA IV	Ant 0	32.3	23.2	21.6	25.1	23.5	23.5	23.0	23.0
WCDMA V	Ant 0	31.2	25.0	24.3	23.0	25.1	24.6	23.0	23.0
WCDMA V	Ant 1	29.3	24.8	24.8	23.0	25.9	24.1	23.0	23.0
LTE Band 25(2)	Ant 2	18.1	20.8	18.5	22.9	21.6	18.1	23.0	23.0
LTE Band 25(2)	Ant 3	18.4	20.9	18.6	22.9	22.1	22.1	23.0	23.0
LTE Band 25(2)	Ant 0	31.8	22.4	22.2	24.2	24.2	23.6	22.0	22.0
LTE Band 25(2)	Ant 1	32.9	22.8	21.2	22.7	25.0	25.0	22.0	22.0
LTE Band 66(4)	Ant 2	18.2	20.9	18.2	23.1	22.2	18.4	23.0	23.0
LTE Band 66(4)	Ant 3	19.1	21.3	19.1	22.7	22.8	21.5	23.0	23.0
LTE Band 66(4)	Ant 0	33.6	22.6	21.4	24.0	23.5	23.2	23.0	23.0
LTE Band 66(4)	Ant 1	34.7	21.9	19.3	22.2	25.2	21.9	22.0	22.0
LTE Band 26(5)	Ant 0	30.6	24.3	24.3	23.0	25.0	24.2	23.0	23.0
LTE Band 26(5)	Ant 1	28.9	24.5	24.5	23.0	26.5	24.7	23.0	23.0
LTE Band 7	Ant 2	18.3	20.8	17.4	22.2	21.7	18.8	23.0	23.0
LTE Band 7	Ant 3	19.9	22.6	18.2	21.3	23.5	20.0	23.0	23.0
LTE Band 7	Ant 0	28	22.4	18.9	22.8	24.9	21.2	22.0	22.0
LTE Band 7	Ant 1	28.3	26.2	23.2	25.1	25.5	25.1	23.0	23.0
LTE Band 12(17)	Ant 0	30.5	25.1	24.5	23.0	26.6	26.6	23.0	23.0
LTE Band 12(17)	Ant 1	29.4	24.9	24.9	23.0	26.7	26.7	23.0	23.0
LTE Band 13	Ant 0	30.1	25.4	24.4	22.0	25.4	25.4	22.0	22.0
LTE Band 13	Ant 1	30.2	25.0	24.9	22.0	27.1	27.1	22.0	22.0
LTE Band 14	Ant 0	29.1	24.9	24.5	23.0	25.3	24.6	23.0	23.0
LTE Band 14	Ant 1	29.5	25.1	25.1	22.0	27.7	25.9	22.0	22.0
LTE Band 30	Ant 2	18.4	20.2	18.4	22.3	21.2	18.4	23.0	23.0
LTE Band 30	Ant 3	18.8	21.3	21.3	22.5	21.8	18.4	21.0	21.0
LTE Band 30	Ant 0	29.4	23.3	22.1	24.2	26.6	22.7	23.0	23.0
LTE Band 30	Ant 1	28.3	25.0	24.3	21.0	27.5	27.5	21.0	21.0
LTE Band 71	Ant 0	30.6	25.5	24.5	23.0	30.0	30.0	23.0	23.0
LTE Band 71	Ant 1	29.2	24.9	23.5	23.0	27.5	27.5	23.0	23.0
LTE Band 41(38)	Ant 2	18.1	20.5	16.9	21.4	21.1	17.6	22.4	22.0
LTE Band 41 HPUE	Ant 2	18.1	20.5	16.9	21.4	21.1	17.6	22.4	22.4
LTE Band 41(38)	Ant 3	15.4	19.3	14.8	19.3	19.8	16.5	22.4	22.0
LTE Band 41 HPUE	Ant 3	15.4	19.3	14.8	19.3	19.8	16.5	22.4	22.4
LTE Band 41(38)	Ant 0	28.8	20.1	17.9	24.2	27.2	21.8	22.4	21.0
LTE Band 41 HPUE	Ant 0	28.8	20.1	17.9	24.2	27.2	21.8	22.4	22.4
LTE Band 41(38)	Ant 1	29.5	23.5	20.9	23.8	24.6	22.4	22.4	22.0
LTE Band 41 HPUE	Ant 1	29.5	23.5	20.9	23.8	24.6	22.4	22.4	22.4
LTE Band 42 Part 27Q	Ant 4	18.9	20.9	16.4	20.5	21.3	18.7	21.0	21.0
LTE Band 42 Part 27Q	Ant 8	18.2	19.3	17.4	19.7	21.2	20.5	21.0	21.0



FCC RF Exposure Report

Report No. : FA4N2802D

LTE Band 42 Part 27Q	Ant 3	16.9	20.2	16.9	19.8	19.8	17.9	20.0	20.0
LTE Band 42 Part 27Q	Ant 5	17.7	20.4	16.5	20.3	21.1	18.1	20.0	20.0
LTE Band 48(43&42 Part96)	Ant 4	17.7	19.4	16.4	20.5	21.1	17.5	22.0	22.0
LTE Band 48(43&42 Part96)	Ant 8	15.5	18.3	16.4	19.4	19.0	17.1	21.0	21.0
LTE Band 48(43&42 Part96)	Ant 3	18	21.4	18.6	22.8	22.8	19.9	21.0	21.0
LTE Band 48(43&42 Part96)	Ant 5	17.9	20.4	16.3	22.0	21.7	19.3	21.0	21.0
FR1 n25(2)	Ant 2	18.6	21.3	17.9	23.5	21.9	18.3	23.0	23.0
FR1 n2 Other Path	Ant 2	18.6	21.3	17.9	23.5	21.9	18.3	23.0	23.0
FR1 n25(2)	Ant 3	19.4	20.4	18.6	23.0	21.9	20.3	23.0	23.0
FR1 n2 Other Path	Ant 3	19.4	20.4	18.6	23.0	21.9	20.3	23.0	23.0
FR1 n25(2)	Ant 0	32.7	23.7	21.1	24.0			23.0	23.0
FR1 n2 Other Path	Ant 0	32.7	23.7	21.1	24.0			23.0	23.0
FR1 n25(2)	Ant 1	34.1	23.2	21.1	24.2			23.0	23.0
FR1 n2 Other Path	Ant 1	34.1	23.2	21.1	24.2			23.0	23.0
FR1 n26(5)	Ant 0	32.2	26.3	26.3	23.0	26.8	27.4	23.0	23.0
FR1 n26(5) Other Path	Ant 0	32.2	26.3	26.3	23.0	26.8	27.4	23.0	23.0
FR1 n26(5)	Ant 1	31.2	26.0	26.0	23.0	26.0	26.4	23.0	23.0
FR1 n26(5) Other Path	Ant 1	31.2	26.0	26.0	23.0	26.0	26.4	23.0	23.0
FR1 n7	Ant 2	18.8	21.5	18.3	23.2	21.7	19.5	23.0	23.0
FR1 n7 Other Path	Ant 2	18.8	21.5	18.3	23.2	21.7	19.5	23.0	23.0
FR1 n7	Ant 3	17.9	20.8	17.9	19.9	23.5	19.9	23.0	23.0
FR1 n7	Ant 0	30.2	23.2	21.2	23.5			23.0	23.0
FR1 n7 Other Path	Ant 0	30.2	23.2	21.2	23.5			23.0	23.0
FR1 n7	Ant 1	29.7	24.0	20.6	24.4			23.0	23.0
FR1 n12	Ant 0	33.3	27.6	26.0	23.5	27.9	27.9	23.5	23.5
FR1 n12 Other Path	Ant 0	33.3	27.6	26.0	23.5	27.9	27.9	23.5	23.5
FR1 n12	Ant 1	32	28.2	28.2	23.0	27.4	27.4	23.0	23.0
FR1 n12 Other Path	Ant 1	32	28.2	28.2	23.0	27.4	27.4	23.0	23.0
FR1 n14	Ant 0	31.4	26.4	26.4	23.5	27.6	27.5	23.5	23.5
FR1 n14 Other Path	Ant 0	31.4	26.4	26.4	23.0	27.6	27.5	23.0	23.0
FR1 n14	Ant 1	32.1	26.0	26.0	23.0	27.3	27.3	23.0	23.0
FR1 n14 Other Path	Ant 1	32.1	26.0	26.0	23.0	27.3	27.3	23.0	23.0
FR1 n30	Ant 2	18.1	21.0	18.1	23.0	21.7	18.5	23.0	23.0
FR1 n30 Other Path	Ant 2	18.1	21.0	18.1	23.0	21.7	18.5	23.0	23.0
FR1 n30	Ant 0	30.5	23.9	21.7	24.5			23.0	23.0
FR1 n30 Other Path	Ant 0	30.5	23.9	21.7	24.5			23.0	23.0
FR1 n66	Ant 2	17.6	20.9	17.7	22.0	21.0	18.0	23.0	23.0
FR1 n66 Other Path	Ant 2	17.6	20.9	17.7	22.0	21.0	18.0	23.0	23.0
FR1 n66	Ant 3	19	21.7	19.1	21.9	22.4	19.9	23.0	23.0
FR1 n66 Other Path	Ant 3	19	21.7	19.1	21.9	22.4	19.9	23.0	23.0
FR1 n66	Ant 0	33.8	23.0	22.0	25.8			23.0	23.0
FR1 n66 Other Path	Ant 0	33.8	23.0	22.0	25.8			23.0	23.0
FR1 n66	Ant 1	37.3	21.9	18.8	24.0			22.0	22.0
FR1 n66 Other Path	Ant 1	37.3	21.9	18.8	24.0			23.0	23.0
FR1 n70	Ant 2	18.5	21.8	18.9	23.4	23.4	20.3	23.0	23.0
FR1 n70	Ant 3	20.7	23.7	20.8	22.0	24.6	21.4	23.0	23.0
FR1 n70	Ant 0	34.5	22.7	22.0	25.1			23.0	23.0
FR1 n70	Ant 1	38.5	22.5	19.2	24.6			23.0	23.0
FR1 n71	Ant 0	33	27.4	26.2	23.0	30.7	28.3	23.0	23.0
FR1 n71 Other Path	Ant 0	33	27.4	26.2	23.0	30.7	28.3	23.0	23.0
FR1 n71	Ant 1	31.2	27.2	26.2	23.0	28.3	28.3	23.0	23.0
FR1 n71 Other Path	Ant 1	31.2	27.2	26.2	23.0	28.3	28.3	23.0	23.0
FR1 n41(38)	Ant 2	18.9	21.5	18.3	22.8	22.7	19.3	23.0	23.0
FR1 n41 HPUE	Ant 2	18.9	21.5	18.3	22.8	22.7	19.3	23.0	23.0
FR1 n41(38)	Ant 3	18.3	20.9	18.0	20.7	22.4	19.6	23.5	23.5
FR1 n41 HPUE	Ant 3	18.3	20.9	18.0	20.7	22.4	19.6	23.5	23.5

**FCC RF Exposure Report****Report No. : FA4N2802D**

FR1 n41(38)	Ant 0	29.2	20.9	18.3	23.5	26.9	22.8	23.0	23.0
FR1 n41 HPUE	Ant 0	29.2	20.9	18.3	23.5	26.9	22.8	23.0	23.0
FR1 n41(38)	Ant 1	29.9	23.6	21.1	23.9	26.4	25.3	23.0	23.0
FR1 n41 HPUE	Ant 1	29.9	23.6	21.1	23.9	26.4	25.3	23.0	23.0
FR1 n48	Ant 4	17.2	20.8	15.3	21.3	21.7	18.1	23.0	23.0
FR1 n48	Ant 8	18.5	19.0	16.8	20.4	20.6	19.8	23.5	23.5
FR1 n48	Ant 3	19	21.5	17.4	20.2	23.8	19.5	23.5	23.5
FR1 n48	Ant 5	19.1	22.7	18.2	21.3	23.5	18.9	21.3	23.0
FR1 n77(78)	Ant 4	16.1	19.2	16.3	19.0	22.1	18.0	23.0	23.0
FR1 n77(78)HPUE	Ant 4	16.1	19.2	16.3	19.0	22.1	18.0	23.0	23.0
FR1 n77(78)	Ant 8	18.3	19.7	18.1	21.1	21.4	19.8	23.0	23.0
FR1 n77(78)HPUE	Ant 8	18.3	19.7	18.1	21.1	21.4	19.8	23.0	23.0
FR1 n77(78)	Ant 3	17.8	21.8	17.6	21.0	22.5	19.2	23.0	23.0
FR1 n77(78)HPUE	Ant 3	17.8	21.8	17.6	21.0	22.5	19.2	23.0	23.0
FR1 n77(78)	Ant 5	15.3	21.8	15.6	19.4	22.6	18.6	19.4	23.0
FR1 n77(78)HPUE	Ant 5	15.3	21.8	15.6	19.4	22.6	18.6	19.4	23.0
UL-MIMO FR1 n25(2)_PC2	Ant 2+3	15.1	18.9	15.4	20.9	19.3	16.7	23.0	23.0
UL-MIMO FR1 n25(2)_PC2	Ant 2+1	18.6	21.3	17.9	23.5			23.0	23.0
UL-MIMO FR1 n25(2)_PC2	Ant 0+3	19.4	21.4	18.6	23.0			23.0	23.0
UL-MIMO FR1 n25(2)_PC2	Ant 0+1	32.7	20.1	18.2	20.3			23.0	23.0
UL-MIMO FR1 n66_PC2	Ant 2+3	16.6	20.9	17.9	22.0	21.8	18.0	23.0	23.0
UL-MIMO FR1 n66_PC2	Ant 2+1	17.6	20.9	17.7	22.0			23.0	23.0
UL-MIMO FR1 n66_PC2	Ant 0+3	19	21.7	19.1	21.9			23.0	23.0
UL-MIMO FR1 n66_PC2	Ant 0+1	33.8	21.6	19.3	24.0			22.5	22.5
UL-MIMO FR1 n41_PC2	Ant 2+3	15.6	18.0	15.1	18.3	20.2	17.1	23.5	23.5
UL-MIMO FR1 n41_PC1.5	Ant 2+3	15.6	18.0	14.1	18.3	20.2	17.1	23.5	23.0
UL-MIMO FR1 n41_PC2	Ant 2+1	18.9	21.5	18.3	22.8	22.4	20.0	23.0	23.0
UL-MIMO FR1 n41_PC1.5	Ant 2+1	18.9	21.5	18.3	22.8	22.4	20.0	23.0	23.0
UL-MIMO FR1 n41_PC2	Ant 0+3	18.3	20.9	18.0	20.7	22.5	19.6	23.5	23.5
UL-MIMO FR1 n41_PC1.5	Ant 0+3	18.3	20.9	18.0	20.7	22.5	19.6	23.5	23.5
UL-MIMO FR1 n41_PC2	Ant 0+1	29.2	21.3	19.0	22.0	26.4	20.3	23.0	23.0
UL-MIMO FR1 n41_PC1.5	Ant 0+1	29.2	21.3	19.0	22.0	26.4	20.3	23.0	23.0
UL-MIMO FR1 n48_PC2	Ant 4+8	16.9	19.1	13.2	15.9	17.0	15.0	20.0	20.0
UL-MIMO FR1 n48_PC2	Ant 4+5	16.2	19.5	10.2	16.8	16.3	13.5	20.0	20.0
UL-MIMO FR1 n48_PC2	Ant 3+8	17.6	19.1	13.8	17.6	16.5	16.2	20.0	20.0
UL-MIMO FR1 n48_PC2	Ant 3+5	17.1	19.1	12.2	14.4	16.5	13.2	20.0	20.0
UL-MIMO FR1 n77(78)_PC2	Ant 4+8	16.5	19.3	16.6	19.8	20.0	18.0	23.0	23.0
UL-MIMO FR1 n77_PC1.5	Ant 4+8	16.5	19.3	16.6	19.8	20.0	18.0	23.0	23.0
UL-MIMO FR1 n77(78)_PC2	Ant 4+5	16	19.6	15.7	19.7	20.0	17.0	23.0	23.0
UL-MIMO FR1 n77_PC1.5	Ant 4+5	16	19.6	15.7	19.7	20.0	17.0	23.0	23.0
UL-MIMO FR1 n77(78)_PC2	Ant 3+8	18.6	19.7	16.6	21.9	20.4	18.8	23.0	23.0
UL-MIMO FR1 n77_PC1.5	Ant 3+8	18.6	19.7	16.6	21.9	20.4	18.8	23.0	23.0
WLAN2.4G	Ant 7	13.5	18.0	13.5	18.0	18.0	13.5	18.0	20.5
WLAN2.4G	Ant 6	14	18.5	14.0	18.5	18.5	14.0	18.5	21.5
WLAN2.4G	Ant 7+6	14	18.5	14.0	18.5	18.5	14.0	18.5	24.0
Bluetooth	Ant 7	12.3	15.3	11.8	16.8	16.3	14.3	16.8	16.8
Bluetooth	Ant 6	15.8	15.8	15.8	15.8	15.8	15.8	15.8	15.8
WLAN5.2G	Ant 7	16.5	17.0	16.5	19.0	17.5	15.5	19.0	19.0
WLAN5.2G	Ant 5	16.5	17.0	16.5	19.0	17.5	15.5	19.0	19.0
WLAN5.2G	Ant 5+7	16.5	17.0	16.5	19.0	17.5	15.5	22.0	22.0
WLAN5.3G	Ant 7	16.5	17.0		19.0	17.5		19.0	19.0
WLAN5.3G	Ant 5	16.5	17.0		19.0	17.5		19.0	19.0
WLAN5.3G	Ant 5+7	16.5	17.0		19.0	17.5		22.0	22.0
WLAN5.5G	Ant 7	15.5	16.0		19.0	17.5		19.0	19.0
WLAN5.5G	Ant 5	15.5	16.0		19.0	17.5		19.0	19.0
WLAN5.5G	Ant 5+7	15.5	16.0		19.0	17.5		22.0	22.0



FCC RF Exposure Report

Report No. : FA4N2802D

WLAN5.8G	Ant 7	16	16.5	16.0	19.5	18.0	18.0	20.0	20.0
WLAN5.8G	Ant 5	16	16.5	16.0	19.5	18.0	18.0	20.0	20.0
WLAN5.8G	Ant 5+7	16	16.5	16.0	19.5	18.0	18.0	23.0	23.0
WLAN6G Band 5	Ant 7	12	13.5		13.5	12.0		13.5	15.5
WLAN6G Band 5	Ant 5	12.5	14.0		14.0	12.5		14.0	16.0
WLAN6G Band 5	Ant 5+7	12.5	14.0		14.0	12.5		14.0	19.0
WLAN6G Band 6	Ant 7	16	14.0		14.0	16.0		14.0	16.0
WLAN6G Band 6	Ant 5	15.5	13.5		13.5	15.5		13.5	15.5
WLAN6G Band 6	Ant 5+7	16	14.0		14.0	16.0		14.0	19.0
WLAN6G Band 7	Ant 7	16	15.0		15.0	12.5		15.0	16.0
WLAN6G Band 7	Ant 5	15.5	14.5		14.5	12.0		14.5	15.5
WLAN6G Band 7	Ant 5+7	16	15.0		15.0	12.5		15.0	18.5
WLAN6G Band 8	Ant 7	15	14.0		14.0	14.0		14.0	16.0
WLAN6G Band 8	Ant 5	15	14.0		14.0	14.0		14.0	16.0
WLAN6G Band 8	Ant 5+7	15	14.0		14.0	14.0		14.0	19.0

Note: 1) *Pmax is used for RF tune up procedure. The maximum allowed output power is equal to Pmax +total uncertainty. (The device uncertainty for sub-6GHz WWAN is 1.0 dB for this DUT, the device uncertainty for WLAN/BT Bands is 1.5 dB).

2) All P_{limit} power levels entered in the Table correspond to average power levels after accounting for duty cycle in the case TDD modulation schemes (for e.g., GSM & LTE TDD & NR TDD).

3) The max allowed output power is the P_{limit} +total uncertainty, and if P_{limit} is higher than P_{max}, the device output power will be P_{max} instead.

4) For closed state, this device cannot transmit with antenna 0 for 5GNR n2/7/25/30/66/70 and antenna 1 for 5GNR n2/7/25/66/70.

5) The following table is duty cycle and factor used for calculating time average power.

GSM/FDD/TDD	Duty Cycle	Time average calculation factor(dB)
GSM 1TX	12.50%	-9.0
GSM 2TX	25%	-6.0
GSM 3TX	37.50%	-4.3
GSM 4TX	50%	-3.0
FDD LTE	100%	0.0
TDD LTE	63.30%	-2.0
TDD HPUE	43.30%	-3.6
NR FDD/TDD	100%	0.0
NR TDD HPUE	50%	-3.0