



**MOTOROLA**

**MOBILE DEVICES BUSINESS**

**PRODUCT SAFETY AND COMPLIANCE  
EMC LABORATORY**


**EMC TEST REPORT**

**Test Report Number** – 18242-1

**Report Date** – April 21, 2006

The test results contained herein relate only to the model(s) identified. It is the manufacturer's responsibility to assure that additional production units of this model are manufactured with identical electrical and mechanical characteristics.

As the responsible EMC Engineer, I hereby declare that the equipment tested as specified in this report conforms to the requirements indicated.

Signature: 

Name: Thanigaiselvan Palaniswami

Title: EMC Engineer

Date: April 21, 2006

This report must not be reproduced, except in full, without written approval from this laboratory.

**THIS REPORT MUST NOT BE USED TO CLAIM PRODUCT ENDORSEMENT BY A2LA OR ANY AGENCY OF THE U.S. GOVERNMENT.**

A2LA Certificate Number: 1651-01

## **Table of Contents**

Description	Page
Test Report Details	3
Applicable Standards	3
Summary of Testing	4
General and Special Conditions	4
Equipment and Cable Configuration	5
Measurement Procedures and Data	6
RF Power Output	6
Measurement results	6
Radiated Power	7
Measurement results	7
Occupied Bandwidth	8
Measurement results	9
Spurious Emissions at Antenna Terminals	13
Measurement results	14
Field Strength of Spurious Emissions	20
Measurement results	21
Frequency Stability	23
Measurement results	24
Field Strength of Spurious Emissions -Unintentional Radiators	26
Measurement results	27
AC Line Conducted Emissions	29
Measurement results	30
Appendix A - Radiated Emissions Test Setup Photos	37
Figure A.1 – Radiated Emissions Measurement	37
Figure A.2 – Substitution Measurement	37

**Test Report Details**

Tests Performed By: Motorola Mobile Devices business  
 Product Safety and Compliance Group  
 600 North US Hwy 45  
 Libertyville, IL 60048  
 PH (847) 523-6167 Fax (847) 523-4538  
 Motorola MDB FRN: 0004321311  
 FCC Registration Number: 316588  
 Industry Canada Number: IC3908

Tests Requested By: Motorola Inc.  
 Mobile Devices business  
 600 North US Hwy 45  
 Libertyville, IL 60048

Product Type: Cellular Phone

Signaling Capability: CDMA 800, 1900 and Bluetooth

Model Number: SJUG2023AA

Serial Numbers: 52744A05, 52744A10, 52744A0F,  
 52744A11

Testing Complete Date: April 21, 2006

**Applicable Standards**

All tests and measurements indicated in this document were performed in accordance with the Code of Federal Regulations Title 47 Part 2, Sub-part J as well as the following parts:

- Part 15 Subpart B – Unintentional Radiators
- Part 22 Subpart H - Public Mobile Services
- Part 24 - Personal Communications Services
- Part 90 - Private Land Mobile Radio Service

Applicable Standards: TIA EIA 137-A, TIA EIA 98-C, ANSI 63.4 2001, RSS-118 (AMPS), RSS-128 (TDMA), RSS-129 (CDMA), RSS-133 (PCS)

**Summary of Testing**

Test #	Test Name	Pass/Fail
1	RF Power Output	NA
2	ERP (Effective Radiated Power)	Pass
3	Occupied Bandwidth	Pass
4	Spurious Emissions at Antenna Terminal	Pass
5	Field Strength of Spurious Emissions	Pass
6	Frequency Stability	Pass
7	Field Strength of Spurious Emissions from Unintentional Radiators	Pass

Test #	Test Name	Margin with respect to the Limit
1	RF Power Output	NA
2	ERP (Effective Radiated Power)	See results
3	Occupied Bandwidth	See Plots
4	Spurious Emissions at Antenna Terminal	8.3 dB
5	Field Strength of Spurious Emissions	13.1
6	Frequency Stability	40.35 Hz
7	Field Strength of Spurious Emissions from Unintentional Radiators	Below noise floor

The margin with respect to the limit is the minimum margin for all modes and bands.

**General and Special Conditions**

The EUT was tested using a fully charged battery when applicable. Where a battery could not be used due to the need for a controlled variation of input voltage, an external power supply was utilized.

All testing was done in an indoor controlled environment with an average temperature of 22° C and relative humidity of 50%.

**Equipment and Cable Configurations**

The EUT was tested in a stand-alone configuration that is representative of typical use.

<b>Manufacturer</b>	<b>Equipment Type</b>	<b>Model No.</b>	<b>Serial Number</b>	<b>Calibration Due Date</b>
Rohde Schwarz	Receiver	ESI26	838786/010	6/17/06
Hewlett-Packard	EMC Analyzer	7405	US39440191	6/8/06
A.H. Systems	DRG Horn Antenna	SAS 200/571	265	5/19/06
A.H. Systems Inc.	DRG Horn Antenna	SAS 200/571	365	5/25/06
ETS	Log-Periodic Antenna	3148	1188	6/14/06
ETS	Biconical Antenna	3110B	3369	8/15/06
Attenuator	Weinschel	AS-6	6675	1/10/07
Attenuator	Weinschel	AS-6	6677	11/14/06
Hewlett-Packard	Signal Generator	83623B	3844A01195	6/20/06
Thermotron	Environmental Chamber	S-4	31580	1/31/07
Agilent	Power Meter	E4416A	GB41293246	02/03/07
Agilent	Power Sensor	E4412B	US38486321	02/03/07
Miteq	Preamp	NSP2650-NFG	1084144	7/11/06

All equipment is on a one-year calibration cycle.

**Measurement Procedures and Data**

**RF POWER OUTPUT**

**Measurement Procedure**

The RF output port of the equipment under test is directly coupled to the input of a Agilent power meter through a 10dB passive attenuator, adaptor (if needed), and specialized RF connector. The peak power output is measured for all channels.

CFR47 Part 2.1046

**Measurement Results**

**CDMA 800**

Frequency (MHz)	Power (dBm)
824.70	25.15
836.52	25.07
848.31	25.15

**CDMA 1900**

Frequency (MHz)	Power (dBm)
1851.25	24.98
1880.00	25.05
1908.75	25.03

**RADIATED POWER (EIRP AND ERP)**

**Measurement Procedure**

The phone was tested in a 16’ anechoic chamber with a 2-axis position system that permits taking complete spherical scans of the EUT’s radiation patterns. For all tests, the phone was supported in a free space type environment, vertically oriented in the chamber. Tests were done for CDMA 800 three frequencies (824.7, 836.52 and 848.31 MHz) and CDMA 1900 three frequencies (1851.25, 1880.00, and 1908.75 MHz)

CDMA measurements were made with the phone placed in a call using the CMU 200 mobile station test set. The phone was weakly coupled to the test set and configured to transmit in full data rate mode. Radiated power was measured at each 15 degree step. The radiated power was measured using a Gigatronics 8542C power meter in “Mod Avg” mode. From these measurements, the software calculates the angle at which maximum radiated power occurs for each case, and the radiated power at this angle was extracted from the data. The max radiated power results for the IHDT56GH1 follows, as EIRP in dBm. To get ERP (effective radiated power referenced to a half-wave dipole), subtract 2.14 dB from these numbers.

**Measurement Results**

CDMA 800:  
 824.70 MHz            23.37 dBm  
 836.52 MHz            23.80 dBm  
 848.31 MHz            24.38 dBm

CDMA 1900:  
 1851.25 MHz:        24.82 dBm  
 1880.00 MHz:        25.51 dBm  
 1908.75 MHz:        25.59 dBm

For all measurements, calibration was performed via gain substitution with a half-wave dipole.

BAND/TECHNOLOGY	MAXIMUM EIRP(dBm)	MAXIMUM ERP (dBm)
800 CDMA	24.38	<b>22.24</b>
1900 CDMA	<b>25.59</b>	23.45

**OCCUPIED BANDWIDTH**

CFR Part 2.1049, 22.917, 24.238

**Measurement Procedure**

The RF output port of the equipment under test is directly coupled to the input of the EMC analyzer through a specialized RF connector and a 10dB passive attenuator. The amplitude of the spectrum analyzer is corrected for the attenuator and any other applicable losses. The analyzer is set for Peak Detector and each trace is set for Max Hold. A fully charged battery was used for the supply voltage.

The middle channel within the designated frequency block was measured. For digital modulation, the lower and upper band edge plots are displayed.

**Equipment Settings**

Plot	Equipment Settings					
	Resolution Bandwidth (kHz)	Video Bandwidth (kHz)	Sweep Points (#)	Trace Mode	Detector	Samples (≥ #)
Reference Plot - CDMA 800	3000	Auto	2001	Max Hold	Peak	100
OCBW - CDMA 800	30	Auto	1601	Max Hold	Peak	100
Lower Band Edge - CDMA 800	1	Auto	2004	Max Hold	Peak	30
Upper Band Edge - CDMA 800	1	Auto	2004	Max Hold	Peak	30
Reference Plot - CDMA 1900	300	Auto	1001	Max Hold	Peak	30
OCBW - CDMA 1900	3	Auto	1001	Max Hold	Peak	30
Lower Band Edge - CDMA 1900	1	Auto	2004	Max Hold	Peak	30
Upper Band Edge - CDMA 1900	1	Auto	2004	Max Hold	Peak	30


- Notes: 1) When the video bandwidth is set to Auto the video bandwidth self adjusts for <sup>3</sup> the resolution bandwidth.  
 2) The plotted data shown for the band edge measurements is representative of data taken with a true 3 kHz resolution bandwidth filter. The raw data was taken using a 1 kHz resolution bandwidth and was integrated to produce a response representative of data taken using a true 3 kHz resolution bandwidth filter.

**Measurement Results**


Attached

### Measurement Results – CDMA 800


CDMA 800 Reference Level




CDMA 850 Occupied Bandwidth



### CDMA 800 Ch 1013 Lower Band Edge




### CDMA 800 Ch 777 Upper Band Edge




### Measurement Results – CDMA 1900


CDMA - PCS Channel 600 Reference Level




CDMA - PCS Channel 600 Occupied Bandwidth



CDMA/PCS 1900 Channel 25 Lower Band Edge



CDMA/PCS 1900 Channel 1175 Upper Band Edge



**SPURIOUS EMISSIONS AT ANTENNA TERMINALS**

CFR47 Part 2.1051, 24.238

**Measurement Procedure**

The RF output port of the Equipment Under Test is directly coupled to the input of the EMC analyzer through a specialized RF connector and a 10dB passive attenuator. A fully charged battery was used for the supply voltage.

The spectrum was investigated from the lowest frequency signal generated, without going below 9 kHz, up to at least the tenth harmonic of the fundamental or 40 GHz, whichever is lower.

Measurements were made at the middle channel within the frequency band and within the base station frequency range (869-894 MHz) for cellular.

The spectrum analyzer settings were as follows:

Units	dBm
Divisions	10 dB
Resolution Bandwidth	1 MHz
Video Bandwidth (AVG)	Auto
Sweep Time	Auto


**Measurement Results**

Attached

**Measurement Results**  
**Modulation: CDMA 800**

**Conducted Spurious and Harmonic Emissions**  
**CHANNEL: 1013**


Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
1649.4	-13	*
2474.1	-13	-43.9
3298.8	-13	-38.4
4123.5	-13	-41.3
4948.2	-13	*
5772.9	-13	*
6597.6	-13	*
7422.3	-13	*
8247.0	-13	*



- Notes:
1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
  2. Each emission reported reflects the highest absolute level at maximum power.
  3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Conducted Spurious and Harmonic Emissions**  
**CHANNEL: 384**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
1673.0	-13	*
2509.6	-13	-45.7
3346.1	-13	-40.4
4182.6	-13	-47.5
5019.1	-13	*
5855.6	-13	*
6692.2	-13	*
7528.7	-13	*
8365.2	-13	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Conducted Spurious and Harmonic Emissions**

**CHANNEL: 777**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
1696.6	-13	*
2544.9	-13	-43.2
3393.2	-13	-37.7
4241.6	-13	-46.7
5089.9	-13	*
5938.2	-13	*
6786.5	-13	*
7634.8	-13	*
8483.1	-13	*




**Notes:**

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Measurement Results**  
**Modulation: CDMA 1900**

**Conducted Spurious and Harmonic Emissions**  
**CHANNEL: 25**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
3702.5	-13	-22.1
5553.8	-13	*
7405.0	-13	*
9256.3	-13	*
11107.5	-13	*
12958.8	-13	*
14810.0	-13	*
16661.3	-13	*
18512.5	-13	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Conducted Spurious and Harmonic Emissions**  
**CHANNEL: 600**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
3760.0	-13	-28.5
5640.0	-13	*
7520.0	-13	*
9400.0	-13	*
11280.0	-13	*
13160.0	-13	*
15040.0	-13	*
16920.0	-13	*
18800.0	-13	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Conducted Spurious and Harmonic Emissions**  
**CHANNEL: 1175**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
3817.5	-13	-21.3
5726.3	-13	*
7635.0	-13	-47.2
9543.8	-13	*
11452.5	-13	*
13361.3	-13	*
15270.0	-13	*
17178.8	-13	*
19087.5	-13	*



Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**FIELD STRENGTH OF SPURIOUS EMISSIONS**

CFR47 Part 2.1053, 22.917, 24.238

**Measurement Procedure**

The equipment under test is placed inside the semi-anechoic chamber on a wooden table at the turntable center. For each spurious frequency, the antenna mast is raised and lowered from 1 to 4 meters and the turntable is rotated 360 degrees to obtain a maximum reading on the spectrum analyzer. This is repeated for both horizontal and vertical polarizations of the receive antenna.

The equipment under test is then replaced with a substitution antenna fed by a signal generator. With the signal generator tuned to a particular spurious frequency, the antenna mast is raised and lowered from 1 to 4 meters to obtain a maximum reading at the spectrum analyzer. The output of the signal generator is then adjusted until a reading identical to that obtained with the actual transmitter is achieved.

The power in dBm of each spurious emission is calculated by correcting the signal generator level for cable loss and gain of the substitution antenna referenced to a dipole. A fully charged battery was used for the supply voltage.

The settings of the receiver were as follows:

Units	dBm
Divisions	5 dB
Resolution Bandwidth	1 MHz
Video Bandwidth (AVG)	Auto
Sweep Time	Auto


**Measurement Results**

Attached

**Measurement Results**  
**Modulation: CDMA 800**

**Radiated Spurious and Harmonic Emissions**

Frequency (MHz)	FCC Maximum Limit (dBm)	Horizontal Measured Emission Equiv. Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into Ideal Dipole (dBm)
2nd harmonic	-13	*	*
3rd harmonic	-13	*	*
4th harmonic	-13	*	*
5th harmonic	-13	*	*
6th harmonic	-13	*	*
7th harmonic	-13	*	*
8th harmonic	-13	*	*
9th harmonic	-13	*	*
10th harmonic	-13	*	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
3. The Spectrum was investigated from 30 MHz to the tenth harmonic of the fundamental.

**Measurement Results**  
**Modulation: CDMA 1900**

**Radiated Spurious and Harmonic Emissions**

Frequency (MHz)	FCC Maximum Limit (dBm)	Horizontal Measured Emission Equiv. Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into Ideal Dipole (dBm)
2nd harmonic	-13	-29.4	-26.1
3rd harmonic	-13	*	*
4th harmonic	-13	*	*
5th harmonic	-13	*	*
6th harmonic	-13	*	*
7th harmonic	-13	*	*
8th harmonic	-13	*	*
9th harmonic	-13	*	*
10th harmonic	-13	*	*



Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
3. The Spectrum was investigated from 30 MHz to the tenth harmonic of the fundamental.

## **FREQUENCY STABILITY**

CFR47 Part 2.1055, 24.235

### **Measurement Procedure**

The equipment under test is placed in an environmental chamber. The antenna port of the Equipment Under Test is directly coupled to the input of the measurement equipment through a specialized RF connector. A power supply is attached as the primary voltage supply.

Frequency measurements are made at the extremes of the temperature range  $-30^{\circ}\text{C}$  to  $+60^{\circ}\text{C}$  and at intervals of  $10^{\circ}\text{C}$  with the primary supply voltage set to the nominal battery operating voltage. A period of time sufficient to stabilize all components of the equipment is allowed at each frequency measurement. The maximum variation of frequency is measured.

At room temperature, the primary supply voltage is reduced to the battery operating endpoint of the equipment under test. The maximum variation of frequency is measured. A battery eliminator was used for the input supply voltage.

### **Measurement Results**


Attached

**Measurement Results**  
**Modulation: CDMA 800**

**Frequency Stability**

**Mode:** CDMA 800      **Operating Frequency:** 836.52 MHz  
**Channel:** 384      **Deviation Limit (PPM):** 0.359ppm (+/-300 Hz)

Temperature C	Frequency Error HZ	Frequency Error (PPM)	Voltage (%)	Voltage (VDC)
-30 C	4.78	0.006	100%	3.80
-20 C	3.67	0.004	100%	3.80
-10 C	4.26	0.005	100%	3.80
0 C	3.66	0.004	100%	3.80
10 C	-3.89	-0.005	100%	3.80
20 C	-5.46	-0.007	100%	3.80
30 C	-5.32	-0.006	100%	3.80
40 C	5.50	0.007	100%	3.80
50 C	6.39	0.008	100%	3.80
60 C	7.11	0.008	100%	3.80
20 C	-3.53	-0.004	Battery Endpoint	3.80




Measurement Results

**Modulation: CDMA1900**

**Frequency Stability**

**Mode:** CDMA 1900      **Operating Frequency:** 1880.0 MHz  
**Channel:** 600      **Deviation Limit (PPM):** 0.08ppm (+/-150Hz)

Temperature C	Frequency Error HZ	Frequency Error (PPM)	Voltage (%)	Voltage (VDC)
-30 C	40.13	0.021	100%	3.80
-20 C	11.45	0.006	100%	3.80
-10 C	13.59	0.007	100%	3.80
0 C	10.42	0.006	100%	3.80
10 C	-10.17	-0.005	100%	3.80
20 C	-12.42	-0.007	100%	3.80
30 C	-15.95	-0.008	100%	3.80
40 C	-15.89	-0.008	100%	3.80
50 C	40.35	0.021	100%	3.80
60 C	16.72	0.009	100%	3.80
20 C	-14.17	-0.008	Battery Endpoint	3.80



**FIELD STRENGTH OF EMISSIONS FROM UNINTENTIONAL RADIATORS**

CFR Part 15.109

**Measurement Procedure**

The equipment under test is placed inside the semi-anechoic chamber on a wooden table at the turntable center. For each radiated emission, the antenna mast is raised and lowered from 1 to 4 meters and the turntable is rotated 360 degrees to obtain a maximum peak reading on the spectrum analyzer. The radiated emissions are then measured using an EMI receiver employing a CISPR quasi-peak detector function below 1000 MHz and an average detector function above 1000 MHz. This is repeated for both horizontal and vertical polarizations of the receive antenna. A fully charged battery was used for the supply voltage.

The field strength of each radiated emission is calculated by correcting the EMI receiver level for cable loss, amplifier gain, and antenna correction factors.

$$\text{Field Strength (dBuV/m)} = \text{EMI Receiver Level (dBuV)} + \text{Cable Loss (dB)} - \text{Amplifier Gain (dB)} + \text{Antenna Correction Factor (1/m)}$$

The receiver settings were as follows:

Units	dBuV
Resolution Bandwidth	30 kHz
Video Bandwidth (AVG)	Auto
Sweep Time	auto
Attenuation	10 dB
Detector	Peak

**Measurement Results**


The data represents the worst case results for channel and orientation.

Attached

**Measurement Results**  
**Modulation: CDMA 800**

**Receiver Radiated Spurious Emissions**

Frequency (MHz)	FCC Maximum Limit (dBuV/m)	Horizontal Measured Field Strength (dBuV/m)	Vertical Measured Field Strength (dBuV/m)
Local Oscillator	46	*	*
2nd harmonic	54	*	*
3rd harmonic	54	*	*
4th harmonic	54	*	*
5th harmonic	54	*	*
6th harmonic	40	*	*
7th harmonic	40	*	*
8th harmonic	40	*	*
9th harmonic	40	*	*
10th harmonic	40	*	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific frequency for the low, mid, and high channels.

**Measurement Results**  
**Modulation: CDMA 1900**

**Receiver Radiated Spurious Emissions**

Frequency (MHz)	FCC Maximum Limit (dBuV/m)	Horizontal Measured Field Strength (dBuV/m)	Vertical Measured Field Strength (dBuV/m)
Local Oscillator	54	*	*
2nd harmonic	54	*	*
3rd harmonic	54	*	*
4th harmonic	54	*	*
5th harmonic	54	*	*
6th harmonic	40	*	*
7th harmonic	40	*	*
8th harmonic	40	*	*
9th harmonic	40	*	*
10th harmonic	40	*	*



Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific frequency for the low, mid, and high channels.

**AC LINE CONDUCTED**

CFR 47 Part 15.207


**Measurement Procedure**

Measured levels of ac power line conducted emission shall be the radio-noise voltage from the line probe or across the 50  $\Omega$  LISN port, where permitted, terminated into a 50  $\Omega$  noise meter, or where permitted or required, the radio-noise current on the power line sensed by a current probe.


All radio-noise voltage and current measurements shall be made on each current-carrying conductor at the plug end of the EUT power cord or calibrated extension cord by the use of mating plugs and receptacles on the EUT and LISN. Equipment shall be tested with power cords that are normally supplied using an LISN, the 50  $\Omega$  measuring port is terminated by a 50  $\Omega$  radio-noise meter or a 50  $\Omega$  resistive load. All other ports are terminated in 50  $\Omega$ .

**Measurement Results**


See attached:




800 CDMA Channel 1013 - Tx Mode - Line Coupling




800 CDMA Channel 1013 - Tx Mode - Neutral Coupling




800 CDMA Channel 384 - Tx Mode - Line Coupling




800 CDMA Channel 384 - Tx Mode - Neutral Coupling




800 CDMA Channel 777 - Tx Mode - Line Coupling




800 CDMA Channel 777 - Tx Mode - Neutral Coupling




CDMA PCS Channel 25 - Tx Mode - Line Coupling




CDMA PCS Channel 25 - Tx Mode - Neutral Coupling




CDMA PCS Channel 600 - Tx Mode - Line Coupling



CDMA PCS Channel 600 - Tx Mode - Neutral Coupling




CDMA PCS Channel 1175 - Tx Mode - Line Coupling




CDMA PCS Channel 1175 - Tx Mode - Neutral Coupling

**Appendix A – Radiated Emissions Test Setup Photos**



A.1 Radiated Emissions Measurement



A.2 Substitution Measurement

**End of Test Report**