



**MOTOROLA**

**PERSONAL COMMUNICATIONS SECTOR**

**PRODUCT SAFETY AND COMPLIANCE  
EMC LABORATORY**

**EMC TEST REPORT**

**Test Report Number** – 14290-1

**Report Date** – June 14, 2004

The test results contained herein relate only to the model(s) identified. It is the manufacturer's responsibility to assure that additional production units of this model are manufactured with identical electrical and mechanical characteristics.

As the responsible EMC Engineer, I hereby declare that the equipment tested as specified in this report conforms to the requirements indicated.

A handwritten signature in blue ink that reads "Michael E. Hill".

Signature

Name: Michael E. Hill

Title: Senior Electrical Engineer

Date : 2004-06-14

This report must not be reproduced, except in full, without written approval from this laboratory.

THIS REPORT MUST NOT BE USED TO CLAIM PRODUCT ENDORSEMENT BY A2LA OR ANY AGENCY OF THE U.S. GOVERNMENT.

A2LA Certificate Number: 1846-01



EXHIBIT 6

**Table of Contents**

<u>Description</u>	<u>Page</u>
Test Report Details	4
Applicable Standards	4
Summary of Testing	5
General and Special Conditions	5
Equipment and Cable Configurations	6
Measuring Equipment and Calibration Information	6
Measurement Procedures and Data	
RF Power Output	7
Radiated Power (ERP)	8
AMPS Audio Response	9
Tx Audio Response-AMPS Mode	9
Frequency Deviation w/Compander On	9
Frequency Deviation w/Compander Off	10
Occupied Bandwidth	11
Measurement Results	11
AMPS-Unmodulated Carrier	12
AMPS Supervisory Audio Tone	12
AMPS Voice	13
AMPS Signaling Tone	13
AMPS – 10kb/s Wideband Data	14
AMPS Lower Band Edge	14
AMPS Upper Band Edge	15
CDMA 800 Reference Level Plot	16
CDMA 800 Occupied Bandwidth Plot	17
CDMA 800 Lower Band Edge	17
CDMA 800 Upper Band Edge	18
Spurious Emissions at Antenna Terminals	19
AMPS 800 Tabular and Graphical Data	20
CDMA 800 Tabular and Graphical Data	21
Field Strength of Spurious Emissions	22
AMPS 800 Tabular and Graphical Data	23
CDMA 800 Tabular and Graphical Data	24
Frequency Stability	25
AMPS 800 Tabular and Graphical Data	26
CDMA 800 Tabular and Graphical Data	27

Field Strength of Spurious Emissions from Unintentional Radiators	28
AMPS 800 Tabular and Graphical Data	29
CDMA 800 Tabular and Graphical Data	30
Appendix A - Radiated Emissions Test Setup Photos	
Figure A.1 – Radiated Emissions Measurement	31
Figure A.2 – Substitution Measurement	31

**Test Report Details**

Tests Performed By: Motorola Personal Communications Sector  
Product Safety and Compliance Group  
600 North US Hwy 45  
Libertyville, IL 60048  
PH (847) 523-6167 Fax (561) 523-4538  
Motorola PCS FRN: 0004321311  
FCC Registration Number: 316588  
Industry Canada Number: IC3908

Tests Requested By: Motorola Inc.  
Personal Communications Sector  
600 North US Hwy 45  
Libertyville, IL 60048

Product Type: Cellular Phone

Signaling Capability: AMPS 800 and CDMA 800

Model Number: C215

Version: SJWF0233BA

Serial Numbers: 321E7F63, 321E7F64, 321E7F67, 321E7F69

Testing Complete Date: June 14, 2004

**Applicable Standards**

All tests and measurements indicated in this document were performed in accordance with the Code of Federal Regulations Title 47 Part 2, Sub-part J as well as the following parts:

- Part 15 Subpart B – Unintentional Radiators
- Part 22 Subpart H - Public Mobile Services
- Part 24 - Personal Communications Services
- Part 90 - Private Land Mobile Radio Service

Applicable Standards: TIA EIA 137-A, TIA EIA 98-C, ANSI 63.4 2001, RSS-118 (AMPS), RSS-128 (CDMA), RSS-129 (CDMA), RSS-133 (PCS)

**Summary of Testing**

Test #	Test Name	Pass/Fail
1	RF Power Output	NA
2	ERP (Effective Radiated Power)	NA
3	Modulation Characteristics	Pass
4	Occupied Bandwidth	Pass
5	Spurious Emissions at Antenna Terminal	Pass
6	Field Strength of Spurious Emissions	Pass
7	Frequency Stability	Pass
8	Field Strength of Spurious Emissions from Unintentional Radiators	Pass

Test #	Test Name	Margin with respect to the Limit
1	RF Power Output	NA
2	ERP (Effective Radiated Power)	NA
3	Modulation Characteristics	NA
4	Occupied Bandwidth	See Plots
5	Spurious Emissions at Antenna Terminal	12.5 dB
6	Field Strength of Spurious Emissions	3.5 dB
7	Frequency Stability	59.0 Hz
8	Field Strength of Spurious Emissions from Unintentional Radiators	9.2 dB

The margin with respect to the limit is the minimum margin for all modes and bands. ( ) indicates the margin at which the product exceeds the limit.

**General and Special Conditions**

The EUT was tested using a fully charged battery when applicable. Where a battery could not be used due to the need for a controlled variation of input voltage, an external power supply was utilized.

All testing was done in an indoor controlled environment with an average temperature of 22° C and relative humidity of 50%.

**Equipment and Cable Configurations**

The EUT was tested in a stand-alone configuration that is representative of typical use.

**Measuring Equipment and Calibration Information**

<b>Manufacturer</b>	<b>Equipment Type</b>	<b>Model No.</b>	<b>Serial Number</b>	<b>Cal. Due Date</b>
Rohde & Schwarz	Receiver	ESI26	838786/010	5/17/2005
Hewlett-Packard	EMC Analyzer	8593EM	3536A00118	10/2/2004
Hewlett-Packard	EMC Analyzer	7405	US39440191	11/13/2004
Miteq	Preamplifier 0.1-26.5GHz	NSP2650-NF-S	966350	1/8/2005
ETS	DRG Horn Antenna	3115	6222	<b>9/29/2004</b>
A.H. Systems Inc.	DRG Horn Antenna	SAS-2--/571	365	12/17/2004
ETS	Log-Periodic Antenna	3148	1188	3/5/2005
ETS	Biconical Antenna	3110B	3370	11/14/2004
Attenuator	Weinschel	AS-6	6675	10/14/2004
Attenuator	Weinschel	AS-6	6677	11/4/2004
Rohde & Schwarz	Mobile Test Set	CMD 80	DE29008	N/A
Hewlett-Packard	Signal Generator	83623B	3844A01195	6/20/2004
Thermotron	Environmental Chamber	S-4	31580	1/5/2005
Hewlett-Packard	Pre-Amplifier	8347A	3307A02001	11/4/2004
Agilent	Power Meter	EE4418B	GB40206388	12/5/2004
Agilent	Power Sensor	E4412B	US38486321	11/23/2004
Hewlett-Packard	Pre-Amplifier	8447F	2805A03419	5/19/2005

All equipment is on a one-year calibration cycle.

**Measurement Procedures and Data**

**RF POWER OUTPUT**

**Measurement Procedure**

The RF output port of the equipment under test is directly coupled to the input of a HPE4406A Vector Signal Analyzer through a 10dB passive attenuator, adaptor (if needed), and specialized RF connector. The peak power output is measured for all channels.

CFR Part 2.1046

**Measurement Results**

**AMPS 800**

Frequency (MHz)	Power (dBm)
824.04	27.55
836.52	27.44
848.97	27.61

**CDMA 800**

Frequency (MHz)	Power (dBm)
824.70	24.91
836.52	25.08
848.31	25.08

## **RADIATED POWER (ERP)**

### **Measurement Procedure**

The phone was tested in a 16' anechoic chamber with a 2-axis position system that permits taking complete spherical scans of the EUT's radiation patterns. For all tests, the phone was supported in a free space type environment, vertically oriented in the chamber. Tests were done for AMPS 800 three frequencies (824.04, 836.52 and 848.97MHz) and CDMA 800 three frequencies (824.04, 836.52 and 848.97 MHz).

CDMA measurements were made with the phone placed in a call using the HP8922M mobile station test set. The phone was weakly coupled to the test set and configured to transmit in full data rate mode. Radiated power was measured at each 15 degree step. The radiated power was measured using a Gigatronics 8542C power meter in "Mod Avg" mode. From these measurements, the software calculates the angle at which maximum radiated power occurs for each case, and the radiated power at this angle was extracted from the data. The max radiated power results for the IHDT5EH1 follows, as EIRP in dBm. To get ERP (effective radiated power referenced to a half-wave dipole), subtract 2.1 dB from these numbers.

### **Measurement Results**

#### **AMPS 800**

824.04 MHz: 24.93 dBm

836.52 MHz: 24.77 dBm

848.97 MHz: 24.75 dBm

#### **CDMA 800**

824.70 MHz: 24.95 dBm

836.52 MHz: 24.29 dBm

848.31 MHz: 24.12 dBm


For all measurements, calibration was performed via gain substitution with a half-wave dipole.

Max EIRP in AMPS 800 is 24.93 dBm (**max ERP is 22.83 dBm**).


Max EIRP in CDMA 800 is 24.95 dBm (**max ERP is 22.85 dBm**).

### AMPS Audio Response


#### Tx Audio Response – AMPS Mode



#### Frequency Deviation with Compander On



### Frequency Deviation with Compander Off



## **OCCUPIED BANDWIDTH**

CFR Part 2.1049, 22.917, 24.238

### **Measurement Procedure**

The RF output port of the equipment under test is directly coupled to the input of the EMC analyzer through a specialized RF connector and a 10dB passive attenuator. The amplitude of the spectrum analyzer is corrected for the attenuator and any other applicable losses. The analyzer is set for Peak Detector and each trace is set for Max Hold. A fully charged battery was used for the supply voltage.


The middle channel within the designated frequency block was measured. For digital modulation, the lower and upper band edge plots are displayed.

### **Measurement Results**


Attached

### Measurement Results – AMPS


#### AMPS - Unmodulated Carrier – Channel 384 (836.52 MHz)




#### AMPS - Supervisory Audio Tone – Channel 384 (836.52 MHz)




**AMPS - Voice – Channel 384 (836.52 MHz)**




**AMPS – Signaling Tone – Channel 384 (836.52 MHz)**




**AMPS – 10kb/s Wideband Data – Channel 384 (836.52 MHz)**



**AMPS – Lower Band Edge – Channel 991 (824.04 MHz)**




### AMPS – Upper Band Edge – Channel 799 (848.97 MHz)




### Measurement Results – CDMA 800


#### CDMA 800 – Reference Level Plot – Channel 384 (836.52 MHz)




#### CDMA 800 – Channel 384 (836.52 MHz)




**CDMA 800 – Channel 384 (836.52 MHz) – Occupied Bandwidth**



**CDMA 800 – Lower Band Edge – Channel 1013 (824.7 MHz)**



### CDMA 800 – Upper Band Edge – Channel 777 (848.31 MHz)



## **SPURIOUS EMISSIONS AT ANTENNA TERMINALS**

CFR Part 2.1051, 22.917, 24.238

### **Measurement Procedure**

The RF output port of the Equipment Under Test is directly coupled to the input of the EMC analyzer through a specialized RF connector and a 10dB passive attenuator. A fully charged battery was used for the supply voltage.

The spectrum was investigated from the lowest frequency signal generated, without going below 9 kHz, up to at least the tenth harmonic of the fundamental or 40 GHz, whichever is lower.

Measurements were made at the middle channel within the frequency band and within the base station frequency range (869-894 MHz) for cellular.

The spectrum analyzer settings were as follows:

Units	dBm
Divisions	10 dB
Resolution Bandwidth	1 MHz
Video Bandwidth (AVG)	Auto
Sweep Time	Auto


### **Measurement Results**

Attached

**Measurement Results**  
**Modulation: AMPS 800**

**Conducted Spurious and Harmonic Emissions**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
2nd harmonic	-13	-25.5
3rd harmonic	-13	-30.1
4th harmonic	-13	-33.3
5th harmonic	-13	-35.8
6th harmonic	-13	-35.9
7th harmonic	-13	-43.4
8th harmonic	-13	-35.4
9th harmonic	-13	-50.5
10th harmonic	-13	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**Measurement Results**  
**Modulation: CDMA 800**

**Conducted Spurious and Harmonic Emissions**

Harmonic of Fundamental	FCC Maximum Limit (dBm)	Conducted Emission (dBm)
2nd harmonic	-13	-26.2
3rd harmonic	-13	-32.7
4th harmonic	-13	-37.4
5th harmonic	-13	-44.1
6th harmonic	-13	-38.4
7th harmonic	-13	-52.5
8th harmonic	-13	-45.9
9th harmonic	-13	*
10th harmonic	-13	*



Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
3. The Spectrum was investigated from 9 kHz to the tenth harmonic of the fundamental.

**FIELD STRENGTH OF SPURIOUS EMISSIONS**

CFR Part 2.1053, 24.238

**Measurement Procedure**

The equipment under test is placed inside the semi-anechoic chamber on a wooden table at the turntable center. For each spurious frequency, the antenna mast is raised and lowered from 1 to 4 meters and the turntable is rotated 360 degrees to obtain a maximum reading on the spectrum analyzer. This is repeated for both horizontal and vertical polarizations of the receive antenna.

The equipment under test is then replaced with a substitution antenna fed by a signal generator. With the signal generator tuned to a particular spurious frequency, the antenna mast is raised and lowered from 1 to 4 meters to obtain a maximum reading at the spectrum analyzer. The output of the signal generator is then adjusted until a reading identical to that obtained with the actual transmitter is achieved.

The power in dBm of each spurious emission is calculated by correcting the signal generator level for cable loss and gain of the substitution antenna referenced to a dipole. A fully charged battery was used for the supply voltage.

The settings of the receiver were as follows:

Units	dBm
Divisions	5 dB
Resolution Bandwidth	1 MHz
Video Bandwidth (AVG)	Auto
Sweep Time	Auto


**Measurement Results**

Attached

**Measurement Results**  
**Modulation: AMPS 800**

**Radiated Spurious and Harmonic Emissions**

Frequency (MHz)	FCC Maximum Limit (dBm)	Horizontal Measured Emission Equiv. Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into Ideal Dipole (dBm)
2nd harmonic	-13	-29.2	-39.1
3rd harmonic	-13	-21.9	-30.1
4th harmonic	-13	-22.3	-27.3
5th harmonic	-13	*	*
6th harmonic	-13	-39.4	-46.6
7th harmonic	-13	-42.3	*
8th harmonic	-13	-40.7	*
9th harmonic	-13	*	*
10th harmonic	-13	*	*




Notes:

- \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
- Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
- The Spectrum was investigated from 30 MHz to the tenth harmonic of the fundamental.

**Measurement Results**  
**Modulation: CDMA 800**

**Radiated Spurious and Harmonic Emissions**

Frequency (MHz)	FCC Maximum Limit (dBm)	Horizontal Measured Emission Equiv. Pwr Into Ideal Dipole (dBm)	Vertical Measured Emission Equiv Pwr Into Ideal Dipole (dBm)
2nd harmonic	-13	-34.2	-38.0
3rd harmonic	-13	-16.5	-23.9
4th harmonic	-13	-19.8	-22.3
5th harmonic	-13	*	*
6th harmonic	-13	-38.3	*
7th harmonic	-13	*	*
8th harmonic	-13	*	*
9th harmonic	-13	*	*
10th harmonic	-13	*	*



Notes:

- \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
- Each emission reported reflects the highest absolute level at the specific harmonic for the low, mid, and high channels at maximum power.
- The Spectrum was investigated from 30 MHz to the tenth harmonic of the fundamental.

## **FREQUENCY STABILITY**

CFR Part 2.1055, 24.235

### **Measurement Procedure**

The equipment under test is placed in an environmental chamber. The antenna port of the Equipment Under Test is directly coupled to the input of the measurement equipment through a specialized RF connector. A power supply is attached as the primary voltage supply.

Frequency measurements are made at the extremes of the temperature range -30° C to +60° C and at intervals of 10° C with the primary supply voltage set to the nominal battery operating voltage. A period of time sufficient to stabilize all components of the equipment is allowed at each frequency measurement. The maximum variation of frequency is measured.

At room temperature, the primary supply voltage is reduced to the battery operating endpoint of the equipment under test. The maximum variation of frequency is measured. A battery eliminator was used for the input supply voltage.

### **Measurement Results**


Attached

**Measurement Results**  
**Modulation: AMPS 800**

**Frequency Stability**

Mode: Analog      Operating Frequency: 836.52 MHz  
 Channel: 384      Deviation Limit (PPM): 2.5ppm

Temperature C	Frequency Error HZ	Frequency Error (PPM)	Voltage (%)	Voltage (VDC)
-30 C	50.00	0.060	100%	3.70
-20 C	49.00	0.059	100%	3.70
-10 C	49.00	0.059	100%	3.70
0 C	48.00	0.057	100%	3.70
10 C	51.00	0.061	100%	3.70
20 C	49.00	0.059	100%	3.70
30 C	53.00	0.063	100%	3.70
40 C	51.00	0.061	100%	3.70
50 C	59.00	0.071	100%	3.70
60 C	49.00	0.059	100%	3.70
20 C	50.00	0.060	Battery Endpoint	3.20




**Measurement Results**  
**Modulation: CDMA 800**

**Frequency Stability**

**Mode:** CDMA 800      **Operating Frequency:** 836.52 MHz  
**Channel:** 384      **Deviation Limit (PPM):** 0.359ppm (+/-300 Hz)

Temperature C	Frequency Error HZ	Frequency Error (PPM)	Voltage (%)	Voltage (VDC)
-30 C	9.00	0.011	100%	3.70
-20 C	-8.00	-0.010	100%	3.70
-10 C	-5.00	-0.006	100%	3.70
0 C	4.00	0.005	100%	3.70
10 C	8.00	0.010	100%	3.70
20 C	7.00	0.008	100%	3.70
30 C	8.00	0.010	100%	3.70
40 C	8.00	0.010	100%	3.70
50 C	7.00	0.008	100%	3.70
60 C	9.00	0.011	100%	3.70
		0		
20 C	6.00	0.007	Battery Endpoint	3.20



## **FIELD STRENGTH OF EMISSIONS FROM UNINTENTIONAL RADIATORS**

CFR Part 15.109

### **Measurement Procedure**

The equipment under test is placed inside the semi-anechoic chamber on a wooden table at the turntable center. For each radiated emission, the antenna mast is raised and lowered from 1 to 4 meters and the turntable is rotated 360 degrees to obtain a maximum peak reading on the spectrum analyzer. The radiated emissions are then measured using an EMI receiver employing a CISPR quasi-peak detector function below 1000 MHz and an average detector function above 1000 MHz. This is repeated for both horizontal and vertical polarizations of the receive antenna. A fully charged battery was used for the supply voltage.

The field strength of each radiated emission is calculated by correcting the EMI receiver level for cable loss, amplifier gain, and antenna correction factors.

$$\text{Field Strength (dBuV/m)} = \text{EMI Receiver Level (dBuV)} + \text{Cable Loss (dB)} - \text{Amplifier Gain (dB)} + \text{Antenna Correction Factor (1/m)}$$

The receiver settings were as follows:

Units	dBuV
Resolution Bandwidth	30 kHz
Video Bandwidth (AVG)	Auto
Sweep Time	auto
Attenuation	10 dB


### **Measurement Results**

Attached

**Measurement Results**  
**Modulation: AMPS 800**

**Receiver Radiated Spurious Emissions**

Frequency (MHz)	FCC Maximum Limit (dBuV/m)	Horizontal Measured Field Strength (dBuV/m)	Vertical Measured Field Strength (dBuV/m)
Local Oscillator	54	*	*
2nd harmonic	54	*	*
3rd harmonic	54	42.7	43.9
4th harmonic	54	*	*
5th harmonic	54	*	*
6th harmonic	54	*	*
7th harmonic	54	*	*
8th harmonic	54	*	*
9th harmonic	54	*	*
10th harmonic	54	*	*




Notes:

- \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
- Each emission reported reflects the highest absolute level at the specific frequency for the low, mid, and high channels.

**Measurement Results**  
**Modulation: CDMA 800**

**Receiver Radiated Spurious Emissions**


Frequency (MHz)	FCC Maximum Limit (dBuV/m)	Horizontal Measured Field Strength (dBuV/m)	Vertical Measured Field Strength (dBuV/m)
Local Oscillator	54	43.5	43.3
2nd harmonic	54	*	*
3rd harmonic	54	*	44.8
4th harmonic	54	*	*
5th harmonic	54	*	*
6th harmonic	54	*	*
7th harmonic	54	*	*
8th harmonic	54	*	*
9th harmonic	54	*	*
10th harmonic	54	*	*




Notes:

1. \* Indicates the spurious emission could not be detected due to noise limitations or ambients.
2. Each emission reported reflects the highest absolute level at the specific frequency for the low, mid, and high channels.

**Appendix A – Radiated Emissions Test Setup Photos**



A.1 Radiated Emissions Measurement



A.2 Substitution Measurement

**End of Test Report**