

Logitech

Antenna Under Test (AUT)

Report

Model Name: SR0194

Equipment Type: Bluetooth speakers

Manufacturer: Logitech Far East LTD.

Test Location: Room 101, Building 1, No. 3, Nanfang 1st Road, Chigang,
Humen Town, Dongguan City, Guangdong Province

Tested by: South Star

Report Date: 2022.09.02

Report Release History

| Report version | Description | Date Issued |
|----------------|------------------|-------------|
| SR0194 Report | Original release | 2022/09/02 |

Table of Contents

| | |
|--|---|
| 1. EUT Antenna Information..... | 3 |
| 2. S-parameter Measured and Calculation of Antenna Gain..... | 3 |
| 3. 2D&3D Radiation Patten Measurement..... | 4 |
| 3.1Description of the anechoic chamber | 4 |
| 3.2 Test Instruments..... | 5 |
| 3.3 Test Procedure..... | 6 |
| 3.4 Test Setup photos | 7 |
| 3.5 2D Pattern Test Plot | 7 |
| 3.6 3D Pattern Test Plot | 8 |

1. EUT Antenna Information

- 1) Antenna Material : PCB on board
- 2) Antenna Type : PIFA
- 3) Antenna Dimension: 30 x 9 mm
- 4) Operating Frequency : 2.4 GHz - 2.4835 GHz
- 5) Input Impedance : 50 Ω
- 6) Standing-Wave Ratio : 2:1

2. S-parameter Measured and Calculation of Antenna Gain




| Passive Test For BT | | |
|---------------------|----------|------------|
| Freq (MHz) | Effi (%) | Gain (dBi) |
| 2400 | 69.22 | 2.39 |
| 2410 | 67.41 | 2.25 |
| 2420 | 68.15 | 2.19 |
| 2430 | 69.33 | 2.18 |
| 2440 | 70.23 | 2.29 |
| 2450 | 70.6 | 2.31 |
| 2460 | 68.5 | 2.14 |
| 2470 | 67.09 | 1.98 |
| 2480 | 67.13 | 2.08 |
| 2490 | 69.08 | 2.29 |
| 2500 | 71.07 | 2.54 |

Test Date: 2022.09.02

3. 2D&3D Radiation Patten Measurement

3.1 Description of the anechoic chamber

Length: 7m
Width: 4m
Height: 3m
Turntable height:1.5m
Measurement antenna height:1.5m



Microwave anechoic chamber model:ETS-743
TD-SCDMA test equipment: StarPoint SP6010/Agilent 8960
WCDMA/GSM/CDMA test equipment: Agilent 8960
Antenna passive testing equipment: Agilent Technologies E5071B



3.2 Test Instruments

| Description | Model No. | Serial No. | Last Calibration |
|------------------------------|-----------|-----------------|------------------|
| Network Analyzer Keysight | E5071B | NDX-WJ294 | 2022-04-22 |
| Communications test Seta | CMW500 | NDX-WJ295 | 2022-04-22 |
| 3D Chamber Test System | ETS-743 | NDX-03 | 2022-04-24 |
| Software | SAM | SAM2.9.10190809 | NA |

3.3 Test Procedure


1. Connect the antenna: Place the device to be tested on the test transfer stand, the antenna is connected to the port of the network analyzer via the RF Cable, and confirmed that the connection is reliable.
2. Set test conditions: Enter the measurement frequency band in the test software according to the antenna working frequency band, and the measurement frequency point.
3. Measure antenna gain: The gain of the antenna to be tested is compared with the standard gain of the known antenna, so as to obtain the gain of DUT antenna.
4. Calculate antenna passive efficiency: Dividing the measured gain value by the antenna's directivity factor gives the antenna efficiency
5. Generate test report: Target the test results and analysis conclusions into test reports, and file and save.

3.4 Test Setup photos

(confidential)

3.5 2D Pattern Test Plot


2D radiation pattern measurement in the anechoic chamber




3.6 3D Pattern Test Plot

3D radiation pattern measurement in the anechoic chamber

2400.000MHz



2450.000MHz



2500.000MHz

