

# RF EXPOSURE REPORT

**REPORT NO.:** SA930910L07A

**MODEL NO.:** F6D3000

**ACCORDING:** FCC Guidelines for Human Exposure  
IEEE C95.1

**APPLICANT:** Belkin Corporation

**ADDRESS:** 501 West Walnut Avenue Compton, CA 90220

**ISSUED BY:** Advance Data Technology Corporation

**LAB ADDRESS:** 47 14th Ling, Chia Pau Tsuen, Lin Kou Hsiang  
244, Taipei Hsien, Taiwan, R.O.C.

**TEST LOCATION:** No. 19, Hwa Ya 2nd Rd., Wen Hwa Tsuen,  
Kwei Shan Hsiang, Taoyuan Hsien 333,  
Taiwan, R.O.C.

## RF Exposure Measurement (Mobile Device)

### 1. Introduction

In this document, we try to prove the safety of radiation harmfulness to the human body for our product. The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The Gain of the antenna used in this product is measured in a Fully Anechoic Chamber (FAC) calibrated for antenna measurement in ADT, and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis transmission formula is a far field assumption, the calculated result of that is an over-prediction for near field power density. We will take that as the worst case to specify the safety range.

### 2. RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of human exposure to radio-frequency (RF) radiation as specified in 1.1307(b)

#### LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm <sup>2</sup> )	Average Time (minutes)
<b>(A)Limits For Occupational / Control Exposures</b>				
300-1500	...	...	F/300	6
1500-100,000	...	...	5	6
<b>(B)Limits For General Population / Uncontrolled Exposure</b>				
300-1500	...	...	F/1500	6
1500-100,000	...	...	1.0	30

F = Frequency in MHz

### 3. Friis Formula

Friis transmission formula :  $P_d = (P_{out} * G) / (4 * \pi * r^2)$

where

$P_d$  = power density in mW/cm<sup>2</sup>

$P_{out}$  = output power to antenna in mW

$G$  = gain of antenna in linear scale

$\pi$  = 3.1416

$R$  = distance between observation point and center of the radiator in cm

If we know the maximum Gain of the antenna and the total power input to the antenna, through the calculation, we will know the MPE value at distance 20cm.

Ref. : David K. Cheng, *Field and Wave Electromagnetics*, Second Edition, Page 640, Eq. (11-133).

### 4 EUT Operating condition

The software provided by Manufacturer enabled the EUT to transmit and receive data at lowest, middle and highest channel individually.

### 5. Classification

This device is not fixed inside the host equipment, it is connected with host through wire. So it is easy to be re-located in the place where at least 20cm far away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance with the antenna should be included in users manual. So, this device is classified as **Mobile Device**.

## 6 Test Results

### 6.1 Antenna Gain

The maximum Gain measured in Fully Anechoic Chamber are 1.0dBi or 1.259 (numeric) for 2.4GHz, 2.0dBi or 1.585 (numeric) for 5GHz.

### 6.2 Output Power Into Antenna & RF Exposure Distance:

For 802.11b (2.4GHz Band):

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	2412	63.387	0.0159	1.0
6	2437	63.096	0.0158	1.0
11	2462	63.241	0.0158	1.0

Turbo mode

For 802.11g (2.4GHz Band):

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
6	2437	28.774	0.0072	1.0

For 802.11a

Normal mode:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	5180	32.137	0.0101	1.0
4	5240	32.137	0.0101	1.0
5	5260	32.359	0.0102	1.0
8	5320	31.623	0.0100	1.0
9	5745	18.281	0.0058	1.0
12	5805	18.365	0.0058	1.0

Turbo mode:

Channel	Channel Frequency (MHz)	Output Power to Antenna (mW)	Power Density (mW/cm <sup>2</sup> )	Limit of Power Density (mW/cm <sup>2</sup> )
1	5210	32.285	0.0102	1.0
2	5250	32.285	0.0102	1.0
3	5290	32.137	0.0101	1.0
4	5760	18.239	0.0058	1.0
5	5800	17.824	0.0056	1.0

**Note:** Both of the 2.4GHz and 5GHz bands can not transmit simultaneously, the maximum power density value is 0.0159mW/cm<sup>2</sup> (for 2.4GHz) and 0.0102mW/cm<sup>2</sup> (for 5GHz) which is less than the 1mW/cm<sup>2</sup> limit.