

RF Exposure Report

FCC ID: ML6WT26

RF Exposure Measurement

The limit for Maximum Permissible Exposure (MPE) specified in FCC 1.1310 is followed. The gain of the antennas used in the product is extracted from the Antenna data sheets provided and also the maximum total power input to the antenna is measured. Through the Friis transmission formula and the maximum gain of the antenna, we can calculate the distance, away from the product, where the limit of MPE is reached.

Although the Friis Transmission formula is far field assumption, the calculated result of that is an over-prediction for near field power density. It is taken as worst case to specify the safety range.

RF Exposure Limit

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environmental impact of the human exposure to radio-frequency (RF) radiation as specified in 1.1307 (b)

Frequency Range (MHz)	Electric Field Strength (V/m)	Magnetic Field Strength (A/m)	Power Density (mW/cm ²)
Limits for Occupational / controlled Exposures			
300 - 1500	--	--	F/300
1500 – 100000	--	--	5.0
Limits for General population / Uncontrolled Exposure			
300 - 1500	--	--	F/1500
1500 – 100000	--	--	1.0
Limits for Maximum Permissible Exposure (MPE)			

F= Frequency in MHz

Friss Formula

Friss Transmission Formula: $P_d = (P_{out} * G) / (4\pi r^2)$

Where

P_d = power density in mW/cm^2

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

$\pi = 3.1416$

R = Distance between observation point and the center of radiator in cm

If we know the maximum gain of the antenna and the total output power to the antenna, through calculation, we will know MPE value at distance 20cm.

EUT Operation condition

EUT was enabled to transmit and receive at lowest, middle and highest channels.

Classification

The antenna of this product, under normal use condition, is at least 20cm away from the body of the user. Warning statement to the user for keeping at least 20cm or more separation distance from the antenna should be included in the User manual. So, this device is classified as Mobile device.

1. BT

Mode	2402-2480MHz
Detector	PEAK
GFSK	3±1dBm

ANT Gain (G)

Antenna gain : 5dBi (gain of antenna in linear scale=3.16

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
GFSK	3.16	2402	4	2.5119	0.00158	1

2. LORA

Mode	Uplink: 902.3~914.9MHz Downlink:923.3~927.5MHz
Detector	Conducted
Uplink	22±1dBm
Downlink	22±1dBm

ANT Gain (G)

Antenna gain : 5dBi (gain of antenna in linear scale=3.16

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
Uplink	3.16	903.9	23	199.5262	0.12550	1
Downlink	3.16	923.3	23	199.5262	0.12550	1

3. 2.4G WIFI

Mode	802.11b/g/n20: 2412-2462MHz
Detector	PEAK
802.11b	15±1dBm
802.11g	15±1dBm
802.11n20	14±1dBm

ANT Gain (G)

Antenna gain : 5dBi (gain of antenna in linear scale=3.16

Protocol	ANT Gain(gain of antenna in linear scale)	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 b	3.16	2437	16	39.8107	0.02504	1
802.11 g	3.16	2437	16	39.8107	0.02504	1
802.11 n20	3.16	2437	15	31.6228	0.01989	1

4. 5G WIFI

ANT Gain (G)

Mode	IEEE 802.11a/n(HT20) 5.180GHz-5.240GHz IEEE 802.11n(HT40) 5.190GHz-5.310GHz
Detector	AV
802.11 a/n(HT20)	3±1dBm
802.11 n(HT40)	3±1dBm

ANT Gain (G)

Antenna gain : 5dBi (gain of antenna in linear scale=3.16

Protocol	ANT Gain(gain of antenna in linear	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a/n(HT20)	3.16	5240	4	2.5119	0.00158	1
802.11 n(HT40)	3.16	5230	3	1.9953	0.00125	1

5G WIFI

ANT Gain (G)

Mode	IEEE 802.11a/n(HT20)5.745GHz-5.825GHz IEEE 802.11n(HT40)5.755GHz-5.795GHz
Detector	PEAK
802.11 a/n(HT20)	1±1dBm
802.11 n(HT40)	1±1dBm

ANT Gain (G)

Antenna gain : 5dBi (gain of antenna in linear scale=3.16

Protocol	ANT Gain(gain of antenna in linear	Channel Frequency (MHz)	Output Power to Antenna (dBm)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
802.11 a/n(HT20)	3.16	5825	2	1.5849	0.00100	1
802.11 n(HT40)	3.16	5795	2	1.5849	0.00100	1

5. Evaluate Simultaneous

Protocol	ANT Gain(gain of antenna in linear scale)	Output Power to Antenna (mW)	Power Density (mW/cm ²)	Limit (mW/cm ²)
BT+WIFI+LORA	3.16	2.5119+199.5262+39.8107=241.8488	0.152041	1

1. Bluetooth, WIFI and Lora can be TX simultaneously.
2. 2.4 WIFI and 5G WIFI can't be TX simultaneously.