

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A

TABLE OF CONTENTS

TEST REPORT CONTAINING:

PAGE 1-2.....TEST EQUIPMENT LIST AND TEST PROCEDURE
PAGE 3.....15.214(d) - SECURITY CODING INFORMATION AND
BASE UNIT CIRCUIT DESCRIPTION
PAGE 4.....HANDSET UNIT CIRCUIT DESCRIPTION
PAGE 5.....RADIATION INTERFERENCE TEST DATA - BASE
PAGE 6.....RADIATION INTERFERENCE TEST DATA - HANDSET
PAGE 7.....OCCUPIED BANDWIDTH TEST DATA
PAGE 8.....POWERLINE CONDUCTED TEST DATA

EXHIBITS CONTAINING:

EXHIBIT 1.....POWER OF ATTORNEY LETTER
EXHIBIT 2.....SECURITY CODE INFORMATION
EXHIBIT 3A.....BLOCK DIAGRAM - BASE MAIN
EXHIBIT 3B.....BLOCK DIAGRAM - BASE RF
EXHIBIT 3C.....BLOCK DIAGRAM - HANDSET MAIN
EXHIBIT 3D.....BLOCK DIAGRAM - HANDSET RF
EXHIBIT 4A.....SCHEMATIC - BASE MAIN
EXHIBIT 4B.....SCHEMATIC - BASE RF
EXHIBIT 4C.....SCHEMATIC - HANDSET MAIN
EXHIBIT 4D.....SCHEMATIC - HANDSET RF
EXHIBIT 5.....FCC ID LABEL SAMPLES
EXHIBIT 6.....SKETCH OF FCC ID LABEL LOCATIONS
EXHIBIT 7A.....EXTERNAL PHOTO - FRONT HANDSET AND BASE
EXHIBIT 7B.....EXTERNAL PHOTO - FRONT BASE AND REAR HANDSET
EXHIBIT 7C.....EXTERNAL PHOTO - REAR HANDSET WITHOUT BATTERY COVER
EXHIBIT 7D.....EXTERNAL PHOTO - REAR HANDSET WITH BATTERY COVER
EXHIBIT 7E.....EXTERNAL PHOTO - REAR HANDSET AND BASE BOTTOM
EXHIBIT 7F.....EXTERNAL PHOTO - HANDSET SITTING IN BASE UNIT
EXHIBIT 7G.....INTERNAL COMPONENT VIEW PHOTO - BASE AND HANDSET
EXHIBIT 7H.....INTERNAL SOLDER SIDE PHOTO - BASE AND HANDSET
EXHIBIT 7I.....EXTERNAL PHOTO - TOP SIDE BASE UNIT
EXHIBIT 8A-80..INSTRUCTION MANUAL
EXHIBIT 9.....OCCUPIED BANDWIDTH PLOT-LOWEST FREQ. NO AUDIO - BASE
EXHIBIT 10.....OCCUPIED BANDWIDTH PLOT-2500 Hz TONE - BASE
EXHIBIT 11.....OCCUPIED BANDWIDTH PLOT-HIGHEST FREQ - HANDSET
EXHIBIT 12.....OCCUPIED BANDWIDTH PLOT-HIGHEST FREQ - LOUD VOICE -HS
EXHIBIT 13.....POWERLINE CONDUCTED PLOT - LINE 1
EXHIBIT 14.....POWERLINE CONDUCTED PLOT - LINE 2

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A

REPORT #: F:\CUS\S\SHINW00\SHI321B8.RPT

PAGE: TABLE OF CONTENTS

TEST EQUIPMENT LIST

1. Spectrum Analyzer: Hewlett Packard 8566B - Opt 462, w/ preselector 85685A, & Quasi-Peak Adapter HP 85650A, & HP 8449B - OPT H02 Cal. 6/26/98
2. Signal Generator, Hewlett Packard 8640B, cal. 10/1/98
3. Eaton Biconnical Antenna Model 94455-1
20-200 MHz Serial No. 0997 Cal. 5/15/98
4. Electro-Metric Dipole Kit, 20-1000 MHz, Model TDA-30 10/15/98
5. Electro-Metric Horn 1-18 GHz, Model RGA-180, Cal. 8/15/98
6. Electro-Metric Antennas Model TDS-25-1, TDS-25-2, 5/15/97
7. Electro-Metric Line Impedance Stabilization Network Model No. EM-7821, Serial No. 101; 100KHz-30MHz 50uH. 12/3/97
8. Electro-Metric Line Impedance Stabilization Network Model No. EM-7820, Serial No. 2682; 10KHz-30MHz 50uH. 12/3/97
9. Special low loss cable was used above 1 GHz

TEST PROCEDURE

GENERAL: This report shall NOT be reproduced except in full without the written approval of TIMCO ENGINEERING, INC.

RADIATION INTERFERENCE: The test procedure used was ANSI STANDARD C63.4-1992 using a HEWLETT PACKARD spectrum analyzer with a preselector. The bandwidth of the spectrum analyzer was 100 kHz with an appropriate sweep speed. The analyzer was calibrated in dB above a microvolt at the output of the antenna. The resolution bandwidth was 100KHz and the video bandwidth was 300KHz. The ambient temperature of the UUT was 83oF with a humidity of 75%.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 1

TEST PROCEDURE (CONT)

ANSI STANDARD C63.4-1992 10.1.7 MEASUREMENT PROCEDURES: The UUT was placed on a table 80 cm high and with dimensions of 1m by 1.5m. The UUT was placed flush with the back of the table (1.5m side). The table used for radiated measurements is capable of continuous rotation.

When an emission was found, the table was rotated to produce the maximum signal strength. At this point, the antenna was raised and lowered from 1m to 4m. The antenna was placed in both the horizontal and vertical planes.

The situation was similar for the conducted measurement except that the table did not rotate. The EUT was setup as described in ANSIC63.4-1992 with the EUT 40 cm from the vertical ground wall.

FORMULA OF CONVERSION FACTORS: The Field Strength at 3m was established by adding the meter reading of the spectrum analyzer (which is set to read in units of dBuV) to the antenna correction factor supplied by the antenna manufacturer. The antenna correction factors are stated in terms of dB. The gain of the Preselector was accounted for in the Spectrum Analyzer Meter Reading.

Example:

Freq (MHz)	METER READING + ACF = FS
33	20 dBuV + 10.36 dB = 30.36 dBuV/m @ 3m

POWER LINE CONDUCTED INTERFERENCE: The procedure used was ANSI STANDARD C63.4-1992 using a 50uH LISN. Both lines were observed. The bandwidth of the spectrum analyzer was 10kHz with an appropriate sweep speed. The ambient temperature of the UUT was 83oF with a humidity of 75%.

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A

REPORT #: F:\CUS\S\SHINW00\SHI321B8.RPT

PAGE #: 2

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A

SECURITY CODING INFORMATION

15.214(d) - THIS DEVICE COMPLIES WITH THE SECURITY CODE REQUIREMENTS OF 15.214(d)(1)(2) AND (3). SEE INFORMATION IN EXHIBIT 2.

CIRCUIT DESCRIPTION

BASE UNIT

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q500 and then to a SAW bandpass filter, FL501. The frequency range of the base receiver is 926-928MHz. From the bandpass filter the signal is fed to the mixer, Q501 which converts the signal down to 26.05MHz. From Q501 the signal is fed to the IF filter FL502 and then to the integrated circuit U500. In the U500 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector the audio is fed to a low pass filter and to the Channel Detector Indicator. From the low pass filter the audio is fed into another low pass filter and shaper and then to the CPU, U311. From the CPU, U311, the audio is fed to a speaker amplifier and the telephone line depending which is selected. From the CPU the line audio is fed to U305A and then to U305B then to the telephone coupling transformer, T301. The CPU also compares the SECURITY CODES and provides the outgoing SECURITY CODE.

On the transmitting side, when a ring signal is detected the transmitter is turned on by photo coupler integrated circuit U301 and the ring detect signal is fed into the CPU, U306, which in turn triggers the transmitter and send a ring signal to the handset. The base transmit frequency range is 902-904MHz. When the handset answers the base unit connects to the phone line and telephone line audio is fed into the speech network and then to an audio amplifier, Q304. The audio is then fed into the compressor U311. From U311 the audio is fed into the VCO, VT which modulated the outgoing carrier. From the VCO the signal is fed through a series of amplifiers, Q508 & Q509. From Q508 the signal is fed to the antenna.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 3

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A

CIRCUIT DESCRIPTIONS CONTD.

HANDSET

The incoming signal comes in on the antenna and is fed through the duplexer to the LNA, Q100 and then to a SAW 903MHz bandpass filter. The frequency range of the handset receiver is 902-904MHz. From the bandpass filter the signal is fed to the mixer, Q101 which converts the signal down to 26.05MHz. From Q101 the signal is fed to the IF filter FL102 and then to the integrated circuit U100. In the U100 the signal is converted down to 450KHz and then to the detector for FM signal. From the detector, p/o U100 the audio is fed to a low pass filter and to the RING Detector Indicator. From the low pass filter the audio is fed simultaneously to the earphone element and to the CPU, U101. The earphone audio is fed into U2 and then to U4 then to the receiver element, RC1. The CPU uses the data to continuously monitor the security code.

The transmitter frequency range is 926-928MHz. The outgoing audio is picked up by the microphone and fed to the audio integrated circuit U2. This audio integrated circuit feeds a low pass filter then feeds the signal to the VCO, VT. From the VCO the signal is fed in to the amplifier Q107 and Q108 to the duplexer and then to the antenna.

ANTENNA AND GROUND CIRCUITRY

This unit makes use of a short, antenna. The antenna is inductively coupled. The antenna is self contained, no provision is made for an external antenna.

No ground connection is provided. The unit relies on the ground track of the printed circuit board.

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 4

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A (BASE)

NAME OF TEST: RADIATION INTERFERENCE

RULES PART NO.: 15.249

REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

FREQUENCY	LEVEL
____MHz____	____dBuV/M____
902- 928 MHz:	54.0 dBuV/M
ABOVE 960 MHz:	54.0 dBuV/M

TEST DATA:

EMISSION FREQUENCY MHz	METER READING AT 3 METERS dBuV	COAX LOSS dB	ANTENNA CORRECTION FACTOR dB	FIELD STRENGTH dBuV/m@3m	MARGIN dB	ANT. POL.
------------------------------	--------------------------------------	--------------------	------------------------------------	--------------------------------	--------------	--------------

BASE TUNED FREQUENCY 902.23MHz

902.23	52.20	2.90	24.19	79.29	14.71	H
1827.10	11.60	1.00	27.31	39.91	14.09	H
2751.90	3.50	1.14	29.88	34.52	19.48	H
3676.87	0.20	1.28	32.19	33.67	20.33	V

BASE TUNED FREQUENCY 905.00MHz

905.00	46.60	2.90	24.18	73.68	20.32	H
1810.00	13.20	1.00	27.24	41.44	12.56	H
2715.00	3.80	1.14	29.79	34.72	19.28	H

SAMPLE CALCULATION:

FSdBuV/m = MR(dBuV) + ACFdB.

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE: NOVEMBER 24, 1998

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 5

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A (HANDSET)

NAME OF TEST: RADIATION INTERFERENCE PAGE 1 OF 1

RULES PART NO.: 15.249

REQUIREMENTS: Carrier frequency will not exceed 94.0 dBuV/m

FREQUENCY	LEVEL
____MHz____	____dBuV/M____
902- 928 MHz:	54.0 dBuV/M
ABOVE 960 MHz:	54.0 dBuV/M

TEST DATA:

EMISSION FREQUENCY MHz	METER READING AT 3 METERS dBuV	COAX LOSS dB	ANTENNA CORRECTION FACTOR dB	FIELD STRENGTH dBuV/m@3m	MARGIN dB	ANT. POL.
------------------------------	--------------------------------------	--------------------	------------------------------------	--------------------------------	--------------	--------------

HANDSET TUNED FREQUENCY 924.93MHz

924.93	57.40	2.90	24.10	84.40	9.60	V
1849.70	11.80	1.01	27.40	40.21	13.79	V
2774.60	16.90	1.15	29.94	47.98	6.02	V
3699.50	2.70	1.29	32.25	36.23	17.77	V
4624.40	4.50	1.42	33.70	39.63	14.37	V
5549.30	2.70	1.56	34.74	39.01	14.99	V

HANDSET TUNED FREQUENCY 927.71MHz

927.71	51.50	2.90	24.12	78.52	15.48	V
1855.42	17.90	1.01	27.42	46.33	7.67	V
2783.11	20.70	1.15	29.96	51.81	2.19	V
3710.82	2.90	1.29	32.28	36.46	17.54	H
4638.52	2.20	1.43	33.72	37.34	16.66	V
5566.23	3.00	1.57	34.76	39.33	14.67	V

SAMPLE CALCULATION:

$F_{SdBuV/m} = MR(dBuV) + ACFdB$.

METHOD OF MEASUREMENT: The procedure used was ANSI STANDARD C63.4-1992 with the following exception: the unit was operated into its own antenna with the antenna at a height of four feet. Measurements were made at Timco Engineering, Inc. 6051 N.W. 19th Lane, Gainesville, FL 32605.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ DATE: NOVEMBER 24, 1998

APPLICANT: SHINWOO TELECOM CO., LTD.

FCC ID: MQUST-903A

REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT

PAGE #: 6

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
NAME OF TEST: Occupied Bandwidth
RULES PART NO.: 15.233
REQUIREMENTS: The field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges shall be attenuated at least 26 dB below the level of the unmodulated carrier or to the general limits of 15.209, whichever permits the higher emission levels.

THE PLOTS IN EXHIBITS 9-12 REPRESENT THE EMISSIONS TAKEN FOR THIS DEVICE.

METHOD OF MEASUREMENT: A small sample of the transmitter output was fed into the spectrum analyzer and the above photo was taken. The vertical scale is set to -10 dBm per division. The horizontal scale is set to 5 kHz per division.

TEST RESULTS: The unit DOES meet the FCC requirements.

PERFORMED BY: _____ NOVEMBER 24, 1998

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 7

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
NAME OF TEST: POWER LINE CONDUCTED INTERFERENCE
RULES PART NUMBER: 15.207
MINIMUM REQUIREMENTS: FREQUENCY LEVEL
 ___MHz___ __uV__
 0.450-30 250
TEST PROCEDURE: ANSI STANDARD C63.4-1992

THE HIGHEST EMISSION READ FOR LINE 1 WAS 23.685 uV @ 800 kHz.

THE HIGHEST EMISSION READ FOR LINE 2 WAS 10.339 uV @ 800 kHz.

THE PLOTS IN EXHIBITS 13-14 REPRESENT THE EMISSIONS READ FOR
POWERLINE CONDUCTED FOR THIS DEVICE.

TEST RESULTS: Both lines were observed. The measurements indicate that the unit DOES appear to meet the FCC requirements for this class of equipment.

PERFORMED BY: _____ DATE: NOVEMBER 24, 1998

APPLICANT: SHINWOO TELECOM CO., LTD.
FCC ID: MQUST-903A
REPORT #: F:\CUS\S\SHINWOO\SHI321B8.RPT
PAGE #: 8