

**GPE International Ltd.**

Application  
For  
Certification  
**(FCC ID: N48PSW-SERIES)**

Transmitter

WO# 0215173(S1)

AL/sc

April 10 2003

FCC ID: N48PSW-SERIES

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited

**Intertek Testing Services Hong Kong Ltd.**  
2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.  
Tel: (852) 2173 8888 Fax: (852) 2745 8306

# INTERTEK TESTING SERVICES

---

---

## LIST OF EXHIBITS

### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

# INTERTEK TESTING SERVICES

---

---

## MEASUREMENT/TECHNICAL REPORT

**GPE International Ltd. - MODEL: PSW5000**  
**FCC ID: N48PSW-SERIES**

This report concerns (check one):      Original Grant X      Class II      Change \_\_\_\_\_

Equipment Type: Low Power Transmitter (example: computer, printer, modem, etc.)

---

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes \_\_\_\_\_      No X

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

---

Transition Rules Request per 15.37?      Yes      No X

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [12-18-01 Edition] provision.

---

Report prepared by:

Alfred Lo  
Intertek Testing Services  
Hong Kong Ltd.  
2/F., Garment Centre,  
576, Castle Peak Road,  
Kowloon, Hong Kong  
Phone: 852-2173-8545  
Fax: 852-2371-0914

# INTERTEK TESTING SERVICES

---

---

## Table of Contents

<b>1.0 <u>General Description</u></b> .....	3
1.1 Product Description.....	3
1.2 Related Submittal(s) Grants.....	3
1.3 Test Methodology.....	4
1.4 Test Facility.....	4
<b>2.0 <u>System Test Configuration</u></b> .....	6
2.1 Justification.....	6
2.2 EUT Exercising Software .....	6
2.3 Special Accessories .....	6
2.4 Equipment Modification.....	7
2.5 Support Equipment List and Description.....	7
<b>3.0 <u>Emission Results</u></b> .....	9
3.1 Field Strength Calculation.....	10
3.1 Field Strength Calculation (cont'd).....	11
3.2 Radiated Emission Configuration Photograph.....	12
3.3 Radiated Emission Data.....	13
<b>4.0 <u>Equipment Photographs</u></b> .....	16
<b>5.0 <u>Product Labelling</u></b> .....	18
<b>6.0 <u>Technical Specifications</u></b> .....	20
<b>7.0 <u>Instruction Manual</u></b> .....	22
<b>8.0 <u>Miscellaneous Information</u></b> .....	24
8.1 Measured Bandwidth.....	25
8.2 Discussion of Pulse Desensitization .....	26
8.3 Calculation of Average Factor.....	27
8.4 Emissions Test Procedures .....	28
8.4 Emissions Test Procedures (cont'd) .....	29

## INTERTEK TESTING SERVICES

---

---

### List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.pdf
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission	radiated.pdf
External Photo	External Photo	ophoto.pdf
Internal Photo	Internal Photo	iphoto.pdf
Block Diagram	Block Diagram	block.pdf
Test Report	Bandwidth Plot	bw.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 1**

**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

---

## 1.0 General Description

### 1.1 Product Description

The Equipment Under Test (EUT) is transmitter of a RF remote control that operating at 433.92MHz with +/-20ppm for its associated receiver which equipped inside the audio subwoofer. The EUT is powered by two pieces of “AAA” size batteries. There have seven rubber buttons on its body for control up and down of volume, up and down of frequency respond of it, 0° phase to 180° phase, and on or stand by mode. During manually operated, it transmits signal to the receiver (the subwoofer), so the receiver will be operated correspondingly as user intend. It ceases transmission in less than 1 second after being released the key.

Basically, the IC (TX 4915) from the transmitter module is a low power ASK transmitter IC, but it was changed to FSK mode by changing the connection of DATA IN from MOD IN to crystal input (OSC 1 and OSC 2). From the provided circuit, it can be seen that the submitted EUT was inserted with the mentioned adjustment (circuit diagram).

In addition, it can be seen that the bare wire antenna (with manufacturer specified length and shape (which shown on descri.pdf) was attached along the PCB of the EUT inside the plastic case (see at the follow EUT’s photo).

For electronic filing, the brief circuit description is saved with filename: descri.pdf

### 1.2 Related Submittal(s) Grants

This is single application for certification of a transmitter.

## INTERTEK TESTING SERVICES

---

---

### 1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). Radiated Emission measurement was performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been placed on file with the FCC.

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 2**

**SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

---

### 2.0 System Test Configuration

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (1992).

The EUT was powered by 2pcs. of new AAA size batteries..

For simplifying of test, the unit was operated to transmit continuously and the worst case bit sequence transmission was suggested by the applicant..

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. The step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device. Once the unit is powered up, it transmits the typical signal continuously.

#### 2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

---

### 2.4 Equipment Modification.

Any modifications installed previous to testing by GPE International Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by Intertek Testing Services.

### 2.5 Measurement Uncertainty

When determining of the test conclusion, the measurement uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

All the items listed under section 2.0 of this report are *confirmed by*:

*Alfred Lo*  
Senior Technical Supervisor - Home Entertainment Electronics  
Intertek Testing Services Hong Kong Ltd.  
Agent for GPE International Ltd.



Signature

April 10 2003 Date

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 3**

**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

---

### 3.0 Emission Results

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in dB $\mu$ V/m

RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

## INTERTEK TESTING SERVICES

---

---

### 3.1 Field Strength Calculation (cont'd)

#### Example

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 62.0 \text{ dB}\mu\text{V}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$PD = 0 \text{ dB}$$

$$AV = -10 \text{ dB}$$

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32 \text{ dB}\mu\text{V/m}$$

$$\text{Level in mV/m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \text{ } \mu\text{V/m}$$

## **INTERTEK TESTING SERVICES**

---

---

### **3.2 Radiated Emission Configuration Photograph**

**Worst Case Radiated Emission  
at  
433.912 MHz**

For electronic filing, the front view and back view of the test configuration photographs are saved with filename: radiated.pdf respectively.

## INTERTEK TESTING SERVICES

---

---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 0.7 dB margin

### **TEST PERSONNEL:**



---

*Signature*

Lawrence H. C. Chow, Compliance Engineer  
*Typed/Printed Name*

---

April 10 2003

Date

# INTERTEK TESTING SERVICES

---

Company: GPE International Ltd.

Date of Test: April 8 2003

Model: PSW5000

Worst Case Operating Mode: Transmitting Mode

**Table 1**

## Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre - Amp Gain (dB)	Net at 3 m (dB $\mu$ V / m)	Limit at 3 m (dB $\mu$ V / m)	Margin (dB)
H	433.912	79.8	16.3	16	80.1	80.8	-0.7
H	867.856	46.6	22.2	16	52.8	60.8	-8.0
V	*1301.957	60.2	25.5	34	51.7	54.0	-2.3
V	1735.657	59.3	26.5	34	51.8	60.8	-9.0
V	2169.557	59.8	29.1	34	54.9	60.8	-5.9
V	2603.509	57.4	29.1	34	52.5	60.8	-8.3
V	3037.398	47.4	31.4	34	44.8	60.8	-16.0
V	3471.829	46.3	31.4	34	43.7	60.8	-17.1
V	*3905.746	43.2	32.8	34	42.0	54.0	-12.0
V	*4339.663	36.9	34.2	34	37.1	54.0	-16.9

NOTES:

1. Average detector is used below 1000MHz unless otherwise stated.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative sign in the column shows value below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.
5. The radiated emission test was observed up to 40GHz.

\* Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Lawrence H. C. Chow

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 4**

**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

---

### 4.0 Equipment Photographs

For electronic filing, photographs of the tested EUT are saved with filename: ophoto.pdf for external photo, and iphoto.pdf for internal photo.

**EXHIBIT 5**

**PRODUCT LABELLING**

## INTERTEK TESTING SERVICES

---

---

### 5.0 **Product Labelling**

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 6**

**TECHNICAL SPECIFICATIONS**

## INTERTEK TESTING SERVICES

---

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematic of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 7**

**INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States. Moreover, it was said that the declaration which mention in following pages will also be committed at the time.

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

## INTERTEK TESTING SERVICES

---

---

### 8.0 Miscellaneous Information

The miscellaneous information includes details of the measured bandwidth, the test procedure and calculation of factor such as pulse desensitization and averaging factor (calculation and timing diagram).

## INTERTEK TESTING SERVICES

---

---

### 8.1 Measured Bandwidth

For electronic filing, the plot shows the fundamental emission when modulated is saved with filename: bw.pdf. From the plot, the bandwidth is observed to be 185kHz, at 20dBc where the bandwidth limit is 1.084MHz.

## **INTERTEK TESTING SERVICES**

---

---

### **8.2 Discussion of Pulse Desensitization**

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, spectrum Analysis... Pulse RF.

Pulse desensitivity is not applicable for this device. The effective period (Teff) is approximately  $340\mu\text{s}$  for digital “1” bit which illustrated on technical specification, with a resolution bandwidth (3dB) of 100KHz, so the pulse desensitivity factor is 0dB.

## **INTERTEK TESTING SERVICES**

---

---

### **8.3 Calculation of Average Factor**

The average factor is not applicable for this device because the average detector is used for measurement.

## INTERTEK TESTING SERVICES

---

---

### 8.4 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services Hong Kong Ltd. in the measurements of Low Power Transmitter operating under the Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 1992.

The equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the groundplane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axis to obtain maximum emission levels. The antenna height and polarization are also varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings. A detailed description for the calculation of the average factor can be found in Exhibit 8.3.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower.

## INTERTEK TESTING SERVICES

---

---

### 8.4 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test. If battery powered, a new, fully charged battery is used.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater when frequency is below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.2). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Measurements are normally conducted at a measurement distance of three meters. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.