

Blank label
before print.



Label printed to
this specification

Hexadecimal Electronic
Serial Number (ESN)
& (Barcode 39)
Factory Serial
Number (FSN)
IBM Part Data:
22 characters,
Barcode 128
Static Data:
EC # & FRU # IBM 11S
Label Requirement
See Table 1.



Antenna Connector call-outs

Batch Revision: Example
"21"=BOM revision 2.1

SKU Identification
(Numeric Format)

Year/Month: Format "ymm",
y= last digit of year,
mm= month of manufacture

NOTES:

- For reference only. Refer to BOM for blank label.
- Hexadecimal ESN number:
 - Printed on label in code 39 bar code format.
 - Printed on label in human readable font below bar code.
- Manufacturing date code YMM:
 - Printed on label in human readable font.
 - Calculate value of "MM" by converting "DDD" part of FSN from Julian date to month digits "MM". The value of "Y" is the same as Year code in the FSN.
- IBM Part Data:
 - Printed on label in human readable font.
 - Barcode height is 2 mm (min.)
 - Part # consists of static part IE: "11SAAAAAAZBBBB" from Table 1 and calculated part "CCCCC".
 - CCCCC is determined as follows:
(From Left to right)

SWI SKU (1100SSS)	Lenovo P/N (AAAAAA)	Header Code (BBBBB)	FRU P/N (YYYYYYY)	EC# (XXXXXX)
1100598	42T0880	1ZCTT	42T0881	L03137
1100601	42T0896	1ZD3F	42T0867	L03137

1st C : Y = last digit of year. Year 2003 ==> 3

2nd C : M = Month ; JAN.=1 FEB.=2 MER.=3 APR.=4 MAY=5 JUN.=6
JUL.=7 AUG.=8 SEP.=9 OCT.=A NOV.=B DEC.=C

3rd C : D = Date ; 1=1 2=2 3=3 4=4 5=5 6=6 7=7 8=8 9=9 10=A 11=B 12=C 13=D
14=E 15=F 16=G 17=H 18=J 19=K 20=L 21=M 22=N 23=P 24=R 25=S
26=T 27=V 28=W 29=X 30=Y 31=Z

4th C : Serial number3 :
012456789ABDEGHJKMNPTUVWXYZ ;
"3", "C", "F", "I", "L", "O", "R", "S" and "Q" are not used.

5th C : Serial number2 :
0123456789ABCDEFGHIJKLMNPRSTUVWXYZ ;
"I", "O" and "Q" are not used.

6th C : Serial number1 :
0123456789ABCDEFGHIJKLMNPRSTUVWXYZ ;
"I", "O" and "Q" are not used.

Maximum volume per date will be 29,403
(=27 x 33 x 33) by Serial numbering.

			
(COPYRIGHT 2001) THIS DOCUMENT, SUBMITTED IN CONFIDENCE, CONTAINS PROPRIETARY INFORMATION WHICH SHALL NOT BE REPRODUCED OR TRANSFERRED TO OTHER DOCUMENTS OR DISCLOSED TO OTHERS OR USED FOR MANUFACTURING OR ANY OTHER PURPOSE WITHOUT WRITTEN PERMISSION OF SIERRA WIRELESS, INC.			
Print Specifications Label, MC5725, LENOVO			
DWG. NO.	REV.	SIZE	
2100982	1.2	A	
SHEET 1		OF 1	

REV	ECO#	DATE	DRFT	CHK	APP	MFG
1.2		02/28/07	RWL			
1.1		02/23/07	RWL			
1.0		12/11/06	RWL			