



HAC TEST REPORT

Test Item: Summary Result HAC Category = M3

REPORT NO.: SA990210L08-4

MODEL NO.: PC36100

RECEIVED: Feb. 23, 2010

TESTED: May 01, 2010

ISSUED: May 03, 2010

APPLICANT: HTC Corporation

ADDRESS: No. 23, Xinghua Rd., Taoyuan City, 330, Taiwan,
R.O.C.

ISSUED BY: Bureau Veritas Consumer Products Services
(H.K.) Ltd., Taoyuan Branch

LAB ADDRESS: No. 47, 14th Ling, Chia Pau Tsuen, Lin Kou
Hsiang, Taipei Hsien 244, Taiwan, R.O.C.

TEST LOCATION: No. 19, Hwa Ya 2nd Rd, Wen Hwa Tsuen, Kwei
Shan Hsiang, Taoyuan Hsien 333, Taiwan,
R.O.C.

This test report consists of 31 pages in total except Appendix. It may be duplicated completely for legal use with the approval of the applicant. It should not be reproduced except in full, without the written approval of our laboratory. The client should not use it to claim product endorsement by any government agencies. The test results in the report only apply to the tested sample.



TABLE OF CONTENTS

1.	CERTIFICATION	3
2.	GENERAL INFORMATION.....	4
2.1	GENERAL DESCRIPTION OF EUT	4
2.2	DESCRIPTION OF SUPPORT UNITS	5
2.3	GENERAL DESCRIPTION OF APPLIED STANDARDS	5
3.	GENERAL INFORMATION OF THE DASY4 SYSTEM.....	6
3.1.	GENERAL INFORMATION OF TEST EQUIPMENT	6
3.2.	TEST EQUIPMENT LIST.....	10
3.3.	MEASUREMENT UNCERTAINTY	11
3.4.	GENERAL DESCRIPTION OF THE HAC EVALUATION	12
4.	PERFORMANCE CATEGORIES	14
5.	SYSTEM CHECK	16
5.1.	VALIDATION STRUCTURE	16
5.2.	SYSTEM CHECK PROCEDURE	17
5.3.	VALIDATION RESULTS	18
6.	MODULATION FACTOR	19
6.1	MODULATION FACTOR TEST RESULTS	20
7.	RF EMISSION TEST PROCEDURES.....	24
7.1.	TEST INSTRUCTION.....	24
7.2.	TEST PROCEDURES	25
7.3.	DESCRIPTION OF TEST POSITION AND CONFIGURATIONS	26
7.4.	SUMMARY OF MEASURED HAC RESULTS	27
8.	INFORMATION ON THE TESTING LABORATORIES	31
	APPENDIX A: TEST CONFIGURATIONS AND TEST DATA	
	APPENDIX D: SYSTEM CERTIFICATE & CALIBRATION	
	APPENDIX E: TEST CONFIGURATIONS	



A D T

1. CERTIFICATION

PRODUCT : Smart Phone
MODEL NO. : PC36100
BRAND : HTC
APPLICANT : HTC Corporation
TESTED : May 01, 2010
TEST SAMPLE : ENGINEERING SAMPLE
STANDARDS : FCC Part 20.19
ANSI C63.19 2007
TEST ITEM: RF emissions

The above equipment (Model: PC36100) have been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's characteristics under the conditions specified in this report.

PREPARED BY : Pettie Chen , **DATE**: May 03, 2010
Pettie Chen / Specialist

TECHNICAL ACCEPTANCE : Long Chen , **DATE**: May 03, 2010
Responsible for RF Long Chen / Senior Engineer

APPROVED BY : Gary Chang , **DATE**: May 03, 2010
Gary Chang / Assistant Manager



2. GENERAL INFORMATION

2.1 GENERAL DESCRIPTION OF EUT

PRODUCT	Smart Phone	
MODEL NO.	PC36100	
FCC ID	NM8PC36100	
POWER SUPPLY	3.7Vdc (Battery) 5.0Vdc (Adapter) 5.0Vdc (host equipment)	
CLASSIFICATION	Portable device, production unit	
MODULATION TYPE	OQPSK, HPSK	
FREQUENCY RANGE	824MHz ~ 849MHz (CDMA850) 1850MHz ~ 1910MHz (CDMA1900)	
CHANNEL FREQUENCIES UNDER TEST AND ITS CONDUCTED OUTPUT POWER	CDMA850: 23.78dBm / 824.70MHz for channel 1013 23.96dBm / 836.50MHz for channel 384 23.11dBm / 848.30MHz for channel 777 CDMA1900: 23.92dBm / 1851.25MHz for channel 25 23.79dBm / 1880.00MHz for channel 600 24.48dBm / 1908.75MHz for channel 1175	
HAC RATE CATEGORY	M3	
ANTENNA TYPE	PIFA antenna	
MAX. ANTENNA GAIN	850MHz: -3dBi	1900MHz: 1.0dBi
DATA CABLE	Refer to NOTE	
I/O PORTS	Refer to user's manual	
ACCESSORY DEVICES	Refer to NOTE	

NOTE:

- The communicated functions of EUT listed as below:

		850MHz	1900MHz	With WLAN 802.11b/g + BT 2.1 with EDR + GPS
3G	CDMA	√	√	
	1*EVDO	√	√	



2. The EUT has following accessories.

NO.	PRODUCT	BRAND	MANU-FACTURE	MODEL	DESCRIPTION
1	Power Adapter	hTC	Delta	TC U250	I/P: 100-240Vac, 50-60Hz, 200mA O/P: 5Vdc, 1A
2			Emerson	TC U250	
3	USB cable	MEC	-	DC M410	1.4m shielded cable without core (For data transmission & charging use)
4		Foxlink	-		
5	Battery	HT ENERGY	-	RHOD160	Rating: 3.7Vdc, 1500mAh
6		Formosa	-		

3. MEID no.: A100000D98

4. The above EUT information was declared by manufacturer and for more detailed features description, please refer to the manufacturer's specifications or User's Manual.

2.2 DESCRIPTION OF SUPPORT UNITS

The EUT has been tested as an independent unit together with other necessary accessories or support units. The following support units or accessories were used to form a representative test configuration during the tests.

NO.	PRODUCT	BRAND	MODEL NO.	SERIAL NO.	CALIBRATED UNTIL
1	Universal Radio Communication Tester	R&S	CMU200	104958	Sep. 15, 2010

NO.	SIGNAL CABLE DESCRIPTION OF THE ABOVE SUPPORT UNITS
1	NA

NOTE: All power cords of the above support units are non shielded (1.8m).

2.3 GENERAL DESCRIPTION OF APPLIED STANDARDS

According to the specifications of the manufacturer, this product must comply with the requirements of the following standards:

FCC Part 20.19

ANSI C63.19 – 2007

All test items have been performed and recorded as per the above standards.



3. GENERAL INFORMATION OF THE DASY4 SYSTEM

3.1. GENERAL INFORMATION OF TEST EQUIPMENT

DASY4 (software 4.7 Build 80) consists of high precision robot, probe alignment sensor, phantom, robot controller, controlled measurement server and near-field probe. The robot includes six axes that can move to the precision position of the DASY4 software defined. The DASY4 software can define the area that is detected by the probe. The robot is connected to controlled box. Controlled measurement server is connected to the controlled robot box. The DAE includes amplifier, signal multiplexing, AD converter, offset measurement and surface detection. It is connected to the Electro-optical coupler (ECO). The ECO performs the conversion from the optical into digital electric signal of the DAE and transfers data to the PC.

ER3DV6 E-FIELD PROBE


CONSTRUCTION	One dipole parallel, two dipoles normal to probe axis Built-in shielding against static charges
CALIBRATION	In air from 100MHz to 3.0GHz (absolute accuracy $\pm 6.0\%$, $k = 2$)
FREQUENCY	100MHz to > 6 GHz; Linearity: ± 0.2 dB (100MHz to 3GHz)
DIRECTIVITY	± 0.2 dB in air (rotation around probe axis) ± 0.4 dB in air (rotation normal to probe axis)
DYNAMIC RANGE	2V/m to > 1000 V/m (M3 or better device readings fall well below diode compression point) Linearity: ± 0.2 dB
DIMENSIONS	Overall length: 330mm (Tip: 16mm) Tip diameter: 8mm (Body: 12mm) Distance from probe tip to dipole centers: 2.5mm

H3DV6 H-FIELD PROBE

CONSTRUCTION	Three concentric loop sensors with 3.8mm loop diameters Resistively loaded detector diodes for linear response Built-in shielding against static charges
FREQUENCY	200MHz to 3GHz (absolute accuracy $\pm 6.0\%$, $k = 2$); Output linearized
DIRECTIVITY	$\pm 0.25\text{dB}$ (spherical isotropy error)
DYNAMIC RANGE	10mA/m to 2A/m at 1GHz (M3 or better device readings fall well below diode compression point)
DIMENSIONS	Overall length: 330mm (Tip: 40mm) Tip diameter: 6mm (Body: 12mm) Distance from probe tip to dipole centers: 3mm
E-FIELD INTERFERENCE	< 10% at 3GHz (for plane wave)

NOTE: The Probe parameters have been calibrated by the SPEAG. Please reference "APPENDIX D" for the Calibration Certification Report.

HAC ARCH



DIMENSIONS 370 x 370 x 370mm

SYSTEM VALIDATION KITS:

- CD835V3** **Frequency Band:** 800 ~ 960MHz (free space)
 Return Loss: > 15dB
 Calibrated at: 835MHz
 Power Capability: 50W continuous
 Length & Height: 166 x 330mm
- CD1880V3** **Frequency Band:** 1710 ~ 2000MHz (free space)
 Return Loss: > 18dB
 Calibrated at: 1880MHz
 Power Capability: 50W continuous
 Length & Height: 80.8 x 330mm

**DEVICE HOLDER**

CONSTRUCTION Supports accurate and reliable positioning of any phone effect on near field
 <+/- 0.5dB

DATA ACQUISITION ELECTRONICS (DAE)



CONSTRUCTION

The data acquisition electronics (DAE3) consists of a highly sensitive electrometer grade preamplifier with auto-zeroing, a channel and gain-switching multiplex, a fast 16 bit AD converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The mechanical probe is mounting device includes two different sensor systems for frontal and sideways probe contacts. They are used for mechanical surface detection and probe collision detection. The input impedance of the DAE3 box is 200M Ω ; the inputs are symmetrical and floating. Common mode rejection is above 80dB.



A D T

3.2. TEST EQUIPMENT LIST

ITEM	NAME	BRAND	TYPE	SERIES NO.	DATE OF CALIBRATION	DUE DATE OF CALIBRATION
1	SAM Phantom	S & P	SD HAC P01 BA	1034	NA	NA
2	Signal Generator	Anritsu	68247B	984703	May 21, 2009	May 20, 2010
3	E-Field Probe	Speag	ER3DV6	2302	Jun. 23, 2009	Jun. 22, 2010
4	H-Field Probe	Speag	H3DV6	6187	Jun. 24, 2009	Jun. 23, 2010
5	DAE	S & P	DAE	861	Jan. 22, 2010	Jan. 21, 2011
6	Robot Positioner	Staubli Unimation	NA	NA	NA	NA
7	Validation Dipole	S & P	CD835V3	1149	Jan. 12, 2010	Jan. 11, 2011
8	Validation Dipole	S & P	CD1880V3	1032	Jul. 16, 2008	Jul. 15, 2010
9	Power Meter	Agilent	E4416A	GB41291763	Sep. 29, 2009	Sep. 28, 2010
10	Power Sensor		E9327A	US40441181	Sep. 29, 2009	Sep. 28, 2010

NOTE: Before starting the measurement, all test equipment shall be warmed up for 30min.



3.3. MEASUREMENT UNCERTAINTY

HAC UNCERTAINTY BUDGET ACCORDING TO ANSI C63.19[1]							
ERROR DESCRIPTION	UNCERTAINTY VALUE	PROBABILITY DISTRIBUTION	DIVISOR	(Ci) E	(Ci) H	STD. UNC. E (%)	STD. UNC. H (%)
MEASUREMENT SYSTEM							
Probe calibration	5.1	Normal	1	1	1	5.1	5.1
Axial isotropy	0.5	Rectangular	$\sqrt{3}$	1	1	0.3	0.3
Sensor Displacement	16.5	Rectangular	$\sqrt{3}$	1	0.145	9.5	1.4
Boundary Effects	2.4	Rectangular	$\sqrt{3}$	1	1	1.4	1.4
Linearity	0.6	Rectangular	$\sqrt{3}$	1	1	0.3	0.3
Scaling to Peak Envelope Power	2.0	Rectangular	$\sqrt{3}$	1	1	1.2	1.2
System Detection Limit	1.0	Rectangular	$\sqrt{3}$	1	1	0.6	0.6
Readout Electronics	0.3	Rectangular	$\sqrt{3}$	1	1	0.2	0.2
Response Time	0.8	Rectangular	$\sqrt{3}$	1	1	0.5	0.5
Integration Time	2.6	Rectangular	$\sqrt{3}$	1	1	1.5	1.5
RF Ambient Condition	3.0	Rectangular	$\sqrt{3}$	1	1	1.7	1.7
RF Reflections	12.0	Rectangular	$\sqrt{3}$	1	1	6.9	6.9
Probe Positioner	1.2	Rectangular	$\sqrt{3}$	1	0.67	0.7	0.5
Probe Positioning	4.7	Rectangular	$\sqrt{3}$	1	0.67	2.7	1.8
Extrap. And Interpolation	1.0	Rectangular	$\sqrt{3}$	1	1	0.6	0.6
TEST SAMPLE RELATED							
Device Positioning Vertical	2.6	Normal	1	1	1	2.6	2.6
Device Positioning Lateral	2.6	Normal	1	1	1	2.6	2.6
Device Holder and Phantom	2.4	Rectangular	$\sqrt{3}$	1	1	1.4	1.4
Power Drift	5.0	Rectangular	$\sqrt{3}$	1	1	2.9	2.9
PHANTOM AND SETUP RELATED							
Phantom Thickness	2.4	Rectangular	$\sqrt{3}$	1	0.67	1.4	0.9
COMBINED STD. UNCERTAINTY						14.4	10.7
EXPANDED STD. UNCERTAINTY ON POWER						28.8	21.3
EXPANDED STD. UNCERTAINTY ON FIELD						14.4	10.7

NOTE: Worst-case uncertainty budget for HAC free field assessment according to ANSI C63.19 [1]. The budget is valid for the frequency range 800MHz ~ 3GHz and represents a worst-case analysis. For specific tests and configurations, the uncertainty could be considerably smaller.



3.4. GENERAL DESCRIPTION OF THE HAC EVALUATION

The DASYS4 post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the micro-volt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe parameters: - Sensitivity	Norm _i , a _{i0} , a _{i1} , a _{i2}
- Conversion factor	ConvF _i
- Diode compression point	dcp _i
Device parameters: - Frequency	F
- Crest factor	Cf

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power. The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

V _i = compensated signal of channel i	(i = x, y, z)
U _i = input signal of channel i	(i = x, y, z)
Cf = crest factor of exciting field	(DASY parameter)
dcp _i = diode compression point	(DASY parameter)

From the compensated input signals the primary field data for each channel can be evaluated:

$$\mathbf{E\text{-field probes: } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}}$$

$$\mathbf{H\text{-field probes: } H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}}$$

V_i = compensated signal of channel i ($i = x, y, z$)

Norm_i = sensor sensitivity of channel i $\mu\text{V}/(\text{V/m})^2$ for E-field Probes ($i = x, y, z$)

ConvF = sensitivity enhancement in solution

a_{ij} = sensor sensitivity factors for H-field probes

f = carrier frequency [GHz]

E_i = electric field strength of channel i in V/m

H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{tot} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

E = field strength in V/m

E_{tot} = total field strength in V/m

NOTE: The signal response time is evaluated as the time required by the system to reach 90% of the expected final value after an on/off switch of the power source with an integration time of 500ms and a probe response time of < 5ms. In the current implementation, DASY4 waits longer than 100ms after having reached the grid point before starting a measurement, i.e., the response time uncertainty is negligible.



4. PERFORMANCE CATEGORIES

The ANSI Standard presents performance requirements for acceptable interoperability of hearing aids with wireless communications devices. When these parameters are met, a hearing aid operates acceptably in close proximity to a wireless communications device.

CATEGORY NEAR FIELD	TELEPHONE RF PARAMETERS < 960MHz				
	AWF	E-FIELD EMISSION CW (dBV/m)	E-FIELD EMISSION CW (V/m)	H-FIELD EMISSION CW (dBA/m)	H-FIELD EMISSION CW (A/m)
M1	0	56.0 to 61.0	631.0 to 1122.0	5.6 to 10.6	1.91 to 3.39
	-5	53.5 to 58.5	473.2 to 841.4	3.1 to 8.1	1.43 to 2.54
M2	0	51.0 to 56.0	354.8 to 631.0	0.6 to 5.6	1.07 to 1.91
	-5	48.5 to 53.5	266.1 to 473.2	-1.9 to 3.1	0.80 to 1.43
M3	0	46.0 to 51.0	199.5 to 354.8	-4.4 to 0.6	0.60 to 1.07
	-5	43.5 to 48.5	149.6 to 266.1	-6.9 to -1.9	0.45 to 0.80
M4	0	< 46.0	< 199.5	< -4.4	< 0.60
	-5	< 43.5	< 149.6	< -6.9	< 0.45

CATEGORY NEAR FIELD	TELEPHONE RF PARAMETERS > 960MHz				
	AWF	E-FIELD EMISSION CW (dBV/m)	E-FIELD EMISSION CW (V/m)	H-FIELD EMISSION CW (dBA/m)	H-FIELD EMISSION CW (A/m)
M1	0	46.0 to 51.0	199.5 to 354.8	-4.4 to 0.6	0.60 to 1.07
	-5	43.5 to 48.5	149.6 to 266.1	-6.9 to -1.9	0.45 to 0.80
M2	0	41.0 to 46.0	112.2 to 199.5	-9.4 to -4.4	0.34 to 0.60
	-5	48.5 to 53.5	84.1 to 149.6	-11.9 to -6.9	0.25 to 0.45
M3	0	36.0 to 41.0	63.1 to 112.2	-14.4 to -9.4	0.19 to 0.34
	-5	33.5 to 38.5	47.3 to 84.1	-16.9 to -11.9	0.14 to 0.25
M4	0	< 36.0	< 63.1	< -14.4	< 0.19
	-5	< 33.5	< 47.3	< -16.9	< 0.14



ARTICULATION WEIGHING FACTOR (AWF)

The following AWF factors shall be used for the standard transmission protocols:

STANDARD	TECHNOLOGY	AWF (dB)
TIA/EIA/IS-2000	CDMA	0
TIA/EIA-136	TDMA (50Hz)	0
iDENTM	TDMA (22 and 11Hz)	0
J-STD-007	GSM (217)	-5
T1/T1P1/3GPP	UMTS (WCDMA)	0


5. SYSTEM CHECK

The measured values (E-field and H-field) were compared with the values provided by the probe manufacturer and must within the allowed tolerance of **25%**.

5.1. VALIDATION STRUCTURE

The input signal was an un-modulated continuous wave. The following points were taken into consideration in performing this check:


- Average Input Power $P = 100\text{mW RMS}$ (20dBm RMS) after adjustment for return loss
- The test fixture must meet the 2 wavelength separation criterion
- The proper measurement of the 1cm probe to dipole separation, which is measured from top surface of the dipole to the calibration reference point of the sensor, defined by the probe manufacturer is shown in the following diagram:



5.2. SYSTEM CHECK PROCEDURE

1. Before you start the system performance check, need only to tell the system with which components (probe type, validation dipole and HAC arch) are performing the system performance check; the system will take care of all parameters.

The system check configuration is shown in the following figure:



2. The dipole was energized with a 20dBm unmodulated continuous-wave signal.
3. The length of the dipole was scanned with both E-field and H-field probes and the maximum values for each were recorded.



5.3. VALIDATION RESULTS

SYSTEM CHECK						
TEST FREQUENCY (MHz)	BEGIN TEST SG POWER (mW)	REQUIRED E-FILED (V/m)	MEASURED E-FILED (V/m)	DEVIATION (%)	SEPARATION DISTANCE (mm)	TESTED DATE
835	100.0	170.7	138.2	-19.04	10	May 01, 2010
1880	100.0	141.8	111.1	-21.65	10	May 01, 2010
TEST FREQUENCY (MHz)	BEGIN TEST SG POWER (mW)	REQUIRED H-FILED (A/m)	MEASURED H-FILED (A/m)	DEVIATION (%)	SEPARATION DISTANCE (mm)	TESTED DATE
835	100.0	0.465	0.414	-10.97	10	May 01, 2010
1880	100.0	0.467	0.391	-16.27	10	May 01, 2010
TESTED BY	Sam Onn					

NOTE: Please see Appendix for the system validation test data.



6. MODULATION FACTOR

A calibration was made of the modulation response of the probe and its instrumentation chain. This calibration was performed with the field probe, attached to its instrumentation. The response of the probe system to a CW field at the frequency of interest is compared to its response to a modulated signal with equal peak amplitude to that of a CW signal. The field level of the test signals are ensured to be more than 10dB above the ambient level and the noise floor of the instrumentation being used. The ratio of the CW reading to that taken with a modulated reading was applied to the DUT measurements.

This was done using the following procedure:

1. Fixing the probe in a set location relative to a field generating device, such as a reference dipole antenna, as illustrated in the system check procedure.
2. Illuminate the probe using the wireless device connected to the reference dipole with a test signal at the intended measurement frequency, Ensure there is sufficient field coupling between the probe and the antenna so the resulting reading is greater than 10dB above the probe system noise floor but within the systems operating range.
3. Record the amplitude applied to the antenna during transmission and the field strength measured by the E-field probe located near the tip of the dipole antenna.
4. Replace the wireless device with an RF signal generator producing an unmodulated CW signal and set to the wireless device operating frequency.
5. Set the amplitude of the unmodulated signal to equal that recorded from the wireless device.
6. Record the reading of the probe measurement system of the unmodulated signal.
7. The RF signal generator producing an 80%AM signal and set to the wireless device operating frequency. Set the amplitude of the signal to equal that recorded from the wireless device.
8. Record the reading of the probe measurement system of the 80%AM signal.
9. The ratio, in linear units, of the probe reading in Step 3) or 8) to the reading in Step 6) is the E-field modulation factor.
10. Steps 1-9 were repeated at all frequency bands and for both E and H field probes.

NOTE: The ratio of the CW to modulated signal reading is the modulation factor. The modulation factors obtained were applied to readings taken of the actual wireless device, in order to obtain an accurate peak field reading using the formula:


$$\text{Peak} = 20 \cdot \log(\text{Raw} \cdot \text{ProbeModulationFactor})$$



6.1 MODULATION FACTOR TEST RESULTS


TEST FREQUENCY (MHz)	PROTOCOL	REFERENCE LEVEL	MEASURED E-FILED (V/m)	E-FILED MODULATION FACTOR	TESTED DATE
836.5	CW	Refer to the next three plots	145.2	NA	May 01, 2010
	80% AM		130.5	1.11	
	CDMA		154.1	0.94	
TEST FREQUENCY (MHz)	PROTOCOL	REFERENCE LEVEL	MEASURED H-FILED (A/m)	H-FILED MODULATION FACTOR	TESTED DATE
836.5	CW	Refer to the next three plots	0.422	NA	May 01, 2010
	80% AM		0.396	1.07	
	CDMA		0.464	0.91	
TESTED BY	Sam Onn				

CW SIGNAL:






80% AM SIGNAL:



CDMA SIGNAL:






A D T


TEST FREQUENCY (MHz)	PROTOCOL	REFERENCE LEVEL	MEASURED E-FILED (V/m)	E-FILED MODULATION FACTOR	TESTED DATE
1880.0	CW	Refer to the next three plots	101.3	NA	May 01, 2010
	80% AM		87.3	1.16	
	CDMA		102.2	0.99	
TEST FREQUENCY (MHz)	PROTOCOL	REFERENCE LEVEL	MEASURED H-FILED (A/m)	H-FILED MODULATION FACTOR	TESTED DATE
1880.0	CW	Refer to the next three plots	0.371	NA	May 01, 2010
	80% AM		0.334	1.11	
	CDMA		0.390	0.95	
TESTED BY	Sam Onn				

CW SIGNAL:






80% AM SIGNAL:




CDMA SIGNAL:



7. RF EMISSION TEST PROCEDURES

7.1. TEST INSTRUCTION






7.2. TEST PROCEDURES

The EUT (Smart Phone) makes a phone call to the GSM base station. Establish the simulation communication configuration rather than the actual communication. Then the EUT could continuously be in transmission mode. Adjust the PCL of the base station could control the EUT to transmit the maximum output power. The base station also could control the transmission channel.

The recommended procedure for assessing the RF emission value consists of the following steps:

1. Proper operation of the field probe, probe measurement system, other instrumentation, and the positioning system was confirmed.
2. WD is positioned in its intended test position, acoustic output point of the device perpendicular to the field probe.
3. The center sub-grid was centered over the center of the acoustic output (also audio band magnetic output, if applicable). The WD audio output was positioned tangent (as physically possible) to the measurement plane.
4. A surface calibration was performed before each setup change to ensure repeatable spacing and proper maintenance of the measurement plane using the HAC arch.
5. The measurement system measured the field strength at the reference location.
6. Measurements at 2mm increments in the 5 x 5cm region were performed and recorded. A 360° rotation about the azimuth axis at the maximum interpolated position was measured. For the worst-case condition, the peak reading from this rotation was used in re-evaluating the HAC category.
7. Steps 1-6 were done for both the E and H-Field measurements.

7.3. DESCRIPTION OF TEST POSITION AND CONFIGURATIONS





7.4. SUMMARY OF MEASURED HAC RESULTS

E-FIELD EMISSION

ENVIRONMENTAL CONDITION			Air Temperature : 23.1°C, Humidity : 57%RH						
TESTED BY			Sam Onn		DATE		May 01, 2010		
FREQ. (MHz)	CHAN.	MODE	CONDUCTED POWER (dBm)	DRIFT (dB)	MEASURED PMF	EXCLUDED CELLS	PEAK FIELD (V/m)	RATING	REMARK
824.70 (Low)	1013	CDMA 850	23.78	-0.003	0.94	7, 8, 9	63.7	M4	Note 2
836.52 (Mid.)	384		23.96	-0.110		7, 8, 9	72.3	M4	Note 2
848.31 (High)	777		23.11	-0.024		7, 8, 9	63.2	M4	Note 2
836.52 (Mid.)	384		23.96	0.068		7, 8, 9	71.7	M4	Note 3

NOTE:

1. WiFi/WiMAX/BT are disabled during HAC test.
2. The LCD back-light "OFF" & battery 1 (Manufactory: HT ENERGY) are the worst case for measurement.
3. The LCD back-light "OFF" & battery 2 (Manufactory: Formosa) are the worst case for measurement.
4. Please see the Appendix A for the measured data and test plots.
5. The variation of the EUT conducted power measured before and after HAC testing should not over 5%.



A D T

ENVIRONMENTAL CONDITION			Air Temperature : 23.1°C, Humidity : 57%RH						
TESTED BY			Sam Onn		DATE		May 01, 2010		
FREQ. (MHz)	CHAN.	MODE	CONDUCTED POWER (dBm)	DRIFT (dB)	MEASURED PMF	EXCLUDED CELLS	PEAK FIELD (V/m)	RATING	REMARK
1851.25 (Low)	25	CDMA 1900	23.92	-0.075	0.99	6, 8, 9	68.1	M3	Note 2
1880.00 (Mid.)	600		23.79	0.112		6, 8, 9	82.7	M3	Note 2
1908.75 (High)	1175		23.48	-0.072		6, 8, 9	77.7	M3	Note 2
1880.00 (Mid.)	600		23.79	-0.047		6, 8, 9	82.4	M3	Note 3

NOTE:

1. WiFi/WiMAX/BT are disabled during HAC test.
2. The LCD back-light "OFF" & battery 1 (Manufactory: HT ENERGY) are the worst case for measurement.
3. The LCD back-light "OFF" & battery 2 (Manufactory: Formosa) are the worst case for measurement.
4. Please see the Appendix A for the measured data and test plots.
5. The variation of the EUT conducted power measured before and after HAC testing should not over 5%.



A D T

H-FIELD EMISSION

ENVIRONMENTAL CONDITION			Air Temperature : 23.1°C, Humidity : 57%RH						
TESTED BY			Sam Onn		DATE		May 01, 2010		
FREQ. (MHz)	CHAN.	MODE	CONDUCTED POWER (dBm)	DRIFT (dB)	MEASURED PMF	EXCLUDED CELLS	PEAK FIELD (A/m)	RATING	REMARK
824.70 (Low)	1013	CDMA 850	23.78	0.057	0.91	4, 7, 8	0.150	M4	Note 2
836.52 (Mid.)	384		23.96	0.011		4, 7, 8	0.157	M4	Note 2
848.31 (High)	777		23.11	-0.042		4, 7, 8	0.146	M4	Note 2
836.52 (Mid.)	384		23.96	-0.107		4, 7, 8	0.156	M4	Note 3

NOTE:

1. WiFi/WiMAX/BT are disabled during HAC test.
2. The LCD back-light "OFF" & battery 1 (Manufactory: HT ENERGY) are the worst case for measurement.
3. The LCD back-light "OFF" & battery 2 (Manufactory: Formosa) are the worst case for measurement.
4. Please see the Appendix A for the measured data and test plots.
5. The variation of the EUT conducted power measured before and after HAC testing should not over 5%.



A D T

ENVIRONMENTAL CONDITION			Air Temperature : 23.1°C, Humidity : 57%RH						
TESTED BY			Sam Onn		DATE		May 01, 2010		
FREQ. (MHz)	CHAN.	MODE	CONDUCTED POWER (dBm)	DRIFT (dB)	MEASURED PMF	EXCLUDED CELLS	PEAK FIELD (A/m)	RATING	REMARK
1851.25 (Low)	25	CDMA 1900	23.92	-0.034	0.95	4, 7, 8	0.224	M3	Note 2
1880.00 (Mid.)	600		23.79	-0.010		4, 7, 8	0.253	M3	Note 2
1908.75 (High)	1175		23.48	-0.119		4, 7, 8	0.242	M3	Note 2
1880.00 (Mid.)	600		23.79	-0.046		4, 7, 8	0.252	M3	Note 3

NOTE:

1. WiFi/WiMAX/BT are disabled during HAC test.
2. The LCD back-light "OFF" & battery 1 (Manufactory: HT ENERGY) are the worst case for measurement.
3. The LCD back-light "OFF" & battery 2 (Manufactory: Formosa) are the worst case for measurement.
4. Please see the Appendix A for the measured data and test plots.
5. The variation of the EUT conducted power measured before and after HAC testing should not over 5%.



A D T

8. INFORMATION ON THE TESTING LABORATORIES

We, Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch, were founded in 1988 to provide our best service in EMC, Radio, Telecom and Safety consultation. Our laboratories are accredited and approved according to ISO/IEC 17025.

Copies of accreditation certificates of our laboratories obtained from approval agencies can be downloaded from our web site:

www.adt.com.tw/index.5/phtml. If you have any comments, please feel free to contact us at the following:

Linko EMC/RF Lab:

Tel: 886-2-26052180

Fax: 886-2-26051924

Hsin Chu EMC/RF Lab:

Tel: 886-3-5935343

Fax: 886-3-5935342

Hwa Ya EMC/RF/Safety/Telecom Lab:

Tel: 886-3-3183232

Fax: 886-3-3185050

Web Site: www.adt.com.tw

The address and road map of all our labs can be found in our web site also.

---END---

Test Laboratory: Bureau Veritas ADT

E_CDMA850-Ch1013

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 824.7 MHz

Communication System: CDMA850 ; Frequency: 824.7 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK
 Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;
 Phantom section: E Device Section ;
 Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch1013/Hearing Aid

Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **63.7** V/m

Probe Modulation Factor = 0.940



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 80.6 V/m; Power Drift = -0.003 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 52.4 M4	Grid 2 58.3 M4	Grid 3 57.1 M4
Grid 4 57.6 M4	Grid 5 63.7 M4	Grid 6 62.1 M4
Grid 7 64.7 M4	Grid 8 69.1 M4	Grid 9 65.9 M4



Test Laboratory: Bureau Veritas ADT

E_CDMA850-Ch384

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch384 /Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **72.3** V/m

Probe Modulation Factor = 0.940



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 93.4 V/m; Power Drift = -0.110 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 62.2 M4	Grid 2 67.3 M4	Grid 3 65.5 M4
Grid 4 67.0 M4	Grid 5 72.3 M4	Grid 6 69.9 M4
Grid 7 74.0 M4	Grid 8 78.2 M4	Grid 9 72.2 M4



Test Laboratory: Bureau Veritas ADT

E_CDMA850-Ch777

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 848.3 MHz

Communication System: CDMA850 ; Frequency: 848.3 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK
 Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;
 Phantom section: E Device Section ;
 Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch777/Hearing Aid

Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **63.2** V/m

Probe Modulation Factor = 0.940



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 82.5 V/m; Power Drift = -0.024 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 55.6 M4	Grid 2 59.0 M4	Grid 3 57.0 M4
Grid 4 60.2 M4	Grid 5 63.2 M4	Grid 6 60.3 M4
Grid 7 67.1 M4	Grid 8 68.8 M4	Grid 9 62.4 M4



Test Laboratory: Bureau Veritas ADT

E_CDMA850-Ch384 bat2

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch384/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **71.7** V/m

Probe Modulation Factor = 0.940



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 92.6 V/m; Power Drift = 0.068 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 61.4 M4	Grid 2 67.2 M4	Grid 3 65.2 M4
Grid 4 66.9 M4	Grid 5 71.7 M4	Grid 6 69.3 M4
Grid 7 73.9 M4	Grid 8 77.0 M4	Grid 9 72.0 M4



Test Laboratory: Bureau Veritas ADT

E_CDMA1900-Ch25

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1851.25 MHz

Communication System: CDMA1900 ; Frequency: 1851.25 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23

- Sensor-Surface: (Fix Surface)

- Electronics: DAE4 Sn861; Calibrated: 2010/1/22

- Phantom: HAC Test Arch; Type: SD HAC P01 BA;

- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch25/Hearing Aid

Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **68.1** V/m

Probe Modulation Factor = 0.990



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 75.7 V/m; Power Drift = -0.075 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 55.1 M4	Grid 2 58.4 M4	Grid 3 58.2 M4
Grid 4 56.7 M4	Grid 5 68.1 M3	Grid 6 66.5 M3
Grid 7 65.6 M3	Grid 8 72.4 M3	Grid 9 68.4 M3



Test Laboratory: Bureau Veritas ADT

E_CDMA1900-Ch600

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch600/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **82.7** V/m

Probe Modulation Factor = 0.990



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 91.1 V/m; Power Drift = 0.112 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 65.5 M3	Grid 2 71.4 M3	Grid 3 71.3 M3
Grid 4 67.8 M3	Grid 5 82.7 M3	Grid 6 80.9 M3
Grid 7 76.0 M3	Grid 8 86.1 M3	Grid 9 82.9 M3



Test Laboratory: Bureau Veritas ADT

E_CDMA1900-Ch1175

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1908.75 MHz

Communication System: CDMA1900 ; Frequency: 1908.75 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23

- Sensor-Surface: (Fix Surface)

- Electronics: DAE4 Sn861; Calibrated: 2010/1/22

- Phantom: HAC Test Arch; Type: SD HAC P01 BA;

- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch1175/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **77.7** V/m

Probe Modulation Factor = 0.990



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 89.6 V/m; Power Drift = -0.072 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 62.4 M4	Grid 2 68.8 M3	Grid 3 68.7 M3
Grid 4 65.3 M3	Grid 5 77.7 M3	Grid 6 76.1 M3
Grid 7 72.7 M3	Grid 8 81.3 M3	Grid 9 76.9 M3



Test Laboratory: Bureau Veritas ADT

E_CDMA1900-Ch600 Bat2

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³ ;

Phantom section: E Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - ER3D - 2007: 15 mm from Probe Center to the Device Ch600/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **82.4** V/m

Probe Modulation Factor = 0.990



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 91.7 V/m; Power Drift = -0.047 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 65.2 M3	Grid 2 71.2 M3	Grid 3 70.7 M3
Grid 4 67.2 M3	Grid 5 82.4 M3	Grid 6 80.6 M3
Grid 7 75.8 M3	Grid 8 85.6 M3	Grid 9 82.3 M3



Test Laboratory: Bureau Veritas ADT

H_CDMA850-Ch1013

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 824.7 MHz

Communication System: CDMA850 ; Frequency: 824.7 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK
 Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;
 Phantom section: H Device Section ;
 Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch1013/Hearing Aid

Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.150** A/m

Probe Modulation Factor = 0.910


Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.157 A/m; Power Drift = 0.057 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.132 M4	Grid 2 0.119 M4	Grid 3 0.093 M4
Grid 4 0.156 M4	Grid 5 0.150 M4	Grid 6 0.118 M4
Grid 7 0.188 M4	Grid 8 0.173 M4	Grid 9 0.133 M4



Test Laboratory: Bureau Veritas ADT

H_CDMA850-Ch384

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch384/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.157** A/m

Probe Modulation Factor = 0.910


Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.169 A/m; Power Drift = 0.011 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.137 M4	Grid 2 0.126 M4	Grid 3 0.100 M4
Grid 4 0.161 M4	Grid 5 0.157 M4	Grid 6 0.128 M4
Grid 7 0.194 M4	Grid 8 0.180 M4	Grid 9 0.144 M4



Test Laboratory: Bureau Veritas ADT

H_CDMA850-Ch777

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 848.3 MHz

Communication System: CDMA850 ; Frequency: 848.3 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK
 Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;
 Phantom section: H Device Section ;
 Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch777/Hearing Aid

Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.146** A/m

Probe Modulation Factor = 0.910



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.162 A/m; Power Drift = -0.042 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.121 M4	Grid 2 0.117 M4	Grid 3 0.096 M4
Grid 4 0.146 M4	Grid 5 0.146 M4	Grid 6 0.122 M4
Grid 7 0.172 M4	Grid 8 0.168 M4	Grid 9 0.137 M4



Test Laboratory: Bureau Veritas ADT

H_CDMA850-Ch384 Bat2

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24

- Sensor-Surface: (Fix Surface)

- Electronics: DAE4 Sn861; Calibrated: 2010/1/22

- Phantom: HAC Test Arch; Type: SD HAC P01 BA;

- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch384/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.156** A/m

Probe Modulation Factor = 0.910



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.168 A/m; Power Drift = -0.107 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.136 M4	Grid 2 0.125 M4	Grid 3 0.099 M4
Grid 4 0.160 M4	Grid 5 0.156 M4	Grid 6 0.125 M4
Grid 7 0.193 M4	Grid 8 0.179 M4	Grid 9 0.141 M4



Test Laboratory: Bureau Veritas ADT

H_CDMA1900-Ch25

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1851.25 MHz

Communication System: CDMA1900 ; Frequency: 1851.25 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch25/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.224** A/m

Probe Modulation Factor = 0.950



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.269 A/m; Power Drift = -0.034 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.189 M4	Grid 2 0.192 M3	Grid 3 0.175 M4
Grid 4 0.219 M3	Grid 5 0.224 M3	Grid 6 0.197 M3
Grid 7 0.220 M3	Grid 8 0.226 M3	Grid 9 0.197 M3



Test Laboratory: Bureau Veritas ADT

H_CDMA1900-Ch600

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DASYS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASYS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch600/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.253** A/m

Probe Modulation Factor = 0.950



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.304 A/m; Power Drift = -0.010 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.214 M3	Grid 2 0.217 M3	Grid 3 0.196 M3
Grid 4 0.246 M3	Grid 5 0.253 M3	Grid 6 0.221 M3
Grid 7 0.247 M3	Grid 8 0.255 M3	Grid 9 0.221 M3



Test Laboratory: Bureau Veritas ADT

H_CDMA1900-Ch1175

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1908.75 MHz

Communication System: CDMA1900 ; Frequency: 1908.75 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch1175/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.242** A/m

Probe Modulation Factor = 0.950



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.296 A/m; Power Drift = -0.119 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.207 M3	Grid 2 0.210 M3	Grid 3 0.189 M4
Grid 4 0.234 M3	Grid 5 0.242 M3	Grid 6 0.213 M3
Grid 7 0.235 M3	Grid 8 0.243 M3	Grid 9 0.213 M3



Test Laboratory: Bureau Veritas ADT

H_CDMA1900-Ch600 Bat2

DUT: Pocket Pc Phone ; Type: PC36100 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz ; Duty Cycle: 1:1 Modulation type: OQPSK

Medium: Air Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³ ;

Phantom section: H Device Section ;

Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA;
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - H3DV6 - 2007: 15 mm from Probe Center to the Device Ch600/Hearing Aid Compatibility Test (101x101x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.252** A/m

Probe Modulation Factor = 0.950



Device Reference Point: 0.000, 0.000, 353.7 mm

Reference Value = 0.302 A/m; Power Drift = -0.046 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.212 M3	Grid 2 0.216 M3	Grid 3 0.194 M3
Grid 4 0.245 M3	Grid 5 0.252 M3	Grid 6 0.220 M3
Grid 7 0.246 M3	Grid 8 0.253 M3	Grid 9 0.220 M3



Test Laboratory: Bureau Veritas ADT

E_Dipole_WD_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: OQPSK

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³

Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **154.1** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 115.4 V/m; Power Drift = -0.148 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 146.7 M4	Grid 2 149.0 M4	Grid 3 143.7 M4
Grid 4 81.1 M4	Grid 5 84.0 M4	Grid 6 82.1 M4
Grid 7 148.5 M4	Grid 8 154.1 M4	Grid 9 150.4 M4



Test Laboratory: Bureau Veritas ADT

E_Dipole_CW_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: CW ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³

Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23

- Sensor-Surface: (Fix Surface)

- Electronics: DAE4 Sn861; Calibrated: 2010/1/22

- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202

- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **145.2** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 109.2 V/m; Power Drift = -0.022 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 139.3 M4	Grid 2 142.1 M4	Grid 3 138.7 M4
Grid 4 76.9 M4	Grid 5 79.8 M4	Grid 6 78.7 M4
Grid 7 140.7 M4	Grid 8 145.2 M4	Grid 9 142.8 M4



Test Laboratory: Bureau Veritas ADT

E_Dipole_AM_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: AM ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: AM
 Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³
 Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **130.5** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 98.9 V/m; Power Drift = -0.009 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 126.3 M4	Grid 2 127.9 M4	Grid 3 125.5 M4
Grid 4 71.0 M4	Grid 5 73.2 M4	Grid 6 72.3 M4
Grid 7 127.4 M4	Grid 8 130.5 M4	Grid 9 128.9 M4



Test Laboratory: Bureau Veritas ADT

E_Dipole_WD_1880

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: OQPSK

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³

Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **102.2** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 101.7 V/m; Power Drift = -0.029 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 101.4 M3	Grid 2 102.2 M3	Grid 3 98.0 M3
Grid 4 71.4 M3	Grid 5 74.0 M3	Grid 6 73.2 M3
Grid 7 98.9 M3	Grid 8 101.5 M3	Grid 9 99.5 M3



Test Laboratory: Bureau Veritas ADT

E_Dipole_CW_1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CW ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: CW
 Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³
 Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **101.3** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 101.1 V/m; Power Drift = -0.020 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 98.9 M3	Grid 2 100.2 M3	Grid 3 96.8 M3
Grid 4 71.9 M3	Grid 5 73.9 M3	Grid 6 72.6 M3
Grid 7 99.1 M3	Grid 8 101.3 M3	Grid 9 99.1 M3



Test Laboratory: Bureau Veritas ADT

E_Dipole_AM_1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: AM ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: AM
 Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³
 Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **87.3** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 87.4 V/m; Power Drift = -0.005 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 85.7 M3	Grid 2 86.6 M3	Grid 3 83.8 M3
Grid 4 62.8 M4	Grid 5 64.4 M3	Grid 6 63.4 M3
Grid 7 85.9 M3	Grid 8 87.3 M3	Grid 9 85.7 M3



Test Laboratory: Bureau Veritas ADT

H_WD_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: CDMA850 ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: OQPSK

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.464** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.487 A/m; Power Drift = -0.096 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.395 M4	Grid 2 0.408 M4	Grid 3 0.380 M4
Grid 4 0.449 M4	Grid 5 0.464 M4	Grid 6 0.435 M4
Grid 7 0.401 M4	Grid 8 0.416 M4	Grid 9 0.392 M4



Test Laboratory: Bureau Veritas ADT

H_CW_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: CW ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.422** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.446 A/m; Power Drift = -0.058 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.366 M4	Grid 2 0.375 M4	Grid 3 0.357 M4
Grid 4 0.412 M4	Grid 5 0.422 M4	Grid 6 0.404 M4
Grid 7 0.367 M4	Grid 8 0.379 M4	Grid 9 0.363 M4



Test Laboratory: Bureau Veritas ADT

H_Dipole_AM_836.52MHz

DUT: HAC-Dipole 835 MHz ; Type: D835V3 ; Serial: 1149 ; Test Frequency: 836.52 MHz

Communication System: AM ; Frequency: 836.52 MHz; Duty Cycle: 1:1; Modulation type: AM

Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.396** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.417 A/m; Power Drift = -0.004 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.342 M4	Grid 2 0.351 M4	Grid 3 0.334 M4
Grid 4 0.386 M4	Grid 5 0.396 M4	Grid 6 0.379 M4
Grid 7 0.343 M4	Grid 8 0.355 M4	Grid 9 0.340 M4



Test Laboratory: Bureau Veritas ADT

H_Dipole_WD_1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CDMA1900 ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: OQPSK

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.390** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.413 A/m; Power Drift = -0.016 dB

Hearing Aid Near-Field Category: M2 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.341 M2	Grid 2 0.351 M2	Grid 3 0.332 M3
Grid 4 0.379 M2	Grid 5 0.390 M2	Grid 6 0.369 M2
Grid 7 0.344 M2	Grid 8 0.356 M2	Grid 9 0.336 M3



Test Laboratory: Bureau Veritas ADT

H_Dipole_CW_1880

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CW ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: CW
 Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³
 Phantom section: H Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.371** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.390 A/m; Power Drift = -0.004 dB

Hearing Aid Near-Field Category: M2 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.329 M3	Grid 2 0.335 M3	Grid 3 0.318 M3
Grid 4 0.364 M2	Grid 5 0.371 M2	Grid 6 0.353 M2
Grid 7 0.333 M3	Grid 8 0.341 M2	Grid 9 0.324 M3



Test Laboratory: Bureau Veritas ADT

H_Dipole_AM_1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: AM ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: AM
 Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³
 Phantom section: H Dipole Section Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.334** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.350 A/m; Power Drift = 0.014 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.294 M3	Grid 2 0.301 M3	Grid 3 0.284 M3
Grid 4 0.326 M3	Grid 5 0.334 M3	Grid 6 0.316 M3
Grid 7 0.298 M3	Grid 8 0.306 M3	Grid 9 0.291 M3



Test Laboratory: Bureau Veritas ADT

E_835MHz

DUT: HAC-Dipole 835 MHz ; Type: CD835V3 ; Serial: 1149 ; Test Frequency: 835 MHz

Communication System: CW ; Frequency: 835 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³

Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **138.2** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 104.7 V/m; Power Drift = -0.041 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak E-field in V/m

Grid 1 135.3 M4	Grid 2 137.1 M4	Grid 3 132.8 M4
Grid 4 74.0 M4	Grid 5 76.8 M4	Grid 6 75.8 M4
Grid 7 133.0 M4	Grid 8 138.2 M4	Grid 9 136.2 M4



Test Laboratory: Bureau Veritas ADT

E_1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CW ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air; Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1000$ kg/m³

Phantom section: E Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: ER3DV6 - SN2302 ; ConvF(1, 1, 1) ; Calibrated: 2009/6/23
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

E Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **111.1** V/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 110.5 V/m; Power Drift = -0.011 dB

Hearing Aid Near-Field Category: M3 (AWF 0 dB)

Peak E-field in V/m

Grid 1 109.6 M3	Grid 2 111.1 M3	Grid 3 106.9 M3
Grid 4 78.0 M3	Grid 5 80.6 M3	Grid 6 79.5 M3
Grid 7 107.8 M3	Grid 8 110.7 M3	Grid 9 108.5 M3



Test Laboratory: Bureau Veritas ADT

H_835MHz

DUT: HAC-Dipole 835 MHz ; Type: CD835V3 ; Serial: 1149 ; Test Frequency: 835 MHz

Communication System: CW ; Frequency: 835 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DAS4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DAS4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD835 Dipole = 10mm/Hearing Aid Compatibility Test (41x361x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.414** A/m

Probe Modulation Factor = 1.00



Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.441 A/m; Power Drift = -0.141 dB

Hearing Aid Near-Field Category: M4 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.357 M4	Grid 2 0.365 M4	Grid 3 0.347 M4
Grid 4 0.404 M4	Grid 5 0.414 M4	Grid 6 0.395 M4
Grid 7 0.361 M4	Grid 8 0.372 M4	Grid 9 0.357 M4



Test Laboratory: Bureau Veritas ADT

H 1880MHz

DUT: HAC Dipole 1880 MHz ; Type: CD1880V3 ; Serial: 1032 ; Test Frequency: 1880 MHz

Communication System: CW ; Frequency: 1880 MHz; Duty Cycle: 1:1; Modulation type: CW

Medium: Air;Medium parameters used: $\sigma = 0$ mho/m, $\epsilon_r = 1$; $\rho = 1$ kg/m³

Phantom section: H Dipole Section Measurement Standard: DASY4 (High Precision Assessment);

DASY4 Configuration:

- Probe: H3DV6 - SN6187 ; ; Calibrated: 2009/6/24
- Sensor-Surface: (Fix Surface)
- Electronics: DAE4 Sn861; Calibrated: 2010/1/22
- Phantom: HAC Test Arch; Type: SD HAC P01 BA; Serial: TP-1202
- Measurement SW: DASY4, V4.7 Build 80; Postprocessing SW: SEMCAD, V1.8 Build 186

H Scan - measurement distance from the probe sensor center to CD1880 Dipole = 10mm/Hearing Aid Compatibility Test (41x181x1): Measurement grid: dx=5mm, dy=5mm

Maximum value of peak Total field = **0.391** A/m

Probe Modulation Factor = 1.00

Device Reference Point: 0.000, 0.000, 354.7 mm

Reference Value = 0.412 A/m; Power Drift = -0.027 dB

Hearing Aid Near-Field Category: M2 (AWF 0 dB)

Peak H-field in A/m

Grid 1 0.347 M2	Grid 2 0.354 M2	Grid 3 0.337 M3
Grid 4 0.384 M2	Grid 5 0.391 M2	Grid 6 0.371 M2
Grid 7 0.351 M2	Grid 8 0.357 M2	Grid 9 0.338 M3

