

# INTERTEK TESTING SERVICES

## MEASUREMENT/TECHNICAL REPORT

**Sky City International Ltd. - MODEL: SC6208ACR**  
**RXFCC ID: NW9-SKY-SC-R**

This report concerns (check one:)      Original Grant       Class II Change

Equipment Type: Superregenerative Receiver (example: computer, printer, modem, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37?      Yes       No

If no, assumed Part 15, Subpart B for unintentional radiator - the new 47 CFR [10-1-96 Edition] provision.

Report prepared by:

C. K. Lam  
Intertek Testing Services  
Hong Kong Ltd.  
2/F., Garment Centre,  
576, Castle Peak Road,  
Kowloon, Hong Kong  
Phone: 852-746-8211  
Fax: 852-785-5487

# INTERTEK TESTING SERVICES

---

## Table of Contents

<b>1.0 General Description</b> .....	2
1.1 Product Description .....	2
1.2 Related Submittal(s) Grants .....	2
1.3 Test Methodology.....	3
1.4 Test Facility .....	3
<b>2.0 System Test Configuration</b> .....	5
2.1 Justification .....	5
2.2 EUT Exercising Software .....	5
2.4 Equipment Modification .....	6
<b>3.0 Emission Results</b> .....	8
3.1 Field Strength Calculation .....	9
3.2 Radiated Emission Configuration Photograph.....	10
3.3 Radiated Emission Data.....	12
3.4 Conducted Emission Configuration Photograph (cont'd) .....	16
<b>4.0 Equipment Photographs</b> .....	21
<b>5.0 Product Labelling</b> .....	23
5.1 Label Artwork.....	24
5.2 Label Location .....	25
<b>6.0 Technical Specifications</b> .....	27
<b>7.0 Instruction Manual</b> .....	31
<b>8.0 Miscellaneous Information</b> .....	33
8.1 Stabilization Waveform .....	34
8.2 Discussion of Pulse Desensitization.....	35
8.3 Calculation of Average Factor .....	36
8.4 Emissions Test Procedures .....	37

## **INTERTEK TESTING SERVICES**

---

---

### **List of Figures**

Figure 5.1	FCC ID Label.....	24
Figure 5.2	Label Location.....	25
Figure 6.1	Superregenerative Receiver Block Diagram.....	28
Figure 6.2	Superregenerative Receiver Schematic .....	29

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 1**

**GENERAL DESCRIPTION**

## INTERTEK TESTING SERVICES

---

### 1.0 **General Description**

#### 1.1 Product Description

The Equipment Under Test (EUT) is a superregenerative receiver of a remote control emergency light operating at 318 MHz. The EUT is powered by AC mains. There is only one control switch (ON/OFF/remote control) on the EUT. Once the switch is turned to remote control, the EUT receives the R.F. signal to control the light ON or OFF. This application is only for the superregenerative receiver, there is another application for the fluorescent lamp which FCCID is NW9-SKY-SC-S.

The brief circuit description is listed in the following.

- $Q_9$  and associated circuit act as an oscillation receiver.
- $U_1$  and associated circuit act as an amplifier.
- $U_2$  and associated circuit act as a starter.
- $U_3$  and associated circuit act as a demodulator.
- $Q_1$  and associated circuit act as a regulator.

#### 1.2 Related Submittal(s) Grants

This is an application for Certification of a receiver. The FCC ID for the transmitter associated with this receiver is NW9-SKY-SC-T.

## INTERTEK TESTING SERVICES

---

### 1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All radiated measurements were performed in an Open Area Test Site. Preliminary scans were performed in the Open Area Test Site only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "Justification Section" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the radiated data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been placed on file with the FCC.

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 2**

**SYSTEM TEST CONFIGURATION**

## **INTERTEK TESTING SERVICES**

---

### **2.0 System Test Configuration**

#### **2.1 Justification**

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (1992).

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The unit was operated standalone and placed in the center of the turntable.

The device was powered from AC mains.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). In order to maximize the emission, the test engineer placed the EUT in three orthogonal axes.

#### **2.2 EUT Exercising Software**

There was no special software to exercise the device. Once the unit is powered up, it received continuously.

#### **2.3 Support Equipment List and Description**

This product was tested in standalone configuration.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by Sky City International Ltd. will be incorporated in each production model sold/leased in the United States.

No modifications were installed by Intertek Testing Services.

### 2.5 Special Accessories

There are no special accessories necessary for compliance of this product.

*Confirmed by:*

*C. K. Lam  
Assistant Manager - EMC  
Intertek Testing Services  
Hong Kong Ltd.  
Agent for Sky City International Ltd.*

*Lam*

Signature

*June 21, 1998*

Date

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 3**  
**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

---

### 3.0 Emission Results

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in  $\text{dB}\mu\text{V}/\text{m}$

RA = Receiver Amplitude (including preamplifier) in  $\text{dB}\mu\text{V}$

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:

$$FS = RR + LF$$

where FS = Field Strength in  $\text{dB}\mu\text{V}/\text{m}$

RR = RA - AG in  $\text{dB}\mu\text{V}$

LF = CF + AF in dB

Assume a receiver reading of 52.0  $\text{dB}\mu\text{V}$  is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB are added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32  $\text{dB}\mu\text{V}/\text{m}$ . This value in  $\text{dB}\mu\text{V}/\text{m}$  was converted to its corresponding level in  $\mu\text{V}/\text{m}$ .

RA = 52.0  $\text{dB}\mu\text{V}/\text{m}$

AF = 7.4 dB

RR = 23.0  $\text{dB}\mu\text{V}$

CF = 1.6 dB

LF = 9.0 dB

AG = 29.0 dB

FS = RR + LF

FS = 23 + 9 = 32  $\text{dB}\mu\text{V}/\text{m}$

Level in  $\mu\text{V}/\text{m}$  = Common Antilogarithm  $[(32 \text{ dB}\mu\text{V}/\text{m})/20] = 39.8 \mu\text{V}/\text{m}$

## INTERTEK TESTING SERVICES

---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 5.8 dB

\*All readings are peak unless stated otherwise

### TEST PERSONNEL:

  
\_\_\_\_\_  
Signature

Kenneth H. M. Lam, Compliance Engineer  
Typed/Printed Name

June 25, 1998  
Date

## INTERTEK TESTING SERVICES

---

Company: Sky City International Ltd.  
Model: SC6208ACR

Date of Test: 16 June, 1998

**Table 1**

### FCC Class B Radiated Emissions

Polarity	Frequency (MHz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
H	306.569	26.7	23	16	33.7	46	-12.3
H	308.064	27.2	23	16	34.2	46	-11.8
H	309.559	28.8	23	16	35.8	46	-10.2
H	311.052	30.4	23	16	37.4	46	-8.6
H	312.548	31.9	23	16	38.9	46	-7.1
H	314.047	33.2	23	16	40.2	46	-5.8
H	315.542	30.6	23	16	37.6	46	-8.4
H	317.038	28.3	23	16	35.3	46	-10.7
H	318.527	28.2	23	16	35.2	46	-10.8
H	320.021	27.6	23	16	34.6	46	-11.4

NOTES: 1. Negative sign in the column shows value below limit.  
2. Peak Detector Data.  
3. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

Test Engineer: Kenneth H. M. Lam

## INTERTEK TESTING SERVICES

---

### 3.5 Conducted Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.


Judgement: Passed by 7.8 dB

\*All readings are peak unless stated otherwise

### **TEST PERSONNEL:**

  
\_\_\_\_\_  
Signature

Kenneth H. M. Lam, Compliance Engineer  
Typed/Printed Name

  
\_\_\_\_\_  
Date

## **INTERTEK TESTING SERVICES**

---

Company: Sky City International Ltd.  
Model: SC6208ACR

Date of Test: 16 June, 1998

Graph 1

### **Conducted Emissions Section 15.107 Requirements**



## **INTERTEK TESTING SERVICES**

---

Company: Sky City International Ltd.  
Model: SC6208ACR

Date of Test: 16 June, 1998

Table 2

**Conducted Emissions  
Section 15.107 Requirements**

# ITS Intertek Testing Services

ETL Testing Laboratories

Report No. 3803399

Tested By:Hong, Report No.:9803399

Scan Settings (1 Range):

Frequencies				Receiver Settings				
Start	Stop	Step	IF BW	Detector	M-Time	Atten	Preamp	OpRge
450k	30M	5k	10k	PK	20ms	AUTO	LN	OFF
60dB								

Final Measurement Results:

Frequency MHz	QP Level dBuV	QP Limit dBuV
0.48000	40.2	48.0
0.60000	37.6	48.0
0.72000	36.5	48.0
0.99000	32.3	48.0
1.35500	32.2	48.0
1.68500	36.9	48.0
2.78000	30.4	48.0
3.26500	33.4	48.0
3.94500	33.8	48.0
4.80000	35.9	48.0

\* limit exceeded

Ctrl. No.: N/A

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 4**

**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 Equipment Photographs

Photographs of the tested EUT are attached.

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

## **INTERTEK TESTING SERVICES**

---

### **8.0 Miscellaneous Information**

This miscellaneous information includes details of the stabilizing process (including a plot of the stabilized waveform), the test procedure and calculation of factors such as pulse desensitization and averaging factor.

## INTERTEK TESTING SERVICES

---

### 8.1 Stabilization Waveform

Previous to the testing, the superregenerative receiver was stabilized as outlined in the test procedure. The plot on the following page shows the fundamental emission when a signal generator was used to stabilize the receiver. Please note that the antenna was placed as close as possible to the EUT for clear demonstration of the waveform and that accurate readings are not possible from this plot.

HF

REF 87.0 dB  $\mu$ V

PEAK  
LOG  
10  
dB/

MARKER  
NORMAL  
△

MARKER  
AMPTD

SELECT  
1 2 3 4

MARKER 1  
ON OFF

More  
1 of 3

SPAN 100.0 MHz  
#SWP 50.0 msec

CENTER 302.5 MHz  
#RES BW 100 kHz

VA SB  
SC FC  
CORR

## **INTERTEK TESTING SERVICES**

---

### **8.2 Discussion of Pulse Desensitization**

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, *Spectrum Analysis ... Pulsed RF*.

This device is a superregenerative receiver. The stabilized signals are continuous, and no desensitization of the measurement equipment occurs.

## INTERTEK TESTING SERVICES

---

### 8.3 Calculation of Average Factor

The emission limits are specified using spectrum analyzers or receivers which incorporate quasi-peak detectors. Typical measurements are made using peak detectors, however, emissions which approach the respective emission limit are measured using a quasi-peak detector.

For measurements above 1 GHz, spectrum analyzers or receivers using average detectors are employed, or the appropriate average factor can be applied.

Measurements using spectrum analyzers with filters other than peak detectors are recorded in the data table section of this report.

This device is a superregenerative receiver.

It is not necessary to apply average factor to the measurement results.

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services Hong Kong Ltd. in the measurements of superregenerative receivers operating under the Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 1992. Superregenerative receivers are stabilized prior to measurement by generating a signal well above the receiver threshold whose frequency is tuned until the emissions stabilize into a line spectrum. The signal is usually generated as CW with a Marconi 2022D signal generator and a short whip antenna and is at a level of several hundred to several thousand mV/m. Plots of the stabilized signal will be shown. If a modulated signal is used, it will be noted.

The equipment under test (EUT) is attached to a cardboard box and placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the groundplane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The cardboard box is adjusted through all three orthogonal axis to obtain maximum emission levels. The antenna height and polarization are also varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings. A detailed description for the calculation of the average factor can be found in Exhibit 8.3.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 450 kHz to 30 MHz.

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures (cont)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements were made as described in ANSI C63.4 - 1992.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.2). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Measurements are normally conducted at a measurement distance of three meters. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.