



SAR TEST REPORT

For

Hi-Target Surveying Instrument Co., Ltd.

Handheld Controller

Test Model:iHand55

Prepared for : Hi-Target Surveying Instrument Co., Ltd.
Address : 202, BLDG 13, Tian' An HQ Center, No.555 North Panyu RD.
Donghuan Block, Panyu District, 511400 Guangzhou, China


Prepared by : Shenzhen LCS Compliance Testing Laboratory Ltd.
Address : 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park
Yabianxueziwei, Shajing Street, Baoan District, Shenzhen,
518000, China
Tel : (86)755-82591330
Fax : (86)755-82591332
Web : www.LCS-cert.com
Mail : webmaster@LCS-cert.com

Date of receipt of test sample : June 26, 2023
Number of tested samples : 1
Sample No. : A062523059-1
Serial number : Prototype
Date of Test : June 26, 2023~ August 03, 2023
Date of Report : August 07, 2023



**SAR TEST REPORT****Report Reference No.**.....: **LCSA062523059EB****Date Of Issue**.....: August 07, 2023**Testing Laboratory Name**.....: **Shenzhen LCS Compliance Testing Laboratory Ltd.****Address**.....: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China**Applicant's Name**.....: **Hi-Target Surveying Instrument Co., Ltd.****Address**.....: 202, BLDG 13, Tian' An HQ Center, No.555 North Panyu RD. Donghuan Block, Panyu District, 511400 Guangzhou, China**Test Specification:****Standard**.....: IEEE Std C95.1, 2019/ IEC-IEEE 62209-1528-2020/FCC Part 2.1093**Test Report Form No.**.....: LCSEMC-1.0**TRF Originator**.....: Shenzhen LCS Compliance Testing Laboratory Ltd.**Master TRF**.....: Dated 2011-03**Shenzhen LCS Compliance Testing Laboratory Ltd. All rights reserved.**


This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen LCS Compliance Testing Laboratory Ltd. is acknowledged as copyright owner and source of the material. Shenzhen LCS Compliance Testing Laboratory Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test Item Description.....: **Handheld Controller****Trade Mark**.....:  **Hi-Target****Model/Type Reference**.....: iHand55**Operation Frequency**.....: GSM 850,1900;WCDMA II,IV,V;
LTE2,4,5,7,12,17,38,41;WLAN2.4G,5.2G,5.3G,5.5G,5.8G;
Bluetooth5.0 and NFC.**Ratings**.....: DC 3.85V by Rechargeable Li-ion Battery, 9200mAh**Result**: **Positive****Compiled by:**

Jay Zhan/ File administrators

Supervised by:

Cary Luo / Technique principal

Approved by:

Gavin Liang/ Manager



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR -- TEST REPORT****Test Report No. : LCSA062523059EB**August 07, 2023
Date of issue

Type / Model..... : iHand55

EUT..... : Handheld Controller

Applicant..... : Hi-Target Surveying Instrument Co., Ltd.Address..... : 202, BLDG 13, Tian' An HQ Center, No.555 North Panyu
RD. Donghuan Block, Panyu District, 511400 Guangzhou,
China

Telephone..... : /

Fax..... : /

Manufacturer..... : Hi-Target Surveying Instrument Co., Ltd.Address..... : 202, BLDG 13, Tian' An HQ Center, No.555 North Panyu
RD. Donghuan Block, Panyu District, 511400 Guangzhou,
China

Telephone..... : /

Fax..... : /

Factory..... : Hi-Target Surveying Instrument Co., Ltd.Address..... : 202, BLDG 13, Tian' An HQ Center, No.555 North Panyu
RD. Donghuan Block, Panyu District, 511400 Guangzhou,
China

Telephone..... : /

Fax..... : /

Test Result**Positive**

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen,
518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Revision History

Revision	Issue Date	Revision Content	Revised By
000	August 07, 2023	Initial Issue	---





TABLE OF CONTENTS

1. TEST STANDARDS AND TEST DESCRIPTION.....	6
1.1. TEST STANDARDS.....	6
1.2. TEST DESCRIPTION.....	6
1.3. GENERAL REMARKS.....	6
1.4. PRODUCT DESCRIPTION.....	6
1.5. STATEMENT OF COMPLIANCE.....	9
2. TEST ENVIRONMENT.....	10
2.1. TEST FACILITY.....	10
2.2. ENVIRONMENTAL CONDITIONS.....	10
2.3. SAR LIMITS.....	10
2.4. EQUIPMENTS USED DURING THE TEST.....	11
3. SAR MEASUREMENTS SYSTEM CONFIGURATION.....	12
3.1. SARMEASUREMENT SET-UP.....	12
3.2. OPENSAR E-FIELD PROBE SYSTEM.....	13
3.3. PHANTOMS.....	14
3.4. DEVICE HOLDER.....	14
3.5. SCANNING PROCEDURE.....	15
3.6. DATA STORAGE AND EVALUATION.....	17
3.7. TISSUE DIELECTRIC PARAMETERS FOR HEAD AND BODY PHANTOMS.....	19
3.8. TISSUE EQUIVALENT LIQUID PROPERTIES.....	19
3.9. SYSTEM CHECK.....	20
3.10. SAR MEASUREMENT PROCEDURE.....	23
3.11. POWER REDUCTION.....	28
3.12. POWER DRIFT.....	28
4. TEST CONDITIONS AND RESULTS.....	29
4.1. CONDUCTED POWER RESULTS.....	29
4.2. TRANSMIT ANTENNAS AND SAR MEASUREMENT POSITION.....	60
4.3. SAR MEASUREMENT RESULTS.....	61
4.4. SIMULTANEOUS TX SAR CONSIDERATIONS.....	67
4.5. SAR MEASUREMENT VARIABILITY.....	71
4.6. GENERAL DESCRIPTION OF TEST PROCEDURES.....	72
4.7. MEASUREMENT UNCERTAINTY (450MHZ-6GHZ).....	72
4.8. SYSTEM CHECK RESULTS.....	73
4.9. SAR TEST GRAPH RESULTS.....	83
5. CALIBRATION CERTIFICATES.....	101
5.1. PROBE-EPGO376 CALIBRATION CERTIFICATE.....	101
5.2. SID750DIPOLE CALIBRATION CERITICATE.....	112
5.3. SID835DIPOLE CALIBRATION CERITICATE.....	123
5.4. SID1800 DIPOLE CALIBRATION CERTIFICATE.....	134
5.5. SID1900 DIPOLE CALIBRATION CERTIFICATE.....	145
5.6. SID2450 DIPOLE CALIBRATION CERITICATE.....	156
5.7. SID2600 DIPOLE CALIBRATION CERITICATE.....	167
5.8. SID5-6G DIPOLE CALIBRATION CERITICATE.....	178
6. PHOTOGRAPHS OF THE LIQUID.....	191
7. PHOTOGRAPHS OF THE TEST.....	196
8. EUT PHOTOGRAPHS.....	197





1. TEST STANDARDS AND TEST DESCRIPTION

1.1. Test Standards

[IEEE Std C95.1-2019](#): IEEE Standard for Safety Levels with Respect to Human Exposure to Electric, Magnetic, and Electromagnetic Fields, 0 Hz to 300 GHz. It specifies the maximum exposure limit of 1.6 W/kg as averaged over any 1 gram of tissue for portable devices being used within 20 cm of the user in the uncontrolled environment.

[IEC-IEEE 62209-1528-2020](#): Measurement procedure for the assessment of specific absorption rate of human exposure to radio frequency fields from hand-held and body-mounted wireless communication devices –Part 1528: Human models, instrumentation, and procedures (Frequency range of 4 MHz to 10 GHz).

[FCC Part 2.1093 Radiofrequency Radiation Exposure Evaluation](#): Portable Devices

[KDB447498 D01 General RF Exposure Guidance v06](#): Mobile and Portable Device RF Exposure Procedures and Equipment Authorization Policies

[KDB447498 D02 SAR Procedures for Dongle Xmtr v02r01](#): SAR Measurement Procedures For USB Dongle Transmitters.

[KDB865664 D01 SAR Measurement 100 MHz to 6 GHz v01r04](#): SAR Measurement Requirements for 100 MHz to 6 GHz

[KDB865664 D02 RF Exposure Reporting v01r02](#): RF Exposure Compliance Reporting and Documentation Considerations

[KDB 248227 D01 802.11 Wi-Fi SAR v02r02](#): SAR GUIDANCE FOR IEEE 802.11 (Wi-Fi) TRANSMITTERS

[KDB941225 D01 3G SAR Procedures](#): 3G SAR MEASUREMENT PROCEDURES

[KDB 941225 D05 SAR for LTE Devices](#): SAR Evaluation Considerations For LTE Devices

1.2. Test Description

The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power. And Test device is identical prototype.

1.3. General Remarks

Date of receipt of test sample	:	June 26, 2023
Testing commenced on	:	June 26, 2023
Testing concluded on	:	August 03, 2023

1.4. Product Description

The Hi-Target Surveying Instrument Co., Ltd.'s Model: iHand55 or the "EUT" as referred to in this report; more general information as follows, for more details, refer to the user's manual of the EUT.

General Description	
EUT :	Handheld Controller
Model/Type reference:	iHand55
Additional Model No.	/
Model Declaration:	/
Hardware Version	V1.0
Firmware Version:	/
Power supply:	DC 3.85V by Rechargeable Li-ion Battery, 9200mAh
The EUT is Handheld Controller. the Handheld Controller is intended for WLAN transmission. It is equipped with Bluetooth,NFC;WiFi2.4G,5.2G, 5.3G, 5.5G,5.8G; GSM 850,1900; WCDMA Band II, Band IV ,Band V; LTE 2,4,5,7,12,17,38,41. For more information see the following datasheet	

Technical Characteristics	
LTE	
Operation Band:	☒ E-UTRA Band 2(U.S.-Band) ☒ E-UTRA Band 4(U.S.-Band)





	☒ E-UTRA Band 5(U.S.-Band) ☒ E-UTRA Band 7(U.S.-Band) ☒ E-UTRA Band 12(U.S.-Band) ☒ E-UTRA Band 17(U.S.-Band) ☒ E-UTRA Band 38(U.S.-Band) ☒ E-UTRA Band 41(U.S.-Band)
Modulation Type:	QPSK/16QAM
Release Version:	R11
Power Class:	Class 3
Antenna Description:	FPC Antenna 1.14dBi (max.) For E-UTRA Band 2 1.03dBi (max.) For E-UTRA Band 4 -2.76dBi (max.) For E-UTRA Band 5 1.05dBi (max.) For E-UTRA Band 7 -3.37dBi (max.) For E-UTRA Band 12 -3.37dBi (max.) For E-UTRA Band 17 1.81dBi (max.) For E-UTRA Band 38 1.81dBi (max.) For E-UTRA Band 41

Bluetooth

Frequency Range:	2402MHz ~ 2480MHz
Chanel Number:	79 channels for Bluetooth V5.0 (DSS) 40 channels for Bluetooth V5.0 (DTS)
Chanel Spacing:	1MHz for Bluetooth V5.0 (DSS) 2MHz for Bluetooth V5.0 (DTS)
Modulation Type;	GFSK, $\pi/4$ -DQPSK, 8-DPSK for Bluetooth V5.0 (DSS) GFSK for Bluetooth V5.0 (DTS)
Bluetooth Version:	V5.0
Antenna Description:	FPC Antenna, 1.66dBi(Max.)

WIFI(2.4G Band)

Frequency Range	2412MHz~2462MHz
Channel Spacing	5MHz
Channel Number	11 Channels for 20MHz bandwidth (2412~2462MHz) 7 Channels for 40MHz bandwidth (2422~2452MHz)
Modulation Type	IEEE 802.11b: DSSS (CCK, DQPSK, DBPSK) IEEE 802.11g: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11n: OFDM (64QAM, 16QAM, QPSK, BPSK)
Antenna Description	FPC Antenna, 1.66dBi(Max.)

WIFI(5.2G Band)

Frequency Range	5180MHz~5240MHz
Channel Number	4 Channels for 20MHz bandwidth(5180MHz~5240MHz) 2 channels for 40MHz bandwidth(5190MHz~5230MHz) 1 channels for 80MHz bandwidth(5210MHz)
Modulation Type	IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Antenna Description	FPC Antenna, 0.89dBi(Max.)

WIFI(5.3G Band)

Frequency Range	5260MHz~5320MHz
Channel Number	4 Channels for 20MHz bandwidth(5260MHz~5320MHz) 2 channels for 40MHz bandwidth(5270MHz~5310MHz) 1 channels for 80MHz bandwidth(5290MHz)
Modulation Type	IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Antenna Description	FPC Antenna, 1.42dBi(Max.)

WIFI(5.5G Band)

Frequency Range	5500MHz~5700MHz
Channel Number	11 Channels for 20MHz bandwidth(5500MHz~5700MHz) 5 Channels for 40MHz bandwidth(5510MHz~5670MHz) 2 Channels for 80MHz bandwidth(5530MHz, 5610MHz)
Modulation Type	IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK)



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



	IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Antenna Description	FPC Antenna, 0.94dBi(Max.)
WIFI(5.8G Band)	
Frequency Range	5745MHz~5825MHz
Channel Number	5 channels for 20MHz bandwidth(5745MHz~5825MHz) 2 channels for 40MHz bandwidth(5755MHz~5795MHz) 1 channels for 80MHz bandwidth(5775MHz)
Modulation Type	IEEE 802.11a/n: OFDM (64QAM, 16QAM, QPSK, BPSK) IEEE 802.11ac: OFDM (256QAM, 64QAM, 16QAM, QPSK, BPSK)
Antenna Description	FPC Antenna, -3.08dBi(Max.)
UMTS	
Operation Band:	☒ WCDMA Band II (U.S.-Band) ☒ WCDMA Band IV (U.S.-Band) ☒ WCDMA Band V (U.S.-Band)
Modulation Type:	QPSK, 16QAM
WCDMA Release Version:	R9&R11
Antenna Description:	FPC Antenna 1.14dBi (max.) For WCDMA Band II 1.03dBi (max.) For WCDMA Band IV -2.76dBi (max.) For WCDMA Band V
GSM	
Support Band:	☒ GSM 900 (EU-Band) ☒ DCS 1800 (EU-Band) ☒ GSM 850 (U.S.-Band) ☒ PCS 1900 (U.S.-Band)
Release Version:	R99
GPRS Class	Class 12
EGPRS Class	Class 12
Modulation Type:	GMSK for GSM/GPRS; GMSK/8PSK for EGPRS
Antenna Description:	FPC Antenna -2.13dBi (max.) For GSM 850 1.03dBi (max.) For PCS 1900
NFC	
Operating Frequency	13.56MHz
Modulation Type	ASK
Antenna Description	FPC Antenna, 0dBi (max.)
GPS function	Support and only RX
Exposure category:	General Population /Uncontrolled Exposure Environment





1.5. Statement of Compliance

The maximum of results of SAR found during testing for iHand55 are follows:

<Highest Reported standalone SAR Summary>

Classment Class	Frequency Band	Hotspot (Report SAR _{1-g} (W/kg)	Body-worn (Report SAR _{1-g} (W/kg)
		(Separation Distance 0mm)	
PCB	GSM 850	0.218	0.218
	GSM1900	0.224	0.224
	WCDMA Band V	0.250	0.250
	WCDMA Band IV	0.808	0.808
	WCDMA Band II	0.396	0.396
	LTE band 2	0.299	0.299
	LTE band 4	0.272	0.272
	LTE band 5	0.165	0.165
	LTE band 7	0.552	0.552
	LTE band 12	0.170	0.170
	LTE band 17	0.219	0.219
	LTE band 38	0.478	0.478
	LTE band 41	0.659	0.659
DTS	WIFI2.4G	0.091	0.091
NII	WIFI5.2G	0.111	0.111
	WIFI5.3G	0.105	0.105
	WIFI5.5G	0.077	0.077
	WIFI5.8G	0.264	0.264

This device is in compliance with Specific Absorption Rate (SAR) for general population/uncontrolled exposure limits (1.6 W/kg) specified in FCC 47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-2019, and had been tested in accordance with the measurement methods and procedures specified in IEC-IEEE 62209-1528-2020.

<Highest Reported simultaneous SAR Summary>

Exposure Position	Classment Class	Highest Reported Simultaneous Transmission SAR _{1-g} (W/kg)
Body-worn	PCB	1.072
	NII	





2. TEST ENVIRONMENT

2.1. Test Facility

The test facility is recognized, certified, or accredited by the following organizations:

Site Description

Sar Lab.

: NVLAP Accreditation Code is 600167-0.

FCC Designation Number is CN5024.

CAB identifier is CN0071.

CNAS Registration Number is L4595.

Test Firm Registration Number: 254912.

2.2. Environmental conditions

During the measurement the environmental conditions were within the listed ranges:

Temperature:	18-25 ° C
Humidity:	40-65 %
Atmospheric pressure:	950-1050mbar

2.3. SAR Limits

FCC Limit (1g Tissue)

EXPOSURE LIMITS	SAR (W/kg)	
	(General Population / Uncontrolled Exposure Environment)	(Occupational / Controlled Exposure Environment)
Spatial Average(averaged over the whole body)	0.08	0.4
Spatial Peak(averaged over any 1 g of tissue)	1.6	8.0
Spatial Peak(hands/wrists/ feet/anklesaveraged over 10 g)	4.0	20.0

Population/Uncontrolled Environments are defined as locations where there is the exposure of individual who have no knowledge or control of their exposure.

Occupational/Controlled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure (i.e. as a result of employment or occupation).



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2.4. Equipments Used during the Test

Item	Equipment	Manufacturer	Model No.	Serial No.	Cal Date	Due Date
1	PC	Lenovo	G5005	MY42081102	N/A	N/A
2	SAR Measurement system	SATIMO	4014_01	SAR_4014_01	N/A	N/A
3	Signal Generator	Agilent	E4438C	MY49072627	2023-06-09	2024-06-08
4	S-parameter Network Analyzer	Agilent	8753ES	US38432944	2023-06-09	2024-06-08
5	Wideband Radio Communication Tester	R&S	CMW500	103818-1	2022-10-29	2023-10-28
6	E-Field PROBE	MVG	SSE2	SN 25/22 EPGO376	2023-06-22	2024-06-21
7	DIPOLE 750	SATIMO	SID 750	SN 07/14 DIP 0G750-302	2021-09-29	2024-09-28
8	DIPOLE 835	SATIMO	SID 835	SN 07/14 DIP 0G835-303	2021-09-29	2024-09-28
9	DIPOLE 1800	SATIMO	SID 1800	SN 07/14 DIP 1G800-301	2021-09-29	2024-09-28
10	DIPOLE 1900	SATIMO	SID 1900	SN 38/18 DIP 1G900-466	2021-09-22	2024-09-21
11	DIPOLE 2450	SATIMO	SID 2450	SN 07/14 DIP 2G450-306	2021-09-29	2024-09-28
12	DIPOLE 2600	SATIMO	SID 2600	SN 38/18 DIP 2G600-468	2021-09-22	2024-09-21
13	DIPOLE 5000-6000	MVG	SWG5500	SN 49/16 WGA 43	2021-09-22	2024-09-21
14	COMOSAR OPENCoaxial Probe	SATIMO	OCPG 68	SN 40/14 OCPG68	2022-10-29	2023-10-28
15	SAR Locator	SATIMO	VPS51	SN 40/14 VPS51	2022-10-29	2023-10-28
16	Communication Antenna	SATIMO	ANTA57	SN 39/14 ANTA57	2022-10-29	2023-10-28
17	FEATURE PHONEPOSITIONING DEVICE	SATIMO	MSH98	SN 40/14 MSH98	N/A	N/A
18	DUMMY PROBE	SATIMO	DP60	SN 03/14 DP60	N/A	N/A
19	SAM PHANTOM	SATIMO	SAM117	SN 40/14 SAM117	N/A	N/A
20	Liquid measurement Kit	HP	85033D	3423A03482	N/A	N/A
21	Power meter	Agilent	E4419B	MY45104493	2022-10-29	2023-10-28
22	Power meter	Agilent	E4419B	MY45100308	2022-10-29	2023-10-28
23	Power sensor	Agilent	E9301H	MY41495616	2022-10-29	2023-10-28
24	Power sensor	Agilent	E9301H	MY41495234	2022-10-29	2023-10-28
25	Directional Coupler	MCLI/USA	4426-20	03746	2023-06-09	2024-06-08

Note:

- 1) Per KDB865664D01 requirements for dipole calibration, the test laboratory has adopted three year extended calibration interval. Each measured dipole is expected to evaluate with following criteria at least on annual interval.
 - a) There is no physical damage on the dipole;
 - b) System check with specific dipole is within 10% of calibrated values;
 - c) The most recent return-loss results, measured at least annually, deviates by no more than 20% from the previous measurement;
 - d) The most recent measurement of the real or imaginary parts of the impedance, measured at least annually is within 5Ω from the previous measurement.
- 2) Network analyzer probe calibration against air, distilled water and a shorting block performed before measuring liquid parameters.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



3.2. OPENSAR E-field Probe System

The SAR measurements were conducted with the dosimetric probe EPGO376 (manufactured by MVG), designed in the classical triangular configuration and optimized for dosimetric evaluation.

Probe Specification

Construction Symmetrical design with triangular core
Interleaved sensors
Built-in shielding against static charges
PEEK enclosure material (resistant to organic solvents, e.g., DGBE)

Calibration ISO/IEC 17025 calibration service available.


Frequency	450 MHz to 6 GHz; Linearity: 0.25 dB (450 MHz to 6 GHz)
Directivity	0.25 dB in HSL (rotation around probe axis) 0.5 dB in tissue material (rotation normal to probe axis)
Dynamic Range	0.01 W/kg to > 100 W/kg; Linearity: 0.25 dB
Dimensions	Overall length: 330 mm (Tip: 16 mm) Tip diameter: 5 mm (Body: 8 mm) Distance from probe tip to sensor centers: 2.5 mm
Application	General dosimetry up to 6 GHz Dosimetry in strong gradient fields Compliance tests of Mobile Phones

Isotropic E-Field Probe

The isotropic E-Field probe has been fully calibrated and assessed for isotropicity, and boundary effect within a controlled environment. Depending on the frequency for which the probe is calibrated the method utilized for calibration will change.

The E-Field probe utilizes a triangular sensor arrangement as detailed in the diagram below:






3.3. Phantoms

The SAM Phantom SAM117 is constructed of a fiberglass shell integrated in a wooden table. The shape of the shell is in compliance with the specification set in IEEE 1528 and EN62209-1, EN62209-2. The phantom enables the dosimetric evaluation of left and right hand phone usage as well as body mounted usage at the flat phantom region. A cover prevents the evaporation of the liquid. Reference markings on the Phantom allow the complete setup of all predefined phantom positions and measurement grids by manually teaching three points in the robot.

System checking was performed using the flat section, whilst Head SAR tests used the left and right head profile sections. Body SAR testing also used the flat section between the head profiles.




SAM Twin Phantom

3.4. Device Holder

In combination with the Generic Twin Phantom SAM117, the Mounting Device enables the rotation of the



mounted transmitter in spherical coordinates whereby the rotation points is the ear opening. The devices can be easily, accurately, and repeatedly positioned according to the FCC specifications. The device holder can be locked at different phantom locations (left head, right head, flat phantom).



Device holder supplied by SATIMO

3.5. Scanning Procedure

The procedure for assessing the peak spatial-average SAR value consists of the following steps

Power Reference Measurement

The reference and drift jobs are useful jobs for monitoring the power drift of the device under test in the batch process. Both jobs measure the field at a specified reference position, at a selectable distance from the phantom surface. The reference position can be either the selected section's grid reference point or a user point in this section. The reference job projects the selected point onto the phantom surface, orients the probe perpendicularly to the surface, and approaches the surface using the selected detection method.

Area Scan

The Area Scan is used as a fast scan in two dimensions to find the area of high field values before running a detailed measurement around the hot spot. Before starting the area scan a grid spacing of 15 mm x 15 mm is set. During the scan the distance of the probe to the phantom remains unchanged. After finishing area scan, the field maxima within a range of 2 dB will be ascertained.

	$\leq 3 \text{ GHz}$	$> 3 \text{ GHz}$
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface	$5 \text{ mm} \pm 1 \text{ mm}$	$\frac{1}{2} \cdot \delta \cdot \ln(2) \text{ mm} \pm 0.5 \text{ mm}$
Maximum probe angle from probe axis to phantom surface normal at the measurement location	$30^\circ \pm 1^\circ$	$20^\circ \pm 1^\circ$
Maximum area scan spatial resolution: $\Delta x_{\text{Area}}, \Delta y_{\text{Area}}$	$\leq 2 \text{ GHz}: \leq 15 \text{ mm}$ $2 - 3 \text{ GHz}: \leq 12 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 12 \text{ mm}$ $4 - 6 \text{ GHz}: \leq 10 \text{ mm}$
	When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be $\leq$ the corresponding x or y dimension of the test device with at least one measurement point on the test device.	

Zoom Scan

Zoom Scans are used to estimate the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. The default Zoom Scan is done by 7x7x7 points within a cube whose base is centered around the maxima found in the preceding area scan.





Maximum zoom scan spatial resolution: $\Delta x_{\text{Zoom}}, \Delta y_{\text{Zoom}}$			$\leq 2 \text{ GHz}: \leq 8 \text{ mm}$ $2 - 3 \text{ GHz}: \leq 5 \text{ mm}^*$	$3 - 4 \text{ GHz}: \leq 5 \text{ mm}^*$ $4 - 6 \text{ GHz}: \leq 4 \text{ mm}^*$
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{\text{Zoom}}(n)$		$\leq 5 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 4 \text{ mm}$ $4 - 5 \text{ GHz}: \leq 3 \text{ mm}$ $5 - 6 \text{ GHz}: \leq 2 \text{ mm}$
	graded grid	$\Delta z_{\text{Zoom}}(1)$: between 1 st two points closest to phantom surface	$\leq 4 \text{ mm}$	$3 - 4 \text{ GHz}: \leq 3 \text{ mm}$ $4 - 5 \text{ GHz}: \leq 2.5 \text{ mm}$ $5 - 6 \text{ GHz}: \leq 2 \text{ mm}$
		$\Delta z_{\text{Zoom}}(n>1)$: between subsequent points	$\leq 1.5 \cdot \Delta z_{\text{Zoom}}(n-1) \text{ mm}$	
Minimum zoom scan volume	x, y, z		$\geq 30 \text{ mm}$	$3 - 4 \text{ GHz}: \geq 28 \text{ mm}$ $4 - 5 \text{ GHz}: \geq 25 \text{ mm}$ $5 - 6 \text{ GHz}: \geq 22 \text{ mm}$

Note: δ is the penetration depth of a plane-wave at normal incidence to the tissue medium; see IEEE Std 1528-2013 for details.

* When zoom scan is required and the *reported* SAR from the *area scan based 1-g SAR estimation* procedures of KDB Publication 447498 is $\leq 1.4 \text{ W/kg}$, $\leq 8 \text{ mm}$, $\leq 7 \text{ mm}$ and $\leq 5 \text{ mm}$ zoom scan resolution may be applied, respectively, for 2 GHz to 3 GHz, 3 GHz to 4 GHz and 4 GHz to 6 GHz.





Power Drift measurement

The drift job measures the field at the same location as the most recent reference job within the same procedure, and with the same settings. The drift measurement gives the field difference in dB from the reading conducted within the last reference measurement. Several drift measurements are possible for one reference measurement. This allows a user to monitor the power drift of the device under test within a batch process. In the properties of the Drift job, the user can specify a limit for the drift and have OPENSAR software stop the measurements if this limit is exceeded.

3.6. Data Storage and Evaluation

Data Storage

The OPENSAR software stores the acquired data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of incorrect parameter settings. For example, if a measurement has been performed with a wrong crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be re-evaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type ([V/m], [A/m], [°C], [mW/g], [mW/cm²], [dBrel], etc.). Some of these units are not available in certain situations or show meaningless results, e.g., a SAR output in a lossless media will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

Data Evaluation

The OPENSAR software automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software:

Probe parameters:	- Sensitivity	Normi, ai0, ai1, ai2
	- Conversion factor	ConvFi
	- Diode compression point	Dcpi
Device parameters:	- Frequency	f
	- Crest factor	cf
Media parameters:	- Conductivity	σ
	- Density	ρ

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the OPENSAR components. In the direct measuring mode of the multimeter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power. The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \cdot \frac{cf}{dcp_i}$$

With V_i = compensated signal of channel i ($i = x, y, z$)

U_i = input signal of channel i ($i = x, y, z$)

cf = crest factor of exciting field

dcp_i = diode compression point

From the compensated input signals the primary field data for each channel can be evaluated:



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



$$\text{E - fieldprobes : } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \cdot \text{ConvF}}}$$

$$\text{H - fieldprobes : } H_i = \sqrt{V_i} \cdot \frac{a_{i0} + a_{i1}f + a_{i2}f^2}{f}$$

With V_i = compensated signal of channel i ($i = x, y, z$)
 Norm_i = sensor sensitivity of channel i ($i = x, y, z$)
 [mV/(V/m)²] for E-field Probes
 ConvF = sensitivity enhancement in solution
 a_{ij} = sensor sensitivity factors for H-field probes
 f = carrier frequency [GHz]
 E_i = electric field strength of channel i in V/m
 H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{tot} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$SAR = E_{tot}^2 \cdot \frac{\sigma}{\rho \cdot 1'000}$$

with SAR = local specific absorption rate in mW/g
 E_{tot} = total field strength in V/m
 σ = conductivity in [mho/m] or [Siemens/m]
 ρ = equivalent tissue density in g/cm³

Note that the density is normally set to 1 (or 1.06), to account for actual brain density rather than the density of the simulation liquid.





3.7. Tissue Dielectric Parameters for Head and Body Phantoms

The liquid is consisted of water,salt,Glycol,Sugar,Preventol and Cellulose.The liquid has previously been proven to be suited for worst-case.It's satisfying the latest tissue dielectric parameters requirements proposed by the KDB865664.

The composition of the tissue simulating liquid

Frequency (MHz)	Bactericide	DGBE	HEC	NaCl	Sucrose	1,2-Propanediol	X100	Water	Conductivity	Permittivity
	%	%	%	%	%	%	%	%	σ	ϵ_r
750	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
835	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
900	/	/	/	0.79	/	64.81	/	34.40	0.97	41.8
1800	/	13.84	/	0.35	/	/	30.45	55.36	1.38	41.0
1900	/	13.84	/	0.35	/	/	30.45	55.36	1.38	41.0
2000	/	7.99	/	0.16	/	/	19.97	71.88	1.55	41.1
2450	/	7.99	/	0.16	/	/	19.97	71.88	1.88	40.3
2600	/	7.99	/	0.16	/	/	19.97	71.88	1.88	40.3

Target Frequency (MHz)	Head	
	ϵ_r	σ (S/m)
450	43.5	0.87
750	41.9	0.89
835	41.5	0.90
900	41.5	0.97
1450	40.5	1.20
1640	40.2	1.31
1800	40.0	1.40
1900	40.0	1.40
2000	40.0	1.40
2300	39.5	1.67
2450	39.2	1.80
2600	39.0	1.96
3000	38.5	2.40
5800	35.3	5.27

3.8. Tissue equivalent liquid properties

Dielectric Performance of Head Tissue Simulating Liquid


Test Engineer: bob.yang									
Tissue Type	Measured Frequency (MHz)	Target Tissue		Measured Tissue				Liquid Temp.	Test Data
		σ	ϵ_r	σ	Dev.	ϵ_r	Dev.		
750H	750	0.89	41.90	0.87	-2.25%	42.53	1.50%	22.4	06/26/2023
835H	835	0.90	41.50	0.88	-2.22%	42.66	2.80%	20.7	06/29/2023
1800H	1800	1.40	40.00	1.37	-2.14%	40.89	2.23%	22.3	07/06/2023
1900H	1900	1.40	40.00	1.36	-2.86%	38.98	-2.55%	21.5	07/11/2023
2450H	2450	1.80	39.20	1.78	-1.11%	39.69	1.25%	22.2	07/14/2023
2600H	2600	1.96	39.00	1.98	-2.25%	38.56	1.50%	22.4	07/21/2023
5200H	5200	4.66	36.00	4.69	0.64%	35.24	-2.11%	23.3	07/25/2023
5400H	5400	4.86	35.80	4.87	0.21%	35.71	-0.25%	22.6	07/27/2023
5600H	5600	5.07	35.50	5.09	0.39%	34.74	-2.14%	23.0	08/01/2023
5800H	5800	5.27	35.30	5.24	-0.57%	36.33	2.92%	22.4	08/03/2023



3.9. System Check

The purpose of the system check is to verify that the system operates within its specifications at the device test frequency. The system check is simple check of repeatability to make sure that the system works correctly at the time of the compliance test;

System check results have to be equal or near the values determined during dipole calibration with the relevant liquids and test system ($\pm 10\%$).



The output power on dipole port must be calibrated to 20 dBm (100mW) before dipole is connected.



Photo of Dipole Setup



**Justification for Extended SAR Dipole Calibrations**

Referring to KDB 865664D01V01r04, if dipoles are verified in return loss ($< -20\text{dB}$, within 20% of prior calibration), and in impedance (within 5 ohm of prior calibration), the annual calibration is not necessary and the calibration interval can be extended. While calibration intervals not exceed 3 years.

SID750 SN 07/14 DIP 0G750-302 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-34.80		50.7		1.6	
2022-09-29	-34.35	-1.29	51.2	0.5	1.5	-0.1

SID835 SN 07/14 DIP 0G835-303 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-24.49		54.9		2.8	
2022-09-29	-24.17	-1.31	54.5	-0.4	2.6	-0.2

SID1800 SN 30/14 DIP 1G800-301 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-20.26		43.1		6.9	
2022-09-29	-20.13	-0.64	42.9	-0.2	6.7	-0.2

SID1900 SN 38/18 DIP 1G900-466 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-26.43		50.5		4.7	
2022-09-22	-26.33	-0.38	50.2	-0.3	4.5	-0.2

SID2450 SN 07/14 DIP 2G450-306 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-25.59		44.7		-1.1	
2022-09-29	-25.68	0.35	44.8	0.1	-1.0	0.1

SID2600 SN 38/18 DIP 2G600-468 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-29.14		49.2		3.4	
2022-09-22	-29.12	-0.07	49.1	-0.1	3.2	-0.1

SID5200 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-8.59		19.38		13.50	
2022-09-29	-8.62	0.35	19.25	-0.13	13.47	-0.03





SID5400 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-10.58		77.13		1.81	
2022-09-22	-10.55	0.28	77.15	0.02	1.74	-0.07

SID5600 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-22	-13.39		30.95		7.75	
2022-09-22	-13.35	0.30	30.91	-0.04	7.72	-0.03

SID5800 SN 49/16 DIP WGA43 Extend Dipole Calibrations

Date of Measurement	Return-Loss (dB)	Delta (%)	Real Impedance (ohm)	Delta (ohm)	Imaginary Impedance (ohm)	Delta (ohm)
2021-09-29	-11.37		54.79		25.47	
2022-09-29	-11.42	0.44	54.68	-0.11	25.26	-0.21

Mixture Type	Frequency (MHz)	Power	SAR _{1g} (W/Kg)	SAR _{10g} (W/Kg)	Drift (%)	1W Target		Difference percentage		Liquid Temp	Date
						SAR _{1g} (W/Kg)	SAR _{10g} (W/Kg)	1g	10g		
Head	750	100 mW	0.824	0.566	-3.65	8.38	5.53	-1.67%	2.35%	22.4	06/26/2023
		Normalize to 1 Watt	8.24	5.66							
Head	835	100 mW	0.947	0.635	0.09	9.60	6.20	-1.35%	2.42%	20.7	06/29/2023
		Normalize to 1 Watt	9.47	6.35							
Head	1800	100 mW	3.826	2.040	-4.85	38.13	20.20	0.34%	0.99%	22.3	07/06/2023
		Normalize to 1 Watt	38.26	20.40							
Head	1900	100 mW	3.974	2.083	-1.96	40.03	20.55	-0.72%	1.36%	21.5	07/11/2023
		Normalize to 1 Watt	39.74	20.83							
Head	2450	100 mW	5.415	2.544	-3.96	53.89	24.15	0.48%	5.34%	22.2	07/14/2023
		Normalize to 1 Watt	54.15	25.44							
Head	2600	100 mW	5.714	2.395	4.63	56.91	24.69	0.40%	-3.00%	22.4	07/21/2023
		Normalize to 1 Watt	57.14	23.95							
Head	5200	100 mW	15.632	5.577	-4.71	165.77	57.2	-5.70%	-2.50%	23.3	07/25/2023
		Normalize to 1 Watt	156.32	55.77							
Head	5400	100 mW	16.89	5.712	0.69	173.20	59.22	-2.60%	-3.55%	22.6	07/27/2023
		Normalize to 1 Watt	168.69	57.12							
Head	5600	100 mW	17.437	5.933	4.17	179.61	60.98	-2.92%	-2.71%	23.0	08/01/2023
		Normalize to 1 Watt	174.37	59.33							
Head	5800	100 mW	18.362	6.168	3.35	186.77	62.84	-1.69%	-1.85%	22.4	08/03/2023
		Normalize to 1 Watt	183.62	61.68							



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



3.10. SAR measurement procedure

The measurement procedures are as follows:

3.10.1 Conducted power measurement

- For WWAN power measurement, use base station simulator connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- Read the WWAN RF power level from the base station simulator.
- For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously Transmission, at maximum RF power in each supported wireless interface and frequency band.
- Connect EUT RF port through RF cable to the power meter, and measure WLAN/BT output power.

3.10.2 GSM Test Configuration

SAR tests for GSM 850 and GSM 1900, a communication link is set up with a System Simulator (SS) by air link. Using CMU200 the power level is set to "5" for GSM 850, set to "0" for GSM 1900. Since the GPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 5. the EGPRS class is 12 for this EUT, it has at most 4 timeslots in uplink and at most 4 timeslots in downlink, the maximum total timeslots is 5.

SAR test reduction for GPRS and EDGE modes is determined by the source-based time-averaged output power specified for production units, including tune-up tolerance. The data mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. GSM voice and GPRS data use GMSK, which is a constant amplitude modulation with minimal peak to average power difference within the time-slot burst. For EDGE, GMSK is used for MCS 1 – MCS 4 and 8-PSK is used for MCS 5 – MCS 9; where 8-PSK has an inherently higher peak-to-average power ratio. The GMSK and 8-PSK EDGE configurations are considered separately for SAR compliance. The GMSK EDGE configurations are grouped with GPRS and considered with respect to time-averaged maximum output power to determine compliance. The 3G SAR test reduction procedure is applied to 8-PSK EDGE with GMSK GPRS/EDGE as the primary mode.

3.10.3 UMTS Test Configuration

3G SAR Test Reduction Procedure

In the following procedures, the mode tested for SAR is referred to as the primary mode. The equivalent modes considered for SAR test reduction are denoted as secondary modes. Both primary and secondary modes must be in the same frequency band. When the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode. This is referred to as the 3G SAR test reduction procedure in the following SAR test guidance, where the primary mode is identified in the applicable wireless mode test procedures and the secondary mode is wireless mode being considered for SAR test reduction by that procedure. When the 3G SAR test reduction procedure is not satisfied, it is identified as "otherwise" in the applicable procedures; SAR measurement is required for the secondary mode.

Output power Verification

Maximum output power is verified on the high, middle and low channels according to procedures described in section 5.2 of 3GPP TS 34.121, using the appropriate RMC or AMR with TPC (transmit power control) set to all "1's" for WCDMA/HSDPA or by applying the required inner loop power control procedures to maintain maximum output power while HSUPA is active. Results for all applicable physical channel configurations (DPCCH, DPDCH and spreading codes, HSDPA, HSPA) are required in the SAR report. All configurations that are not supported by the handset or cannot be measured due to technical or equipment limitations must be clearly identified.

Head SAR

SAR for next to the ear head exposure is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to AMR configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for 12.2 kbps AMR in 3.4 kbps SRB (signaling radio bearer) using the highest reported SAR configuration in 12.2 kbps RMC for head exposure.



1) Body-Worn Accessory SAR

SAR for body-worn accessory configurations is measured using a 12.2 kbps RMC with TPC bits configured to all "1's". The 3G SAR test reduction procedure is applied to other spreading codes and multiple DPDCHn configurations supported by the handset with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured using an applicable RMC configuration with the corresponding spreading code or DPDCHn, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When more than 2 DPDCHn are supported by the handset, it may be necessary to configure additional DPDCHn using FTM (Factory Test Mode) or other chipset based test approaches with parameters similar to those used in 384 kbps and 768 kbps RMC.

2) Handsets with Release 5 HSDPA

The 3G SAR test reduction procedure is applied to HSDPA body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSDPA using the HSDPA body SAR procedures in the "Release 5 HSDPA Data Devices" section of this document, for the highest reported SAR body-worn accessory exposure configuration in 12.2 kbps RMC. Handsets with both HSDPA and HSUPA are tested according to Release 6 HSPA test procedures.

HSDPA should be configured according to the UE category of a test device. The number of HSDSCH/ HS-PDSCHs, HARQ processes, minimum inter-TTI interval, transport block sizes and RV coding sequence are defined by the H-set. To maintain a consistent test configuration and stable transmission conditions, QPSK is used in the H-set for SAR testing. HS-DPCCH should be configured with a CQI feedback cycle of 4 ms with a CQI repetition factor of 2 to maintain a constant rate of active CQI slots. DPCCH and DPDCH gain factors (β_c , β_d), and HS-DPCCH power offset parameters (Δ_{ACK} , Δ_{NACK} , Δ_{CQI}) should be set according to values indicated in the Table below. The CQI value is determined by the UE category, transport block size, number of HS-PDSCHs and modulation used in the H-set.

Table 2: Subtests for UMTS Release 5 HSDPA

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	β_{hs} (note 1, note 2)	CM(dB) (note 3)	MPR(dB)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (note 4)	15/15 (note 4)	64	12/15 (note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Rightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Rightarrow \beta_{hs} = 30/15 * \beta_c$

Note2: CM=1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$.

Note3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TFC1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

HSUPA Test Configuration

The 3G SAR test reduction procedure is applied to HSPA (HSUPA/HSDPA with RMC) body-worn accessory configurations with 12.2 kbps RMC as the primary mode. Otherwise, SAR is measured for HSPA using the HSPA body SAR procedures in the "Release 6 HSPA Data Devices" section of this document, for the highest reported body-worn accessory exposure SAR configuration in 12.2 kbps RMC. When VOIP is applicable for next to the ear head exposure in HSPA, the 3G SAR test reduction procedure is applied to HSPA with 12.2 kbps RMC as the primary mode; otherwise, the same HSPA configuration used for body-worn accessory measurements is tested for next to the ear head exposure.

Due to inner loop power control requirements in HSPA, a communication test set is required for output power and SAR tests. The 12.2 kbps RMC, FRC H-set 1 and E-DCH configurations for HSPA are configured according to the β values indicated in Table 2 and other applicable procedures described in the 'WCDMA Handset' and 'Release 5 HSDPA Data Devices' sections of this document.

Table 3: Sub-Test 5 Setup for Release 6 HSUPA

Sub-set	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E- TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1} \cdot 47/15$	4	2	2.0	1.0	15	92



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



							$\beta_{ed2} 47/15$						
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS- DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Figure 5.1g.

Note 6: β_{ed} can not be set directly; it is set by Absolute Grant Value.

3.10.4 WIFI Test Configuration

The SAR measurement and test reduction procedures are structured according to either the DSSS or OFDM transmission mode configurations used in each standalone frequency band and aggregated band. For devices that operate in exposure configurations that require multiple test positions, additional SAR test reduction may be applied. The maximum output power specified for production units, including tune-up tolerance, are used to determine initial SAR test requirements for the 802.11 transmission modes in a frequency band. SAR is measured using the highest measured maximum output power channel for the initial test configuration. SAR measurement and test reduction for the remaining 802.11 modes and test channels are determined according to measured or specified maximum output power and reported SAR of the initial measurements. The general test reduction and SAR measurement approaches are summarized in the following:

1. The maximum output power specified for production units are determined for all applicable 802.11 transmission modes in each standalone and aggregated frequency band. Maximum output power is measured for the highest maximum output power configuration(s) in each frequency band according to the default power measurement procedures.
2. For OFDM transmission configurations in the 2.4 GHz and 5 GHz bands, an "initial test configuration" is first determined for each standalone and aggregated frequency band according to the maximum output power and tune-up tolerance specified for production units.
 - a. When the same maximum power is specified for multiple transmission modes in a frequency band, the largest channel bandwidth, lowest order modulation, lowest data rate and lowest order 802.11a/g/n/ac mode is used for SAR measurement, on the highest measured output power channel in the initial test configuration, for each frequency band.
 - b. SAR is measured for OFDM configurations using the initial test configuration procedures. Additional frequency band specific SAR test reduction may be considered for individual frequency bands
 - c. Depending on the reported SAR of the highest maximum output power channel tested in the initial test configuration, SAR test reduction may apply to subsequent highest output channels in the initial test configuration to reduce the number of SAR measurements.
3. The Initial test configuration does not apply to DSSS. The 2.4 GHz band SAR test requirements and 802.11b DSSS procedures are used to establish the transmission configurations required for SAR measurement.
4. An "initial test position" is applied to further reduce the number of SAR tests for devices operating in next to the ear, UMPC mini-tablet or hotspot mode exposure configurations that require multiple test positions.
 - a. SAR is measured for 802.11b according to the 2.4 GHz DSSS procedure using the exposure condition established by the initial test position.
 - b. SAR is measured for 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration. 802.11b/g/n operating modes are tested independently according to the service requirements in each frequency band. 802.11b/g/n modes are tested on the maximum average output channel.
5. The Initial test position does not apply to devices that require a fixed exposure test position. SAR is measured in a fixed exposure test position for these devices in 802.11b according to the 2.4 GHz DSSS procedure or in 2.4 GHz and 5 GHz OFDM configurations using the initial test configuration procedures.
6. The "subsequent test configuration" procedures are applied to determine if additional SAR measurements are required for the remaining OFDM transmission modes that have not been tested in the initial test configuration. SAR test exclusion is determined according to reported SAR in the initial test configuration and maximum output power specified or measured for these other OFDM configurations.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2.4 GHz and 5GHz SAR Procedures

Separate SAR procedures are applied to DSSS and OFDM configurations in the 2.4 GHz band to simplify DSSS test requirements. For 802.11b DSSS SAR measurements, DSSS SAR procedure applies to fixed exposure test position and initial test position procedure applies to multiple exposure test positions. When SAR measurement is required for an OFDM configuration, the initial test configuration, subsequent test configuration and initial test position procedures are applied. The SAR test exclusion requirements for 802.11g/n OFDM configurations are described in section 5.2.2.

1. 802.11b DSSS SAR Test Requirements

SAR is measured for 2.4 GHz 802.11b DSSS using either a fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:

- a. When the reported SAR of the highest measured maximum output power channel (section 3.1) for the exposure configuration is ≤ 0.8 W/kg, no further SAR testing is required for 802.11b DSSS in that exposure configuration.
- b. When the reported SAR is > 0.8 W/kg, SAR is required for that exposure configuration using the next highest measured output power channel. When any reported SAR is > 1.2 W/kg, SAR is required for the third channel; i.e., all channels require testing.

1. 2.4 GHz 802.11g/n OFDM SAR Test Exclusion Requirements

When SAR measurement is required for 2.4 GHz 802.11g/n OFDM configurations, the measurement and test reduction procedures for OFDM are applied (section 5.3). SAR is not required for the following 2.4 GHz OFDM conditions.

- a. When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration
- b. When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.

2. SAR Test Requirements for OFDM Configurations

When SAR measurement is required for 802.11 a/g/n/ac OFDM configurations, each standalone and frequency aggregated band is considered separately for SAR test reduction. When the same transmitter and antenna(s) are used for U-NII-1 and U-NII-2A bands, additional SAR test reduction applies. When band gap channels between U-NII-2C band and 5.8 GHz U-NII-3 or §15.247 band are supported, the highest maximum output power transmission mode configuration and maximum output power channel across the bands must be used to determine SAR test reduction, according to the initial test configuration and subsequent test configuration requirements.²⁰ In applying the initial test configuration and subsequent test configuration procedures, the 802.11 transmission configuration with the highest specified maximum output power and the channel within a test configuration with the highest measured maximum output power should be clearly distinguished to apply the procedures.

3. OFDM Transmission Mode SAR Test Configuration and Channel Selection Requirements

The initial test configuration for 2.4 GHz and 5 GHz OFDM transmission modes is determined by the 802.11 configuration with the highest maximum output power specified for production units, including tune-up tolerance, in each standalone and aggregated frequency band. SAR for the initial test configuration is measured using the highest maximum output power channel determined by the default power measurement procedures (section 4). When multiple configurations in a frequency band have the same specified maximum output power, the initial test configuration is determined according to the following steps applied sequentially.

- a. The largest channel bandwidth configuration is selected among the multiple configurations with the same specified maximum output power.
- b. If multiple configurations have the same specified maximum output power and largest channel bandwidth, the lowest order modulation among the largest channel bandwidth configurations is selected.
- c. If multiple configurations have the same specified maximum output power, largest channel bandwidth and lowest order modulation, the lowest data rate configuration among these configurations is selected.
- d. When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n.

After an initial test configuration is determined, if multiple test channels have the same measured maximum output power, the channel chosen for SAR measurement is determined according to the following. These channel selection procedures apply to both the initial test configuration and subsequent test configuration(s), with respect to the default power measurement procedures or additional power measurements required for further SAR test reduction. The same procedures also apply to subsequent highest output power channel(s) selection.





- a. Channels with measured maximum output power within $\frac{1}{4}$ dB of each other are considered to have the same maximum output.
- b. When there are multiple test channels with the same measured maximum output power, the channel closest to mid-band frequency is selected for SAR measurement.
- c. When there are multiple test channels with the same measured maximum output power and equal separation from mid-band frequency; for example, high and low channels or two mid-band channels, the higher frequency (number) channel is selected for SAR measurement.

Initial Test Configuration Procedures

An initial test configuration is determined for OFDM transmission modes according to the channel bandwidth, modulation and data rate combination(s) with the highest maximum output power specified for production units in each standalone and aggregated frequency band. SAR is measured using the highest measured maximum output power channel. For configurations with the same specified or measured maximum output power, additional transmission mode and test channel selection procedures are required (see section 5.3.2). SAR test reduction of subsequent highest output test channels is based on the reported SAR of the initial test configuration.

For next to the ear, hotspot mode and UMC mini-tablet exposure configurations where multiple test positions are required, the initial test position procedure is applied to minimize the number of test positions required for SAR measurement using the initial test configuration transmission mode.²³ For fixed exposure conditions that do not have multiple SAR test positions, SAR is measured in the transmission mode determined by the initial test configuration. When the reported SAR of the initial test configuration is > 0.8 W/kg, SAR measurement is required for the subsequent next highest measured output power channel(s) in the initial test configuration until the reported SAR is ≤ 1.2 W/kg or all required channels are tested.

4. Subsequent Test Configuration Procedures

SAR measurement requirements for the remaining 802.11 transmission mode configurations that have not been tested in the initial test configuration are determined separately for each standalone and aggregated frequency band, in each exposure condition, according to the maximum output power specified for production units. The initial test position procedure is applied to next to the ear, UMPC mini-tablet and hotspot mode configurations. When the same maximum output power is specified for multiple transmission modes, the procedures in section 5.3.2 are applied to determine the test configuration. Additional power measurements may be required to determine if SAR measurements are required for subsequent highest output power channels in a subsequent test configuration. The subsequent test configuration and SAR measurement procedures are described in the following.

- a. When SAR test exclusion provisions of KDB Publication 447498 are applicable and SAR measurement is not required for the initial test configuration, SAR is also not required for the next highest maximum output power transmission mode subsequent test configuration(s) in that frequency band or aggregated band and exposure configuration.
- b. When the highest reported SAR for the initial test configuration (when applicable, include subsequent highest output channels), according to the initial test position or fixed exposure position requirements, is adjusted by the ratio of the subsequent test configuration to initial test configuration specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for that subsequent test configuration.
- c. The number of channels in the initial test configuration and subsequent test configuration can be different due to differences in channel bandwidth. When SAR measurement is required for a subsequent test configuration and the channel bandwidth is smaller than that in the initial test configuration, all channels in the subsequent test configuration that overlap with the larger bandwidth channel tested in the initial test configuration should be used to determine the highest maximum output power channel. This step requires additional power measurement to identify the highest maximum output power channel in the subsequent test configuration to determine SAR test reduction.
 - 1). SAR should first be measured for the channel with highest measured output power in the subsequent test configuration.
 - 2). SAR for subsequent highest measured maximum output power channels in the subsequent test configuration is required only when the reported SAR of the preceding higher maximum output power channel(s) in the subsequent test configuration is > 1.2 W/kg or until all required channels are tested.
 - a) For channels with the same measured maximum output power, SAR should be measured using the channel closest to the center frequency of the larger channel bandwidth channel in the initial test configuration.
- d. SAR measurements for the remaining highest specified maximum output power OFDM transmission mode configurations that have not been tested in the initial test configuration (highest maximum output) or subsequent test configuration(s) (subsequent next highest maximum output power) is determined by



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



applying the subsequent test configuration procedures in this section to the remaining configurations according to the following:

- 1) replace “subsequent test configuration” with “next subsequent test configuration” (i.e., subsequent next highest specified maximum output power configuration)
- 2) replace “initial test configuration” with “all tested higher output power configurations.”

3.11. Power Reduction

The product without any power reduction.

3.12. Power Drift

To control the output power stability during the SAR test, SAR system calculates the power drift by measuring the E-field at the same location at the beginning and at the end of the measurement for each test position. This ensures that the power drift during one measurement is within 5%.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



4. TEST CONDITIONS AND RESULTS

4.1. Conducted Power Results

According KDB 447498D01 General RF Exposure Guidance v06 Section 4.1 2) states that “Unless it is specified differently in the published RF exposure KDB procedures, these requirements also apply to test reduction and test exclusion considerations. Time-averaged maximum conducted output power applies to SAR and, as required by § 2.1091(c), time-averaged ERP applies to MPE. When an antenna port is not available on the device to support conducted power measurement, such as FRS and certain Part 15 transmitters with built-in integral antennas, the maximum output power allowed for production units should be used to determine RF exposure test exclusion and compliance.”

<GSM Conducted Power>

General Note:

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. According to October 2013TCB Workshop, for GSM / GPRS / EGPRS, the number of time slots to test for SAR should correspond to the highest frame-average maximum output power configuration, considering the possibility of e.g. 3rd party VoIP operation for head and body-worn SAR testing, the EUT was set in GPRS (4Tx slot) for GSM850/GSM1900 band due to their highest frame-average power.
3. For hotspot mode SAR testing, GPRS should be evaluated, therefore the EUT was set in GPRS (4 Tx slots) for GSM850/GSM1900 band due to its highest frame-average power.

Conducted power measurement results for GSM850/PCS1900

GSM 850		Tune -up	Burst Conducted power (dBm)			Division Factors	Tune- up	Average power (dBm)		
			Channel/Frequency(MHz)					Channel/Frequency(MHz)		
		Max	128/ 824.2	190/ 836.6	251/ 848.8		Max	128/ 824.2	190/ 836.6	251/8 48.8
GSM		32.00	31.88	31.74	31.85	-9.03dB	22.97	22.85	22.71	22.82
GPRS (GMSK)	1TX slot	32.00	31.87	31.75	31.85	-9.03dB	22.97	22.84	22.72	22.82
	2TX slot	31.50	31.40	31.27	31.35	-6.02dB	25.48	25.38	25.25	25.33
	3TX slot	30.00	30.00	29.82	29.90	-4.26dB	25.74	25.74	25.56	25.64
	4TX slot	29.50	29.02	28.86	28.94	-3.01dB	26.49	26.01	25.85	25.93
EGPRS (8PSK)	1TX slot	27.50	27.20	27.14	27.09	-9.03dB	18.47	18.17	18.11	18.06
	2TX slot	26.50	26.06	25.95	25.90	-6.02dB	20.48	20.04	19.93	19.88
	3TX slot	24.00	23.79	23.66	23.66	-4.26dB	19.74	19.53	19.40	19.40
	4TX slot	23.00	22.69	22.61	22.47	-3.01dB	19.99	19.68	19.60	19.46
GSM 1900		Tune -up	Burst Conducted power (dBm)			Division Factors	Tune- up	Average power (dBm)		
			Channel/Frequency(MHz)					Channel/Frequency(MHz)		
		Max	512/ 1850.2	661/ 1880	810/ 1909.8		Max.	512/ 1850.2	661/ 1880	810/ 1909. 8
GSM		30.00	29.26	29.64	29.63	-9.03dB	20.97	20.23	20.61	20.60
GPRS (GMSK)	1TX slot	30.00	29.23	29.61	29.60	-9.03dB	20.97	20.20	20.58	20.57
	2TX slot	29.50	28.68	29.07	29.09	-6.02dB	23.48	22.66	23.05	23.07
	3TX slot	28.00	27.16	27.55	27.61	-4.26dB	23.74	22.90	23.29	23.35
	4TX slot	27.00	26.09	26.53	26.56	-3.01dB	23.99	23.08	23.52	23.55
EGPRS (8PSK)	1TX slot	27.00	26.64	26.71	26.41	-9.03dB	17.97	17.61	17.68	17.38
	2TX slot	25.50	25.28	25.44	25.23	-6.02dB	19.48	19.26	19.42	19.21
	3TX slot	23.50	22.94	23.11	22.88	-4.26dB	19.24	18.68	18.85	18.62
	4TX slot	22.00	21.81	21.93	21.70	-3.01dB	18.99	18.80	18.92	18.69

Notes:

1. Division Factors

To average the power, the division factor is as follows:

1TX-slot = 1 transmit time slot out of 8 time slots=> conducted power divided by (8/1) => -9.00dB

2TX-slots = 2 transmit time slots out of 8 time slots=> conducted power divided by (8/2) => -6.00dB

3TX-slots = 3 transmit time slots out of 8 time slots=> conducted power divided by (8/3) => -4.26dB

4TX-slots = 4 transmit time slots out of 8 time slots=> conducted power divided by (8/4) => -3.00dB



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



2. According to the conducted power as above, the GPRS measurements are performed with 4Txslot for GPRS850 and 4Txslot GPRS1900.

<UMTS Conducted Power>

The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification. A summary of these settings are illustrated below:

HSDPA Setup Configuration:

- The EUT was connected to Base Station E5515C referred to the Setup Configuration.
- The RF path losses were compensated into the measurements.
- A call was established between EUT and Base Station with following setting:
 - Set Gain Factors (β_c and β_d) and parameters were set according to each
 - Specific sub-test in the following table, C10.1.4, quoted from the TS 34.121
 - Set RMC 12.2Kbps + HSDPA mode.
 - Set Cell Power = -86 dBm
 - Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - Select HSDPA Uplink Parameters
 - Set Delta ACK, Delta NACK and Delta CQI = 8
 - Set Ack-Nack Repetition Factor to 3
 - Set CQI Feedback Cycle (k) to 4 ms
 - Set CQI Repetition Factor to 2
 - Power Ctrl Mode = All Up bits
- The transmitted maximum output power was recorded.

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (Note 4)	15/15 (Note 4)	64	12/15 (Note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5
Note 1: Δ_{ACK}, Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$. Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{HS} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{HS} = 24/15 * \beta_c$. Note 3: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{HS}/\beta_c = 24/15$. For all other combinations of DPDCCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases. Note 4: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.							

Setup Configuration

HSUPA Setup Configuration:

- The EUT was connected to Base Station R&S CMU200 referred to the Setup Configuration.
- The RF path losses were compensated into the measurements.
- A call was established between EUT and Base Station with following setting *:
 - Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121
 - Set Cell Power = -86 dBm
 - Set Channel Type = 12.2k + HSPA
 - Set UE Target Power
 - Power Ctrl Mode= Alternating bits
 - Set and observe the E-TFCI
 - Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtest's E-TFCI



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



d. The transmitted maximum output power was recorded.

Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{HS} (Note 1)	β_{ec}	β_{ed} (Note 5) (Note 6)	β_{ed} (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 6)	E-TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/25	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4 4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 (Note 4)	15/15 (Note 4)	64	15/15 (Note 4)	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g.

Note 6: β_{ed} can not be set directly, it is set by Absolute Grant Value.

General Note

1. Per KDB 941225 D01, RMC 12.2kbps setting is used to evaluate SAR. If AMR 12.2kbps power is < 0.25dB higher than RMC 12.2kbps, SAR tests with AMR 12.2kbps can be excluded.

2. By design, AMR and HSDPA/HSUPA RF power will not be larger than RMC 12.2kbps, detailed information is included in Tune-up Procure exhibit.

3. It is expected by the manufacturer that MPR for some HSDPA/HSUPA subtests may differ from the specification of 3GPP, according to the chipset implementation in this model. The implementation and expected deviation are detailed in tune-up procedure exhibit.

Conducted Power Measurement Results(WCDMA Band II/IV/V)

Item	Band	FDD Band V result (dBm)			FDD Band IV result (dBm)			FDD Band II result (dBm)		
		Test Channel			Test Channel			Test Channel		
		4132/ 826.4	4182/ 836.6	4233/ 846.6	1312/ 1712.4	1413/ 1732.6	1513/ 1752.6	9262/ 1852.4	9400/ 1880	9538/ 1907.6
RMC	12.2kbps	22.52	22.44	22.46	21.51	21.39	21.67	21.59	21.63	21.65
HSDPA	Subtest 1	21.98	21.99	21.94	20.96	20.98	20.93	20.94	20.97	20.91
	Subtest 2	21.93	21.95	21.99	20.97	20.97	20.97	20.99	20.94	20.99
	Subtest 3	21.96	21.90	21.94	20.90	20.92	20.98	20.90	20.90	20.91
	Subtest 4	21.91	21.99	21.92	20.93	20.95	20.92	20.98	20.99	20.96
HSUPA	Subtest 1	21.96	21.91	21.95	20.90	20.90	20.95	20.92	20.98	20.91
	Subtest 2	21.93	21.99	21.93	20.97	20.97	20.93	20.98	20.98	20.96
	Subtest 3	21.91	21.94	21.96	20.96	20.92	20.94	20.98	20.95	20.97
	Subtest 4	21.94	21.99	21.95	20.91	20.99	20.99	20.97	20.98	20.91
	Subtest 5	21.94	21.94	21.99	20.92	20.98	20.96	20.90	20.90	20.92

Note: 1. When the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq 1/2$ dB higher than the primary mode (RMC 12.2kbps) or when the highest reported SAR of the primary mode is scaled by the ratio of specified maximum output power and tune-up tolerance of secondary to primary mode and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for the secondary mode.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band2

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band2	1.4MHz	QPSK	18607	1RB#0	21.57	PASS
Band2	1.4MHz	16QAM	18607	1RB#0	21.86	PASS
Band2	1.4MHz	QPSK	18607	1RB#2	21.57	PASS
Band2	1.4MHz	16QAM	18607	1RB#2	21.85	PASS
Band2	1.4MHz	QPSK	18607	1RB#5	21.50	PASS
Band2	1.4MHz	16QAM	18607	1RB#5	21.85	PASS
Band2	1.4MHz	QPSK	18607	3RB#0	21.45	PASS
Band2	1.4MHz	16QAM	18607	3RB#0	20.45	PASS
Band2	1.4MHz	QPSK	18607	3RB#1	21.43	PASS
Band2	1.4MHz	16QAM	18607	3RB#1	20.46	PASS
Band2	1.4MHz	QPSK	18607	3RB#3	21.47	PASS
Band2	1.4MHz	16QAM	18607	3RB#3	20.27	PASS
Band2	1.4MHz	QPSK	18607	6RB#0	20.47	PASS
Band2	1.4MHz	16QAM	18607	6RB#0	19.64	PASS
Band2	1.4MHz	QPSK	18900	1RB#0	21.90	PASS
Band2	1.4MHz	16QAM	18900	1RB#0	21.44	PASS
Band2	1.4MHz	QPSK	18900	1RB#2	21.96	PASS
Band2	1.4MHz	16QAM	18900	1RB#2	21.39	PASS
Band2	1.4MHz	QPSK	18900	1RB#5	22.09	PASS
Band2	1.4MHz	16QAM	18900	1RB#5	21.38	PASS
Band2	1.4MHz	QPSK	18900	3RB#0	21.63	PASS
Band2	1.4MHz	16QAM	18900	3RB#0	20.61	PASS
Band2	1.4MHz	QPSK	18900	3RB#1	21.65	PASS
Band2	1.4MHz	16QAM	18900	3RB#1	20.62	PASS
Band2	1.4MHz	QPSK	18900	3RB#3	21.69	PASS
Band2	1.4MHz	16QAM	18900	3RB#3	20.71	PASS
Band2	1.4MHz	QPSK	18900	6RB#0	20.67	PASS
Band2	1.4MHz	16QAM	18900	6RB#0	19.82	PASS
Band2	1.4MHz	QPSK	19193	1RB#0	22.59	PASS
Band2	1.4MHz	16QAM	19193	1RB#0	21.32	PASS
Band2	1.4MHz	QPSK	19193	1RB#2	22.59	PASS
Band2	1.4MHz	16QAM	19193	1RB#2	21.36	PASS
Band2	1.4MHz	QPSK	19193	1RB#5	22.63	PASS
Band2	1.4MHz	16QAM	19193	1RB#5	21.35	PASS
Band2	1.4MHz	QPSK	19193	3RB#0	22.53	PASS
Band2	1.4MHz	16QAM	19193	3RB#0	21.62	PASS
Band2	1.4MHz	QPSK	19193	3RB#1	22.59	PASS
Band2	1.4MHz	16QAM	19193	3RB#1	21.62	PASS
Band2	1.4MHz	QPSK	19193	3RB#3	22.55	PASS
Band2	1.4MHz	16QAM	19193	3RB#3	21.56	PASS
Band2	1.4MHz	QPSK	19193	6RB#0	21.67	PASS
Band2	1.4MHz	16QAM	19193	6RB#0	20.71	PASS
Band2	3MHz	QPSK	18615	1RB#0	21.46	PASS
Band2	3MHz	16QAM	18615	1RB#0	20.86	PASS
Band2	3MHz	QPSK	18615	1RB#8	21.55	PASS
Band2	3MHz	16QAM	18615	1RB#8	20.81	PASS
Band2	3MHz	QPSK	18615	1RB#14	21.49	PASS
Band2	3MHz	16QAM	18615	1RB#14	20.81	PASS
Band2	3MHz	QPSK	18615	8RB#0	20.47	PASS
Band2	3MHz	16QAM	18615	8RB#0	19.72	PASS
Band2	3MHz	QPSK	18615	8RB#4	20.48	PASS
Band2	3MHz	16QAM	18615	8RB#4	19.78	PASS
Band2	3MHz	QPSK	18615	8RB#7	20.51	PASS
Band2	3MHz	16QAM	18615	8RB#7	19.74	PASS
Band2	3MHz	QPSK	18615	15RB#0	20.46	PASS
Band2	3MHz	16QAM	18615	15RB#0	19.65	PASS
Band2	3MHz	QPSK	18900	1RB#0	21.93	PASS
Band2	3MHz	16QAM	18900	1RB#0	20.84	PASS
Band2	3MHz	QPSK	18900	1RB#8	22.06	PASS
Band2	3MHz	16QAM	18900	1RB#8	20.93	PASS
Band2	3MHz	QPSK	18900	1RB#14	22.17	PASS
Band2	3MHz	16QAM	18900	1RB#14	21.04	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	3MHz	QPSK	18900	8RB#0	20.84	PASS
Band2	3MHz	16QAM	18900	8RB#0	20.12	PASS
Band2	3MHz	QPSK	18900	8RB#4	20.85	PASS
Band2	3MHz	16QAM	18900	8RB#4	20.09	PASS
Band2	3MHz	QPSK	18900	8RB#7	20.99	PASS
Band2	3MHz	16QAM	18900	8RB#7	20.13	PASS
Band2	3MHz	QPSK	18900	15RB#0	20.96	PASS
Band2	3MHz	16QAM	18900	15RB#0	20.12	PASS
Band2	3MHz	QPSK	19185	1RB#0	22.70	PASS
Band2	3MHz	16QAM	19185	1RB#0	21.49	PASS
Band2	3MHz	QPSK	19185	1RB#8	22.76	PASS
Band2	3MHz	16QAM	19185	1RB#8	21.55	PASS
Band2	3MHz	QPSK	19185	1RB#14	22.78	PASS
Band2	3MHz	16QAM	19185	1RB#14	21.55	PASS
Band2	3MHz	QPSK	19185	8RB#0	21.78	PASS
Band2	3MHz	16QAM	19185	8RB#0	21.08	PASS
Band2	3MHz	QPSK	19185	8RB#4	21.78	PASS
Band2	3MHz	16QAM	19185	8RB#4	21.08	PASS
Band2	3MHz	QPSK	19185	8RB#7	21.76	PASS
Band2	3MHz	16QAM	19185	8RB#7	21.13	PASS
Band2	3MHz	QPSK	19185	15RB#0	21.78	PASS
Band2	3MHz	16QAM	19185	15RB#0	20.91	PASS
Band2	5MHz	QPSK	18625	1RB#0	21.30	PASS
Band2	5MHz	16QAM	18625	1RB#0	19.81	PASS
Band2	5MHz	QPSK	18625	1RB#12	21.36	PASS
Band2	5MHz	16QAM	18625	1RB#12	19.94	PASS
Band2	5MHz	QPSK	18625	1RB#24	21.38	PASS
Band2	5MHz	16QAM	18625	1RB#24	19.84	PASS
Band2	5MHz	QPSK	18625	12RB#0	20.35	PASS
Band2	5MHz	16QAM	18625	12RB#0	19.44	PASS
Band2	5MHz	QPSK	18625	12RB#6	20.36	PASS
Band2	5MHz	16QAM	18625	12RB#6	19.44	PASS
Band2	5MHz	QPSK	18625	12RB#13	20.35	PASS
Band2	5MHz	16QAM	18625	12RB#13	19.44	PASS
Band2	5MHz	QPSK	18625	25RB#0	20.30	PASS
Band2	5MHz	16QAM	18625	25RB#0	19.55	PASS
Band2	5MHz	QPSK	18900	1RB#0	21.84	PASS
Band2	5MHz	16QAM	18900	1RB#0	20.16	PASS
Band2	5MHz	QPSK	18900	1RB#12	21.74	PASS
Band2	5MHz	16QAM	18900	1RB#12	20.38	PASS
Band2	5MHz	QPSK	18900	1RB#24	21.88	PASS
Band2	5MHz	16QAM	18900	1RB#24	20.32	PASS
Band2	5MHz	QPSK	18900	12RB#0	20.66	PASS
Band2	5MHz	16QAM	18900	12RB#0	19.78	PASS
Band2	5MHz	QPSK	18900	12RB#6	20.65	PASS
Band2	5MHz	16QAM	18900	12RB#6	19.78	PASS
Band2	5MHz	QPSK	18900	12RB#13	20.85	PASS
Band2	5MHz	16QAM	18900	12RB#13	19.86	PASS
Band2	5MHz	QPSK	18900	25RB#0	20.71	PASS
Band2	5MHz	16QAM	18900	25RB#0	19.97	PASS
Band2	5MHz	QPSK	19175	1RB#0	22.33	PASS
Band2	5MHz	16QAM	19175	1RB#0	21.88	PASS
Band2	5MHz	QPSK	19175	1RB#12	22.42	PASS
Band2	5MHz	16QAM	19175	1RB#12	21.97	PASS
Band2	5MHz	QPSK	19175	1RB#24	22.44	PASS
Band2	5MHz	16QAM	19175	1RB#24	22.02	PASS
Band2	5MHz	QPSK	19175	12RB#0	21.62	PASS
Band2	5MHz	16QAM	19175	12RB#0	20.77	PASS
Band2	5MHz	QPSK	19175	12RB#6	21.63	PASS
Band2	5MHz	16QAM	19175	12RB#6	20.78	PASS
Band2	5MHz	QPSK	19175	12RB#13	21.63	PASS
Band2	5MHz	16QAM	19175	12RB#13	20.83	PASS
Band2	5MHz	QPSK	19175	25RB#0	21.58	PASS
Band2	5MHz	16QAM	19175	25RB#0	20.67	PASS
Band2	10MHz	QPSK	18650	1RB#0	21.28	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	10MHz	16QAM	18650	1RB#0	20.69	PASS
Band2	10MHz	QPSK	18650	1RB#24	21.27	PASS
Band2	10MHz	16QAM	18650	1RB#24	20.62	PASS
Band2	10MHz	QPSK	18650	1RB#49	21.27	PASS
Band2	10MHz	16QAM	18650	1RB#49	20.53	PASS
Band2	10MHz	QPSK	18650	25RB#0	20.39	PASS
Band2	10MHz	16QAM	18650	25RB#0	19.37	PASS
Band2	10MHz	QPSK	18650	25RB#12	20.30	PASS
Band2	10MHz	16QAM	18650	25RB#12	19.38	PASS
Band2	10MHz	QPSK	18650	25RB#25	20.31	PASS
Band2	10MHz	16QAM	18650	25RB#25	19.38	PASS
Band2	10MHz	QPSK	18650	50RB#0	20.28	PASS
Band2	10MHz	16QAM	18650	50RB#0	19.56	PASS
Band2	10MHz	QPSK	18900	1RB#0	21.42	PASS
Band2	10MHz	16QAM	18900	1RB#0	20.85	PASS
Band2	10MHz	QPSK	18900	1RB#24	21.62	PASS
Band2	10MHz	16QAM	18900	1RB#24	20.94	PASS
Band2	10MHz	QPSK	18900	1RB#49	21.82	PASS
Band2	10MHz	16QAM	18900	1RB#49	21.11	PASS
Band2	10MHz	QPSK	18900	25RB#0	20.63	PASS
Band2	10MHz	16QAM	18900	25RB#0	19.71	PASS
Band2	10MHz	QPSK	18900	25RB#12	20.64	PASS
Band2	10MHz	16QAM	18900	25RB#12	19.72	PASS
Band2	10MHz	QPSK	18900	25RB#25	20.91	PASS
Band2	10MHz	16QAM	18900	25RB#25	19.99	PASS
Band2	10MHz	QPSK	18900	50RB#0	20.79	PASS
Band2	10MHz	16QAM	18900	50RB#0	19.87	PASS
Band2	10MHz	QPSK	19150	1RB#0	22.19	PASS
Band2	10MHz	16QAM	19150	1RB#0	21.49	PASS
Band2	10MHz	QPSK	19150	1RB#24	22.40	PASS
Band2	10MHz	16QAM	19150	1RB#24	21.64	PASS
Band2	10MHz	QPSK	19150	1RB#49	22.54	PASS
Band2	10MHz	16QAM	19150	1RB#49	21.67	PASS
Band2	10MHz	QPSK	19150	25RB#0	21.33	PASS
Band2	10MHz	16QAM	19150	25RB#0	20.67	PASS
Band2	10MHz	QPSK	19150	25RB#12	21.33	PASS
Band2	10MHz	16QAM	19150	25RB#12	20.63	PASS
Band2	10MHz	QPSK	19150	25RB#25	21.57	PASS
Band2	10MHz	16QAM	19150	25RB#25	20.83	PASS
Band2	10MHz	QPSK	19150	50RB#0	21.41	PASS
Band2	10MHz	16QAM	19150	50RB#0	20.65	PASS
Band2	15MHz	QPSK	18675	1RB#0	21.28	PASS
Band2	15MHz	16QAM	18675	1RB#0	20.63	PASS
Band2	15MHz	QPSK	18675	1RB#38	21.33	PASS
Band2	15MHz	16QAM	18675	1RB#38	20.58	PASS
Band2	15MHz	QPSK	18675	1RB#74	21.23	PASS
Band2	15MHz	16QAM	18675	1RB#74	20.63	PASS
Band2	15MHz	QPSK	18675	38RB#0	20.32	PASS
Band2	15MHz	16QAM	18675	38RB#0	20.32	PASS
Band2	15MHz	QPSK	18675	38RB#18	20.32	PASS
Band2	15MHz	16QAM	18675	38RB#18	20.32	PASS
Band2	15MHz	QPSK	18675	38RB#37	20.32	PASS
Band2	15MHz	16QAM	18675	38RB#37	20.32	PASS
Band2	15MHz	QPSK	18675	75RB#0	20.31	PASS
Band2	15MHz	16QAM	18675	75RB#0	19.40	PASS
Band2	15MHz	QPSK	18900	1RB#0	21.35	PASS
Band2	15MHz	16QAM	18900	1RB#0	20.73	PASS
Band2	15MHz	QPSK	18900	1RB#38	21.64	PASS
Band2	15MHz	16QAM	18900	1RB#38	20.99	PASS
Band2	15MHz	QPSK	18900	1RB#74	21.89	PASS
Band2	15MHz	16QAM	18900	1RB#74	21.26	PASS
Band2	15MHz	QPSK	18900	38RB#0	20.79	PASS
Band2	15MHz	16QAM	18900	38RB#0	20.79	PASS
Band2	15MHz	QPSK	18900	38RB#18	20.79	PASS
Band2	15MHz	16QAM	18900	38RB#18	20.79	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band2	15MHz	QPSK	18900	38RB#37	20.79	PASS
Band2	15MHz	16QAM	18900	38RB#37	20.79	PASS
Band2	15MHz	QPSK	18900	75RB#0	20.79	PASS
Band2	15MHz	16QAM	18900	75RB#0	19.87	PASS
Band2	15MHz	QPSK	19125	1RB#0	21.72	PASS
Band2	15MHz	16QAM	19125	1RB#0	21.38	PASS
Band2	15MHz	QPSK	19125	1RB#38	22.04	PASS
Band2	15MHz	16QAM	19125	1RB#38	21.55	PASS
Band2	15MHz	QPSK	19125	1RB#74	22.30	PASS
Band2	15MHz	16QAM	19125	1RB#74	21.79	PASS
Band2	15MHz	QPSK	19125	38RB#0	21.30	PASS
Band2	15MHz	16QAM	19125	38RB#0	21.30	PASS
Band2	15MHz	QPSK	19125	38RB#18	21.30	PASS
Band2	15MHz	16QAM	19125	38RB#18	21.30	PASS
Band2	15MHz	QPSK	19125	38RB#37	21.30	PASS
Band2	15MHz	16QAM	19125	38RB#37	21.30	PASS
Band2	15MHz	QPSK	19125	75RB#0	21.30	PASS
Band2	15MHz	16QAM	19125	75RB#0	20.60	PASS
Band2	20MHz	QPSK	18700	1RB#0	21.64	PASS
Band2	20MHz	16QAM	18700	1RB#0	20.64	PASS
Band2	20MHz	QPSK	18700	1RB#49	21.54	PASS
Band2	20MHz	16QAM	18700	1RB#49	20.59	PASS
Band2	20MHz	QPSK	18700	1RB#99	21.59	PASS
Band2	20MHz	16QAM	18700	1RB#99	20.58	PASS
Band2	20MHz	QPSK	18700	50RB#0	20.39	PASS
Band2	20MHz	16QAM	18700	50RB#0	19.57	PASS
Band2	20MHz	QPSK	18700	50RB#25	20.40	PASS
Band2	20MHz	16QAM	18700	50RB#25	19.58	PASS
Band2	20MHz	QPSK	18700	50RB#50	20.26	PASS
Band2	20MHz	16QAM	18700	50RB#50	19.48	PASS
Band2	20MHz	QPSK	18700	100RB#0	20.39	PASS
Band2	20MHz	16QAM	18700	100RB#0	19.50	PASS
Band2	20MHz	QPSK	18900	1RB#0	21.50	PASS
Band2	20MHz	16QAM	18900	1RB#0	20.60	PASS
Band2	20MHz	QPSK	18900	1RB#49	21.83	PASS
Band2	20MHz	16QAM	18900	1RB#49	20.79	PASS
Band2	20MHz	QPSK	18900	1RB#99	22.23	PASS
Band2	20MHz	16QAM	18900	1RB#99	21.18	PASS
Band2	20MHz	QPSK	18900	50RB#0	20.63	PASS
Band2	20MHz	16QAM	18900	50RB#0	19.74	PASS
Band2	20MHz	QPSK	18900	50RB#25	20.64	PASS
Band2	20MHz	16QAM	18900	50RB#25	19.74	PASS
Band2	20MHz	QPSK	18900	50RB#50	20.85	PASS
Band2	20MHz	16QAM	18900	50RB#50	20.07	PASS
Band2	20MHz	QPSK	18900	100RB#0	20.83	PASS
Band2	20MHz	16QAM	18900	100RB#0	19.93	PASS
Band2	20MHz	QPSK	19100	1RB#0	22.15	PASS
Band2	20MHz	16QAM	19100	1RB#0	21.66	PASS
Band2	20MHz	QPSK	19100	1RB#49	22.39	PASS
Band2	20MHz	16QAM	19100	1RB#49	21.84	PASS
Band2	20MHz	QPSK	19100	1RB#99	22.73	PASS
Band2	20MHz	16QAM	19100	1RB#99	22.11	PASS
Band2	20MHz	QPSK	19100	50RB#0	21.20	PASS
Band2	20MHz	16QAM	19100	50RB#0	20.39	PASS
Band2	20MHz	QPSK	19100	50RB#25	21.11	PASS
Band2	20MHz	16QAM	19100	50RB#25	20.39	PASS
Band2	20MHz	QPSK	19100	50RB#50	21.55	PASS
Band2	20MHz	16QAM	19100	50RB#50	20.61	PASS
Band2	20MHz	QPSK	19100	100RB#0	21.37	PASS
Band2	20MHz	16QAM	19100	100RB#0	20.55	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band4

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band4	1.4MHz	QPSK	19957	1RB#0	22.51	PASS
Band4	1.4MHz	16QAM	19957	1RB#0	22.76	PASS
Band4	1.4MHz	QPSK	19957	1RB#2	22.52	PASS
Band4	1.4MHz	16QAM	19957	1RB#2	22.73	PASS
Band4	1.4MHz	QPSK	19957	1RB#5	22.51	PASS
Band4	1.4MHz	16QAM	19957	1RB#5	22.76	PASS
Band4	1.4MHz	QPSK	19957	3RB#0	22.59	PASS
Band4	1.4MHz	16QAM	19957	3RB#0	21.69	PASS
Band4	1.4MHz	QPSK	19957	3RB#1	22.53	PASS
Band4	1.4MHz	16QAM	19957	3RB#1	21.69	PASS
Band4	1.4MHz	QPSK	19957	3RB#3	22.54	PASS
Band4	1.4MHz	16QAM	19957	3RB#3	21.68	PASS
Band4	1.4MHz	QPSK	19957	6RB#0	21.70	PASS
Band4	1.4MHz	16QAM	19957	6RB#0	21.31	PASS
Band4	1.4MHz	QPSK	20175	1RB#0	22.43	PASS
Band4	1.4MHz	16QAM	20175	1RB#0	21.32	PASS
Band4	1.4MHz	QPSK	20175	1RB#2	22.25	PASS
Band4	1.4MHz	16QAM	20175	1RB#2	21.27	PASS
Band4	1.4MHz	QPSK	20175	1RB#5	22.35	PASS
Band4	1.4MHz	16QAM	20175	1RB#5	21.28	PASS
Band4	1.4MHz	QPSK	20175	3RB#0	22.35	PASS
Band4	1.4MHz	16QAM	20175	3RB#0	21.64	PASS
Band4	1.4MHz	QPSK	20175	3RB#1	22.36	PASS
Band4	1.4MHz	16QAM	20175	3RB#1	21.72	PASS
Band4	1.4MHz	QPSK	20175	3RB#3	22.39	PASS
Band4	1.4MHz	16QAM	20175	3RB#3	21.63	PASS
Band4	1.4MHz	QPSK	20175	6RB#0	21.50	PASS
Band4	1.4MHz	16QAM	20175	6RB#0	20.96	PASS
Band4	1.4MHz	QPSK	20393	1RB#0	22.54	PASS
Band4	1.4MHz	16QAM	20393	1RB#0	22.38	PASS
Band4	1.4MHz	QPSK	20393	1RB#2	22.52	PASS
Band4	1.4MHz	16QAM	20393	1RB#2	22.34	PASS
Band4	1.4MHz	QPSK	20393	1RB#5	22.53	PASS
Band4	1.4MHz	16QAM	20393	1RB#5	22.44	PASS
Band4	1.4MHz	QPSK	20393	3RB#0	22.52	PASS
Band4	1.4MHz	16QAM	20393	3RB#0	21.25	PASS
Band4	1.4MHz	QPSK	20393	3RB#1	22.51	PASS
Band4	1.4MHz	16QAM	20393	3RB#1	21.27	PASS
Band4	1.4MHz	QPSK	20393	3RB#3	22.50	PASS
Band4	1.4MHz	16QAM	20393	3RB#3	21.28	PASS
Band4	1.4MHz	QPSK	20393	6RB#0	21.69	PASS
Band4	1.4MHz	16QAM	20393	6RB#0	21.02	PASS
Band4	3MHz	QPSK	19965	1RB#0	22.49	PASS
Band4	3MHz	16QAM	19965	1RB#0	21.90	PASS
Band4	3MHz	QPSK	19965	1RB#8	22.49	PASS
Band4	3MHz	16QAM	19965	1RB#8	21.94	PASS
Band4	3MHz	QPSK	19965	1RB#14	22.40	PASS
Band4	3MHz	16QAM	19965	1RB#14	21.83	PASS
Band4	3MHz	QPSK	19965	8RB#0	21.75	PASS
Band4	3MHz	16QAM	19965	8RB#0	21.10	PASS
Band4	3MHz	QPSK	19965	8RB#4	21.78	PASS
Band4	3MHz	16QAM	19965	8RB#4	21.10	PASS
Band4	3MHz	QPSK	19965	8RB#7	21.70	PASS
Band4	3MHz	16QAM	19965	8RB#7	21.11	PASS
Band4	3MHz	QPSK	19965	15RB#0	21.76	PASS
Band4	3MHz	16QAM	19965	15RB#0	21.12	PASS
Band4	3MHz	QPSK	20175	1RB#0	22.39	PASS
Band4	3MHz	16QAM	20175	1RB#0	21.29	PASS
Band4	3MHz	QPSK	20175	1RB#8	22.36	PASS
Band4	3MHz	16QAM	20175	1RB#8	21.24	PASS
Band4	3MHz	QPSK	20175	1RB#14	22.36	PASS
Band4	3MHz	16QAM	20175	1RB#14	21.22	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	3MHz	QPSK	20175	8RB#0	21.46	PASS
Band4	3MHz	16QAM	20175	8RB#0	20.99	PASS
Band4	3MHz	QPSK	20175	8RB#4	21.45	PASS
Band4	3MHz	16QAM	20175	8RB#4	20.98	PASS
Band4	3MHz	QPSK	20175	8RB#7	21.41	PASS
Band4	3MHz	16QAM	20175	8RB#7	20.96	PASS
Band4	3MHz	QPSK	20175	15RB#0	21.51	PASS
Band4	3MHz	16QAM	20175	15RB#0	20.69	PASS
Band4	3MHz	QPSK	20385	1RB#0	22.30	PASS
Band4	3MHz	16QAM	20385	1RB#0	21.65	PASS
Band4	3MHz	QPSK	20385	1RB#8	22.44	PASS
Band4	3MHz	16QAM	20385	1RB#8	21.62	PASS
Band4	3MHz	QPSK	20385	1RB#14	22.46	PASS
Band4	3MHz	16QAM	20385	1RB#14	21.62	PASS
Band4	3MHz	QPSK	20385	8RB#0	21.74	PASS
Band4	3MHz	16QAM	20385	8RB#0	20.96	PASS
Band4	3MHz	QPSK	20385	8RB#4	21.66	PASS
Band4	3MHz	16QAM	20385	8RB#4	21.04	PASS
Band4	3MHz	QPSK	20385	8RB#7	21.78	PASS
Band4	3MHz	16QAM	20385	8RB#7	21.04	PASS
Band4	3MHz	QPSK	20385	15RB#0	21.65	PASS
Band4	3MHz	16QAM	20385	15RB#0	20.88	PASS
Band4	5MHz	QPSK	19975	1RB#0	22.60	PASS
Band4	5MHz	16QAM	19975	1RB#0	21.39	PASS
Band4	5MHz	QPSK	19975	1RB#12	22.50	PASS
Band4	5MHz	16QAM	19975	1RB#12	21.27	PASS
Band4	5MHz	QPSK	19975	1RB#24	22.50	PASS
Band4	5MHz	16QAM	19975	1RB#24	21.32	PASS
Band4	5MHz	QPSK	19975	12RB#0	21.80	PASS
Band4	5MHz	16QAM	19975	12RB#0	21.08	PASS
Band4	5MHz	QPSK	19975	12RB#6	21.74	PASS
Band4	5MHz	16QAM	19975	12RB#6	21.07	PASS
Band4	5MHz	QPSK	19975	12RB#13	21.76	PASS
Band4	5MHz	16QAM	19975	12RB#13	21.07	PASS
Band4	5MHz	QPSK	19975	25RB#0	21.72	PASS
Band4	5MHz	16QAM	19975	25RB#0	21.11	PASS
Band4	5MHz	QPSK	20175	1RB#0	22.22	PASS
Band4	5MHz	16QAM	20175	1RB#0	22.00	PASS
Band4	5MHz	QPSK	20175	1RB#12	22.19	PASS
Band4	5MHz	16QAM	20175	1RB#12	21.90	PASS
Band4	5MHz	QPSK	20175	1RB#24	22.19	PASS
Band4	5MHz	16QAM	20175	1RB#24	21.92	PASS
Band4	5MHz	QPSK	20175	12RB#0	21.47	PASS
Band4	5MHz	16QAM	20175	12RB#0	20.86	PASS
Band4	5MHz	QPSK	20175	12RB#6	21.47	PASS
Band4	5MHz	16QAM	20175	12RB#6	20.86	PASS
Band4	5MHz	QPSK	20175	12RB#13	21.52	PASS
Band4	5MHz	16QAM	20175	12RB#13	20.80	PASS
Band4	5MHz	QPSK	20175	25RB#0	21.57	PASS
Band4	5MHz	16QAM	20175	25RB#0	20.67	PASS
Band4	5MHz	QPSK	20375	1RB#0	22.33	PASS
Band4	5MHz	16QAM	20375	1RB#0	21.16	PASS
Band4	5MHz	QPSK	20375	1RB#12	22.38	PASS
Band4	5MHz	16QAM	20375	1RB#12	21.19	PASS
Band4	5MHz	QPSK	20375	1RB#24	22.41	PASS
Band4	5MHz	16QAM	20375	1RB#24	21.25	PASS
Band4	5MHz	QPSK	20375	12RB#0	21.79	PASS
Band4	5MHz	16QAM	20375	12RB#0	20.97	PASS
Band4	5MHz	QPSK	20375	12RB#6	21.71	PASS
Band4	5MHz	16QAM	20375	12RB#6	20.94	PASS
Band4	5MHz	QPSK	20375	12RB#13	21.68	PASS
Band4	5MHz	16QAM	20375	12RB#13	20.93	PASS
Band4	5MHz	QPSK	20375	25RB#0	21.68	PASS
Band4	5MHz	16QAM	20375	25RB#0	21.01	PASS
Band4	10MHz	QPSK	20000	1RB#0	22.52	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	10MHz	16QAM	20000	1RB#0	21.97	PASS
Band4	10MHz	QPSK	20000	1RB#24	22.37	PASS
Band4	10MHz	16QAM	20000	1RB#24	21.90	PASS
Band4	10MHz	QPSK	20000	1RB#49	22.36	PASS
Band4	10MHz	16QAM	20000	1RB#49	21.91	PASS
Band4	10MHz	QPSK	20000	25RB#0	21.79	PASS
Band4	10MHz	16QAM	20000	25RB#0	21.00	PASS
Band4	10MHz	QPSK	20000	25RB#12	21.69	PASS
Band4	10MHz	16QAM	20000	25RB#12	21.00	PASS
Band4	10MHz	QPSK	20000	25RB#25	21.71	PASS
Band4	10MHz	16QAM	20000	25RB#25	21.00	PASS
Band4	10MHz	QPSK	20000	50RB#0	21.75	PASS
Band4	10MHz	16QAM	20000	50RB#0	21.06	PASS
Band4	10MHz	QPSK	20175	1RB#0	22.36	PASS
Band4	10MHz	16QAM	20175	1RB#0	21.73	PASS
Band4	10MHz	QPSK	20175	1RB#24	22.28	PASS
Band4	10MHz	16QAM	20175	1RB#24	21.74	PASS
Band4	10MHz	QPSK	20175	1RB#49	22.28	PASS
Band4	10MHz	16QAM	20175	1RB#49	21.67	PASS
Band4	10MHz	QPSK	20175	25RB#0	21.48	PASS
Band4	10MHz	16QAM	20175	25RB#0	21.01	PASS
Band4	10MHz	QPSK	20175	25RB#12	21.47	PASS
Band4	10MHz	16QAM	20175	25RB#12	21.00	PASS
Band4	10MHz	QPSK	20175	25RB#25	21.51	PASS
Band4	10MHz	16QAM	20175	25RB#25	20.97	PASS
Band4	10MHz	QPSK	20175	50RB#0	21.44	PASS
Band4	10MHz	16QAM	20175	50RB#0	20.87	PASS
Band4	10MHz	QPSK	20350	1RB#0	22.07	PASS
Band4	10MHz	16QAM	20350	1RB#0	21.39	PASS
Band4	10MHz	QPSK	20350	1RB#24	22.10	PASS
Band4	10MHz	16QAM	20350	1RB#24	21.47	PASS
Band4	10MHz	QPSK	20350	1RB#49	22.19	PASS
Band4	10MHz	16QAM	20350	1RB#49	21.56	PASS
Band4	10MHz	QPSK	20350	25RB#0	21.61	PASS
Band4	10MHz	16QAM	20350	25RB#0	20.83	PASS
Band4	10MHz	QPSK	20350	25RB#12	21.65	PASS
Band4	10MHz	16QAM	20350	25RB#12	20.84	PASS
Band4	10MHz	QPSK	20350	25RB#25	21.69	PASS
Band4	10MHz	16QAM	20350	25RB#25	20.91	PASS
Band4	10MHz	QPSK	20350	50RB#0	21.74	PASS
Band4	10MHz	16QAM	20350	50RB#0	20.94	PASS
Band4	15MHz	QPSK	20025	1RB#0	22.41	PASS
Band4	15MHz	16QAM	20025	1RB#0	21.95	PASS
Band4	15MHz	QPSK	20025	1RB#38	22.35	PASS
Band4	15MHz	16QAM	20025	1RB#38	21.88	PASS
Band4	15MHz	QPSK	20025	1RB#74	22.34	PASS
Band4	15MHz	16QAM	20025	1RB#74	21.81	PASS
Band4	15MHz	QPSK	20025	38RB#0	21.63	PASS
Band4	15MHz	16QAM	20025	38RB#0	21.64	PASS
Band4	15MHz	QPSK	20025	38RB#18	21.64	PASS
Band4	15MHz	16QAM	20025	38RB#18	21.64	PASS
Band4	15MHz	QPSK	20025	38RB#37	21.64	PASS
Band4	15MHz	16QAM	20025	38RB#37	21.64	PASS
Band4	15MHz	QPSK	20025	75RB#0	21.64	PASS
Band4	15MHz	16QAM	20025	75RB#0	21.02	PASS
Band4	15MHz	QPSK	20175	1RB#0	22.04	PASS
Band4	15MHz	16QAM	20175	1RB#0	21.86	PASS
Band4	15MHz	QPSK	20175	1RB#38	21.87	PASS
Band4	15MHz	16QAM	20175	1RB#38	21.72	PASS
Band4	15MHz	QPSK	20175	1RB#74	21.99	PASS
Band4	15MHz	16QAM	20175	1RB#74	21.75	PASS
Band4	15MHz	QPSK	20175	38RB#0	21.48	PASS
Band4	15MHz	16QAM	20175	38RB#0	21.46	PASS
Band4	15MHz	QPSK	20175	38RB#18	21.45	PASS
Band4	15MHz	16QAM	20175	38RB#18	21.45	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band4	15MHz	QPSK	20175	38RB#37	21.45	PASS
Band4	15MHz	16QAM	20175	38RB#37	21.44	PASS
Band4	15MHz	QPSK	20175	75RB#0	21.44	PASS
Band4	15MHz	16QAM	20175	75RB#0	20.82	PASS
Band4	15MHz	QPSK	20325	1RB#0	22.07	PASS
Band4	15MHz	16QAM	20325	1RB#0	21.29	PASS
Band4	15MHz	QPSK	20325	1RB#38	22.16	PASS
Band4	15MHz	16QAM	20325	1RB#38	21.39	PASS
Band4	15MHz	QPSK	20325	1RB#74	22.25	PASS
Band4	15MHz	16QAM	20325	1RB#74	21.52	PASS
Band4	15MHz	QPSK	20325	38RB#0	21.67	PASS
Band4	15MHz	16QAM	20325	38RB#0	21.66	PASS
Band4	15MHz	QPSK	20325	38RB#18	21.66	PASS
Band4	15MHz	16QAM	20325	38RB#18	21.66	PASS
Band4	15MHz	QPSK	20325	38RB#37	21.66	PASS
Band4	15MHz	16QAM	20325	38RB#37	21.66	PASS
Band4	15MHz	QPSK	20325	75RB#0	21.66	PASS
Band4	15MHz	16QAM	20325	75RB#0	20.86	PASS
Band4	20MHz	QPSK	20050	1RB#0	22.93	PASS
Band4	20MHz	16QAM	20050	1RB#0	21.79	PASS
Band4	20MHz	QPSK	20050	1RB#49	22.83	PASS
Band4	20MHz	16QAM	20050	1RB#49	21.76	PASS
Band4	20MHz	QPSK	20050	1RB#99	22.66	PASS
Band4	20MHz	16QAM	20050	1RB#99	21.48	PASS
Band4	20MHz	QPSK	20050	50RB#0	21.71	PASS
Band4	20MHz	16QAM	20050	50RB#0	21.08	PASS
Band4	20MHz	QPSK	20050	50RB#25	21.74	PASS
Band4	20MHz	16QAM	20050	50RB#25	21.08	PASS
Band4	20MHz	QPSK	20050	50RB#50	21.57	PASS
Band4	20MHz	16QAM	20050	50RB#50	20.98	PASS
Band4	20MHz	QPSK	20050	100RB#0	21.61	PASS
Band4	20MHz	16QAM	20050	100RB#0	21.04	PASS
Band4	20MHz	QPSK	20175	1RB#0	22.37	PASS
Band4	20MHz	16QAM	20175	1RB#0	22.28	PASS
Band4	20MHz	QPSK	20175	1RB#49	22.26	PASS
Band4	20MHz	16QAM	20175	1RB#49	22.16	PASS
Band4	20MHz	QPSK	20175	1RB#99	22.16	PASS
Band4	20MHz	16QAM	20175	1RB#99	22.03	PASS
Band4	20MHz	QPSK	20175	50RB#0	21.49	PASS
Band4	20MHz	16QAM	20175	50RB#0	20.94	PASS
Band4	20MHz	QPSK	20175	50RB#25	21.58	PASS
Band4	20MHz	16QAM	20175	50RB#25	20.93	PASS
Band4	20MHz	QPSK	20175	50RB#50	21.56	PASS
Band4	20MHz	16QAM	20175	50RB#50	20.89	PASS
Band4	20MHz	QPSK	20175	100RB#0	21.51	PASS
Band4	20MHz	16QAM	20175	100RB#0	20.92	PASS
Band4	20MHz	QPSK	20300	1RB#0	22.71	PASS
Band4	20MHz	16QAM	20300	1RB#0	21.13	PASS
Band4	20MHz	QPSK	20300	1RB#49	22.66	PASS
Band4	20MHz	16QAM	20300	1RB#49	21.31	PASS
Band4	20MHz	QPSK	20300	1RB#99	22.83	PASS
Band4	20MHz	16QAM	20300	1RB#99	21.28	PASS
Band4	20MHz	QPSK	20300	50RB#0	21.57	PASS
Band4	20MHz	16QAM	20300	50RB#0	20.90	PASS
Band4	20MHz	QPSK	20300	50RB#25	21.50	PASS
Band4	20MHz	16QAM	20300	50RB#25	20.89	PASS
Band4	20MHz	QPSK	20300	50RB#50	21.68	PASS
Band4	20MHz	16QAM	20300	50RB#50	21.02	PASS
Band4	20MHz	QPSK	20300	100RB#0	21.55	PASS
Band4	20MHz	16QAM	20300	100RB#0	20.94	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band5

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band5	1.4MHz	QPSK	20407	1RB#0	22.85	PASS
Band5	1.4MHz	16QAM	20407	1RB#0	23.27	PASS
Band5	1.4MHz	QPSK	20407	1RB#2	22.77	PASS
Band5	1.4MHz	16QAM	20407	1RB#2	23.20	PASS
Band5	1.4MHz	QPSK	20407	1RB#5	22.74	PASS
Band5	1.4MHz	16QAM	20407	1RB#5	23.23	PASS
Band5	1.4MHz	QPSK	20407	3RB#0	22.70	PASS
Band5	1.4MHz	16QAM	20407	3RB#0	22.01	PASS
Band5	1.4MHz	QPSK	20407	3RB#1	22.65	PASS
Band5	1.4MHz	16QAM	20407	3RB#1	22.08	PASS
Band5	1.4MHz	QPSK	20407	3RB#3	22.73	PASS
Band5	1.4MHz	16QAM	20407	3RB#3	22.10	PASS
Band5	1.4MHz	QPSK	20407	6RB#0	21.80	PASS
Band5	1.4MHz	16QAM	20407	6RB#0	21.42	PASS
Band5	1.4MHz	QPSK	20525	1RB#0	22.56	PASS
Band5	1.4MHz	16QAM	20525	1RB#0	21.52	PASS
Band5	1.4MHz	QPSK	20525	1RB#2	22.58	PASS
Band5	1.4MHz	16QAM	20525	1RB#2	21.59	PASS
Band5	1.4MHz	QPSK	20525	1RB#5	22.59	PASS
Band5	1.4MHz	16QAM	20525	1RB#5	21.52	PASS
Band5	1.4MHz	QPSK	20525	3RB#0	22.29	PASS
Band5	1.4MHz	16QAM	20525	3RB#0	22.02	PASS
Band5	1.4MHz	QPSK	20525	3RB#1	22.29	PASS
Band5	1.4MHz	16QAM	20525	3RB#1	22.02	PASS
Band5	1.4MHz	QPSK	20525	3RB#3	22.32	PASS
Band5	1.4MHz	16QAM	20525	3RB#3	22.00	PASS
Band5	1.4MHz	QPSK	20525	6RB#0	21.86	PASS
Band5	1.4MHz	16QAM	20525	6RB#0	21.27	PASS
Band5	1.4MHz	QPSK	20643	1RB#0	22.59	PASS
Band5	1.4MHz	16QAM	20643	1RB#0	22.30	PASS
Band5	1.4MHz	QPSK	20643	1RB#2	22.49	PASS
Band5	1.4MHz	16QAM	20643	1RB#2	22.33	PASS
Band5	1.4MHz	QPSK	20643	1RB#5	22.39	PASS
Band5	1.4MHz	16QAM	20643	1RB#5	22.07	PASS
Band5	1.4MHz	QPSK	20643	3RB#0	22.53	PASS
Band5	1.4MHz	16QAM	20643	3RB#0	22.17	PASS
Band5	1.4MHz	QPSK	20643	3RB#1	22.55	PASS
Band5	1.4MHz	16QAM	20643	3RB#1	22.16	PASS
Band5	1.4MHz	QPSK	20643	3RB#3	22.64	PASS
Band5	1.4MHz	16QAM	20643	3RB#3	22.01	PASS
Band5	1.4MHz	QPSK	20643	6RB#0	21.85	PASS
Band5	1.4MHz	16QAM	20643	6RB#0	21.45	PASS
Band5	3MHz	QPSK	20415	1RB#0	22.40	PASS
Band5	3MHz	16QAM	20415	1RB#0	21.84	PASS
Band5	3MHz	QPSK	20415	1RB#8	22.38	PASS
Band5	3MHz	16QAM	20415	1RB#8	21.74	PASS
Band5	3MHz	QPSK	20415	1RB#14	22.40	PASS
Band5	3MHz	16QAM	20415	1RB#14	21.83	PASS
Band5	3MHz	QPSK	20415	8RB#0	21.74	PASS
Band5	3MHz	16QAM	20415	8RB#0	21.28	PASS
Band5	3MHz	QPSK	20415	8RB#4	21.73	PASS
Band5	3MHz	16QAM	20415	8RB#4	21.28	PASS
Band5	3MHz	QPSK	20415	8RB#7	21.63	PASS
Band5	3MHz	16QAM	20415	8RB#7	21.35	PASS
Band5	3MHz	QPSK	20415	15RB#0	21.70	PASS
Band5	3MHz	16QAM	20415	15RB#0	21.13	PASS
Band5	3MHz	QPSK	20525	1RB#0	22.47	PASS
Band5	3MHz	16QAM	20525	1RB#0	21.53	PASS
Band5	3MHz	QPSK	20525	1RB#8	22.56	PASS
Band5	3MHz	16QAM	20525	1RB#8	21.57	PASS
Band5	3MHz	QPSK	20525	1RB#14	22.56	PASS
Band5	3MHz	16QAM	20525	1RB#14	21.54	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	3MHz	QPSK	20525	8RB#0	21.71	PASS
Band5	3MHz	16QAM	20525	8RB#0	21.35	PASS
Band5	3MHz	QPSK	20525	8RB#4	21.64	PASS
Band5	3MHz	16QAM	20525	8RB#4	21.35	PASS
Band5	3MHz	QPSK	20525	8RB#7	21.47	PASS
Band5	3MHz	16QAM	20525	8RB#7	21.37	PASS
Band5	3MHz	QPSK	20525	15RB#0	21.68	PASS
Band5	3MHz	16QAM	20525	15RB#0	21.02	PASS
Band5	3MHz	QPSK	20635	1RB#0	22.65	PASS
Band5	3MHz	16QAM	20635	1RB#0	22.50	PASS
Band5	3MHz	QPSK	20635	1RB#8	22.56	PASS
Band5	3MHz	16QAM	20635	1RB#8	22.49	PASS
Band5	3MHz	QPSK	20635	1RB#14	22.37	PASS
Band5	3MHz	16QAM	20635	1RB#14	22.04	PASS
Band5	3MHz	QPSK	20635	8RB#0	21.76	PASS
Band5	3MHz	16QAM	20635	8RB#0	21.37	PASS
Band5	3MHz	QPSK	20635	8RB#4	21.67	PASS
Band5	3MHz	16QAM	20635	8RB#4	21.37	PASS
Band5	3MHz	QPSK	20635	8RB#7	21.70	PASS
Band5	3MHz	16QAM	20635	8RB#7	21.23	PASS
Band5	3MHz	QPSK	20635	15RB#0	21.71	PASS
Band5	3MHz	16QAM	20635	15RB#0	21.24	PASS
Band5	5MHz	QPSK	20425	1RB#0	22.76	PASS
Band5	5MHz	16QAM	20425	1RB#0	21.56	PASS
Band5	5MHz	QPSK	20425	1RB#12	22.64	PASS
Band5	5MHz	16QAM	20425	1RB#12	21.54	PASS
Band5	5MHz	QPSK	20425	1RB#24	22.61	PASS
Band5	5MHz	16QAM	20425	1RB#24	21.57	PASS
Band5	5MHz	QPSK	20425	12RB#0	21.69	PASS
Band5	5MHz	16QAM	20425	12RB#0	21.19	PASS
Band5	5MHz	QPSK	20425	12RB#6	21.69	PASS
Band5	5MHz	16QAM	20425	12RB#6	21.19	PASS
Band5	5MHz	QPSK	20425	12RB#13	21.58	PASS
Band5	5MHz	16QAM	20425	12RB#13	21.22	PASS
Band5	5MHz	QPSK	20425	25RB#0	21.67	PASS
Band5	5MHz	16QAM	20425	25RB#0	21.20	PASS
Band5	5MHz	QPSK	20525	1RB#0	22.53	PASS
Band5	5MHz	16QAM	20525	1RB#0	22.48	PASS
Band5	5MHz	QPSK	20525	1RB#12	22.29	PASS
Band5	5MHz	16QAM	20525	1RB#12	22.60	PASS
Band5	5MHz	QPSK	20525	1RB#24	22.52	PASS
Band5	5MHz	16QAM	20525	1RB#24	22.57	PASS
Band5	5MHz	QPSK	20525	12RB#0	21.66	PASS
Band5	5MHz	16QAM	20525	12RB#0	21.13	PASS
Band5	5MHz	QPSK	20525	12RB#6	21.59	PASS
Band5	5MHz	16QAM	20525	12RB#6	21.13	PASS
Band5	5MHz	QPSK	20525	12RB#13	21.68	PASS
Band5	5MHz	16QAM	20525	12RB#13	21.27	PASS
Band5	5MHz	QPSK	20525	25RB#0	21.69	PASS
Band5	5MHz	16QAM	20525	25RB#0	21.15	PASS
Band5	5MHz	QPSK	20625	1RB#0	23.18	PASS
Band5	5MHz	16QAM	20625	1RB#0	22.23	PASS
Band5	5MHz	QPSK	20625	1RB#12	23.09	PASS
Band5	5MHz	16QAM	20625	1RB#12	22.25	PASS
Band5	5MHz	QPSK	20625	1RB#24	22.78	PASS
Band5	5MHz	16QAM	20625	1RB#24	22.03	PASS
Band5	5MHz	QPSK	20625	12RB#0	21.68	PASS
Band5	5MHz	16QAM	20625	12RB#0	21.12	PASS
Band5	5MHz	QPSK	20625	12RB#6	21.77	PASS
Band5	5MHz	16QAM	20625	12RB#6	21.14	PASS
Band5	5MHz	QPSK	20625	12RB#13	21.59	PASS
Band5	5MHz	16QAM	20625	12RB#13	21.18	PASS
Band5	5MHz	QPSK	20625	25RB#0	21.95	PASS
Band5	5MHz	16QAM	20625	25RB#0	21.36	PASS
Band5	10MHz	QPSK	20450	1RB#0	22.56	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band5	10MHz	16QAM	20450	1RB#0	22.42	PASS
Band5	10MHz	QPSK	20450	1RB#24	22.56	PASS
Band5	10MHz	16QAM	20450	1RB#24	22.26	PASS
Band5	10MHz	QPSK	20450	1RB#49	22.44	PASS
Band5	10MHz	16QAM	20450	1RB#49	22.26	PASS
Band5	10MHz	QPSK	20450	25RB#0	21.73	PASS
Band5	10MHz	16QAM	20450	25RB#0	21.35	PASS
Band5	10MHz	QPSK	20450	25RB#12	21.72	PASS
Band5	10MHz	16QAM	20450	25RB#12	21.35	PASS
Band5	10MHz	QPSK	20450	25RB#25	21.63	PASS
Band5	10MHz	16QAM	20450	25RB#25	21.17	PASS
Band5	10MHz	QPSK	20450	50RB#0	21.81	PASS
Band5	10MHz	16QAM	20450	50RB#0	21.13	PASS
Band5	10MHz	QPSK	20525	1RB#0	22.59	PASS
Band5	10MHz	16QAM	20525	1RB#0	22.31	PASS
Band5	10MHz	QPSK	20525	1RB#24	22.49	PASS
Band5	10MHz	16QAM	20525	1RB#24	22.37	PASS
Band5	10MHz	QPSK	20525	1RB#49	22.70	PASS
Band5	10MHz	16QAM	20525	1RB#49	22.30	PASS
Band5	10MHz	QPSK	20525	25RB#0	21.74	PASS
Band5	10MHz	16QAM	20525	25RB#0	21.33	PASS
Band5	10MHz	QPSK	20525	25RB#12	21.61	PASS
Band5	10MHz	16QAM	20525	25RB#12	21.33	PASS
Band5	10MHz	QPSK	20525	25RB#25	21.86	PASS
Band5	10MHz	16QAM	20525	25RB#25	21.24	PASS
Band5	10MHz	QPSK	20525	50RB#0	21.50	PASS
Band5	10MHz	16QAM	20525	50RB#0	21.25	PASS
Band5	10MHz	QPSK	20600	1RB#0	22.56	PASS
Band5	10MHz	16QAM	20600	1RB#0	22.77	PASS
Band5	10MHz	QPSK	20600	1RB#24	22.58	PASS
Band5	10MHz	16QAM	20600	1RB#24	22.75	PASS
Band5	10MHz	QPSK	20600	1RB#49	22.53	PASS
Band5	10MHz	16QAM	20600	1RB#49	22.57	PASS
Band5	10MHz	QPSK	20600	25RB#0	21.80	PASS
Band5	10MHz	16QAM	20600	25RB#0	21.43	PASS
Band5	10MHz	QPSK	20600	25RB#12	21.67	PASS
Band5	10MHz	16QAM	20600	25RB#12	21.45	PASS
Band5	10MHz	QPSK	20600	25RB#25	21.78	PASS
Band5	10MHz	16QAM	20600	25RB#25	21.43	PASS
Band5	10MHz	QPSK	20600	50RB#0	21.46	PASS
Band5	10MHz	16QAM	20600	50RB#0	21.26	PASS





LTE Band 7

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band7	5MHz	QPSK	20775	1RB#0	21.58	PASS
Band7	5MHz	16QAM	20775	1RB#0	20.79	PASS
Band7	5MHz	QPSK	20775	1RB#12	21.69	PASS
Band7	5MHz	16QAM	20775	1RB#12	20.82	PASS
Band7	5MHz	QPSK	20775	1RB#24	21.04	PASS
Band7	5MHz	16QAM	20775	1RB#24	20.81	PASS
Band7	5MHz	QPSK	20775	12RB#0	21.26	PASS
Band7	5MHz	16QAM	20775	12RB#0	20.49	PASS
Band7	5MHz	QPSK	20775	12RB#6	21.29	PASS
Band7	5MHz	16QAM	20775	12RB#6	20.50	PASS
Band7	5MHz	QPSK	20775	12RB#13	21.25	PASS
Band7	5MHz	16QAM	20775	12RB#13	20.51	PASS
Band7	5MHz	QPSK	20775	25RB#0	21.26	PASS
Band7	5MHz	16QAM	20775	25RB#0	20.54	PASS
Band7	5MHz	QPSK	21100	1RB#0	21.69	PASS
Band7	5MHz	16QAM	21100	1RB#0	21.38	PASS
Band7	5MHz	QPSK	21100	1RB#12	21.47	PASS
Band7	5MHz	16QAM	21100	1RB#12	21.45	PASS
Band7	5MHz	QPSK	21100	1RB#24	21.80	PASS
Band7	5MHz	16QAM	21100	1RB#24	21.56	PASS
Band7	5MHz	QPSK	21100	12RB#0	21.10	PASS
Band7	5MHz	16QAM	21100	12RB#0	20.38	PASS
Band7	5MHz	QPSK	21100	12RB#6	21.13	PASS
Band7	5MHz	16QAM	21100	12RB#6	20.41	PASS
Band7	5MHz	QPSK	21100	12RB#13	21.25	PASS
Band7	5MHz	16QAM	21100	12RB#13	20.56	PASS
Band7	5MHz	QPSK	21100	25RB#0	21.13	PASS
Band7	5MHz	16QAM	21100	25RB#0	20.35	PASS
Band7	5MHz	QPSK	21425	1RB#0	21.76	PASS
Band7	5MHz	16QAM	21425	1RB#0	20.77	PASS
Band7	5MHz	QPSK	21425	1RB#12	22.00	PASS
Band7	5MHz	16QAM	21425	1RB#12	20.80	PASS
Band7	5MHz	QPSK	21425	1RB#24	21.73	PASS
Band7	5MHz	16QAM	21425	1RB#24	20.80	PASS
Band7	5MHz	QPSK	21425	12RB#0	21.32	PASS
Band7	5MHz	16QAM	21425	12RB#0	20.54	PASS
Band7	5MHz	QPSK	21425	12RB#6	21.30	PASS
Band7	5MHz	16QAM	21425	12RB#6	20.53	PASS
Band7	5MHz	QPSK	21425	12RB#13	21.34	PASS
Band7	5MHz	16QAM	21425	12RB#13	20.45	PASS
Band7	5MHz	QPSK	21425	25RB#0	21.29	PASS
Band7	5MHz	16QAM	21425	25RB#0	20.45	PASS
Band7	10MHz	QPSK	20800	1RB#0	21.44	PASS
Band7	10MHz	16QAM	20800	1RB#0	21.22	PASS
Band7	10MHz	QPSK	20800	1RB#24	21.18	PASS
Band7	10MHz	16QAM	20800	1RB#24	21.12	PASS
Band7	10MHz	QPSK	20800	1RB#49	21.04	PASS
Band7	10MHz	16QAM	20800	1RB#49	21.01	PASS
Band7	10MHz	QPSK	20800	25RB#0	21.30	PASS
Band7	10MHz	16QAM	20800	25RB#0	20.43	PASS
Band7	10MHz	QPSK	20800	25RB#12	21.24	PASS
Band7	10MHz	16QAM	20800	25RB#12	20.43	PASS
Band7	10MHz	QPSK	20800	25RB#25	21.09	PASS
Band7	10MHz	16QAM	20800	25RB#25	20.36	PASS
Band7	10MHz	QPSK	20800	50RB#0	21.25	PASS
Band7	10MHz	16QAM	20800	50RB#0	20.44	PASS
Band7	10MHz	QPSK	21100	1RB#0	21.85	PASS
Band7	10MHz	16QAM	21100	1RB#0	21.04	PASS
Band7	10MHz	QPSK	21100	1RB#24	21.95	PASS
Band7	10MHz	16QAM	21100	1RB#24	21.05	PASS
Band7	10MHz	QPSK	21100	1RB#49	21.93	PASS
Band7	10MHz	16QAM	21100	1RB#49	21.10	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	10MHz	QPSK	21100	25RB#0	20.94	PASS
Band7	10MHz	16QAM	21100	25RB#0	20.35	PASS
Band7	10MHz	QPSK	21100	25RB#12	20.97	PASS
Band7	10MHz	16QAM	21100	25RB#12	20.36	PASS
Band7	10MHz	QPSK	21100	25RB#25	21.11	PASS
Band7	10MHz	16QAM	21100	25RB#25	20.48	PASS
Band7	10MHz	QPSK	21100	50RB#0	21.02	PASS
Band7	10MHz	16QAM	21100	50RB#0	20.33	PASS
Band7	10MHz	QPSK	21400	1RB#0	21.36	PASS
Band7	10MHz	16QAM	21400	1RB#0	21.31	PASS
Band7	10MHz	QPSK	21400	1RB#24	21.71	PASS
Band7	10MHz	16QAM	21400	1RB#24	21.28	PASS
Band7	10MHz	QPSK	21400	1RB#49	21.91	PASS
Band7	10MHz	16QAM	21400	1RB#49	21.31	PASS
Band7	10MHz	QPSK	21400	25RB#0	21.22	PASS
Band7	10MHz	16QAM	21400	25RB#0	20.45	PASS
Band7	10MHz	QPSK	21400	25RB#12	21.27	PASS
Band7	10MHz	16QAM	21400	25RB#12	20.44	PASS
Band7	10MHz	QPSK	21400	25RB#25	21.30	PASS
Band7	10MHz	16QAM	21400	25RB#25	20.44	PASS
Band7	10MHz	QPSK	21400	50RB#0	21.23	PASS
Band7	10MHz	16QAM	21400	50RB#0	20.58	PASS
Band7	15MHz	QPSK	20825	1RB#0	21.44	PASS
Band7	15MHz	16QAM	20825	1RB#0	21.31	PASS
Band7	15MHz	QPSK	20825	1RB#38	20.96	PASS
Band7	15MHz	16QAM	20825	1RB#38	21.08	PASS
Band7	15MHz	QPSK	20825	1RB#74	20.87	PASS
Band7	15MHz	16QAM	20825	1RB#74	21.01	PASS
Band7	15MHz	QPSK	20825	38RB#0	21.06	PASS
Band7	15MHz	16QAM	20825	38RB#0	21.05	PASS
Band7	15MHz	QPSK	20825	38RB#18	21.05	PASS
Band7	15MHz	16QAM	20825	38RB#18	21.04	PASS
Band7	15MHz	QPSK	20825	38RB#37	21.04	PASS
Band7	15MHz	16QAM	20825	38RB#37	21.04	PASS
Band7	15MHz	QPSK	20825	75RB#0	21.03	PASS
Band7	15MHz	16QAM	20825	75RB#0	20.33	PASS
Band7	15MHz	QPSK	21100	1RB#0	21.73	PASS
Band7	15MHz	16QAM	21100	1RB#0	21.25	PASS
Band7	15MHz	QPSK	21100	1RB#38	21.78	PASS
Band7	15MHz	16QAM	21100	1RB#38	21.40	PASS
Band7	15MHz	QPSK	21100	1RB#74	21.90	PASS
Band7	15MHz	16QAM	21100	1RB#74	21.46	PASS
Band7	15MHz	QPSK	21100	38RB#0	21.01	PASS
Band7	15MHz	16QAM	21100	38RB#0	21.03	PASS
Band7	15MHz	QPSK	21100	38RB#18	21.04	PASS
Band7	15MHz	16QAM	21100	38RB#18	21.04	PASS
Band7	15MHz	QPSK	21100	38RB#37	21.05	PASS
Band7	15MHz	16QAM	21100	38RB#37	21.05	PASS
Band7	15MHz	QPSK	21100	75RB#0	21.04	PASS
Band7	15MHz	16QAM	21100	75RB#0	20.33	PASS
Band7	15MHz	QPSK	21375	1RB#0	21.39	PASS
Band7	15MHz	16QAM	21375	1RB#0	21.10	PASS
Band7	15MHz	QPSK	21375	1RB#38	21.55	PASS
Band7	15MHz	16QAM	21375	1RB#38	21.45	PASS
Band7	15MHz	QPSK	21375	1RB#74	21.72	PASS
Band7	15MHz	16QAM	21375	1RB#74	21.60	PASS
Band7	15MHz	QPSK	21375	38RB#0	21.29	PASS
Band7	15MHz	16QAM	21375	38RB#0	21.24	PASS
Band7	15MHz	QPSK	21375	38RB#18	21.23	PASS
Band7	15MHz	16QAM	21375	38RB#18	21.23	PASS
Band7	15MHz	QPSK	21375	38RB#37	21.23	PASS
Band7	15MHz	16QAM	21375	38RB#37	21.23	PASS
Band7	15MHz	QPSK	21375	75RB#0	21.23	PASS
Band7	15MHz	16QAM	21375	75RB#0	20.53	PASS
Band7	20MHz	QPSK	20850	1RB#0	21.52	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band7	20MHz	16QAM	20850	1RB#0	21.03	PASS
Band7	20MHz	QPSK	20850	1RB#49	20.95	PASS
Band7	20MHz	16QAM	20850	1RB#49	20.79	PASS
Band7	20MHz	QPSK	20850	1RB#99	22.04	PASS
Band7	20MHz	16QAM	20850	1RB#99	20.71	PASS
Band7	20MHz	QPSK	20850	50RB#0	20.97	PASS
Band7	20MHz	16QAM	20850	50RB#0	20.57	PASS
Band7	20MHz	QPSK	20850	50RB#25	20.97	PASS
Band7	20MHz	16QAM	20850	50RB#25	20.57	PASS
Band7	20MHz	QPSK	20850	50RB#50	20.94	PASS
Band7	20MHz	16QAM	20850	50RB#50	20.42	PASS
Band7	20MHz	QPSK	20850	100RB#0	21.14	PASS
Band7	20MHz	16QAM	20850	100RB#0	20.32	PASS
Band7	20MHz	QPSK	21100	1RB#0	21.80	PASS
Band7	20MHz	16QAM	21100	1RB#0	21.59	PASS
Band7	20MHz	QPSK	21100	1RB#49	21.93	PASS
Band7	20MHz	16QAM	21100	1RB#49	21.71	PASS
Band7	20MHz	QPSK	21100	1RB#99	22.09	PASS
Band7	20MHz	16QAM	21100	1RB#99	21.78	PASS
Band7	20MHz	QPSK	21100	50RB#0	21.03	PASS
Band7	20MHz	16QAM	21100	50RB#0	20.35	PASS
Band7	20MHz	QPSK	21100	50RB#25	21.11	PASS
Band7	20MHz	16QAM	21100	50RB#25	20.37	PASS
Band7	20MHz	QPSK	21100	50RB#50	21.27	PASS
Band7	20MHz	16QAM	21100	50RB#50	20.37	PASS
Band7	20MHz	QPSK	21100	100RB#0	21.18	PASS
Band7	20MHz	16QAM	21100	100RB#0	20.44	PASS
Band7	20MHz	QPSK	21350	1RB#0	21.52	PASS
Band7	20MHz	16QAM	21350	1RB#0	21.34	PASS
Band7	20MHz	QPSK	21350	1RB#49	21.17	PASS
Band7	20MHz	16QAM	21350	1RB#49	21.24	PASS
Band7	20MHz	QPSK	21350	1RB#99	22.03	PASS
Band7	20MHz	16QAM	21350	1RB#99	21.27	PASS
Band7	20MHz	QPSK	21350	50RB#0	21.24	PASS
Band7	20MHz	16QAM	21350	50RB#0	20.53	PASS
Band7	20MHz	QPSK	21350	50RB#25	21.21	PASS
Band7	20MHz	16QAM	21350	50RB#25	20.65	PASS
Band7	20MHz	QPSK	21350	50RB#50	21.24	PASS
Band7	20MHz	16QAM	21350	50RB#50	20.47	PASS
Band7	20MHz	QPSK	21350	100RB#0	21.34	PASS
Band7	20MHz	16QAM	21350	100RB#0	20.48	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band 12

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band12	1.4MHz	QPSK	23017	1RB#0	23.03	PASS
Band12	1.4MHz	16QAM	23017	1RB#0	23.27	PASS
Band12	1.4MHz	QPSK	23017	1RB#2	22.89	PASS
Band12	1.4MHz	16QAM	23017	1RB#2	23.18	PASS
Band12	1.4MHz	QPSK	23017	1RB#5	23.07	PASS
Band12	1.4MHz	16QAM	23017	1RB#5	22.80	PASS
Band12	1.4MHz	QPSK	23017	3RB#0	22.98	PASS
Band12	1.4MHz	16QAM	23017	3RB#0	21.55	PASS
Band12	1.4MHz	QPSK	23017	3RB#1	22.84	PASS
Band12	1.4MHz	16QAM	23017	3RB#1	21.55	PASS
Band12	1.4MHz	QPSK	23017	3RB#3	22.69	PASS
Band12	1.4MHz	16QAM	23017	3RB#3	21.51	PASS
Band12	1.4MHz	QPSK	23017	6RB#0	22.00	PASS
Band12	1.4MHz	16QAM	23017	6RB#0	21.25	PASS
Band12	1.4MHz	QPSK	23095	1RB#0	22.89	PASS
Band12	1.4MHz	16QAM	23095	1RB#0	21.75	PASS
Band12	1.4MHz	QPSK	23095	1RB#2	22.84	PASS
Band12	1.4MHz	16QAM	23095	1RB#2	21.72	PASS
Band12	1.4MHz	QPSK	23095	1RB#5	22.82	PASS
Band12	1.4MHz	16QAM	23095	1RB#5	21.83	PASS
Band12	1.4MHz	QPSK	23095	3RB#0	22.65	PASS
Band12	1.4MHz	16QAM	23095	3RB#0	21.58	PASS
Band12	1.4MHz	QPSK	23095	3RB#1	22.75	PASS
Band12	1.4MHz	16QAM	23095	3RB#1	21.58	PASS
Band12	1.4MHz	QPSK	23095	3RB#3	22.65	PASS
Band12	1.4MHz	16QAM	23095	3RB#3	21.56	PASS
Band12	1.4MHz	QPSK	23095	6RB#0	21.89	PASS
Band12	1.4MHz	16QAM	23095	6RB#0	21.18	PASS
Band12	1.4MHz	QPSK	23173	1RB#0	22.60	PASS
Band12	1.4MHz	16QAM	23173	1RB#0	22.09	PASS
Band12	1.4MHz	QPSK	23173	1RB#2	22.58	PASS
Band12	1.4MHz	16QAM	23173	1RB#2	22.08	PASS
Band12	1.4MHz	QPSK	23173	1RB#5	22.51	PASS
Band12	1.4MHz	16QAM	23173	1RB#5	22.18	PASS
Band12	1.4MHz	QPSK	23173	3RB#0	22.58	PASS
Band12	1.4MHz	16QAM	23173	3RB#0	21.78	PASS
Band12	1.4MHz	QPSK	23173	3RB#1	22.61	PASS
Band12	1.4MHz	16QAM	23173	3RB#1	21.78	PASS
Band12	1.4MHz	QPSK	23173	3RB#3	22.60	PASS
Band12	1.4MHz	16QAM	23173	3RB#3	21.78	PASS
Band12	1.4MHz	QPSK	23173	6RB#0	21.80	PASS
Band12	1.4MHz	16QAM	23173	6RB#0	21.00	PASS
Band12	3MHz	QPSK	23025	1RB#0	22.83	PASS
Band12	3MHz	16QAM	23025	1RB#0	21.87	PASS
Band12	3MHz	QPSK	23025	1RB#8	22.81	PASS
Band12	3MHz	16QAM	23025	1RB#8	21.78	PASS
Band12	3MHz	QPSK	23025	1RB#14	22.91	PASS
Band12	3MHz	16QAM	23025	1RB#14	21.82	PASS
Band12	3MHz	QPSK	23025	8RB#0	21.85	PASS
Band12	3MHz	16QAM	23025	8RB#0	21.23	PASS
Band12	3MHz	QPSK	23025	8RB#4	22.12	PASS
Band12	3MHz	16QAM	23025	8RB#4	21.23	PASS
Band12	3MHz	QPSK	23025	8RB#7	21.77	PASS
Band12	3MHz	16QAM	23025	8RB#7	21.21	PASS
Band12	3MHz	QPSK	23025	15RB#0	21.98	PASS
Band12	3MHz	16QAM	23025	15RB#0	21.12	PASS
Band12	3MHz	QPSK	23095	1RB#0	22.79	PASS
Band12	3MHz	16QAM	23095	1RB#0	21.76	PASS
Band12	3MHz	QPSK	23095	1RB#8	22.79	PASS
Band12	3MHz	16QAM	23095	1RB#8	21.72	PASS
Band12	3MHz	QPSK	23095	1RB#14	22.71	PASS
Band12	3MHz	16QAM	23095	1RB#14	21.70	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band12	3MHz	QPSK	23095	8RB#0	21.68	PASS
Band12	3MHz	16QAM	23095	8RB#0	21.12	PASS
Band12	3MHz	QPSK	23095	8RB#4	21.68	PASS
Band12	3MHz	16QAM	23095	8RB#4	21.15	PASS
Band12	3MHz	QPSK	23095	8RB#7	21.77	PASS
Band12	3MHz	16QAM	23095	8RB#7	21.15	PASS
Band12	3MHz	QPSK	23095	15RB#0	21.81	PASS
Band12	3MHz	16QAM	23095	15RB#0	20.87	PASS
Band12	3MHz	QPSK	23165	1RB#0	22.63	PASS
Band12	3MHz	16QAM	23165	1RB#0	22.19	PASS
Band12	3MHz	QPSK	23165	1RB#8	22.63	PASS
Band12	3MHz	16QAM	23165	1RB#8	22.15	PASS
Band12	3MHz	QPSK	23165	1RB#14	22.53	PASS
Band12	3MHz	16QAM	23165	1RB#14	22.13	PASS
Band12	3MHz	QPSK	23165	8RB#0	21.77	PASS
Band12	3MHz	16QAM	23165	8RB#0	20.95	PASS
Band12	3MHz	QPSK	23165	8RB#4	21.77	PASS
Band12	3MHz	16QAM	23165	8RB#4	20.98	PASS
Band12	3MHz	QPSK	23165	8RB#7	21.69	PASS
Band12	3MHz	16QAM	23165	8RB#7	20.94	PASS
Band12	3MHz	QPSK	23165	15RB#0	21.63	PASS
Band12	3MHz	16QAM	23165	15RB#0	20.85	PASS
Band12	5MHz	QPSK	23035	1RB#0	22.83	PASS
Band12	5MHz	16QAM	23035	1RB#0	21.37	PASS
Band12	5MHz	QPSK	23035	1RB#12	22.75	PASS
Band12	5MHz	16QAM	23035	1RB#12	21.31	PASS
Band12	5MHz	QPSK	23035	1RB#24	22.73	PASS
Band12	5MHz	16QAM	23035	1RB#24	21.19	PASS
Band12	5MHz	QPSK	23035	12RB#0	21.95	PASS
Band12	5MHz	16QAM	23035	12RB#0	21.03	PASS
Band12	5MHz	QPSK	23035	12RB#6	21.95	PASS
Band12	5MHz	16QAM	23035	12RB#6	21.03	PASS
Band12	5MHz	QPSK	23035	12RB#13	21.79	PASS
Band12	5MHz	16QAM	23035	12RB#13	21.02	PASS
Band12	5MHz	QPSK	23035	25RB#0	21.78	PASS
Band12	5MHz	16QAM	23035	25RB#0	21.21	PASS
Band12	5MHz	QPSK	23095	1RB#0	22.51	PASS
Band12	5MHz	16QAM	23095	1RB#0	22.26	PASS
Band12	5MHz	QPSK	23095	1RB#12	22.30	PASS
Band12	5MHz	16QAM	23095	1RB#12	22.13	PASS
Band12	5MHz	QPSK	23095	1RB#24	22.44	PASS
Band12	5MHz	16QAM	23095	1RB#24	22.11	PASS
Band12	5MHz	QPSK	23095	12RB#0	21.81	PASS
Band12	5MHz	16QAM	23095	12RB#0	20.92	PASS
Band12	5MHz	QPSK	23095	12RB#6	21.81	PASS
Band12	5MHz	16QAM	23095	12RB#6	21.00	PASS
Band12	5MHz	QPSK	23095	12RB#13	21.65	PASS
Band12	5MHz	16QAM	23095	12RB#13	21.00	PASS
Band12	5MHz	QPSK	23095	25RB#0	21.75	PASS
Band12	5MHz	16QAM	23095	25RB#0	20.81	PASS
Band12	5MHz	QPSK	23155	1RB#0	22.89	PASS
Band12	5MHz	16QAM	23155	1RB#0	21.65	PASS
Band12	5MHz	QPSK	23155	1RB#12	22.94	PASS
Band12	5MHz	16QAM	23155	1RB#12	21.62	PASS
Band12	5MHz	QPSK	23155	1RB#24	22.60	PASS
Band12	5MHz	16QAM	23155	1RB#24	21.64	PASS
Band12	5MHz	QPSK	23155	12RB#0	21.78	PASS
Band12	5MHz	16QAM	23155	12RB#0	20.74	PASS
Band12	5MHz	QPSK	23155	12RB#6	21.78	PASS
Band12	5MHz	16QAM	23155	12RB#6	20.85	PASS
Band12	5MHz	QPSK	23155	12RB#13	21.65	PASS
Band12	5MHz	16QAM	23155	12RB#13	20.94	PASS
Band12	5MHz	QPSK	23155	25RB#0	21.74	PASS
Band12	5MHz	16QAM	23155	25RB#0	20.98	PASS
Band12	10MHz	QPSK	23060	1RB#0	22.73	PASS





Band12	10MHz	16QAM	23060	1RB#0	22.05	PASS
Band12	10MHz	QPSK	23060	1RB#24	22.67	PASS
Band12	10MHz	16QAM	23060	1RB#24	21.93	PASS
Band12	10MHz	QPSK	23060	1RB#49	22.47	PASS
Band12	10MHz	16QAM	23060	1RB#49	22.02	PASS
Band12	10MHz	QPSK	23060	25RB#0	22.05	PASS
Band12	10MHz	16QAM	23060	25RB#0	21.06	PASS
Band12	10MHz	QPSK	23060	25RB#12	21.80	PASS
Band12	10MHz	16QAM	23060	25RB#12	21.06	PASS
Band12	10MHz	QPSK	23060	25RB#25	21.59	PASS
Band12	10MHz	16QAM	23060	25RB#25	20.87	PASS
Band12	10MHz	QPSK	23060	50RB#0	21.85	PASS
Band12	10MHz	16QAM	23060	50RB#0	21.04	PASS
Band12	10MHz	QPSK	23095	1RB#0	22.87	PASS
Band12	10MHz	16QAM	23095	1RB#0	21.91	PASS
Band12	10MHz	QPSK	23095	1RB#24	22.79	PASS
Band12	10MHz	16QAM	23095	1RB#24	21.78	PASS
Band12	10MHz	QPSK	23095	1RB#49	22.77	PASS
Band12	10MHz	16QAM	23095	1RB#49	21.71	PASS
Band12	10MHz	QPSK	23095	25RB#0	21.91	PASS
Band12	10MHz	16QAM	23095	25RB#0	21.12	PASS
Band12	10MHz	QPSK	23095	25RB#12	21.92	PASS
Band12	10MHz	16QAM	23095	25RB#12	21.12	PASS
Band12	10MHz	QPSK	23095	25RB#25	21.68	PASS
Band12	10MHz	16QAM	23095	25RB#25	21.11	PASS
Band12	10MHz	QPSK	23095	50RB#0	21.84	PASS
Band12	10MHz	16QAM	23095	50RB#0	21.01	PASS
Band12	10MHz	QPSK	23130	1RB#0	22.50	PASS
Band12	10MHz	16QAM	23130	1RB#0	22.60	PASS
Band12	10MHz	QPSK	23130	1RB#24	22.51	PASS
Band12	10MHz	16QAM	23130	1RB#24	22.63	PASS
Band12	10MHz	QPSK	23130	1RB#49	22.58	PASS
Band12	10MHz	16QAM	23130	1RB#49	21.85	PASS
Band12	10MHz	QPSK	23130	25RB#0	21.64	PASS
Band12	10MHz	16QAM	23130	25RB#0	21.05	PASS
Band12	10MHz	QPSK	23130	25RB#12	21.65	PASS
Band12	10MHz	16QAM	23130	25RB#12	21.00	PASS
Band12	10MHz	QPSK	23130	25RB#25	21.69	PASS
Band12	10MHz	16QAM	23130	25RB#25	21.02	PASS
Band12	10MHz	QPSK	23130	50RB#0	21.70	PASS
Band12	10MHz	16QAM	23130	50RB#0	21.48	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



LTE Band17

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band17	5MHz	QPSK	23755	1RB#0	21.77	PASS
Band17	5MHz	16QAM	23755	1RB#0	22.25	PASS
Band17	5MHz	QPSK	23755	1RB#12	22.56	PASS
Band17	5MHz	16QAM	23755	1RB#12	22.11	PASS
Band17	5MHz	QPSK	23755	1RB#24	22.32	PASS
Band17	5MHz	16QAM	23755	1RB#24	21.69	PASS
Band17	5MHz	QPSK	23755	12RB#0	21.87	PASS
Band17	5MHz	16QAM	23755	12RB#0	20.98	PASS
Band17	5MHz	QPSK	23755	12RB#6	21.87	PASS
Band17	5MHz	16QAM	23755	12RB#6	20.98	PASS
Band17	5MHz	QPSK	23755	12RB#13	21.74	PASS
Band17	5MHz	16QAM	23755	12RB#13	20.87	PASS
Band17	5MHz	QPSK	23755	25RB#0	21.82	PASS
Band17	5MHz	16QAM	23755	25RB#0	20.80	PASS
Band17	5MHz	QPSK	23790	1RB#0	22.88	PASS
Band17	5MHz	16QAM	23790	1RB#0	21.47	PASS
Band17	5MHz	QPSK	23790	1RB#12	22.84	PASS
Band17	5MHz	16QAM	23790	1RB#12	21.43	PASS
Band17	5MHz	QPSK	23790	1RB#24	22.85	PASS
Band17	5MHz	16QAM	23790	1RB#24	21.80	PASS
Band17	5MHz	QPSK	23790	12RB#0	21.75	PASS
Band17	5MHz	16QAM	23790	12RB#0	20.82	PASS
Band17	5MHz	QPSK	23790	12RB#6	21.76	PASS
Band17	5MHz	16QAM	23790	12RB#6	20.90	PASS
Band17	5MHz	QPSK	23790	12RB#13	21.78	PASS
Band17	5MHz	16QAM	23790	12RB#13	20.97	PASS
Band17	5MHz	QPSK	23790	25RB#0	21.75	PASS
Band17	5MHz	16QAM	23790	25RB#0	20.99	PASS
Band17	5MHz	QPSK	23825	1RB#0	22.53	PASS
Band17	5MHz	16QAM	23825	1RB#0	21.22	PASS
Band17	5MHz	QPSK	23825	1RB#12	22.42	PASS
Band17	5MHz	16QAM	23825	1RB#12	21.13	PASS
Band17	5MHz	QPSK	23825	1RB#24	22.52	PASS
Band17	5MHz	16QAM	23825	1RB#24	21.11	PASS
Band17	5MHz	QPSK	23825	12RB#0	21.64	PASS
Band17	5MHz	16QAM	23825	12RB#0	20.84	PASS
Band17	5MHz	QPSK	23825	12RB#6	21.63	PASS
Band17	5MHz	16QAM	23825	12RB#6	20.83	PASS
Band17	5MHz	QPSK	23825	12RB#13	21.66	PASS
Band17	5MHz	16QAM	23825	12RB#13	20.91	PASS
Band17	5MHz	QPSK	23825	25RB#0	21.74	PASS
Band17	5MHz	16QAM	23825	25RB#0	21.03	PASS
Band17	10MHz	QPSK	23780	1RB#0	22.55	PASS
Band17	10MHz	16QAM	23780	1RB#0	21.77	PASS
Band17	10MHz	QPSK	23780	1RB#24	22.44	PASS
Band17	10MHz	16QAM	23780	1RB#24	21.64	PASS
Band17	10MHz	QPSK	23780	1RB#49	22.52	PASS
Band17	10MHz	16QAM	23780	1RB#49	21.73	PASS
Band17	10MHz	QPSK	23780	25RB#0	21.81	PASS
Band17	10MHz	16QAM	23780	25RB#0	20.88	PASS
Band17	10MHz	QPSK	23780	25RB#12	21.67	PASS
Band17	10MHz	16QAM	23780	25RB#12	20.88	PASS
Band17	10MHz	QPSK	23780	25RB#25	21.75	PASS
Band17	10MHz	16QAM	23780	25RB#25	20.88	PASS
Band17	10MHz	QPSK	23780	50RB#0	21.78	PASS
Band17	10MHz	16QAM	23780	50RB#0	20.92	PASS
Band17	10MHz	QPSK	23790	1RB#0	22.79	PASS
Band17	10MHz	16QAM	23790	1RB#0	21.78	PASS
Band17	10MHz	QPSK	23790	1RB#24	22.73	PASS
Band17	10MHz	16QAM	23790	1RB#24	21.74	PASS
Band17	10MHz	QPSK	23790	1RB#49	22.65	PASS
Band17	10MHz	16QAM	23790	1RB#49	21.65	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band17	10MHz	QPSK	23790	25RB#0	21.72	PASS
Band17	10MHz	16QAM	23790	25RB#0	21.01	PASS
Band17	10MHz	QPSK	23790	25RB#12	21.73	PASS
Band17	10MHz	16QAM	23790	25RB#12	21.01	PASS
Band17	10MHz	QPSK	23790	25RB#25	21.75	PASS
Band17	10MHz	16QAM	23790	25RB#25	21.03	PASS
Band17	10MHz	QPSK	23790	50RB#0	21.81	PASS
Band17	10MHz	16QAM	23790	50RB#0	20.95	PASS
Band17	10MHz	QPSK	23800	1RB#0	22.49	PASS
Band17	10MHz	16QAM	23800	1RB#0	22.59	PASS
Band17	10MHz	QPSK	23800	1RB#24	22.50	PASS
Band17	10MHz	16QAM	23800	1RB#24	22.61	PASS
Band17	10MHz	QPSK	23800	1RB#49	22.31	PASS
Band17	10MHz	16QAM	23800	1RB#49	22.56	PASS
Band17	10MHz	QPSK	23800	25RB#0	21.69	PASS
Band17	10MHz	16QAM	23800	25RB#0	20.93	PASS
Band17	10MHz	QPSK	23800	25RB#12	21.63	PASS
Band17	10MHz	16QAM	23800	25RB#12	20.93	PASS
Band17	10MHz	QPSK	23800	25RB#25	21.67	PASS
Band17	10MHz	16QAM	23800	25RB#25	20.92	PASS
Band17	10MHz	QPSK	23800	50RB#0	21.73	PASS
Band17	10MHz	16QAM	23800	50RB#0	20.99	PASS





LTE Band38

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band38	5MHz	QPSK	37775	1RB#0	22.60	PASS
Band38	5MHz	16QAM	37775	1RB#0	22.13	PASS
Band38	5MHz	QPSK	37775	1RB#12	22.56	PASS
Band38	5MHz	16QAM	37775	1RB#12	22.41	PASS
Band38	5MHz	QPSK	37775	1RB#24	22.54	PASS
Band38	5MHz	16QAM	37775	1RB#24	22.15	PASS
Band38	5MHz	QPSK	37775	12RB#0	21.41	PASS
Band38	5MHz	16QAM	37775	12RB#0	20.68	PASS
Band38	5MHz	QPSK	37775	12RB#6	21.35	PASS
Band38	5MHz	16QAM	37775	12RB#6	20.69	PASS
Band38	5MHz	QPSK	37775	12RB#13	21.33	PASS
Band38	5MHz	16QAM	37775	12RB#13	20.65	PASS
Band38	5MHz	QPSK	37775	25RB#0	21.38	PASS
Band38	5MHz	16QAM	37775	25RB#0	20.74	PASS
Band38	5MHz	QPSK	38000	1RB#0	21.61	PASS
Band38	5MHz	16QAM	38000	1RB#0	21.68	PASS
Band38	5MHz	QPSK	38000	1RB#12	21.57	PASS
Band38	5MHz	16QAM	38000	1RB#12	21.53	PASS
Band38	5MHz	QPSK	38000	1RB#24	21.60	PASS
Band38	5MHz	16QAM	38000	1RB#24	21.52	PASS
Band38	5MHz	QPSK	38000	12RB#0	20.90	PASS
Band38	5MHz	16QAM	38000	12RB#0	20.22	PASS
Band38	5MHz	QPSK	38000	12RB#6	20.92	PASS
Band38	5MHz	16QAM	38000	12RB#6	20.23	PASS
Band38	5MHz	QPSK	38000	12RB#13	20.84	PASS
Band38	5MHz	16QAM	38000	12RB#13	20.15	PASS
Band38	5MHz	QPSK	38000	25RB#0	20.90	PASS
Band38	5MHz	16QAM	38000	25RB#0	20.20	PASS
Band38	5MHz	QPSK	38225	1RB#0	21.74	PASS
Band38	5MHz	16QAM	38225	1RB#0	21.03	PASS
Band38	5MHz	QPSK	38225	1RB#12	21.64	PASS
Band38	5MHz	16QAM	38225	1RB#12	20.98	PASS
Band38	5MHz	QPSK	38225	1RB#24	21.80	PASS
Band38	5MHz	16QAM	38225	1RB#24	21.01	PASS
Band38	5MHz	QPSK	38225	12RB#0	20.71	PASS
Band38	5MHz	16QAM	38225	12RB#0	20.04	PASS
Band38	5MHz	QPSK	38225	12RB#6	20.72	PASS
Band38	5MHz	16QAM	38225	12RB#6	20.04	PASS
Band38	5MHz	QPSK	38225	12RB#13	20.72	PASS
Band38	5MHz	16QAM	38225	12RB#13	19.87	PASS
Band38	5MHz	QPSK	38225	25RB#0	20.75	PASS
Band38	5MHz	16QAM	38225	25RB#0	20.10	PASS
Band38	10MHz	QPSK	37800	1RB#0	22.33	PASS
Band38	10MHz	16QAM	37800	1RB#0	21.81	PASS
Band38	10MHz	QPSK	37800	1RB#24	22.27	PASS
Band38	10MHz	16QAM	37800	1RB#24	21.84	PASS
Band38	10MHz	QPSK	37800	1RB#49	22.30	PASS
Band38	10MHz	16QAM	37800	1RB#49	21.77	PASS
Band38	10MHz	QPSK	37800	25RB#0	21.17	PASS
Band38	10MHz	16QAM	37800	25RB#0	20.49	PASS
Band38	10MHz	QPSK	37800	25RB#12	21.15	PASS
Band38	10MHz	16QAM	37800	25RB#12	20.55	PASS
Band38	10MHz	QPSK	37800	25RB#25	21.06	PASS
Band38	10MHz	16QAM	37800	25RB#25	20.52	PASS
Band38	10MHz	QPSK	37800	50RB#0	21.10	PASS
Band38	10MHz	16QAM	37800	50RB#0	20.48	PASS
Band38	10MHz	QPSK	38000	1RB#0	21.89	PASS
Band38	10MHz	16QAM	38000	1RB#0	21.44	PASS
Band38	10MHz	QPSK	38000	1RB#24	21.81	PASS
Band38	10MHz	16QAM	38000	1RB#24	21.36	PASS
Band38	10MHz	QPSK	38000	1RB#49	21.76	PASS
Band38	10MHz	16QAM	38000	1RB#49	21.16	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band38	10MHz	QPSK	38000	25RB#0	21.13	PASS
Band38	10MHz	16QAM	38000	25RB#0	20.65	PASS
Band38	10MHz	QPSK	38000	25RB#12	21.14	PASS
Band38	10MHz	16QAM	38000	25RB#12	20.66	PASS
Band38	10MHz	QPSK	38000	25RB#25	21.09	PASS
Band38	10MHz	16QAM	38000	25RB#25	20.59	PASS
Band38	10MHz	QPSK	38000	50RB#0	21.03	PASS
Band38	10MHz	16QAM	38000	50RB#0	20.31	PASS
Band38	10MHz	QPSK	38200	1RB#0	21.88	PASS
Band38	10MHz	16QAM	38200	1RB#0	21.33	PASS
Band38	10MHz	QPSK	38200	1RB#24	21.81	PASS
Band38	10MHz	16QAM	38200	1RB#24	21.37	PASS
Band38	10MHz	QPSK	38200	1RB#49	21.88	PASS
Band38	10MHz	16QAM	38200	1RB#49	21.34	PASS
Band38	10MHz	QPSK	38200	25RB#0	20.73	PASS
Band38	10MHz	16QAM	38200	25RB#0	20.07	PASS
Band38	10MHz	QPSK	38200	25RB#12	20.75	PASS
Band38	10MHz	16QAM	38200	25RB#12	20.10	PASS
Band38	10MHz	QPSK	38200	25RB#25	20.71	PASS
Band38	10MHz	16QAM	38200	25RB#25	20.10	PASS
Band38	10MHz	QPSK	38200	50RB#0	20.86	PASS
Band38	10MHz	16QAM	38200	50RB#0	20.11	PASS
Band38	15MHz	QPSK	37825	1RB#0	22.33	PASS
Band38	15MHz	16QAM	37825	1RB#0	22.62	PASS
Band38	15MHz	QPSK	37825	1RB#38	22.28	PASS
Band38	15MHz	16QAM	37825	1RB#38	22.58	PASS
Band38	15MHz	QPSK	37825	1RB#74	22.19	PASS
Band38	15MHz	16QAM	37825	1RB#74	22.41	PASS
Band38	15MHz	QPSK	37825	38RB#0	21.22	PASS
Band38	15MHz	16QAM	37825	38RB#0	21.23	PASS
Band38	15MHz	QPSK	37825	38RB#18	21.22	PASS
Band38	15MHz	16QAM	37825	38RB#18	21.23	PASS
Band38	15MHz	QPSK	37825	38RB#37	21.23	PASS
Band38	15MHz	16QAM	37825	38RB#37	21.23	PASS
Band38	15MHz	QPSK	37825	75RB#0	21.23	PASS
Band38	15MHz	16QAM	37825	75RB#0	20.58	PASS
Band38	15MHz	QPSK	38000	1RB#0	22.24	PASS
Band38	15MHz	16QAM	38000	1RB#0	20.94	PASS
Band38	15MHz	QPSK	38000	1RB#38	21.88	PASS
Band38	15MHz	16QAM	38000	1RB#38	20.42	PASS
Band38	15MHz	QPSK	38000	1RB#74	21.85	PASS
Band38	15MHz	16QAM	38000	1RB#74	20.66	PASS
Band38	15MHz	QPSK	38000	38RB#0	20.95	PASS
Band38	15MHz	16QAM	38000	38RB#0	21.10	PASS
Band38	15MHz	QPSK	38000	38RB#18	21.10	PASS
Band38	15MHz	16QAM	38000	38RB#18	21.10	PASS
Band38	15MHz	QPSK	38000	38RB#37	21.10	PASS
Band38	15MHz	16QAM	38000	38RB#37	21.10	PASS
Band38	15MHz	QPSK	38000	75RB#0	21.10	PASS
Band38	15MHz	16QAM	38000	75RB#0	20.42	PASS
Band38	15MHz	QPSK	38175	1RB#0	21.88	PASS
Band38	15MHz	16QAM	38175	1RB#0	21.48	PASS
Band38	15MHz	QPSK	38175	1RB#38	21.87	PASS
Band38	15MHz	16QAM	38175	1RB#38	21.34	PASS
Band38	15MHz	QPSK	38175	1RB#74	21.89	PASS
Band38	15MHz	16QAM	38175	1RB#74	21.36	PASS
Band38	15MHz	QPSK	38175	38RB#0	20.79	PASS
Band38	15MHz	16QAM	38175	38RB#0	20.78	PASS
Band38	15MHz	QPSK	38175	38RB#18	20.78	PASS
Band38	15MHz	16QAM	38175	38RB#18	20.78	PASS
Band38	15MHz	QPSK	38175	38RB#37	20.78	PASS
Band38	15MHz	16QAM	38175	38RB#37	20.78	PASS
Band38	15MHz	QPSK	38175	75RB#0	20.79	PASS
Band38	15MHz	16QAM	38175	75RB#0	20.14	PASS
Band38	20MHz	QPSK	37850	1RB#0	21.91	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band38	20MHz	16QAM	37850	1RB#0	21.67	PASS
Band38	20MHz	QPSK	37850	1RB#49	22.00	PASS
Band38	20MHz	16QAM	37850	1RB#49	21.56	PASS
Band38	20MHz	QPSK	37850	1RB#99	21.80	PASS
Band38	20MHz	16QAM	37850	1RB#99	21.52	PASS
Band38	20MHz	QPSK	37850	50RB#0	21.30	PASS
Band38	20MHz	16QAM	37850	50RB#0	20.86	PASS
Band38	20MHz	QPSK	37850	50RB#25	21.31	PASS
Band38	20MHz	16QAM	37850	50RB#25	20.86	PASS
Band38	20MHz	QPSK	37850	50RB#50	21.13	PASS
Band38	20MHz	16QAM	37850	50RB#50	20.80	PASS
Band38	20MHz	QPSK	37850	100RB#0	21.22	PASS
Band38	20MHz	16QAM	37850	100RB#0	20.55	PASS
Band38	20MHz	QPSK	38000	1RB#0	22.22	PASS
Band38	20MHz	16QAM	38000	1RB#0	21.64	PASS
Band38	20MHz	QPSK	38000	1RB#49	22.02	PASS
Band38	20MHz	16QAM	38000	1RB#49	21.36	PASS
Band38	20MHz	QPSK	38000	1RB#99	22.00	PASS
Band38	20MHz	16QAM	38000	1RB#99	21.27	PASS
Band38	20MHz	QPSK	38000	50RB#0	21.13	PASS
Band38	20MHz	16QAM	38000	50RB#0	20.43	PASS
Band38	20MHz	QPSK	38000	50RB#25	21.15	PASS
Band38	20MHz	16QAM	38000	50RB#25	20.43	PASS
Band38	20MHz	QPSK	38000	50RB#50	21.00	PASS
Band38	20MHz	16QAM	38000	50RB#50	20.30	PASS
Band38	20MHz	QPSK	38000	100RB#0	20.97	PASS
Band38	20MHz	16QAM	38000	100RB#0	20.44	PASS
Band38	20MHz	QPSK	38150	1RB#0	21.97	PASS
Band38	20MHz	16QAM	38150	1RB#0	21.75	PASS
Band38	20MHz	QPSK	38150	1RB#49	21.78	PASS
Band38	20MHz	16QAM	38150	1RB#49	21.51	PASS
Band38	20MHz	QPSK	38150	1RB#99	21.96	PASS
Band38	20MHz	16QAM	38150	1RB#99	21.82	PASS
Band38	20MHz	QPSK	38150	50RB#0	20.58	PASS
Band38	20MHz	16QAM	38150	50RB#0	20.08	PASS
Band38	20MHz	QPSK	38150	50RB#25	20.59	PASS
Band38	20MHz	16QAM	38150	50RB#25	20.08	PASS
Band38	20MHz	QPSK	38150	50RB#50	20.63	PASS
Band38	20MHz	16QAM	38150	50RB#50	20.01	PASS
Band38	20MHz	QPSK	38150	100RB#0	20.56	PASS
Band38	20MHz	16QAM	38150	100RB#0	20.04	PASS





LTE Band41

Band	Bandwidth	Modulation	Channel	RB Configuration	Result(dBm)	Verdict
Band41	5MHz	QPSK	39675	1RB#0	21.00	PASS
Band41	5MHz	16QAM	39675	1RB#0	21.66	PASS
Band41	5MHz	QPSK	39675	1RB#12	21.65	PASS
Band41	5MHz	16QAM	39675	1RB#12	21.58	PASS
Band41	5MHz	QPSK	39675	1RB#24	21.65	PASS
Band41	5MHz	16QAM	39675	1RB#24	21.54	PASS
Band41	5MHz	QPSK	39675	12RB#0	21.12	PASS
Band41	5MHz	16QAM	39675	12RB#0	20.27	PASS
Band41	5MHz	QPSK	39675	12RB#6	21.13	PASS
Band41	5MHz	16QAM	39675	12RB#6	20.27	PASS
Band41	5MHz	QPSK	39675	12RB#13	20.94	PASS
Band41	5MHz	16QAM	39675	12RB#13	20.24	PASS
Band41	5MHz	QPSK	39675	25RB#0	20.97	PASS
Band41	5MHz	16QAM	39675	25RB#0	20.40	PASS
Band41	5MHz	QPSK	40620	1RB#0	22.13	PASS
Band41	5MHz	16QAM	40620	1RB#0	21.47	PASS
Band41	5MHz	QPSK	40620	1RB#12	22.07	PASS
Band41	5MHz	16QAM	40620	1RB#12	21.43	PASS
Band41	5MHz	QPSK	40620	1RB#24	22.09	PASS
Band41	5MHz	16QAM	40620	1RB#24	21.31	PASS
Band41	5MHz	QPSK	40620	12RB#0	20.95	PASS
Band41	5MHz	16QAM	40620	12RB#0	20.29	PASS
Band41	5MHz	QPSK	40620	12RB#6	20.93	PASS
Band41	5MHz	16QAM	40620	12RB#6	20.30	PASS
Band41	5MHz	QPSK	40620	12RB#13	20.87	PASS
Band41	5MHz	16QAM	40620	12RB#13	20.21	PASS
Band41	5MHz	QPSK	40620	25RB#0	20.91	PASS
Band41	5MHz	16QAM	40620	25RB#0	20.31	PASS
Band41	5MHz	QPSK	41565	1RB#0	21.56	PASS
Band41	5MHz	16QAM	41565	1RB#0	20.85	PASS
Band41	5MHz	QPSK	41565	1RB#12	21.59	PASS
Band41	5MHz	16QAM	41565	1RB#12	20.89	PASS
Band41	5MHz	QPSK	41565	1RB#24	21.56	PASS
Band41	5MHz	16QAM	41565	1RB#24	20.88	PASS
Band41	5MHz	QPSK	41565	12RB#0	20.39	PASS
Band41	5MHz	16QAM	41565	12RB#0	19.76	PASS
Band41	5MHz	QPSK	41565	12RB#6	20.41	PASS
Band41	5MHz	16QAM	41565	12RB#6	19.76	PASS
Band41	5MHz	QPSK	41565	12RB#13	20.35	PASS
Band41	5MHz	16QAM	41565	12RB#13	19.68	PASS
Band41	5MHz	QPSK	41565	25RB#0	20.60	PASS
Band41	5MHz	16QAM	41565	25RB#0	19.93	PASS
Band41	10MHz	QPSK	39700	1RB#0	22.23	PASS
Band41	10MHz	16QAM	39700	1RB#0	21.77	PASS
Band41	10MHz	QPSK	39700	1RB#24	22.16	PASS
Band41	10MHz	16QAM	39700	1RB#24	21.73	PASS
Band41	10MHz	QPSK	39700	1RB#49	22.11	PASS
Band41	10MHz	16QAM	39700	1RB#49	21.58	PASS
Band41	10MHz	QPSK	39700	25RB#0	21.19	PASS
Band41	10MHz	16QAM	39700	25RB#0	20.42	PASS
Band41	10MHz	QPSK	39700	25RB#12	20.87	PASS
Band41	10MHz	16QAM	39700	25RB#12	20.31	PASS
Band41	10MHz	QPSK	39700	25RB#25	20.77	PASS
Band41	10MHz	16QAM	39700	25RB#25	20.09	PASS
Band41	10MHz	QPSK	39700	50RB#0	20.78	PASS
Band41	10MHz	16QAM	39700	50RB#0	20.24	PASS
Band41	10MHz	QPSK	40620	1RB#0	22.28	PASS
Band41	10MHz	16QAM	40620	1RB#0	21.89	PASS
Band41	10MHz	QPSK	40620	1RB#24	22.14	PASS
Band41	10MHz	16QAM	40620	1RB#24	21.73	PASS
Band41	10MHz	QPSK	40620	1RB#49	21.76	PASS
Band41	10MHz	16QAM	40620	1RB#49	21.36	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band41	10MHz	QPSK	40620	25RB#0	20.95	PASS
Band41	10MHz	16QAM	40620	25RB#0	20.25	PASS
Band41	10MHz	QPSK	40620	25RB#12	20.93	PASS
Band41	10MHz	16QAM	40620	25RB#12	20.33	PASS
Band41	10MHz	QPSK	40620	25RB#25	20.81	PASS
Band41	10MHz	16QAM	40620	25RB#25	20.21	PASS
Band41	10MHz	QPSK	40620	50RB#0	20.76	PASS
Band41	10MHz	16QAM	40620	50RB#0	20.24	PASS
Band41	10MHz	QPSK	41540	1RB#0	21.66	PASS
Band41	10MHz	16QAM	41540	1RB#0	21.10	PASS
Band41	10MHz	QPSK	41540	1RB#24	21.61	PASS
Band41	10MHz	16QAM	41540	1RB#24	21.08	PASS
Band41	10MHz	QPSK	41540	1RB#49	21.69	PASS
Band41	10MHz	16QAM	41540	1RB#49	21.11	PASS
Band41	10MHz	QPSK	41540	25RB#0	20.57	PASS
Band41	10MHz	16QAM	41540	25RB#0	19.75	PASS
Band41	10MHz	QPSK	41540	25RB#12	20.58	PASS
Band41	10MHz	16QAM	41540	25RB#12	19.75	PASS
Band41	10MHz	QPSK	41540	25RB#25	20.55	PASS
Band41	10MHz	16QAM	41540	25RB#25	19.79	PASS
Band41	10MHz	QPSK	41540	50RB#0	20.65	PASS
Band41	10MHz	16QAM	41540	50RB#0	19.91	PASS
Band41	15MHz	QPSK	39725	1RB#0	22.22	PASS
Band41	15MHz	16QAM	39725	1RB#0	21.79	PASS
Band41	15MHz	QPSK	39725	1RB#38	22.04	PASS
Band41	15MHz	16QAM	39725	1RB#38	21.66	PASS
Band41	15MHz	QPSK	39725	1RB#74	22.05	PASS
Band41	15MHz	16QAM	39725	1RB#74	21.57	PASS
Band41	15MHz	QPSK	39725	38RB#0	21.07	PASS
Band41	15MHz	16QAM	39725	38RB#0	21.08	PASS
Band41	15MHz	QPSK	39725	38RB#18	20.71	PASS
Band41	15MHz	16QAM	39725	38RB#18	20.71	PASS
Band41	15MHz	QPSK	39725	38RB#37	20.71	PASS
Band41	15MHz	16QAM	39725	38RB#37	20.71	PASS
Band41	15MHz	QPSK	39725	75RB#0	20.71	PASS
Band41	15MHz	16QAM	39725	75RB#0	20.25	PASS
Band41	15MHz	QPSK	40620	1RB#0	22.38	PASS
Band41	15MHz	16QAM	40620	1RB#0	22.01	PASS
Band41	15MHz	QPSK	40620	1RB#38	22.19	PASS
Band41	15MHz	16QAM	40620	1RB#38	21.91	PASS
Band41	15MHz	QPSK	40620	1RB#74	22.09	PASS
Band41	15MHz	16QAM	40620	1RB#74	21.64	PASS
Band41	15MHz	QPSK	40620	38RB#0	21.19	PASS
Band41	15MHz	16QAM	40620	38RB#0	21.19	PASS
Band41	15MHz	QPSK	40620	38RB#18	21.20	PASS
Band41	15MHz	16QAM	40620	38RB#18	21.10	PASS
Band41	15MHz	QPSK	40620	38RB#37	21.10	PASS
Band41	15MHz	16QAM	40620	38RB#37	21.10	PASS
Band41	15MHz	QPSK	40620	75RB#0	21.10	PASS
Band41	15MHz	16QAM	40620	75RB#0	20.48	PASS
Band41	15MHz	QPSK	41515	1RB#0	21.70	PASS
Band41	15MHz	16QAM	41515	1RB#0	21.15	PASS
Band41	15MHz	QPSK	41515	1RB#38	21.64	PASS
Band41	15MHz	16QAM	41515	1RB#38	21.14	PASS
Band41	15MHz	QPSK	41515	1RB#74	21.73	PASS
Band41	15MHz	16QAM	41515	1RB#74	21.23	PASS
Band41	15MHz	QPSK	41515	38RB#0	20.57	PASS
Band41	15MHz	16QAM	41515	38RB#0	20.57	PASS
Band41	15MHz	QPSK	41515	38RB#18	20.38	PASS
Band41	15MHz	16QAM	41515	38RB#18	20.38	PASS
Band41	15MHz	QPSK	41515	38RB#37	20.38	PASS
Band41	15MHz	16QAM	41515	38RB#37	20.38	PASS
Band41	15MHz	QPSK	41515	75RB#0	20.38	PASS
Band41	15MHz	16QAM	41515	75RB#0	19.82	PASS
Band41	20MHz	QPSK	39750	1RB#0	21.81	PASS



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Band41	20MHz	16QAM	39750	1RB#0	21.50	PASS
Band41	20MHz	QPSK	39750	1RB#49	21.59	PASS
Band41	20MHz	16QAM	39750	1RB#49	21.28	PASS
Band41	20MHz	QPSK	39750	1RB#99	21.40	PASS
Band41	20MHz	16QAM	39750	1RB#99	21.05	PASS
Band41	20MHz	QPSK	39750	50RB#0	21.06	PASS
Band41	20MHz	16QAM	39750	50RB#0	20.63	PASS
Band41	20MHz	QPSK	39750	50RB#25	21.08	PASS
Band41	20MHz	16QAM	39750	50RB#25	20.66	PASS
Band41	20MHz	QPSK	39750	50RB#50	20.82	PASS
Band41	20MHz	16QAM	39750	50RB#50	20.42	PASS
Band41	20MHz	QPSK	39750	100RB#0	21.02	PASS
Band41	20MHz	16QAM	39750	100RB#0	20.39	PASS
Band41	20MHz	QPSK	40620	1RB#0	22.30	PASS
Band41	20MHz	16QAM	40620	1RB#0	22.16	PASS
Band41	20MHz	QPSK	40620	1RB#49	22.16	PASS
Band41	20MHz	16QAM	40620	1RB#49	22.16	PASS
Band41	20MHz	QPSK	40620	1RB#99	21.98	PASS
Band41	20MHz	16QAM	40620	1RB#99	21.80	PASS
Band41	20MHz	QPSK	40620	50RB#0	21.16	PASS
Band41	20MHz	16QAM	40620	50RB#0	20.58	PASS
Band41	20MHz	QPSK	40620	50RB#25	20.92	PASS
Band41	20MHz	16QAM	40620	50RB#25	20.59	PASS
Band41	20MHz	QPSK	40620	50RB#50	20.82	PASS
Band41	20MHz	16QAM	40620	50RB#50	20.39	PASS
Band41	20MHz	QPSK	40620	100RB#0	20.95	PASS
Band41	20MHz	16QAM	40620	100RB#0	20.33	PASS
Band41	20MHz	QPSK	41490	1RB#0	21.75	PASS
Band41	20MHz	16QAM	41490	1RB#0	21.46	PASS
Band41	20MHz	QPSK	41490	1RB#49	21.69	PASS
Band41	20MHz	16QAM	41490	1RB#49	21.34	PASS
Band41	20MHz	QPSK	41490	1RB#99	21.80	PASS
Band41	20MHz	16QAM	41490	1RB#99	21.47	PASS
Band41	20MHz	QPSK	41490	50RB#0	20.56	PASS
Band41	20MHz	16QAM	41490	50RB#0	20.12	PASS
Band41	20MHz	QPSK	41490	50RB#25	20.55	PASS
Band41	20MHz	16QAM	41490	50RB#25	19.96	PASS
Band41	20MHz	QPSK	41490	50RB#50	20.54	PASS
Band41	20MHz	16QAM	41490	50RB#50	20.06	PASS
Band41	20MHz	QPSK	41490	100RB#0	20.66	PASS
Band41	20MHz	16QAM	41490	100RB#0	19.89	PASS

<WLAN 2.4GHz Conducted Power>

Mode	Channel	Frequency (MHz)	Average Output Power (dBm)
IEEE 802.11b	1	2412	11.20
	6	2437	12.45
	11	2462	11.97
IEEE 802.11g	1	2412	12.52
	6	2437	12.58
	11	2462	13.20
IEEE 802.11n HT20	1	2412	12.47
	6	2437	13.80
	11	2462	13.30
IEEE 802.11n HT40	3	2422	11.82
	6	2437	12.10
	9	2452	11.30

Note: SAR is not required for the following 2.4 GHz OFDM conditions as the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.





<WLAN 5.2G Conducted Power>

Mode	Channel	Frequency (MHz)	Average Conducted Output Power(dBm)	Worst Case Test Rate Data
IEEE 802.11a	36	5180	13.07	MCS0
	40	5200	12.42	MCS0
	48	5240	13.22	MCS0
IEEE 802.11n HT20	36	5180	12.33	MCS0
	40	5200	11.99	MCS0
	48	5240	12.76	MCS0
IEEE 802.11n HT40	38	5190	11.88	MCS0
	46	5230	12.81	MCS0
IEEE 802.11AC20	36	5180	11.03	MCS0
	40	5200	12.77	MCS0
	48	5240	13.27	MCS0
IEEE 802.11AC40	38	5190	12.38	MCS0
	46	5230	12.56	MCS0
IEEE 802.11AC80	42	5210	12.10	MCS0

<WLAN 5.3G Conducted Power>

Mode	Channel	Frequency (MHz)	Conducted Output Power(dBm)	Worst Case Test Rate Data
IEEE 802.11a	52	5260	12.93	MCS0
	60	5300	11.88	MCS0
	64	5320	12.64	MCS0
IEEE 802.11n HT20	52	5260	13.23	MCS0
	60	5300	12.24	MCS0
	64	5320	12.45	MCS0
IEEE 802.11n HT40	54	5270	12.84	MCS0
	62	5310	12.32	MCS0
IEEE 802.11ac VHT20	52	5260	12.79	MCS0
	60	5300	12.63	MCS0
	64	5320	12.93	MCS0
IEEE 802.11ac VHT40	54	5270	12.84	MCS0
	62	5310	12.32	MCS0
IEEE 802.11ac VHT80	58	5290	12.78	MCS0



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



<WLAN 5.5G Conducted Power>

Mode	Channel	Frequency (MHz)	Conducted Output Power(dBm)	Worst Case Test Rate Data
IEEE 802.11a	100	5500	11.17	MCS0
	116	5580	12.17	MCS0
	140	5700	11.25	MCS0
IEEE 802.11n HT20	100	5500	12.36	MCS0
	116	5580	12.83	MCS0
	140	5700	11.48	MCS0
IEEE 802.11n HT40	102	5510	12.94	MCS0
	110	5550	12.30	MCS0
	134	5670	12.52	MCS0
IEEE 802.11ac VHT20	100	5500	12.35	MCS0
	116	5580	12.30	MCS0
	140	5700	11.97	MCS0
IEEE 802.11ac VHT40	102	5510	12.34	MCS0
	110	5550	12.31	MCS0
	134	5670	12.30	MCS0
IEEE 802.11ac VHT80	106	5530	12.05	MCS0
	122	5610	11.29	MCS0

<WLAN 5.8GHz Conducted Power>

Mode	Channel	Frequency (MHz)	Average Conducted Output Power(dBm)	Worst Case Test Rate Data
IEEE 802.11a	149	5745	11.53	MCS0
	157	5785	12.48	MCS0
	165	5825	11.57	MCS0
IEEE 802.11n HT20	149	5745	11.51	MCS0
	157	5785	10.15	MCS0
	165	5825	10.17	MCS0
IEEE 802.11n HT40	151	5755	12.20	MCS0
	159	5795	11.18	MCS0
IEEE 802.11AC20	149	5745	11.32	MCS0
	157	5785	10.98	MCS0
	165	5825	10.10	MCS0
IEEE 802.11AC40	151	5755	11.14	MCS0
	159	5795	10.57	MCS0
IEEE 802.11AC80	155	5775	10.82	MCS0



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



<BT Conducted Power>

Mode	channel	Frequency (MHz)	Conducted AVG output power (dBm)
BLE_1M	0	2402	0.40
	20	2442	-0.69
	39	2480	-0.31
BLE_2M	0	2402	0.42
	20	2442	-0.66
	39	2480	-0.31
GFSK	0	2402	-1.77
	39	2441	-1.65
	78	2480	-1.49
$\pi/4$ -DQPSK	0	2402	-1.96
	39	2441	-2.02
	78	2480	-1.65
8DPSK	0	2402	-1.92
	39	2441	-1.76
	78	2480	-1.68

Per KDB 447498 D01v06, the 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances ≤ 50 mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$ for 1-g SAR and ≤ 7.5 for 10-g extremity SAR

- $f(\text{GHz})$ is the RF channel transmit frequency in GHz
- Power and distance are rounded to the nearest mW and mm before calculation
- The result is rounded to one decimal place for comparison

Bluetooth Tune up Power (dBm)	Separation Distance (mm)	Frequency (GHz)	Exclusion Thresholds
0.5	5	2.45	0.4

Per KDB 447498 D01v06, when the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion. The test exclusion threshold is $0.4 < 3.0$, SAR testing is not required.

Test Mode	Channel Frequency (MHz)	Field Strength (dBuV/m@3m)	Max Output Power(mW)	Calculate on Value(Note)	Threshold Value (mW)
NFC	13.56	53.05	0.0001	0.000002	3

Note:


1. Calculate the SAR test to eliminate thresholds from chapter 2 conditions "3" formula
2. Field Strength (dBuV/m@3m) = Field Strength (dBuV/m@30m) + $40 \cdot \log(30/3)$
3. Max Power (dBm) = Field Strength of Fundamental (dBuV/m@3m) - 95.23
4. Max Power (mW) = $10^{(\text{Max power (dBm)} / 10)}$

Since Source-base time average power is below SAR test exclusion power thresholds, the SAR evaluation is not required.





4.2. Transmit Antennas and SAR Measurement Position



Antenna information:

WLAN/BT Antenna	WLAN/BT TX/RX
WWAN Antenna	GSM/UMTS/LTE TX/RX

Note:

- 1). Per KDB648474 D04, 10-g extremity SAR is not required when Body-Worn mode 1-g reported SAR < 1.2 W/Kg.
- 2). According to the KDB941225 D06 Hot Spot SAR v02, the edges with less than 25 mm distance to the antennas need to be tested for SAR.
- 3). Per KDB 616217 D04, The antennas in tablets are typically located near the back (bottom) surface and/or along the edges of the devices; therefore, SAR evaluation is required for these configurations. Exposures from antennas through the front (top) surface of the displaysection of a full-size tablet, away from the edges, are generally limited to the user's hands.

Distance of The Antenna to the EUT surface and edge (mm)						
Antennas	Front	Back	Top Side	Bottom Side	Left Side	Right Side
WWAN	<5	<5	<5	62	167	<5
WLAN/BT	<5	<5	55	<5	211	<5

Positions for SAR tests; Hotspot mode						
Antennas	Front	Back	Top Side	Bottom Side	Left Side	Right Side
WWAN	Yes	Yes	Yes	NO	NO	Yes
WLAN/BT	Yes	Yes	NO	Yes	NO	Yes

General Note: Referring to KDB 941225 D06 v02, When the overall device length and width are $\geq 9\text{cm} \times 5\text{cm}$, the test distance is 0mm, SAR must be measured for all sides and surfaces with a transmitting antenna located with 25mm from that surface or edge.





4.3. SAR Measurement Results

The calculated SAR is obtained by the following formula:

$$\text{Reported SAR} = \text{Measured SAR} * 10^{(P_{\text{target}} - P_{\text{measured}})/10}$$

$$\text{Scaling factor} = 10^{(P_{\text{target}} - P_{\text{measured}})/10}$$

$$\text{Reported SAR} = \text{Measured SAR} * \text{Scaling factor}$$

Where

P_{target} is the power of manufacturing upper limit;

P_{measured} is the measured power;

Measured SAR is measured SAR at measured power which including power drift)

Reported SAR which including Power Drift and Scaling factor

Duty Cycle

Test Mode	Duty Cycle
GSM	1:2
UMTS	1:1
LTE	1:1
WLAN2450	1:1
WLAN5200	1:1
WLAN5300	1:1
WLAN5500	1:1
WLAN5800	1:1

4.3.1 SAR Results

SAR Values [GSM 850]

Ch.	Freq. (MHz)	Time slots	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
128	824.2	4Txslots	Front	29.02	29.50	-4.42	1.117	0.122	0.136	Plot 1
128	824.2	4Txslots	Rear	29.02	29.50	-0.95	1.117	0.195	0.218	
128	824.2	4Txslots	Right	29.02	29.50	0.36	1.117	0.106	0.118	
128	824.2	4Txslots	Top	29.02	29.50	4.52	1.117	0.093	0.104	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.

2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).

SAR Values [GSM 1900]

Ch.	Freq. (MHz)	time slots	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers – Body (distance 0mm)										
810	1909.8	4Txslots	Front	26.56	27.00	-2.06	1.107	0.168	0.186	Plot 2
810	1909.8	4Txslots	Rear	26.56	27.00	1.79	1.107	0.202	0.224	
810	1909.8	4Txslots	Right	26.56	27.00	-1.98	1.107	0.154	0.170	
810	1909.8	4Txslots	Top	26.56	27.00	0.24	1.107	0.133	0.147	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.

2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR Values [WCDMA Band V]**

Ch.	Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
4132	826.4	RMC*	Front	22.52	23.00	-2.56	1.117	0.189	0.211	Plot 3
4132	826.4	RMC*	Rear	22.52	23.00	-0.64	1.117	0.224	0.250	
4132	826.4	RMC*	Right	22.52	23.00	3.35	1.117	0.167	0.187	
4132	826.4	RMC*	Top	22.52	23.00	-1.42	1.117	0.152	0.170	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. RMC* - RMC 12.2kbps mode;

SAR Values [WCDMA Band IV]

Ch.	Freq. (MHz)	Channel Type	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
1513	1752.6	RMC*	Front	21.67	22.00	-4.52	1.079	0.621	0.670	Plot 4
1513	1752.6	RMC*	Rear	21.67	22.00	-2.38	1.079	0.749	0.808	
1513	1752.6	RMC*	Right	21.67	22.00	1.44	1.079	0.608	0.656	
1513	1752.6	RMC*	Top	21.67	22.00	0.78	1.079	0.594	0.641	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. RMC* - RMC 12.2kbps mode;

SAR Values [WCDMA Band II]

Ch.	Freq. (MHz)	Chan nel Type	Test Position	Condu cted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
9538	1907.6	RMC	Front	21.65	22.00	-3.45	1.084	0.344	0.373	Plot 5
9538	1907.6	RMC	Rear	21.65	22.00	0.27	1.084	0.365	0.396	
9538	1907.6	RMC	Right	21.65	22.00	0.77	1.084	0.335	0.363	
9538	1907.6	RMC	Top	21.65	22.00	-1.05	1.084	0.316	0.343	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.
2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).
3. RMC* - RMC 12.2kbps mode;



**SAR Values [LTE Band 2]**

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
19100	1900.0	1RB	Front	22.15	22.50	-4.65	1.084	0.221	0.240	Plot 6
19100	1900.0	1RB	Rear	22.15	22.50	-0.05	1.084	0.276	0.299	
19100	1900.0	1RB	Right	22.15	22.50	3.78	1.084	0.214	0.232	
19100	1900.0	1RB	Top	22.15	22.50	0.02	1.084	0.202	0.219	
19100	1900.0	50%RB	Front	21.20	21.50	-4.25	1.072	0.112	0.120	
19100	1900.0	50%RB	Rear	21.20	21.50	-4.52	1.072	0.140	0.150	
19100	1900.0	50%RB	Right	21.20	21.50	3.30	1.072	0.097	0.104	
19100	1900.0	50%RB	Top	21.20	21.50	-1.08	1.072	0.075	0.080	

SAR Values [LTE Band 4]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
20050	1720.0	1RB	Front	22.93	23.00	-1.21	1.016	0.247	0.251	Plot 7
20050	1720.0	1RB	Rear	22.93	23.00	0.31	1.016	0.268	0.272	
20050	1720.0	1RB	Right	22.93	23.00	-0.23	1.016	0.232	0.236	
20050	1720.0	1RB	Top	22.93	23.00	3.00	1.016	0.217	0.221	
20050	1720.0	50%RB	Front	21.71	22.00	-2.23	1.069	0.124	0.133	
20050	1720.0	50%RB	Rear	21.71	22.00	-0.23	1.069	0.133	0.142	
20050	1720.0	50%RB	Right	21.71	22.00	3.02	1.069	0.114	0.122	
20050	1720.0	50%RB	Top	21.71	22.00	1.96	1.069	0.102	0.109	

SAR Values [LTE Band 5]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
20525	836.5	1RB	Front	22.59	23.00	3.02	1.099	0.103	0.113	Plot 8
20525	836.5	1RB	Rear	22.59	23.00	0.41	1.099	0.150	0.165	
20525	836.5	1RB	Right	22.59	23.00	-1.65	1.099	0.088	0.097	
20525	836.5	1RB	Top	22.59	23.00	0.34	1.099	0.074	0.081	
20450	829.0	50%RB	Front	21.81	22.00	-2.89	1.045	0.052	0.054	
20450	829.0	50%RB	Rear	21.81	22.00	-4.75	1.045	0.079	0.083	
20450	829.0	50%RB	Right	21.81	22.00	3.64	1.045	0.046	0.048	
20450	829.0	50%RB	Top	21.81	22.00	0.55	1.045	0.040	0.042	

SAR Values [LTE Band 7]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
21100	2535.0	1RB	Front	21.80	22.00	0.06	1.047	0.398	0.417	Plot 9
21100	2535.0	1RB	Rear	21.80	22.00	-2.30	1.047	0.527	0.552	
21100	2535.0	1RB	Right	21.80	22.00	-4.74	1.047	0.376	0.394	
21100	2535.0	1RB	Top	21.80	22.00	-0.21	1.047	0.362	0.379	
21350	2560.0	50%RB	Front	21.24	21.50	2.65	1.062	0.200	0.212	
21350	2560.0	50%RB	Rear	21.24	21.50	-3.65	1.062	0.230	0.244	
21350	2560.0	50%RB	Right	21.24	21.50	4.10	1.062	0.194	0.206	
21350	2560.0	50%RB	Top	21.24	21.50	-4.54	1.062	0.188	0.200	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR Values [LTE Band 12]**

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
23095	707.5	1RB	Front	22.87	23.00	3.20	1.030	0.096	0.099	Plot 10
23095	707.5	1RB	Rear	22.87	23.00	-0.35	1.030	0.165	0.170	
23095	707.5	1RB	Right	22.87	23.00	-3.65	1.030	0.084	0.087	
23095	707.5	1RB	Top	22.87	23.00	0.08	1.030	0.069	0.071	
23060	704.0	50%RB	Front	21.85	22.00	0.05	1.035	0.050	0.052	
23060	704.0	50%RB	Rear	21.85	22.00	0.85	1.035	0.083	0.086	
23060	704.0	50%RB	Right	21.85	22.00	-1.11	1.035	0.044	0.046	
23060	704.0	50%RB	Top	21.85	22.00	3.52	1.035	0.032	0.033	

SAR Values [LTE Band 17]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
23790	710.0	1RB	Front	22.79	23.00	3.65	1.050	0.124	0.130	Plot 11
23790	710.0	1RB	Rear	22.79	23.00	-0.15	1.050	0.209	0.219	
23790	710.0	1RB	Right	22.79	23.00	-3.65	1.050	0.113	0.119	
23790	710.0	1RB	Top	22.79	23.00	-0.01	1.050	0.092	0.097	
23790	710.0	50%RB	Front	21.81	22.00	0.85	1.045	0.062	0.065	
23790	710.0	50%RB	Rear	21.81	22.00	-4.78	1.045	0.105	0.110	
23790	710.0	50%RB	Right	21.81	22.00	3.64	1.045	0.055	0.057	
23790	710.0	50%RB	Top	21.81	22.00	0.95	1.045	0.048	0.050	

SAR Values [LTE Band 38]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
38000	2595.0	1RB	Front	22.22	22.50	-3.65	1.067	0.369	0.394	Plot 12
38000	2595.0	1RB	Rear	22.22	22.50	0.45	1.067	0.448	0.478	
38000	2595.0	1RB	Right	22.22	22.50	-3.65	1.067	0.347	0.370	
38000	2595.0	1RB	Top	22.22	22.50	-0.38	1.067	0.335	0.357	
37850	2580.0	50%RB	Front	21.30	21.50	0.89	1.047	0.188	0.197	
37850	2580.0	50%RB	Rear	21.30	21.50	-1.74	1.047	0.226	0.237	
37850	2580.0	50%RB	Right	21.30	21.50	-2.06	1.047	0.169	0.177	
37850	2580.0	50%RB	Top	21.30	21.50	-3.08	1.047	0.154	0.161	

SAR Values [LTE Band 41]

Ch.	Freq. (MHz)	Channel Type (20M)	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (distance 0mm)										
39750	2506.0	1RB	Front	21.81	22.00	-3.98	1.045	0.552	0.577	Plot 13
39750	2506.0	1RB	Rear	21.81	22.00	-0.33	1.045	0.631	0.659	
39750	2506.0	1RB	Right	21.81	22.00	2.54	1.045	0.536	0.560	
39750	2506.0	1RB	Top	21.81	22.00	4.74	1.045	0.528	0.552	
40620	2593.0	50%RB	Front	21.16	21.50	-3.52	1.081	0.278	0.301	
40620	2593.0	50%RB	Rear	21.16	21.50	0.74	1.081	0.321	0.347	
40620	2593.0	50%RB	Right	21.16	21.50	4.52	1.081	0.264	0.285	
40620	2593.0	50%RB	Top	21.16	21.50	-3.33	1.081	0.241	0.261	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**SAR Values [WIFI2.4G]**

Ch.	Freq. (MHz)	Service	Test Position	Condu cted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reporte d	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
6	2437	802.11b	Front	12.45	12.50	-3.66	1.012	0.048	0.049	
6	2437	802.11b	Rear	12.45	12.50	1.02	1.012	0.069	0.070	
6	2437	802.11b	Right	12.45	12.50	-4.78	1.012	0.034	0.034	
6	2437	802.11b	Bottom	12.45	12.50	-3.05	1.012	0.024	0.024	
6	2437	802.11n HT20	Front	13.80	14.00	-3.65	1.047	0.054	0.057	
6	2437	802.11n HT20	Rear	13.80	14.00	-0.14	1.047	0.087	0.091	Plot 14
6	2437	802.11n HT20	Right	13.80	14.00	0.02	1.047	0.048	0.050	
6	2437	802.11n HT20	Bottom	13.80	14.00	-4.52	1.047	0.041	0.043	

SAR Values [WIFI5.2G]

Ch.	Freq. (MHz)	Service	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
48	5240	802.11AC20	Front	13.27	13.50	-4.44	1.054	0.075	0.079	
48	5240	802.11AC20	Rear	13.27	13.50	-1.54	1.054	0.105	0.111	Plot 15
48	5240	802.11AC20	Right	13.27	13.50	1.58	1.054	0.066	0.070	
48	5240	802.11AC20	Bottom	13.27	13.50	0.96	1.054	0.058	0.061	

SAR Values [WIFI5.3G]

Ch.	Freq. (MHz)	Service	Test Position	Conduc ted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
52	5260	802.11n HT20	Front	13.23	13.50	-3.45	1.064	0.069	0.073	Plot 16
52	5260	802.11n HT20	Rear	13.23	13.50	2.17	1.064	0.099	0.105	
52	5260	802.11n HT20	Right	13.23	13.50	0.06	1.064	0.058	0.062	
52	5260	802.11n HT20	Bottom	13.23	13.50	-1.77	1.064	0.050	0.053	

SAR Values [WIFI5.5G]

Ch.	Freq. (MHz)	Service	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
102	5510	802.11n HT40	Front	12.94	13.00	-1.11	1.014	0.052	0.053	Plot 17
102	5510	802.11n HT40	Rear	12.94	13.00	0.55	1.014	0.076	0.077	
102	5510	802.11n HT40	Right	12.94	13.00	3.52	1.014	0.044	0.045	
102	5510	802.11n HT40	Bottom	12.94	13.00	0.09	1.014	0.032	0.032	

SAR Values [WIFI5.8G]

Ch.	Freq. (MHz)	Service	Test Position	Conducted Power (dBm)	Maximum Allowed Power (dBm)	Power Drift (%)	Scaling Factor	SAR _{1-g} results(W/kg)		Graph Results
								Measured	Reported	
measured / reported SAR numbers - Body (hotspot open, distance 0mm)										
157	5785	802.11a	Front	12.48	12.50	-4.41	1.005	0.201	0.202	Plot 18
157	5785	802.11a	Rear	12.48	12.50	-0.32	1.005	0.263	0.264	
157	5785	802.11a	Right	12.48	12.50	0.39	1.005	0.194	0.195	
157	5785	802.11a	Bottom	12.48	12.50	1.47	1.005	0.182	0.183	

Remark:

1. The value with blue color is the maximum SAR Value of each test band.





2. Per FCC KDB Publication 447498 D01, if the reported (scaled) SAR measured at the middle channel or highest output power channel for each test configuration is ≤ 0.8 W/kg then testing at the other channels is optional for such test configuration(s).

3. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, each band is tested independently for SAR.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



4.3.2 Standalone SAR Test Exclusion Considerations and Estimated SAR

Per KDB447498 requires when the standalone SAR test exclusion of section 4.3.1 is applied to an antenna that transmits simultaneously with other antennas, the standalone SAR must be estimated according to the following to determine simultaneous transmission SAR test exclusion;

• (max. power of channel, including tune-up tolerance, mW)/(min. test separation distance, mm)] • [√f(GHz)/x] W/kg for test separation distances ≤ 50 mm;

where x = 7.5 for 1-g SAR, and x = 18.75 for 10-g SAR.

• 0.4 W/kg for 1-g SAR and 1.0 W/kg for 10-g SAR, when the test separation distances is > 50 mm

Per FCC KD B447498 D01, simultaneous transmission SAR test exclusion may be applied when the sum of the 1-g SAR for all the transmitting antenna in a specific a physical test configuration is ≤1.6 W/Kg. When the sum is greater than the SAR limit, SAR test exclusion is determined by the SAR to peak location separation ratio.

$$\text{Ratio} = \frac{(\text{SAR}_1 + \text{SAR}_2)^{1.5}}{(\text{peak location separation, mm})} < 0.04$$

Estimated stand alone SAR					
Communication system	Frequency (MHz)	Configuration	Maximum Power (dBm)	Separation Distance (mm)	Estimated SAR _{1-g} (W/kg)
Bluetooth*	2450	Body-worn	0.5	5	0.047
Bluetooth*	2450	Hotspot	0.5	5	0.047
NFC	13.56	Hotspot	-42.21	5	0.000002512
NFC	13.56	Body-worn	-42.21	5	0.000002512

Remark:

1. Bluetooth/NFC- Including Lower power Bluetooth/NFC;
2. Maximum average power including tune-up tolerance;
3. When the minimum test separation distance is < 5 mm, a distance of 5 mm is applied to determine SAR test exclusion
4. Body as body use distance is 0mm from manufacturer declaration of user manual

4.4. Simultaneous TX SAR Considerations

4.4.1 Introduction

Simultaneous transmission SAR test exclusion is determined for each operating configuration and exposure condition according to the reported standalone SAR of each applicable simultaneous transmitting antenna. The device has 4 antennas, WWAN main antenna, WWAN diversity antenna(RX only), and WiFi antenna supports 2.4Wi-Fi. The 2 TX antennas can always transmit simultaneously. The work mode combination is showed as below table.;

Application Simultaneous Transmission information:

Combination No.	Mode
1	WWAN+WIFI
2	WWAN+BT
3	WWAN+NFC
4	WIFI+ NFC
5	BT+ NFC

4.4.2 Evaluation of Simultaneous SAR

Body Hotspot Exposure Conditions

Simultaneous transmission SAR for WiFi and GSM

Test Position	GSM850 Reported SAR _{1-g} (W/kg)	GSM1900 Reported SAR _{1-g} (W/kg)	WiFi2.4G Reported SAR _{1-g} (W/kg)	WiFi5.2G Reported SAR _{1-g} (W/kg)	WiFi5.3G Reported SAR _{1-g} (W/kg)	WiFi5.5G Reported SAR _{1-g} (W/kg)	WiFi5.8G Reported SAR _{1-g} (W/kg)	MAX. ΣSAR _{1-g} (W/kg)	SAR _{1-g} Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.136	0.186	0.057	0.079	0.073	0.053	0.202	0.388	1.6	no	no



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Rear	0.218	0.224	0.091	0.111	0.105	0.077	0.264	0.488	1.6	no	no
Left	/	/	/	/	/	/	/	/	1.6	no	no
Right	0.118	0.170	0.050	0.070	0.062	0.045	0.195	0.365	1.6	no	no
Bottom	/	/	0.043	0.061	0.053	0.032	0.183	0.183	1.6	no	no
Top	0.104	0.147	/	/	/	/	/	0.147	1.6	no	no

Simultaneous transmission SAR for WiFi and UMTS

Test Position	UMTS Band V Reported SAR1-g (W/kg)	UMTS Band IV Reported SAR1-g (W/kg)	UMTS Band II Reported SAR1-g (W/kg)	WiFi2.4 G Reported SAR1-g (W/kg)	WiFi5.2 G Reported SAR1-g (W/kg)	WiFi5.3 G Reported SAR1-g (W/kg)	WiFi5.5 G Reported SAR1-g (W/kg)	WiFi5.8 G Reported SAR1-g (W/kg)	MAX. ΣSAR1-g (W/kg)	SAR 1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.211	0.670	0.373	0.057	0.079	0.073	0.053	0.202	0.872	1.6	no	no
Rear	0.250	0.808	0.396	0.091	0.111	0.105	0.077	0.264	1.072	1.6	no	no
Left	/	/	/	/	/	/	/	/	/	1.6	no	no
Right	0.187	0.656	0.363	0.050	0.070	0.062	0.045	0.195	0.851	1.6	no	no
Bottom	/	/	/	0.043	0.061	0.053	0.032	0.183	0.183	1.6	no	no
Top	0.170	0.641	0.343	/	/	/	/	/	0.641	1.6	no	no

Simultaneous transmission SAR for WiFi and LTE

Reported SAR1-g(W/kg)	Test Position					
	Front	Rear	Left	Right	Bottom	Top
LTE Band2	0.240	0.299	/	0.232	/	0.219
LTE Band4	0.251	0.272	/	0.236	/	0.221
LTE Band5	0.113	0.165	/	0.097	/	0.081
LTE Band7	0.417	0.552	/	0.394	/	0.379
LTE Band12	0.099	0.170	/	0.087	/	0.071
LTE Band17	0.130	0.219	/	0.119	/	0.097
LTE Band38	0.394	0.478	/	0.370	/	0.357
LTE Band41	0.577	0.659	/	0.560	/	0.552
WiFi2.4G	0.057	0.091	/	0.050	0.043	/
WiFi5.2G	0.079	0.111	/	0.070	0.061	/
WiFi5.3G	0.073	0.105	/	0.062	0.053	/
WiFi5.5G	0.053	0.077	/	0.045	0.032	/
WiFi5.8G	0.202	0.264	/	0.195	0.183	/
MAX. ΣSAR1-g (W/kg)	0.779	0.923	/	0.755	0.183	0.552
SAR1-g Limit (W/kg)	1.6	1.6	1.6	1.6	1.6	1.6
Peak location separation ratio	no	no	no	no	no	no
Simut Meas. Required	no	no	no	no	no	no

Simultaneous transmission SAR for BT and GSM

Test Position	GSM850 Reported SAR1-g (W/kg)	GSM1900 Reported SAR1-g (W/kg)	BT Estimated SAR1-g (W/kg)	MAX. ΣSAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.136	0.186	0.047	0.233	1.6	no	no
Rear	0.218	0.224	0.047	0.271	1.6	no	no
Left	/	/	/	/	1.6	no	no
Right	0.118	0.170	0.047	0.217	1.6	no	no
Bottom	/	/	0.047	0.047	1.6	no	no
Top	0.104	0.147	/	0.147	1.6	no	no

Simultaneous transmission SAR for BT and UMTS

Test Position	UMTS Band V Reported SAR1-g (W/kg)	UMTS Band IV Reported SAR1-g (W/kg)	UMTS Band II Reported SAR1-g (W/kg)	BT Estimated SAR1-g (W/kg)	MAX. ΣSAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.211	0.670	0.373	0.047	0.717	1.6	no	no
Rear	0.250	0.808	0.396	0.047	0.855	1.6	no	no
Left	/	/	/	/	/	1.6	no	no



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Right	0.187	0.656	0.363	0.047	0.703	1.6	no	no
Bottom	/	/	/	0.047	0.047	1.6	no	no
Top	0.170	0.641	0.343	/	0.641	1.6	no	no

Simultaneous transmission SAR for BT and LTE

Reported SAR1-g(W/kg)	Test Position					
	Front	Rear	Left	Right	Bottom	Top
LTE Band2	0.240	0.299	/	0.232	/	0.219
LTE Band4	0.251	0.272	/	0.236	/	0.221
LTE Band5	0.113	0.165	/	0.097	/	0.081
LTE Band7	0.417	0.552	/	0.394	/	0.379
LTE Band12	0.099	0.170	/	0.087	/	0.071
LTE Band17	0.130	0.219	/	0.119	/	0.097
LTE Band38	0.394	0.478	/	0.370	/	0.357
LTE Band41	0.577	0.659	/	0.560	/	0.552
BT Estimated SAR1-g (W/kg)	0.047	0.047	/	0.047	0.047	/
MAX. ΣSAR1-g (W/kg)	0.624	0.706	/	0.607	0.047	0.552
SAR1-g Limit (W/kg)	1.6	1.6	1.6	1.6	1.6	1.6
Peak location separation ratio	no	no	no	no	no	no
Simut Meas. Required	no	no	no	no	no	no

Simultaneous transmission SAR for NFC and GSM

Test Position	GSM850 Reported SAR1-g (W/kg)	GSM1900 Reported SAR1-g (W/kg)	NFC Estimated SAR1-g (W/kg)	MAX. ΣSAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.136	0.186	0.000002512	0.186002512	1.6	no	no
Rear	0.218	0.224	0.000002512	0.224002512	1.6	no	no
Left	/	/	/	/	1.6	no	no
Right	0.118	0.170	0.000002512	0.170002512	1.6	no	no
Bottom	/	/	0.000002512	0.000002512	1.6	no	no
Top	0.104	0.147	0.000002512	0.147002512	1.6	no	no

Simultaneous transmission SAR for NFC and UMTS

Test Position	UMTS Band V Reported SAR1-g (W/kg)	UMTS Band IV Reported SAR1-g (W/kg)	UMTS Band II Reported SAR1-g (W/kg)	NFC Estimated SAR1-g (W/kg)	MAX. ΣSAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.211	0.670	0.373	0.000002512	0.670002512	1.6	no	no
Rear	0.250	0.808	0.396	0.000002512	0.808002512	1.6	no	no
Left	/	/	/	/	/	1.6	no	no
Right	0.187	0.656	0.363	0.000002512	0.656002512	1.6	no	no
Bottom	/	/	/	0.000002512	0.000002512	1.6	no	no
Top	0.170	0.641	0.343	0.000002512	0.641002512	1.6	no	no

Simultaneous transmission SAR for NFC and LTE

Reported SAR1-g(W/kg)	Test Position					
	Front	Rear	Left	Right	Bottom	Top
LTE Band2	0.240	0.299	/	0.232	/	0.219
LTE Band4	0.251	0.272	/	0.236	/	0.221
LTE Band5	0.113	0.165	/	0.097	/	0.081
LTE Band7	0.417	0.552	/	0.394	/	0.379
LTE Band12	0.099	0.170	/	0.087	/	0.071
LTE Band17	0.130	0.219	/	0.119	/	0.097
LTE Band38	0.394	0.478	/	0.370	/	0.357
LTE Band41	0.577	0.659	/	0.560	/	0.552
NFC Estimated SAR1-g (W/kg)	0.000002512	0.000002512	/	0.000002512	0.000002512	0.000002512
MAX. ΣSAR1-g (W/kg)	0.577002512	0.659002512	/	0.560002512	0.000002512	0.552002512
SAR1-g Limit (W/kg)	1.6	1.6	1.6	1.6	1.6	1.6
Peak location separation ratio	no	no	no	no	no	no
Simut Meas. Required	no	no	no	no	no	no



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity

**Simultaneous transmission SAR for WiFi and NFC**

Test Position	NFC Estimated SAR1-g (W/kg)	WiFi2.4G Reported SAR1-g (W/kg)	WiFi5.2G Reported SAR1-g (W/kg)	WiFi5.3G Reported SAR1-g (W/kg)	WiFi5.5G Reported SAR1-g (W/kg)	WiFi5.8G Reported SAR1-g (W/kg)	MAX. Σ SAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.000002512	0.057	0.079	0.073	0.053	0.202	0.202002512	1.6	no	no
Rear	0.000002512	0.091	0.111	0.105	0.077	0.264	0.264002512	1.6	no	no
Left	/	/	/	/	/	/	/	1.6	no	no
Right	0.000002512	0.050	0.070	0.062	0.045	0.195	0.195002512	1.6	no	no
Bottom	0.000002512	0.043	0.061	0.053	0.032	0.183	0.183002512	1.6	no	no
Top	0.000002512	/	/	/	/	/	0.000002512	1.6	no	no

Simultaneous transmission SAR for BT and NFC

Test Position	NFC Estimated SAR1-g (W/kg)	BT Estimated SAR1-g (W/kg)	MAX. Σ SAR1-g (W/kg)	SAR1-g Limit (W/kg)	Peak location separation ratio	Simut Meas. Required
Front	0.000002512	0.047	0.047002512	1.6	no	no
Rear	0.000002512	0.047	0.047002512	1.6	no	no
Left	/	/	/	1.6	no	no
Right	0.000002512	0.047	0.047002512	1.6	no	no
Bottom	0.000002512	0.047	0.047002512	1.6	no	no
Top	0.000002512	/	0.000002512	1.6	no	no

Note:

1. The WiFi and BT share same antenna, so cannot transmit at same time.
2. The value with block color is the maximum values of standalone
3. The value with blue color is the maximum values of Σ SAR1-g





4.5. SAR Measurement Variability

According to KDB865664, Repeated measurements are required only when the measured SAR is ≥ 0.80 W/kg. If the measured SAR value of the initial repeated measurement is < 1.45 W/kg with $\leq 20\%$ variation, only one repeated measurement is required to reaffirm that the results are not expected to have substantial variations, which may introduce significant compliance concerns. A second repeated measurement is required only if the measured result for the initial repeated measurement is within 10% of the SAR limit and vary by more than 20%, which are often related to device and measurement setup difficulties. The following procedures are applied to determine if repeated measurements are required. The same procedures should be adapted for measurements according to extremity and occupational exposure limits by applying a factor of 2.5 for extremity exposure and a factor of 5 for occupational exposure to the corresponding SAR thresholds.¹⁹ The repeated measurement results must be clearly identified in the SAR report. All measured SAR, including the repeated results, must be considered to determine compliance and for reporting according to KDB 690783. Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg; steps 2) through 4) do not apply.

- 3) When the original highest measured SAR is ≥ 0.80 W/kg, repeat that measurement once.
- 4) Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is > 1.20 or when the original or repeated measurement is ≥ 1.45 W/kg ($\sim 10\%$ from the 1-g SAR limit).
- 5) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .
- 6) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .

Frequency Band (MHz)	Air Interface	RF Exposure Configuration	Test Position	Repeated SAR (yes/no)	Highest Measured SAR _{1-g} (W/Kg)	First Repeated	
						Measured SAR _{1-g} (W/Kg)	Largest to Smallest SAR Ratio
750	LTE Band 12	Standalone	Body-Rear	no	0.165	n/a	n/a
	LTE Band 17	Standalone	Body-Rear	no	0.209	n/a	n/a
850	GSM 850	Standalone	Body-Rear	no	0.195	n/a	n/a
	WCDMA Band V	Standalone	Body- Rear	no	0.224	n/a	n/a
	LTE Band 5	Standalone	Body- Rear	no	0.150	n/a	n/a
1800	WCDMA Band IV	Standalone	Body- Rear	no	0.749	n/a	n/a
	LTE Band 4	Standalone	Body- Rear	no	0.268	n/a	n/a
1900	GSM 1900	Standalone	Body-Rear	no	0.202	n/a	n/a
	WCDMA Band II	Standalone	Body-Rear	no	0.365	n/a	n/a
2450	LTE Band 2	Standalone	Body-Rear	no	0.276	n/a	n/a
	2.4GWLAN	Standalone	Body-Rear	no	0.087	n/a	n/a
2600	LTE Band 7	Standalone	Body-Rear	no	0.527	n/a	n/a
	LTE Band 38	Standalone	Body-Rear	no	0.448	n/a	n/a
	LTE Band 41	Standalone	Body-Rear	no	0.631	n/a	n/a
5200	5.2GWLAN	Standalone	Body-Rear	no	0.105	n/a	n/a
5400	5.3GWLAN	Standalone	Body-Rear	no	0.099	n/a	n/a
5600	5.5GWLAN	Standalone	Body-Rear	no	0.076	n/a	n/a
5800	5.8GWLAN	Standalone	Body-Rear	no	0.263	n/a	n/a

Remark:

1. Second Repeated Measurement is not required since the ratio of the largest to smallest SAR for the original and first repeated measurement is not > 1.20 or 3 (1-g or 10-g respectively)





4.6. General description of test procedures

1. Test positions as described in the tables above are in accordance with the specified test standard.
2. Tests in body position were performed in that configuration, which generates the highest time based averaged output power (see conducted power results).
3. According to IEEE 1528 the SAR test shall be performed at middle channel. Testing of top and bottom channel is optional.
4. According to KDB 447498 D01 testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz
 - ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz
 - ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
5. IEEE 1528-2003 require the middle channel to be tested first. This generally applies to wireless devices that are designed to operate in technologies with tight tolerances for maximum output power variations across channels in the band. When the maximum output power variation across the required test channels is $> \frac{1}{2}$ dB, instead of the middle channel, the highest output power channel must be used.
6. When the same maximum output power is specified for both bands, begin SAR measurement in U-NII-2A band by applying the OFDM SAR requirements. If the highest reported SAR for a test configuration is ≤ 1.2 W/kg, SAR is not required for U-NII-1 band for that configuration (802.11 mode and exposure condition); otherwise, each band is tested independently for SAR.
7. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, each band is tested independently for SAR.

4.7. Measurement Uncertainty (450MHz-6GHz)

Not required as SAR measurement uncertainty analysis is required in SAR reports only when the highest measured SAR in a frequency band is ≥ 1.5 W/kg for 1-g SAR according to KDB865664D01.



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



4.8. System Check Results



Test mode:750MHz(Head)


Product Description:Validation

Model:Dipole SID750

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: June 26, 2023

Medium(liquid type)	HSL_750
Frequency (MHz)	750.0000
Relative permittivity (real part)	42.53
Conductivity (S/m)	0.87
Input power	100mW
Crest Factor	1.0
Conversion Factor	1.69
Variation (%)	-3.650000
SAR 10g (W/Kg)	0.566452
SAR 1g (W/Kg)	0.824413
SURFACE SAR	VOLUME SAR
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:835MHz(Head)




Product Description:Validation

Model:Dipole SID835

E-Field Probe:SSE2(SN 25/22 EPG0376)

Test Date: June 29, 2023

Medium(liquid type)	HSL 835
Frequency (MHz)	835.0000
Relative permittivity (real part)	42.66
Conductivity (S/m)	0.88
Input power	100mW
Crest Factor	1.0
Conversion Factor	1.75
Variation (%)	0.090000
SAR 10g (W/Kg)	0.635132
SAR 1g (W/Kg)	0.947488
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:1800MHz(Head)




Product Description:Validation

Model :Dipole SID1800

E-Field Probe:SSE2(SN 25/22 EPG0376)

Test Date: July 06, 2023

Medium(liquid type)	HSL_1800
Frequency (MHz)	1800.0000
Relative permittivity (real part)	40.89
Conductivity (S/m)	1.37
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.09
Variation (%)	-4.850000
SAR 10g (W/Kg)	2.040283
SAR 1g (W/Kg)	3.826085
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China




Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:1900MHz(Head)
Product Description:Validation
Model :Dipole SID1900
E-Field Probe:SSE2(SN 25/22 EPGO376)
Test Date: July 11, 2023

Medium(liquid type)	HSL_1900
Frequency (MHz)	1900.0000
Relative permittivity (real part)	38.98
Conductivity (S/m)	1.36
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.14
Variation (%)	-1.960000
SAR 10g (W/Kg)	2.083260
SAR 1g (W/Kg)	3.974162
SURFACE SAR	VOLUME SAR





Test mode:2450MHz(Head)




Product Description:Validation

Model:Dipole SID2450

E-Field Probe:SSE2(SN 25/22 EPG0376)

Test Date: July 14, 2023

Medium(liquid type)	HSL_2450
Frequency (MHz)	2450.0000
Relative permittivity (real part)	39.69
Conductivity (S/m)	1.78
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.60
Variation (%)	-0.770000
SAR 10g (W/Kg)	2.544463
SAR 1g (W/Kg)	5.415016
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





Test mode:2600MHz(Head)


Product Description:Validation

Model:Dipole SID2600

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: July 21, 2023

Medium(liquid type)	HSL_2600
Frequency (MHz)	2600.0000
Relative permittivity (real part)	38.56
Conductivity (S/m)	1.98
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.39
Variation (%)	4.630000
SAR 10g (W/Kg)	2.395235
SAR 1g (W/Kg)	5.714023
SURFACE SAR	VOLUME SAR
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:5200MHz(Head)




Product Description:Validation

Model:Dipole SWG5500

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: July 25, 2023

Medium(liquid type)	HSL_5000
Frequency (MHz)	5200.0000
Relative permittivity (real part)	35.24
Conductivity (S/m)	4.69
Input power	100mW
Crest Factor	1.0
Conversion Factor	1.85
Variation (%)	-4.710000
SAR 10g (W/Kg)	5.577210
SAR 1g (W/Kg)	15.632034
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:5400MHz(Head)




Product Description:Validation

Model:Dipole SID5000

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: July 27, 2023

Medium(liquid type)	HSL_5000
Frequency (MHz)	5400.0000
Relative permittivity (real part)	35.71
Conductivity (S/m)	4.87
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.07
Variation (%)	0.690000
SAR 10g (W/Kg)	5.712120
SAR 1g (W/Kg)	16.890222
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:5600MHz(Head)




Product Description:Validation

Model:Dipole SID5000

E-Field Probe: SSE2(SN 25/22 EPGO376)

Test Date: August 01, 2023

Medium(liquid type)	HSL_5000
Frequency (MHz)	5600.0000
Relative permittivity (real part)	34.74
Conductivity (S/m)	5.09
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.19
Variation (%)	4.170000
SAR 10g (W/Kg)	5.933036
SAR 1g (W/Kg)	17.437212
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.



Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China


Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



Test mode:5800MHz(Head)
Product Description:Validation
Model:Dipole SID5000
E-Field Probe: SSE2(SN 25/22 EPGO376)
Test Date: August 03, 2023

Medium(liquid type)	HSL_5000
Frequency (MHz)	5800.0000
Relative permittivity (real part)	36.33
Conductivity (S/m)	5.24
Input power	100mW
Crest Factor	1.0
Conversion Factor	2.01
Variation (%)	3.350000
SAR 10g (W/Kg)	6.168085
SAR 1g (W/Kg)	18.362250
SURFACE SAR	VOLUME SAR
	





4.9. SAR Test Graph Results

SAR plots for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination





#1 Test Mode: GSM850MHz, Low channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: June 29, 2023

Medium(liquid type)	HSL 835
Frequency (MHz)	824.2000
Relative permittivity (real part)	43.49
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPG0376
Crest Factor	2.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.950000
SAR 10g (W/Kg)	0.132623
SAR 1g (W/Kg)	0.194818
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







#2

Test Mode: GPRS1900MHz,High channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: July 11, 2023

Medium(liquid type)	HSL 1900
Frequency (MHz)	1909.8000
Relative permittivity (real part)	36.52
Conductivity (S/m)	1.39
E-Field Probe	SN 25/22 EPGO376
Crest Factor	2.0
Conversion Factor	2.14
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	1.790000
SAR 10g (W/Kg)	0.150701
SAR 1g (W/Kg)	0.201536
SURFACE SAR	VOLUME SAR
	
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity







#3

Test Mode: WCDMA Band V, Low channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: June 29, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	826.4000
Relative permittivity (real part)	43.49
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.640000
SAR 10g (W/Kg)	0.158324
SAR 1g (W/Kg)	0.224046
SURFACE SAR	VOLUME SAR
	
	



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#4





Test Mode: WCDMA Band IV, Middle channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: July 06, 2023

Medium(liquid type)	HSL_1800
Frequency (MHz)	1752.6000
Relative permittivity (real part)	41.48
Conductivity (S/m)	1.35
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.09
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-2.380000
SAR 10g (W/Kg)	0.524363
SAR 1g (W/Kg)	0.749479
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#5





Test Mode: WCDMA Band II, High channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: July 11, 2023

Medium(liquid type)	HSL 1900
Frequency (MHz)	1907.6000
Relative permittivity (real part)	36.52
Conductivity (S/m)	1.39
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	2.14
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	0.270000
SAR 10g (W/Kg)	0.260745
SAR 1g (W/Kg)	0.364633
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#6





Test Mode: LTE Band 2, 1RB, High channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 11, 2023

Medium (liquid type)	HSL 1900
Frequency (MHz)	1900.0000
Relative permittivity (real part)	36.52
Conductivity (S/m)	1.39
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.14
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7, dx=8mm dy=8mm dz=5mm
Variation (%)	-0.050000
SAR 10g (W/Kg)	0.197827
SAR 1g (W/Kg)	0.276164
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#7





Test Mode: LTE Band 4, 1RB, Low channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 06, 2023

Medium (liquid type)	HSL_1800
Frequency (MHz)	1720.0000
Relative permittivity (real part)	41.48
Conductivity (S/m)	1.35
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.09
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7, dx=8mm dy=8mm dz=5mm
Variation (%)	0.310000
SAR 10g (W/Kg)	0.181508
SAR 1g (W/Kg)	0.267779
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#8





Test Mode: LTE Band 5, 1RB,Middle channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: June 29, 2023

Medium(liquid type)	HSL_835
Frequency (MHz)	836.5000
Relative permittivity (real part)	43.49
Conductivity (S/m)	0.85
E-Field Probe	SN 25/22 EPGO376
Crest Factor	2.0
Conversion Factor	1.75
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	0.410000
SAR 10g (W/Kg)	0.105442
SAR 1g (W/Kg)	0.149881
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#9





Test Mode: LTE Band 7, 1RB,Middle channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: July 21, 2023

Medium(liquid type)	HSL 2600
Frequency (MHz)	2535.0000
Relative permittivity (real part)	37.26
Conductivity (S/m)	2.01
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.39
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-2.300000
SAR 10g (W/Kg)	0.333405
SAR 1g (W/Kg)	0.526952
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#10





Test Mode: LTE Band 12, 1RB, Middle channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: June 26, 2023

Medium(liquid type)	HSL 750
Frequency (MHz)	707.5000
Relative permittivity (real part)	42.95
Conductivity (S/m)	0.86
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	1.69
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.350000
SAR 10g (W/Kg)	0.105789
SAR 1g (W/Kg)	0.165355
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#11





Test Mode: LTE Band 17, 1RB, Middle channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: June 26, 2023

Medium(liquid type)	HSL 750
Frequency (MHz)	710.0000
Relative permittivity (real part)	42.95
Conductivity (S/m)	0.86
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	1.69
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.150000
SAR 10g (W/Kg)	0.132938
SAR 1g (W/Kg)	0.209274
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#12





Test Mode: LTE Band 38, 1RB,Middle channel(Body Rear Side)

Product Description:Handheld Controller

Model:iHand55

Test Date: July 21, 2023

Medium(liquid type)	HSL 2600
Frequency (MHz)	2595.0000
Relative permittivity (real part)	37.26
Conductivity (S/m)	2.01
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.39
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	0.450000
SAR 10g (W/Kg)	0.269991
SAR 1g (W/Kg)	0.448087
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#13





Test Mode: LTE Band 41, 1RB, Low channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 21, 2023

Medium (liquid type)	HSL 2600
Frequency (MHz)	2506.0000
Relative permittivity (real part)	37.26
Conductivity (S/m)	2.01
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	2.39
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7, dx=8mm dy=8mm dz=5mm
Variation (%)	-0.330000
SAR 10g (W/Kg)	0.379935
SAR 1g (W/Kg)	0.631321
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#14





Test Mode: 802.11n HT20 (WiFi2.4G), Middle channel(Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 14, 2023

Medium(liquid type)	HSL 2450
Frequency (MHz)	2437.0000
Relative permittivity (real part)	38.22
Conductivity (S/m)	1.80
E-Field Probe	SN 25/22 EPG0376
Crest Factor	1.0
Conversion Factor	2.60
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.140000
SAR 10g (W/Kg)	0.052779
SAR 1g (W/Kg)	0.086609
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#15





Test Mode: 802.11AC20 (WiFi5.2G), High channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 25, 2023

Medium(liquid type)	HSL 5200
Frequency (MHz)	5240.0000
Relative permittivity (real part)	36.14
Conductivity (S/m)	4.66
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	1.85
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-1.540000
SAR 10g (W/Kg)	0.053148
SAR 1g (W/Kg)	0.105410
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#16





Test Mode: 802.11n HT20 (WiFi5.3G), Low channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: July 27, 2023

Medium(liquid type)	HSL_5000
Frequency (MHz)	5260.0000
Relative permittivity (real part)	35.97
Conductivity (S/m)	4.86
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.07
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7, dx=8mm dy=8mm dz=5mm
Variation (%)	2.170000
SAR 10g (W/Kg)	0.061822
SAR 1g (W/Kg)	0.099363
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#17





Test Mode: 802.11n HT40 (WiFi5.5G), Low channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: August 01, 2023

Medium(liquid type)	HSL 5000
Frequency (MHz)	5510.0000
Relative permittivity (real part)	35.60
Conductivity (S/m)	5.06
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.19
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	0.550000
SAR 10g (W/Kg)	0.040492
SAR 1g (W/Kg)	0.076109
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



#18





Test Mode: 802.11a(WiFi5.8G), Middle channel (Body Rear Side)

Product Description: Handheld Controller

Model: iHand55

Test Date: August 03, 2023

Medium(liquid type)	HSL 5800
Frequency (MHz)	5785.0000
Relative permittivity (real part)	35.54
Conductivity (S/m)	5.27
E-Field Probe	SN 25/22 EPGO376
Crest Factor	1.0
Conversion Factor	2.01
Sensor	4mm
Area Scan	dx=8mm dy=8mm
Zoom Scan	5x5x7,dx=8mm dy=8mm dz=5mm
Variation (%)	-0.320000
SAR 10g (W/Kg)	0.130753
SAR 1g (W/Kg)	0.263227
SURFACE SAR	VOLUME SAR



Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity



5. CALIBRATION CERTIFICATES

5.1 Probe-EPGO376 Calibration Certificate



COMOSAR E-Field Probe Calibration Report

Ref : ACR.180.4.42.BES.A

SHENZHEN LCS COMPLIANCE TESTING LABORATORY LTD.

**1F., XINGYUAN INDUSTRIAL PARK, TONGDA ROAD, BAO'AN
BLVD**

BAO'AN DISTRICT, SHENZHEN, GUANGDONG, CHINA

MVG COMOSAR DOSIMETRIC E-FIELD PROBE

SERIAL NO.: SN 25/22 EPGO376

Calibrated at MVG

Z.I. de la pointe du diable

Technopôle Brest Iroise – 295 avenue Alexis de Rochon

29280 PLOUZANE - FRANCE

Calibration date: 06/22/2023



Accreditations #2-6792
Scope available on www.cofrac.fr

The use of the Cofrac brand and the accreditation references is prohibited from any reproduction.

Summary:

This document presents the method and results from an accredited COMOSAR Dosimetric E-Field Probe calibration performed at MVG, using the CALIPROBE test bench, for use with a MVG COMOSAR system only. The test results covered by accreditation are traceable to the International System of Units (SI).





COMOSAR E-FIELD PROBE CALIBRATION REPORT

Ref: ACR.180.4.42.BES.A

	Name	Function	Date	Signature
Prepared by :	Jérôme Le Gall	Measurement Responsible	6/23/2023	
Checked & approved by:	Jérôme Luc	Technical Manager	6/23/2023	
Authorized by:	Yann Toutain	Laboratory Director	6/23/2023	

2023.06.23

13:37:50 +02'03'

	Customer Name
Distribution :	Shenzhen LCS Compliance Testing Laboratory Ltd.

Issue	Name	Date	Modifications
A	Jérôme Le Gall	6/23/2023	Initial release

Page: 2/11

Template_ACR.DDD.N.YY.MVGB.ISSUE_COMOSAR Probe vK

This document shall not be reproduced, except in full or in part, without the written approval of MVG. The information contained herein is to be used only for the purpose for which it is submitted and is not to be released in whole or part without written approval of MVG.

