

**\*\* MPE Calculations \*\***

The MPE calculation for this exposure is shown below.

The peak radiated output power (EIRP) is calculated as follows:

|  |  |
|--|--|
| $EIRP = P + G$                             | Where,                                       |
| $EIRP = 18.71\text{dBm} + 1.47\text{ dBi}$ | $P = \text{Power input to the antenna (mW)}$ |
| $EIRP = 20.18\text{ dBm}$                  | $G = \text{Power gain of the antenna (dBi)}$ |

**Power density at the specific separation:**

|   |   |
|---|---|
| $S = PG/(4R^2 \pi)$                     | Where,  |
| $S = (74.30 * 1.34) / (4 * 20^2 * \pi)$ | $S = \text{Maximum power density (mW/cm}^2\text{)}$<br>$P = \text{Power input to the antenna (mW)}$<br>$G = \text{Numeric power gain of the antenna}$ |
| $S = 0.0198\text{ mW/cm}^2$             | $R = \text{Distance to the center of the radiation of the antenna}$<br>(20 cm = limit for MPE)  |

The Maximum permissible exposure (MPE) for the general population is 1 mW/cm<sup>2</sup>.

The power density does not exceed the 1 mW/cm<sup>2</sup> limit.

Therefore, the exposure condition is compliant with FCC rules.

**Estimated safe separation:**

|                                    |  |
|------------------------------------|--|
| $R = \sqrt{(PG / 4\pi)}$           | Where,   |
| $R = \sqrt{(74.30 * 1.34 / 4\pi)}$ | $P = \text{Power input to the antenna (mW)}$<br>$G = \text{Numeric power gain of the antenna}$ |
| $R = 2.81\text{ cm}$               | $R = \text{Distance to the center of the radiation of the antenna}$<br>(20 cm = limit for MPE) |

The numeric gain(G) of the antenna with a gain specified in dB is determined by:

$$G = \text{Log}^{-1} (\text{dB antenna gain} / 10)$$

$$G = \text{Log}^{-1} (1.47 / 10)$$

$$G = 1.34$$