

Rhein Tech Laboratories, Inc.  
360 Herndon Parkway  
Suite 1400  
Herndon, VA 20170  
<http://www.rheintech.com>

Client: Harris Corp.  
Model: M7300/M5300 Mobile Radio  
FCC ID: OWDTR-0060-E  
Standard: FCC Part 90  
Report #: 2010092

## **Appendix D: AFC Attestation**

Please refer to the following page.



HARRIS CORPORATION

221 Jefferson Ridge Parkway  
Lynchburg, VA 24501  
[www.harris.com](http://www.harris.com)

## ATTESTATION

### Locked/unlocked AFC Operation

The M7300 Mobile Radio uses a single TCXO as its frequency reference. All local oscillators are phase locked to this single reference. The reference is specified to be better than +/- 1.5ppm over the operating temperature and voltage ranges. This reference oscillator has an electronic frequency control (EFC) range of 108 Hz (minimum) at the TCXO output. The EFC can be fine-tuned through software. The initial tuning is performed at factory test, calibration and configuration time. This function is performed by providing a GPS locked RF carrier to the radio under test, while the radio's AFC function is enabled. The radio software computes the difference between the internal reference and the applied GPS locked RF carrier and adjusts the EFC voltage to minimize the difference. The radio is then commanded to transmit an unmodulated carrier and the frequency of that carrier is checked to confirm that it is within tolerance. The EFC correction factor is stored in the radio's non-volatile memory.

Software control is used to implement AFC, when operating in the 700 MHz band (Part 90, Subpart R rules). In AFC locked mode, the digital signal processor examines the received base station signal and determines if there is any residual frequency error. The software then adjusts to minimize the residual frequency error. Hardware correction provides a resolution of below 0.1 ppm when adjusting the TCXO and so it is straightforward to control the TCXO to within the +/- 0.5 ppm requirement. The received base station signal correction is a continuously executed radio function.

When the radio operates on channels that are configuration defined as other than base station channels (i.e., on-scene incident response or itinerant channels) the radio's AFC uses the last determined base station correction value for frequency control.