

Mad Catz (Asia) Ltd.

Application
For
Certification
(FCC ID: P23HHMC-6004F2501)

Transmitter, Model : 6004

We hereby certify that the sample of the above item is considered to comply with the requirements
of FCC Part 15, Subpart B for TV interface devices,
mention 47 CFR [10-1-2000 edition]

WO# 0104210
WN/at
November 19, 2001

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited

FCC ID : P23HHMC-6004F2501

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

Mad Catz (Asia) Ltd. - MODEL: 6004
FCC ID: P23HHMC-6004F2501

November 19, 2001

This report concerns (check one): Original Grant Class II Change _____

Equipment Type: TV interface devices (example: computer, printer, modem, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes No

If yes, defer until: _____ date

Company Name agrees to notify the Commission by: _____ date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes No

If no, assumed Part 15, Subpart B for TV interface devices.

Report prepared by: Wilbur Ng
Intertek Testing Services
2/F., Garment Center,
576, Castle Peak Road,
HONG KONG
Phone: 852-2173-8502
Fax: 852-2742-9149

INTERTEK TESTING SERVICES

Table of Contents

1.0 General Description	2
1.1 Product Description.....	2
1.2 Related Submittal(s) Grants.....	2
1.3 Test Methodology	3
1.4 Test Facility.....	3
2.0 System Test Configuration	5
2.1 Justification.....	5
2.2 EUT Exercising Software	6
2.3 Special Accessories.....	6
2.4 Equipment Modification	6
2.5 Support Equipment List and Description.....	6
3.0 Emission Results	8
3.1 Field Strength Calculation.....	9
3.1 Field Strength Calculation (cont'd).....	10
3.2 Radiated Emission Configuration Photograph	11
3.3 Radiated Emission Data	12
3.4 RF Output Voltage Measurement Data	14
3.5 Voltage Measurement at the receiving antenna input terminal per 15.115 c (1)(ii).....	17
4.0 Equipment Photographs	19
5.0 Product Labelling	21
6.0 Technical Specifications	23
7.0 Instruction Manual	25
8.0 Miscellaneous Information	27
8.1 Measured Bandwidth.....	28
8.2 Emissions Test Procedures	29
8.2 Emissions Test Procedures (cont'd)	30

INTERTEK TESTING SERVICES

List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.doc
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission	radiated1.jpg to radiated2.jpg
Test Report	Bandwidth Plot	bw.pdf
External Photo	External Photo	ophoto1.jpg to ophoto2.jpg
Internal Photo	Internal Photo	iphoto1.jpg to iphoto3.jpg
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1

GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 General Description

1.1 Product Description

The equipment under test (EUT) is RF Adaptor for TV Interface Device operating at 60.417 MHz or 66.545 MHz which is controlled by a L.C. Oscillator. The EUT is powered by Game Station. There are a channel switch, one RF output port, 3 signal input port of N64, Play Station and Dream Cast. Connect one of the signal input port to the game station, connect the RF output port to the TV RF input port, and select the channel on the TV to obtain the game picture and sound from the game station.

The brief circuit description is saved with filename: descri.pdf

1.2 Related Submittal(s) Grants

This is a single application for certification of TV interface device.

INTERTEK TESTING SERVICES

1.3 Test Methodology

The radiated emission measurements were performed according to the procedures in ANSI C63.4 (1992). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site and conducted measurement facility used to collect the emission data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

INTERTEK TESTING SERVICES

EXHIBIT 2

SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 System Test Configuration

2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (1992.)

The EUT was powered by the game station.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The unit was operated with the Video Game and TV receiver, and placed in the turntable.

The Video Game compliance with ANSI C63.4-1992.

The EUT operate at 60.417 MHz and 66.545 MHz.

The test configuration compliance with ANSI C63.4-1992 section 12.2.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on a turn table, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

For simplicity of testing, the unit was wired to transmit continuously.

INTERTEK TESTING SERVICES

2.2 EUT Exercising Software

There was no special software to exercise the device.

2.3 Special Accessories

The TV receiver input cables was supplied by the applicant.

2.4 Equipment Modification

Any modifications installed previous to testing by Mad Catz (Asia) Ltd. will be incorporated in each production model sold/leased in the United States.

Modifications were installed by Intertek Testing Services.

2.5 Support Equipment List and Description

This product was tested in a standalone configuration.

All the items listed under section 2.0 of this report are

Confirmed by:

Wilbur Ng
Manager
Intertek Testing Services
Agent for Mad Catz (Asia) Ltd.



Signature

November 19, 2001 _____ Date

INTERTEK TESTING SERVICES

EXHIBIT 3
EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 Emission Results

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in dB μ V/m

RA = Receiver Amplitude (including preamplifier) in dB μ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation (cont'd)

Example

Assume a receiver reading of 62.0 dB μ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB μ V/m. This value in dB μ V/m was converted to its corresponding level in μ V/m.

RA = 62.0 dB μ V

AF = 7.4 dB

CF = 1.6 dB

AG = 29.0 dB

PD = 0 dB

AV = -10 dB

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32 \text{ dB}\mu\text{V/m}$$

$$\text{Level in mV/m} = \text{Common Antilogarithm} [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission

60.417 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated1.jpg to radiated2.jpg

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 11.7 dB

TEST PERSONNEL:



Signature

Ivan Y. M. Wong, Compliance Engineer
Typed/Printed Name

November 19, 2001

Date

INTERTEK TESTING SERVICES

Company: Mad Catz (Asia) Ltd.
Model: 6004

Date of Test: May 9, 2001

**Table 1 (Channel 3)
Radiated Emissions**

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
V	66.545	34.0	9	16	27.0	40.0	-13.0
V	*133.090	27.3	13	16	24.3	43.5	-19.2
H	199.636	21.6	16	16	21.6	43.5	-21.9
H	*266.180	17.0	21	16	22.0	46.0	-24.0
H	*332.725	13.4	24	16	21.4	46.0	-24.6

**Table 2 (Channel 4)
Radiated Emissions**

Polarity	Frequency (MHz)	Reading (dB μ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB μ V/m)	Limit at 3m (dB μ V/m)	Margin (dB)
V	60.417	34.3	10	16	28.3	40.0	-11.7
H	*120.835	28.5	13	16	25.5	43.5	-18.0
H	181.253	19.2	20	16	23.2	43.5	-20.3
H	*241.681	18.1	19	16	21.1	46.0	-24.9
H	302.099	15.3	22	16	21.3	46.0	-24.7

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3 meter distance were measured at 0.3 meter and an inverse proportional extrapolation was performed to compare the signal level to the 3 meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3 meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna and average detector are used for the emission over 1000MHz.

*Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and average detector data for frequencies over 1000 MHz.

Test Engineer: Ivan Y. M. Wong

INTERTEK TESTING SERVICES

3.4 RF Output RMS Voltage Measurement

The data on the following page list the RF output frequencies, the limit and the measurement reading.

INTERTEK TESTING SERVICES

Company: Mad Catz (Asia) Ltd.
Model: 6004

Date of Test: May 9, 2001

Table 3 (Channel 3)

Video Output RMS Voltage Measurement

Frequency (MHz)	Limit (μ V)	Reading (μ V)
66.5	3000	125.9
133.0	95	88.1
199.6	95	42.2
266.1	95	21.6

Table 4 (Channel 3)

Audio Output RMS Voltage Measurement

Frequency (MHz)	Limit (μ V)	Reading (μ V)
71.0	671	62.9
137.51	95	43.0
204.1	95	26.6
270.6	95	25.9

Notes: The output impedance of EUT is 75 Ohm.

Test Engineer: Ivan Y. M. Wong

INTERTEK TESTING SERVICES

Company: Mad Catz (Asia) Ltd.
Model: 6004

Date of Test: May 9, 2001

Table 5 (Channel 4)

Video Output RMS Voltage Measurement

Frequency (MHz)	Limit (μ V)	Reading (μ V)
60.4	3000	218.9
120.8	95	77.6
181.2	95	63.1
241.6	95	47.3

Table 6 (Channel 4)

Audio Output RMS Voltage Measurement

Frequency (MHz)	Limit (μ V)	Reading (μ V)
64.9	671	82.1
125.3	95	53.9
185.8	95	30.7
246.1	95	30.5

Notes: The output impedance of EUT is 75 Ohm.

Test Engineer: Ivan Y. M. Wong

INTERTEK TESTING SERVICES

3.5 Voltage Measurement at the receiving antenna input terminal per 15.115 c (1)(ii).

The measurement reading of maximum voltage appearing at the receiving antenna input terminals do not exceed 3uV.

INTERTEK TESTING SERVICES

EXHIBIT 4
EQUIPMENT PHOTOGRAPHS

INTERTEK TESTING SERVICES

4.0 Equipment Photographs

For electronic filing, the photographs are saved with filename: ophoto1.jpg to ophoto2.jpg and iphoto1.jpg to iphoto3.jpg

INTERTEK TESTING SERVICES

EXHIBIT 5

PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 Product Labelling

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf

INTERTEK TESTING SERVICES

EXHIBIT 6

TECHNICAL SPECIFICATIONS

INTERTEK TESTING SERVICES

6.0 Technical Specifications

For electronic filing, the block diagram and schematics are saved with filename: block.pdf and circuit.pdf respectively.

INTERTEK TESTING SERVICES

EXHIBIT 7

INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

This manual will be provided to the end-user with each unit sold/leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 8

MISCELLANEOUS INFORMATION

INTERTEK TESTING SERVICES

8.0 Miscellaneous Information

This miscellaneous information includes details of the measured bandwidth and the test procedure.

INTERTEK TESTING SERVICES

8.1 Measured Bandwidth

The plot on saved in bw.pdf shows the fundamental emission is confined in the specified band.

Figure 8.1 Bandwidth

INTERTEK TESTING SERVICES

8.2 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart B rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 1992.

The test procedures compliance the special test procedure for TV Interface Devices in ANSI C63.4-1992 section 12.2.

The transmitting equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The antenna height and polarization are varied during the testing to search for maximum signal levels.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 450 kHz to 30 MHz.

INTERTEK TESTING SERVICES

8.2 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements are made as described in ANSI C63.4 - 1992.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the forbidden bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, but those measurements taken at a closer distance are so marked.