

**Triple source to BT5.3 LE Audio Transmitter**

**BA-550T**

**USER'S GUIDE**

## Features

1. Triple audio source to BT5.3 LE Audio Transmitter.
2. Supports Auracast: Enables multiple individuals to listen to audio simultaneously.
3. Supports LE Audio / LC3.
4. Supports aptX Classic / LL / HD / Adaptive.

## Button Functions

Function	Action Button	LED Indicator
Bluetooth pairing	Double-Press Quickly	● Blue LED rapidly flashing
Trun On/Off Auracast	Triple-Press Quickly	● Orange LED On/Off
Trun On/Off Device	Press/ Press and Hold for 3 seconds	On - ● activated Off - All Led turn Off
Increase + / Decrease - Volumn	Press and Hold for few seconds	N/A
Reset to default	Press and Hold for 6 seconds	● Blue LED constantly on for 1second

## LED Indicators

Color	Description
● Green - LEA	LED rapidly flashing- Connected in LE, LC3 mode
○ White - aptX	LED rapidly flashing - Connected in aptX Mode
● Blue - BT	Rapid Flashing (50ms) - Attempting to reconnect to a device in the pairing list Rapid Flashing (100ms) - Bluetooth pairing Slow Flashing (2 secs) - Waiting to reconnect to a device in the pairing list Constantly On for 1 sec - Factory Reset Completed Off - Pairing failed, enter idle mode
● Orange - Auracast	LED rapidly flashing - Auracast mode activated
● Green	Charging status: Green - Solid on while battery Full charge.
● Orange	Orange - rapidly flashing while battery in charging.
● Red	Red - rapidly flashing while low battery.

## Triple audio source

Switch position	Source
Left	USB IN
Middle	3.5mm TRS
Right	1/4" TRS

### Notices

1. Before pairing, you should check the transport mode(LE or BR/EDR) of the device to be paired, and triple click button to switch the BA-550T to the corresponding mode.
  - If the device is BR/EDR, Turn Off Auracast mode on the BA-550T during pairing, Orange LED will turn off. (default)
  - If the device is LE mode, Turn On Auracast mode on the BA-550T during pairing, Orange LED will light up.The correct procedure is to switch BA-550T modes during pairing, then power on the device to be paired and enter pairing mode.
2. Please make sure there is only one pairing device around BA-550T. if there are two or more devices nearby, pairing may not be successful.

- This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
  - (1) this device may not cause harmful interference, and
  - (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

\* Any changes or modifications not expressly approved by the party responsible for compliance could void the authority to operate equipment.

#### FCC RF Radiation Exposure Statement:

For portable operation, this device has been tested and meets FCC RF exposure guidelines. When used with an accessory that contains metal may not ensure compliance with FCC RF exposure guidelines.

