

# RF Exposure Evaluation

## FCC ID: PMJRX2

### 1. Client Information

**Applicant** : Amphony Corp.  
**Address** : 1006 S. Raven Rd., Shorewood, IL 60432, USA  
**Manufacturer** : Suzhou Feiye Electronics  
**Address** : No. 18 Xinzong Rd., Wuzhong District, Suzhou, China

### 2. General Description of EUT

<b>EUT Name</b>	:	Audio Receiver	
<b>Models No.</b>	:	RX2	
<b>Model Difference</b>	:	N/A	
<b>Product Description</b>	Operation Frequency: Bluetooth:2402~2480MHz		
	Number of Channel: Bluetooth:79 Channels		
	Max Peak Output Power: GFSK: 4.363dBm (Conducted Power)		
	Antenna Gain: 0 dBi PCB Antenna		
	Modulation Type: GFSK 1Mbps(1 Mbps) π /4-DQPSK(2 Mbps) 8-DPSK(3 Mbps)		
<b>Power Supply</b>	:	DC Voltage supplied from AC/DC adapter	
<b>Power Rating</b>	:	Input: 100~240V, 50/60Hz, 0.3A Output: 7.5V, 1000mA	
<b>Connecting I/O Port(S)</b>	:	Please refer to the User's Manual	

#### Note:

More test information about the EUT please refer the RF Test Report.

## SAR Test Exclusion Calculations

1. FCC: According to KDB 447498 D01 Mobile and Portable Devices RF Exposure Procedures and Equipment Authorization Policies v05r02.

- (1) Clause 4.3: General SAR test reduction and exclusion guidance

Sub clause 4.31: Standalone SAR test exclusion considerations

1) The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6GHz at test separation distance  $\leq 5$  mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation, mm})]^{1/2} \leq 3.0$  for 1-g SAR

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation, mm})]^{1/2} \leq 7.5.0$  for 10-g SAR

## 2.

## Calculation:

Test separation: 5mm						
Bluetooth Mode (GFSK)						
Frequency (GHz)	Conducted Power (dBm)	Ant Gain (dBi)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	2.909	0	$\pm 1$	2.460	0.762	3.0
2.441	3.747	0	$\pm 1$	2.983	0.932	3.0
2.480	4.363	0	$\pm 1$	3.438	1.083	3.0
Bluetooth Mode (8-DPSK)						
Frequency (GHz)	Conducted Power (dBm)	Ant Gain (dBi)	Turn-up Power Tolerance (dB)	Max power of tune up tolerance (mw)	Calculation Value	Threshold Value
2.402	2.738	0	$\pm 1$	2.365	0.733	3.0
2.441	3.477	0	$\pm 1$	2.803	0.876	3.0
2.480	4.035	0	$\pm 1$	3.188	1.004	3.0

So standalone SAR measurements are not required.