



SU01 Antenna Report

Introduction


This report Passive/Active Measurement results .(return loss, Isolation , Gain, Radiation Pattern)

- The return loss and Isolation are measured by Agilent E063A.
- The radiation pattern, antenna gain and efficiency are measured by IAC's SATIMO SG24 chamber.





Introduction



| Antenna Information | |
|------------------------------------|---|
| Wireless Function | ■2.4G antenna 2x2 |
| Antenna type and solution | ■On-board antenna - Signal band 2.4G antenna*2 |
| Specification and measurement data | |
| Return loss | <-6.417 dB |
| Isolation | ■2.4G antenna <-11.669dB |
| Peak Gain | ■2.4G:>-3.31dBi |
| Antenna efficiency | ■2.4G Antenna >18% |




HMB Ant Layout Placement

P Antenna



F Antenna

S-parameter (Return Loss & Isolation)




- P Antenna Return Loss
- F Antenna Return Loss
- P Ant to F Ant Isolation

Test Environment & Equipment




| | XZ Phi 0 | YZ phi90 | XY theta90 |
|-----|----------|----------|------------|
| 0 | Top | Top | Front |
| 90 | Right | Front | Left |
| 180 | Bottom | Bottom | Back |
| 270 | Left | Back | Right |


HMB P ant Radiation pattern-2402GHz




HMB P ant Radiation pattern-2440GHz




HMB P ant Radiation pattern-2480GHz




HMB F ant Radiation pattern-2402GHz



HMB F ant Radiation pattern-2440GHz



HMB F ant Radiation pattern-2480GHz



HMB F Antenna Gain Table

| Frequency (MHz) | XZ plane | | YZ plane | | XY plane | | E-total (dBi) | Efficiency (%) |
|--------------------|-----------------------|--------------------------|--------------------|--------------------------|--------------------|--------------------------|------------------|-------------------|
| | Peak Gain (dBi) | Average Gain (dBi) | Peak Gain (dBi) | Average Gain (dBi) | Peak Gain (dBi) | Average Gain (dBi) | | |
| 2402 | -3.02 | -7.55 | -4.34 | -7.4 | -6.51 | -8.52 | -2.88 | 21% |
| 2440 | -2.74 | -6.9 | -3.9 | -6.41 | -5.04 | -7.51 | -2.69 | 21% |
| 2480 | -2.61 | -6.79 | -3.16 | -6.64 | -5.4 | -7.57 | -2.56 | 20% |

HMB P Antenna Gain Table

| Frequency (MHz) | XZ plane | | YZ plane | | XY plane | | E-total (dBi) | Efficiency (%) |
|--------------------|-----------------------|--------------------------|--------------------|--------------------------|--------------------|--------------------------|------------------|-------------------|
| | Peak Gain (dBi) | Average Gain (dBi) | Peak Gain (dBi) | Average Gain (dBi) | Peak Gain (dBi) | Average Gain (dBi) | | |
| 2402 | -1.16 | -5.52 | -2.01 | -5.14 | -4.52 | -6.55 | -1.15 | 27% |
| 2440 | -2.06 | -7.07 | -3.03 | -6.25 | -5.41 | -7.52 | -2.05 | 21% |
| 2480 | -3.31 | -8.45 | -4.19 | -7.88 | -7.21 | -8.88 | -3.31 | 18% |

Thank You