

HB009-Ultra-thin Bluetooth backlight keyboard with solar charging

Packing contents:

- Cordless keyboard
- USB power charging cable
- User manual

1. Bluetooth Keyboard Specification

- Built-in BROADCOM Bluetooth module 3.0
- Fashion ultra-thin aluminum cover design for IOS,&Android&Windows tablets pc
- The combination design of the leather and plastic
- MICRO interface, easy to charge
- Built-in rechargeable lithium battery
- Light weight, quiet keystrokes, water-proof, dust-proof
- Energy saving keyboard sleep mode
- It can be easily shifted among three system:android&IOS&Windows, by combinations of "Fn+Apple" "Fn+Android" "Fn+windows"

The combination of "Fn + ↑" and "Fn + ↓" can shift among 7 different colors backlights

2. Bluetooth Keyboard Specification

- Bluetooth 3.0 interface standard
- Operating Distance to 10 meters
- Modulating System: GFSK
- Operation Voltage: 1.8-3.6V
- Working Current: <2.0mA
- Standby Current: <0.3-0.5mA
- Sleeping Current: <25UA
- Charging Current≥ 100mA

1

- Charging Time:5-6hours
- Lithium Battery Capacity:800mA
- With backlights on the uninterrupted Working Time:3hours
- With backlights off the uninterrupted Working Time:180days
- Direct solar radiation solar panel current:3.5mA, the charging time;15 hours
- Lithium Battery Life:3year
- Lithium Battery Specification: 392263mm
- Key Strength:80±10g
- Key life:5 million strokes
- Operating Temperature:-10-+55 C

3. Bluetooth Keyboard Pairing

- Step 1: Turn on the power toggle switch. The state indicator light will be on for 4 seconds, then the light will go off.
- Step2: Press on the [connect]button, the [Bluetooth] indicator light will be blinking and the [Power]indicator will be off,until the [Bluetooth] indicator light be off, the keyboard is now ready to be connect to Ipad.
- Step3: Turn on and unlock Ipad,Click on the Ipad[setting] icon.
- Step4: On the setting menu,select item[general] to access [Bluetooth] settings.Click on[Bluetooth] to turn on the connection. Ipad will automatically search for a Bluetooth-enabled device.
- Step5: Bluetooth 3.0 Keyboard is found, Click on the device to connect.
- Step6: Enter the password code as displayed on screen.
- Step7: Wireless Keyboard connected successfully. Wireless keyboard [Status] indicator light will off.
- Special Note:
1. For other Bluetooth enabled device,please verify the Bluetooth Standard&

2

compatibility before attempting to connect to the keyboard.

4. Charging

When the battery power is low, the [power] indicator light will start blinking, it is time to recharge the keyboard.

Step1: Used the USB power charge cable MICR plug to the keyboard MICR interface.

Step2: Connect USB other plug to the power adapter or computer's USB interface.

Step3: the [charge] red indicator light will stay on when the keyboard is charging. Once it finished charging the [charge] indicator light will turn off.

5. Energy Saving Sleep Mode

The keyboard will kick into sleep mode when it is inactive for 15 minutes and the keyboard [power] indicator or light will go off. To activate from sleep mode, just press any key and wait 3seconds ,the keyboard will come back on.

6. Safety Caution

- 1.Keep the item away from sharp objects.
- 2.Do not place heavy object on top of the keyboard.
- 3.Do not Microwave the item.
- 4.Do not force or distorted the keyboard
- 5.Keep away from oil.chemical or any other organic liquid.

7. Safety Caution

Clean the silicone keyboard with water, alcohol or alcohol based disinfectant

3

8. Troubleshooting

A. Unable to connect

1. Make sure the power switch is on.(the power light is on or off)
2. Make sure the keyboard is within the operating distance.(the available distance is 10 meter)
3. Make sure the battery is charged.(connect the USB power charge cable, the [charge] red indicator light is stay on. The keyboards will be used after charging)
4. Make sure Ipad Bluetooth setting is on .
5. Make sure wireless keyboard is connected to Ipad.(Press on the [connect] switch, the [Bluetooth] indicator light [Status] will be blinking.)
6. Make sure wireless keyboard has been paired with the Ipad.

B. Unable to Charge Keyboard

1. Make sure the USB power cable is connected properly to the keyboard and the power source.
2. Make sure the wall charger is plug into the power outlet.

3. Table of Toxic and Hazardous Substance / Elements and Their Content

Ingredients	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Cable	X	O	O	O	O	O
PWAs	X	O	O	O	O	O
Plastic parts	O	O	O	O	O	O
Membrane	O	O	O	O	O	O
Meter parts	X	O	O	O	O	O
Rubber dome	O	O	O	O	O	O

O stands for this toxic and hazardous content in homogeneous material is under the SJ/T11363-2006 Standards limits

X stands for this toxic and hazardous content in homogeneous material is beyond the SJ/T11363-2006 Standards limits

Under the ingredients with 'X' in the form all are up to ROHS;

"on 27 January 2003 the European parliament and the council announce electronic equipment in limiting the use of certain hazardous substances directive 2002/95 / EC"

Note: the environmental protection using period reference standard depends on the product of the regular work temperature and humidity conditions.

15. Special Note

The keyboard on the charge state Instructions for use:

If the keyboard is out of power, or there is no power when using, in this case need charging please use the power cord in the original packaging. Other MICR interface cable is also available, but it can not be used immediately, if you want to use, then you must disconnect the data cable. Please understand the inconvenience!

4

5

FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.