

Bluetooth Keyboard

Packing Contents:

- Cordless keyboard
- User manual
- Cable
- Foopad

1. Bluetooth Keyboard Specification:

- Built-in Bluetooth 3.0 keyboard
- Ultra - thin aluminum case
- MICRO interface, easy to charge
- Suitable for Iphone
- Built-in rechargeable lithium battery, last for approximately 100 hours per charge
- Special [home] screen key for one touch access to variety of application.
- Light weight, quiet keystrokes, water-proof, dust-proof
- Energy saving keyboard sleep mode

Bluetooth Keyboard Specification and Pairing Instruction:

2. Bluetooth Keyboard Specification

● Bluetooth 3.0 interface standard	● Operating Distance to 10 meters
● Modulating System: GFSK	● Operation Voltage: 1.8-3.6V
● Working Current: <2.0mA	● Standby Current: 0.3-0.5mA
● Sleeping Current: <25uA	● Charging Current \geq 100mA
● Standby Time: 90days	● Charging Time: 4-5hours
● Lithium Battery Capacity: 280mA	● Uninterrupted Working Time: 100hours
● Lithium Battery Life: 3year	● Lithium Battery Specification: 382035mm
● Key Strength: 80 ± 10 g	● Key life: 5 million strokes
● Operating Temperature: -10-+55 C	

3. Bluetooth Keyboard Pairing

Step 1: Turn on the power toggle switch. The state indicator light will be on for 4 seconds, and then the light will go off.

Step 2: Press on the [connect]button, the [Bluetooth] indicator light will be blinking and the [Power]indicator will be on, the keyboard is now ready to be connect to Ipad.

Step 3: Turn on and unlock Ipad,Click on the Ipad[setting] icon.

Step 4: On the setting menu,select item[general] to access [Bluetooth] settings. Click on [Bluetooth] to turn on the connection. Ipad will automatically search for a Bluetooth-enabled device.

Step 5: Wireless Keyboard is found, Click on the device to connect.

Step 6: Enter the password code as displayed on screen.

Step 7: Wireless Keyboard connected successfully. [Power] indicator light will stay on until the keyboard is switched off.

Special Note:

For other Bluetooth enabled device, please verify the Bluetooth Standard&compatibility before attempting to connect to the keyboard.

4. Battery

The long-lasting rechargeable battery can service you for several weeks
With no memory effect, the lithium battery can be charged at any time.
In order to extend service life, we recommend you turn the keyboard off when there is long time with no interactive.

5. Charging

When the battery power is low, the [power] indicator light will start blinking, it is time to recharge the keyboard.

Step 1: Connect USB-B of the native USB power cable to the keyboard charging interface.

Step 2: Connect USB-A to the power adapter or computer's USB interface.

Step 3: the [charge] red indicator light will stay on when the keyboard is charging. Once it finished charging the [charge] indicator light will turn off.

6. Energy Saving Sleep Mode

The keyboard will kick into sleep mode when it is inactive for 15 minutes and the keyboard [power] indicator or light will go off. To activate from sleep mode, just press any key and wait 3seconds, the keyboard will come back on.

7. Safety Caution

- Keep the item away from sharp objects.
- Do not place heavy object on top of the keyboard.
- Do not Microwave the item.
- Do not force or distorted the keyboard
- Keep away from oil, chemical or any other organic liquid.

8. Cleaning

Clean the keyboard with water, alcohol or alcohol based disinfectant

9. Troubleshooting

A. Unable to connect

- Make sure the power switch is on.
- Make sure the keyboard is within the operating distance.
- Make sure the battery is charged.
- Make sure Ipad Bluetooth setting is on.
- Make sure wireless keyboard is connected to Ipad.
- Make sure wireless keyboard has been paired with the Ipad.

B. Unable to Charge Keyboard

- Make sure the USB power cable is connected properly to the keyboard and the power source.
- Make sure the wall charger is plug into the power outlet.

10. Special Keys Description

Long press [Fn] and combination with [F1-F12] and [insert] keys to the shift multimedia keys, and mainly be used in the operation of Ipad multimedia.

11. Special Features and Options

Please note that the Keyboard Case is made from aircraft aluminum with a high grade finish similar to the finish on many popular devices.

Options: A set of four rubber feet is included, which you can place on each corner of the Keyboard Case bottom to help prevent scratching high-grade finish of the Keyboard Case.

What do you think about our Bluetooth keyboards?

Please take a minute to tell us.

Thanks for purchasing our product.

www.haskey.com.cn

12. Product End of Life:

Keyboard battery disposal

- Insert screwdriver between plastic top and metal case at keyboard top or bottom
- Pry up plastic top and remove it completely. This action destroys keyboard
- Turn top over and remove tape from battery.
- Separate battery from circuit board
- Dispose of battery according to local laws. Recycle remaining keyboard parts.

Table of Toxic and Hazardous Substance / Elements and Their Content

Ingredients	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Cable	X	O	O	O	O	O
PWAs	X	O	O	O	O	O
Plastic parts	O	O	O	O	O	O
Membrane	O	O	O	O	O	O
Meter parts	X	O	O	O	O	O
Rubber dome	O	O	O	O	O	O

O stands for this toxic and hazardous content in homogeneous material is under the SJ/T11363-2006 Standards limits

X stands for this toxic and hazardous content in homogeneous material is beyond the SJ/T11363-2006 Standards limits

Under the ingredients with 'X' in the form all are up to ROHS;
"on 27 January 2003 the European parliament and the council announce electronic equipment in limiting the use of certain hazardous substances directive 2002/95/EC"

Note: the environmental protection using period reference standard depends on the product of the regular work temperature and humidity conditions.

FCC Warning

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.