

HB022 Bluetooth folding keyboard

Packing Contents:

- Cordless keyboard
- User manual
- power cable

1. Bluetooth Keyboard Specification:

- Built-in Broadcom Bluetooth module 3.0
- Suitable for tablet pc with system IOS,Android,windows
- Folding functional design, convenient to carry
- Keyboard protective cover with a support frame, easy to hold your tablet pc
- MICR interface, easy to charge
- The power cable is suitable for all kinds of power adapter with a USB interface (Output:DC5.0V \ 500mA)
- Built-in rechargeable lithium battery
- Light weight, quiet keystrokes, water-proof, dust-proof
- Energy saving keyboard in sleep mode

Bluetooth Keyboard Specification and Pairing Instruction:

2. Keyboard Specification

- Standard MICR interface
- Operating distance up to 10 meters
- Modulation system: GFSK
- Operation voltage:3.0-4.2v
- Operating current: <2.5mA
- Standby current: <0.3mA
- Sleep current: <40uA
- Charge current:≥200mA

1

- Standby time: >30 days
- Charge time:<2 hours
- Lithium battery capacity:110mA
- Sustainable working time with backlit on :44 hours
- Lithium battery life: 3 years
- Lithium battery dimensions:3.0*25*25mm
- Key Strength: 80±10g
- Key life: 5 million strokes
- Working temperature: -10 - +55 degree

3. Bluetooth Keyboard Pairing

Step 1: Turn on the power toggle switch. The state indicator light will be on for 5 seconds, and then the light will go off.

Step2: Press on the [connect] button, the [Bluetooth] indicator light will be blinking.

Step3: Access [Bluetooth] settings and Click on [Bluetooth] to turn on the connection. computer will automatically search for a Bluetooth-enabled device. Wireless Keyboard is found Tablet and click on the device to connect. (Bluetooth ID: Bluetooth 3.0 keyboard)

Step4:Enter the password code as displayed on screen.

Step5:Wireless Keyboard connected successfully. Bluetooth indicator light will go off.

4. Keyboard indicator lamp

1) The function of CAPS: you can click it when you need to switch the letter "A" to "a" When the CAPS is blue, it can input uppercase letter; the CAPS light dies out, it inputs lowercase letter.

2) * is Bluetooth indicator lamp. When Bluetooth keyboard is connecting with computer, the lamp is blue by clicking . * It connects successfully, and then the lamp dies out.

2

3)."Charge" is indicator lamp of charging. When it is charging, it is red. And when it is full, the lamp will go off.

4)"Power" is power indicator. Open ing Bluetooth, it is blue and it will die out after 5 seconds. Meanwhile, when voltage is below 3.5v, the power indicator will be blue and shine; until Bluetooth keyboard stops working, it will go off.

Special Note:

For other Bluetooth enabled device, please verify the Bluetooth Standard& compatibility before attempting to connect to the keyboard.

5. Battery

The long-lasting rechargeable battery can service you for several weeks.

With no memory effect, the lithium battery can be charged at any time.

In order to extend service life, we recommend you turn the keyboard off when there is long time with no interactive.

6.Charging

When the battery power is low, the [power] indicator light will start blinking, it is time to recharge the keyboard.

Step1: connect power line to MICR interface in keyboard (make sure the direction is correct)

Step2: Connect USB-A to the power adapter (Output: DC5.0V \ 500mA) or computer's USB interface.

Step3:the [] red indicator light will stay on when the keyboard is charging. Once it finished charging the [] indicator light will turn off.

3

7.Energy Saving Sleep mode

The keyboard will kick into sleep mode when it is inactive for 15 minutes and the keyboard [power] indicator or light will go off. To activate from sleep mode, just press any key and wait 3 seconds, the keyboard will come back on.

8.Safety Caution

- Keep the item away from sharp objects.
- Do not place heavy object on the keyboard.
- Do not Microwave the item.
- Do not force or distorted the keyboard
- Keep away from oil, chemical or any other organic liquid.

9.Cleaning

Clean the keyboard with water, alcohol or alcohol based disinfectant

10.Troubleshooting

A, Unable to connect

- 1.Make sure the keyboard is on (the power indicator is shine)
- 2.Make sure the keyboard is in operating distance (within 10 meters)
- 3.Make sure the battery can work (check ways: the power indicator is red when keyboard is connected by power line, if so, the battery needs to charge)
- 4.Make sure the Bluetooth in tablet computer is on
- 5.Press the key "connect" check the Bluetooth status
- 6.The solution of problems above 1-5:
Maybe the reason is without charging for a long time. Charging is best way to solve them.

B, Unable to Charge Keyboard

- 1.Make sure the USB power cable is connected properly to the keyboard and the power source.

4

2.make sure the wall charger is plug into the power outlet.

Warm warning:

the output voltage and current of power adapter cannot surpass DC5.0V,500mA.or it will damage the keyboard.

11.Special Keys Description

Long press [Fn], Combination media keys will make you operate computer easily.

12.Special Features and Options

The keyboard is very convenient in storage and carrying, and the simple protective sleeve can set tablet PC up.

13. Carry tablet computer on trip

- 1) Storage: put tablet PC and keyboard into package respectively (put keyboard into protective sleeve)
- 2) Disboard: take tablet PC down from protective sleeve

14. Product End of Life:

Keyboard battery disposal

- 1.Pry up plastic top and remove it completely. This action destroys keyboard
- 2.Turn top over and remove tape from battery.
- 3.Separate battery from circuit board
- 4.Dispose of battery according to local laws. Recycle remaining keyboard parts.

5.Table of Toxic and Hazardous Substance / Elements and Their Content

5

Ingredients	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Cable	X	O	O	O	O	O
PWAs	X	O	O	O	O	O
Plastic parts	O	O	O	O	O	O
Membrane	O	O	O	O	O	O
Meter parts	X	O	O	O	O	O
Rubber dome	O	O	O	O	O	O

O stands for this toxic and hazardous content in homogeneous material is under the SJ/T11363-2006 Standards limits

X stands for this toxic and hazardous content in homogeneous material is beyond the SJ/T11363-2006 Standards limits

Under the ingredients with 'X' in the form all are up to ROHS;

"on 27 January 2003 the European parliament and the council announce electronic equipment in limiting the use of certain hazardous substances directive 2002/95 / EC"

Note: the environmental protection using period reference standard depends on the product of the regular work temperature and humidity conditions.

15.Special Note

The keyboard on charging state instructions:

Please use original power line to charge if there is low battery when you are using it. You also can use other data line with MICR interface, but it cannot be used immediately unless you take data line out. Sorry for any inconvenience caused!

6

FCC WARNING

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE 1: Any changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.