



Bandai (HK) Company Limited

Application For Certification

FCC ID: PQ337480DDTG14

TAMAGOTCHI FRIENDS DIGITAL FRIEND

Model: UV0037480-DD

**Additional Models: UV0037493, UV0037494, UV0037495, UV0037496,
UV0037497, UV0037498**

Transceiver

Report No.: SZHH00896286-003

We hereby certify that the sample of the above item is considered to comply with the requirements of FCC Part 15, Subpart C for Intentional Radiator, mention 47 CFR [10-01-13]

Prepared and Checked by:

Approved by:

Sign on file

Jimmy Wen
Engineer

Andy Yan
Senior Project Engineer
Date: December 23, 2014

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF No.: FCC 15C_Tx_b

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labeling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information
<i>EXHIBIT 9:</i>	Test Equipment List

INTERTEK TESTING SERVICES

MEASUREMENT / TECHNICAL REPORT

Bandai (HK) Company Limited
Model: UV0037480-DD

**Additional Models: UV0037493, UV0037494, UV0037495, UV0037496,
UV0037497, UV0037498**

FCC ID: PQ337480DDTG14

This report concerns (check one:) Original Grant Class II Change

Equipment Type: DCD-Low Power Transmitter Below 1705 KHz

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes No

If yes, defer until: _____
date

Company Name agrees to notify the Commission by: _____
date

of the intended date of announcement of the product so that the grant can be issued on
that date.

Transition Rules Request per 15.37? Yes No

If no, assumed Part 15, Subpart C for intentional radiator – the new 47 CFR [10-01-13
Edition] provision.

Report prepared by:

Jimmy Wen
Intertek Testing Services Shenzhen Ltd.
Kejiyuan Branch
6F, D Block, Huahan Building, Langshan Road
Nanshan District, Shenzhen, P. R. China
Phone: (86 755) 8614 0713
Fax: (86 755) 8601 6751

INTERTEK TESTING SERVICES

Table of Contents

1.0 General Description	2
1.1 Product Description.....	2
1.2 Related Submittal(s) Grants.....	2
1.3 Test Methodology.....	2
1.4 Test Facility.....	2
2.0 System Test Configuration	4
2.1 Justification	4
2.2 EUT Exercising Software	4
2.3 Special Accessories	4
2.4 Equipment Modification.....	4
2.5 Measurement Uncertainty	5
2.6 Support Equipment List and Description	5
3.0 Emission Results	7
3.1 Field Strength Calculation	8
3.2 Radiated Emission Data and Configuration Photograph	9
4.0 Equipment Photographs	12
5.0 Product Labelling	14
6.0 Technical Specifications	16
7.0 Instruction Manual	18
8.0 Miscellaneous Information	20
8.1 Emissions Test Procedures	20
9.0 Test Equipment List	22

INTERTEK TESTING SERVICES

List of attached file

Exhibit Type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated photos	radiated photos.pdf
External Photo	External Photos	external photos.pdf
Internal Photo	Internal Photos	internal photos.pdf
Schematics	Circuit Diagram	circuit.pdf
Operation Description	Technical Description	descri.pdf
Block Diagram	Block Diagram	block.pdf
ID Label / Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Letter of Agency	agency.pdf

INTERTEK TESTING SERVICES

EXHIBIT 1

GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 General Description

1.1 Product Description

The equipment under test (EUT) is a TAMAGOTCHI FRIENDS DIGITAL FRIEND operating at the frequency 125 KHz. The EUT is powered by DC 3.0V (2 x 1.5V AAA batteries).

The Models: UV0037493, UV0037494, UV0037495, UV0037496, UV0037497, UV0037498 are the same as the Model: UV0037480-DD in hardware aspect. The difference in item name and main body color serves as marketing strategy.

Antenna Type: Integral antenna

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

1.2 Related Submittal(s) Grants

This is a single application for certification of a transceiver.

1.3 Test Methodology

Both AC mains line-conducted and radiated emission measurements was performed according to the procedures in ANSI C63.4 (2009). Radiated emission measurement was performed in Semi-anechoic chamber. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the **"Justification Section"** of this Application.

1.4 Test Facility

The Semi-anechoic chamber used to collect the radiated data is **Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch** and located at 6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China. This test facility and site measurement data have been fully placed on file with the FCC (Registration Number: 242492).

INTERTEK TESTING SERVICES

EXHIBIT 2

SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 System Test Configuration

2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2009).

The EUT was powered by two new DC 1.5V AAA batteries during the test and only the worst data was reported in this report.

For maximizing emissions below 30 MHz, the EUT was rotated through 360°, the centre of the loop antenna was placed 1 meter above the ground, and the antenna polarization was changed. For maximizing emission at and above 30 MHz, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data report in Exhibit 3.0.

The unit was operated standalone and placed in the center of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the Engineer to maximize emissions through its placement in the three orthogonal axes.

2.2 EUT Exercising Software

N/A.

2.3 Special Accessories

No special accessory.

2.4 Equipment Modification

Any modifications installed previous to testing by Bandai (HK) Company Limited will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch.

INTERTEK TESTING SERVICES

2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

2.6 Support Equipment List and Description

N/A

INTERTEK TESTING SERVICES

EXHIBIT 3

EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 Emission Results

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in $\text{dB}\mu\text{V}/\text{m}$

RA = Receiver Amplitude (including preamplifier) in $\text{dB}\mu\text{V}$

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

Example

Assume a receiver reading of 62.0dB μ V is obtained. The antenna factor of 7.4dB and cable factor of 1.6dB is added. The amplifier gain of 29dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0dB, and the resultant average factor was -10dB. The net field strength for comparison to the appropriate emission limit is 32dB μ V/m. This value in $\text{dB}\mu\text{V}/\text{m}$ was converted to its corresponding level in $\mu\text{V}/\text{m}$.

RA = 62.0dB μ V

AF = 7.4dB

CF = 1.6dB

AG = 29.0dB

PD = 0dB

AV = -10dB

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32\text{dB}\mu\text{V}/\text{m}$$

$$\text{Level in } \mu\text{V}/\text{m} = \text{Common Antilogarithm } [(32\text{dB}\mu\text{V}/\text{m})/20] = 39.8\mu\text{V}/\text{m}$$

INTERTEK TESTING SERVICES

3.2 Radiated Emission Data and Configuration Photograph

Worst Case Radiated Emission
At
0.500 MHz

Judgement: Passed by 23.8 dB

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.pdf.

TEST PERSONNEL:

Sign on file

Jimmy Wen, Engineer

Typed / Printed Name

October 31, 2014

Date

INTERTEK TESTING SERVICES

Company: Bandai (HK) Company Limited
Model: UV0037480-DD
Operating Mode: Transmit

Date of Test: October 31, 2014

Table 1

Radiated Emissions

Polarization	Frequency (MHz)	Net at 3m (dB μ V)	Distance Factor (-dB) (dB)	Calculated at 300m (dB μ V/m)	Limit at 300m (dB μ V/m)	Margin (dB)
Vertical	0.125	66.1	80.0	-13.9	25.7	-39.6
Vertical	0.250	55.9	80.0	-24.1	19.6	-43.7
Vertical	0.375	56.6	80.0	-23.4	16.1	-39.5

Polarization	Frequency (MHz)	Net at 3m (dB μ V)	Distance Factor (-dB) (dB)	Calculated at 30m (dB μ V/m)	Limit at 30m (dB μ V/m)	Margin (dB)
Vertical	0.500	49.8	40.0	9.8	33.6	-23.8
Vertical	0.625	45.7	40.0	5.7	31.7	-26.0
Vertical	0.750	46.2	40.0	6.2	30.1	-23.9
Vertical	0.875	44.1	40.0	4.1	28.8	-24.7
Vertical	1.000	42.7	40.0	2.7	27.6	-24.9
Vertical	1.125	42.7	40.0	2.7	26.6	-23.9

NOTES:

1. Peak Detector Data unless otherwise stated.
2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3 meter distances were measured at 0.3- meter and an inverse proportional extrapolation was performed to compare the signal level to the 3 meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Loop Antenna was used for the frequency band below 30MHz.
5. The formula of factor at frequencies below 30MHz is extrapolated according to FCC part 15.31 (f) as below.
Limit dB μ V/m at 3m = Limit dB μ V/m at 300m + 40log(300/3) dB
Limit dB μ V/m at 3m = Limit dB μ V/m at 30m + 40log(30/3) dB

Test Engineer: Jimmy Wen

EXHIBIT 4

EQUIPMENT PHOTOGRAPHS

INTERTEK TESTING SERVICES

4.0 Equipment Photographs

For electronic filing, photographs of the tested EUT are saved with filename: external photos.pdf and internal photos.pdf.

EXHIBIT 5

PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 Product Labelling

For electronics filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

INTERTEK TESTING SERVICES

EXHIBIT 6

TECHNICAL SPECIFICATIONS

INTERTEK TESTING SERVICES

6.0 Technical Specifications

For electronic filing, the block diagram of the tested EUT is saved with filename: block.pdf and circuit.pdf respectively.

INTERTEK TESTING SERVICES

EXHIBIT 7

INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold / leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 8

MISCELLANEOUS INFORMATION

INTERTEK TESTING SERVICES

8.0 Miscellaneous Information

This miscellaneous information includes emission measuring procedure.

8.1 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitter operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 – 2009.

The Transmitter equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjust through all three orthogonal axes to obtain maximum emission levels. For maximizing emissions below 30 MHz, the EUT was rotated through 360°, the centre of the loop antenna was placed 1 meter above the ground, and the antenna polarization was changed. For maximizing emission at and above 30 MHz, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed.

The IF bandwidth used for measurement of radiated signal strength was 10 KHz for emission below 30 MHz and 120 KHz for emission from 30 MHz to 1000 MHz.

For radiated emission, the frequency range scanned is 9KHz to 1GHz.

INTERTEK TESTING SERVICES

EXHIBIT 9

TEST EQUIPMENT LIST

INTERTEK TESTING SERVICES

9.0 Test Equipment List

Equipment No.	Equipment	Manufacturer	Model No.	Serial No.	Cal. Date	Due Date
SZ061-03	BiConiLog Antenna	ETS	3142C	00066460	28-Jun-14	28-Jun-15
SZ185-01	EMI Receiver	R&S	ESCI	100547	10-Mar-14	10-Mar-15
SZ061-06	Active Loop Antenna	Electro-Metrics	EM-6876	217	29-Apr-14	29-Apr-15
SZ188-01	Anechoic Chamber	ETS	RFD-F/A-100	4102	19-Apr-14	19-Mar-15
SZ062-22	RF Cable	HUBER+SUH NER	SF104PE	MY1913/4PE	11-Nov-13	11-Nov-14
SZ062-23	RF Cable	HUBER+SUH NER	SF104PE	MY4262/4PE	11-Nov-13	11-Nov-14
SZ062-26	RF Cable	HUBER+SUH NER	SF104PE	MY4556/4PE	14-Jan-14	14-Jan-15