

**CCP Co., Ltd.**

Application  
For  
Certification

**FCC ID: PSN3702-RX24**

**Produce Names: Xmods 1/16 Buggy Starter Kit  
Limited Edition, Xmods 1/16 Buggy Starter Kit  
Models: 6000938, 6000940**

**Accessory Names: Xmods Accessory Kit 1/16 Truck  
Conversion Kit, Xmods Accessory Kit 1/16 High Speed Rear Kit  
Accessory Models: 6000948, 6000949**

**Brand Name: RadioShack**

**2.4GHz Transceiver**

**Report No.: 130715001SZN-001**

We hereby certify that the sample of the above item is considered to comply with the requirements of FCC Part 15, Subpart C for Intentional Radiator, mention 47 CFR [10-1-12]

Prepared and Checked by:

Sign on file

**Harry Wu**  
Assistant Engineer

Approved by:

---

**Billy Li**  
Supervisor  
Date: August 26, 2013

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to copy or distribute this report. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results referenced from this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

TRF No.: FCC 15C\_TX\_b

**Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch**  
6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China

Tel: (86 755) 8601 6288 Fax: (86 755) 8601 6751 Website: [www.china.intertek-etlsemko.com](http://www.china.intertek-etlsemko.com)

# INTERTEK TESTING SERVICES

---

---

## LIST OF EXHIBITS

### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information
<i>EXHIBIT 9:</i>	Test Equipment List

# INTERTEK TESTING SERVICES

---

## MEASUREMENT/TECHNICAL REPORT

CCP Co., Ltd.  
Model: 6000938, 6000940  
Accessory Models: 6000948, 6000949  
FCC ID: PSN3702-RX24

This report concerns (check one):      Original Grant       Class II Change

Equipment Type: DXX - Part 15 Low Power Communication Device Transmitter

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date  
of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37?      Yes       No

If no, assumed Part 15, Subpart C for intentional radiator – the new 47 CFR [10-1-12 Edition] provision.

Report prepared by:

Billy Li  
Intertek Testing Services Shenzhen Ltd.  
Kejiyuan Branch  
6F, Block D, Huahan Building, Langshan Road,  
Nanshan District, Shenzhen, P. R. China  
Phone: (86 755) 8601 0645  
Fax: (86 755) 8601 6751

# INTERTEK TESTING SERVICES

---

---

## Table of Contents

<b>1.0 <u>General Description</u></b> .....	2
1.1 Product Description .....	2
1.2 Related Submittal(s) Grants .....	2
1.3 Test Methodology.....	3
1.4 Test Facility.....	3
<b>2.0 <u>System Test Configuration</u></b> .....	5
2.1 Justification .....	5
2.2 EUT Exercising Software.....	5
2.3 Special Accessories .....	5
2.4 Equipment Modification .....	6
2.5 Measurement Uncertainty .....	6
2.6 Support Equipment List and Description .....	6
<b>3.0 <u>Emission Results</u></b> .....	8
3.1 Radiated Test Results.....	9
3.1.1 Field Strength Calculation.....	9
3.1.2 Radiated Emission Configuration Photograph.....	10
3.1.3 Radiated Emissions.....	10
3.1.4 Transmitter Spurious Emissions (Radiated)	12
<b>4.0 <u>Equipment Photographs</u></b> .....	17
<b>5.0 <u>Product Labelling</u></b> .....	19
<b>6.0 <u>Technical Specifications</u></b> .....	21
<b>7.0 <u>Instruction Manual</u></b> .....	23
<b>8.0 <u>Miscellaneous Information</u></b> .....	25
8.1 Bandedge Plot .....	26
8.2 Discussion of Pulse Desensitizatio .....	28
8.3 Transmitter Duty Cycle Calculation.....	29
8.4 Emissions Test Procedures .....	30
<b>9.0 <u>Test Equipment List</u></b> .....	33

## INTERTEK TESTING SERVICES

---

---

### List of attached file

Exhibit type	File Description	Filename
Test Report	Test Report	report.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Report	Bandedge Plot	bandedge.pdf
Test Report	20dB BW Plot	bw.pdf
Test Report	Timing Plot	af.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	internal photos.pdf
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
Operation Description	Technical Description	descri.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf
Cover Letter	Letter of Agency	agency.pdf

**EXHIBIT 1**

**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

## 1.0 General Description

### 1.1 Product Description

The Equipment under Test (EUT) is a Car unit for Xmods 1/16 Buggy Starter Kit Limited Edition model: 6000938 operating at 2.4GHz band. It is powered by 6 x 1.5V AA size batteries or 1 x 9.6V Rechargeable Lithium Battery. For more detail information pls. refer to the user manual.

The Model: 6000940 is the same as the Model: 6000938 in mainboard hardware aspect. The models are different in the accessories, appearance and model no. for trading purpose.

The Models: 6000948 and 6000949 are accessories for the Model: 6000938.

That 6000938 contains 6000948 and 6000949. Thus, combination of 6000940 + 6000948 + 6000949.

The models no. corresponding to name listing.

Name	Model No.
Xmods 1/16 Buggy Starter Kit Limited Edition	6000938
Xmods 1/16 Buggy Starter Kit	6000940
Xmods Accessory Kit 1/16 Truck Conversion Kit	6000948
Xmods Accessory Kit 1/16 High Speed Rear Kit	6000949

Antenna Type: Integral antenna

Modulation Type: GFSK

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

### 1.2 Related Submittal(s) Grants

This is an application for certification of a transceiver for the Car unit, and the corresponding Remote Controller unit (2.4GHz transceiver) has been granted with FCC ID: PSN3701-TX24.

## INTERTEK TESTING SERVICES

---

### 1.3 Test Methodology

Radiated emission measurement was performed according to the procedures in ANSI C63.4 (2009). Radiated emission measurement was performed in Semi-anechoic chamber. For radiated emission measurement, preliminary scans were performed in the semi-anechoic chamber only to determine the worst case modes. All radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application. All other measurements were made in accordance with the procedures in part 2 of CFR 47.

### 1.4 Test Facility

The Semi-anechoic chamber used to collect the radiated data is **Intertek Testing Services Shenzhen Ltd. Kejiyuan Branch** and located at 6F, D Block, Huahan Building, Langshan Road, Nanshan District, Shenzhen, P. R. China. This test facility and site measurement data have been fully placed on file with the FCC(Registration Number: 242492).

**EXHIBIT 2**

**SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2009).

The EUT was powered by six new 1.5V AA size batteries or one new 9.6V rechargeable lithium battery during the test. Only the worse data was reported in this report.

Combinations as below groups were tested, only the worse data was reported in this report.

Group 1, item 6000940

Group 2, item 6000940 + 6000948

Group 3, item 6000940 + 6000948 + 6000949

Group 3 is the worse case operating mode.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.

The unit was operated standalone and placed in the centre of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on a turn table, which enabled the Engineer to maximize emissions through its placement in the three orthogonal axes.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device.

#### 2.3 Special Accessories

No special accessories used.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by CCP Co., Ltd. will be incorporated in each production model sold / leased in the United States.

No modifications were installed by Intertek Testing Services Shenzhen Ltd Kejiyuan Branch.

### 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

Description	Manufacturer	Model No.
Xmods 1/16 Buggy Starter Kit Limited Edition	RadioShack	6000938
Xmods 1/16 Buggy Starter Kit	RadioShack	6000940
Xmods Accessory Kit 1/16 Truck Conversion Kit	RadioShack	6000948
Xmods Accessory Kit 1/16 High Speed Rear Kit	RadioShack	6000949
Xmods 1/24 Starter Kit(Remote controller)	RadioShack	6000939

**EXHIBIT 3**

**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 Emission Results

Data is included worst-case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

### 3.1 Radiated Test Results

A sample calculation, configuration photographs and data tables of the emissions are included.

#### 3.1.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

Where

FS = Field Strength in dB $\mu$ V/m

RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 62.0 \text{ dB}\mu\text{V}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$PD = 0 \text{ dB}$$

$$AV = -10 \text{ dB}$$

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32 \text{ dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

## INTERTEK TESTING SERVICES

---

### 3.1.2 Radiated Emission Configuration Photograph

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

### 3.1.3 Radiated Emissions

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Worst Case Radiated Emission  
at  
749.720 MHz

Judgement: Passed by 17.4 dB

### ***TEST PERSONNEL:***

*Sign on file*

Harry Wu, Assistant Engineer  
*Typed/Printed Name*

August 26, 2013

*Date*

# INTERTEK TESTING SERVICES

---

Applicant: CCP Co., Ltd.

Date of Test: August 26, 2013

Sample: 1/1

Worst Case Operating Mode: Transmit

Table 1

## Radiated Emissions

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Horizontal	163.010	25.7	20.0	10.1	15.8	43.5	-27.7
Horizontal	408.785	27.5	20.0	16.8	24.3	46.0	-21.7
Horizontal	749.720	25.4	20.0	23.2	28.6	46.0	-17.4
Vertical	91.595	28.8	20.0	7.9	16.7	43.5	-26.8
Vertical	162.890	34.2	20.0	10.1	24.3	43.5	-19.2
Vertical	536.825	27.8	20.0	18.9	26.7	46.0	-19.3

NOTES: 1. Quasi-Peak detector is used except for others stated.

2. All measurements were made at 3 meters. Harmonic emissions not detected at the 3-meter distances were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. All emissions are below the QP limit.

## INTERTEK TESTING SERVICES

---

### 3.1.4 Transmitter Spurious Emissions (Radiated)

Worst Case Radiated Emission  
at  
7209.000 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos. pdf.

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 10.6 dB

### **TEST PERSONNEL:**

*Sign on file*

Harry Wu, Assistant Engineer  
*Typed/Printed Name*

August 26, 2013

*Date*

# INTERTEK TESTING SERVICES

Applicant: CCP Co., Ltd.

Date of Test: August 26, 2013

Sample: 1/1

Worst Case Operating Mode: Transmit

Table 2

## Radiated Emissions

(2403MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2403.000	100.5	36.7	28.5	92.3	114.0	-21.7
Vertical	4806.000	48.9	36.7	35.0	47.2	74.0	-26.8
Vertical	7209.000	54.5	36.1	37.0	55.4	74.0	-18.6
Vertical	9612.000	53.4	36.2	37.5	54.7	74.0	-19.3

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2403.000	100.5	36.7	28.5	12.0	80.3	94.0	-13.7
Vertical	4806.000	48.9	36.7	35.0	12.0	35.2	54.0	-18.8
Vertical	7209.000	54.5	36.1	37.0	12.0	43.4	54.0	-10.6
Vertical	9612.000	53.4	36.2	37.5	12.0	42.7	54.0	-11.3

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Harry Wu

---

TRF No.: FCC 15C\_TX\_b

FCC ID: PSN3702-RX24

Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

Applicant: CCP Co., Ltd.

Date of Test: August 26, 2013

Sample: 1/1

Worst Case Operating Mode: Transmit

Table 3

### Radiated Emissions

(2441MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Peak Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2441.000	101.6	36.7	28.5	93.4	114.0	-20.6
Vertical	4882.000	49.0	36.7	35.0	47.3	74.0	-26.7
Vertical	7323.000	53.6	36.1	37.0	54.5	74.0	-19.5
Vertical	9764.000	53.0	36.2	38.0	54.8	74.0	-19.2

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2441.000	101.6	36.7	28.5	12.0	81.4	94.0	-12.6
Vertical	4882.000	49.0	36.7	35.0	12.0	35.3	54.0	-18.7
Vertical	7323.000	53.6	36.1	37.0	12.0	42.5	54.0	-11.5
Vertical	9764.000	53.0	36.2	38.0	12.0	42.8	54.0	-11.2

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Harry Wu

---

TRF No.: FCC 15C\_TX\_b

FCC ID: PSN3702-RX24

Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

Applicant: CCP Co., Ltd.

Date of Test: August 26, 2013

Sample: 1/1

Worst Case Operating Mode: Transmit

Table 4

### Radiated Emissions

(2471MHz)

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2471.000	103.3	36.7	28.3	94.9	114.0	-19.1
Vertical	4942.000	48.0	36.7	35.3	46.6	74.0	-27.4
Vertical	7413.000	54.1	36.1	37.0	55.0	74.0	-19.0
Vertical	9884.000	52.0	36.3	38.7	54.4	74.0	-19.6

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Pre-Amp Gain (dB)	Antenna Factor (dB)	Average Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Average Limit at 3m (dB $\mu$ V/m)	Margin (dB)
Vertical	2471.000	103.3	36.7	28.3	12.0	82.9	94.0	-11.1
Vertical	4942.000	48.0	36.7	35.3	12.0	34.6	54.0	-19.4
Vertical	7413.000	54.1	36.1	37.0	12.0	43.0	54.0	-11.0
Vertical	9884.000	52.0	36.3	38.7	12.0	42.4	54.0	-11.6

Notes: 1. Peak Detector Data unless otherwise stated.

2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
3. Negative value in the margin column shows emission below limit.
4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Harry Wu

---

TRF No.: FCC 15C\_TX\_b

FCC ID: PSN3702-RX24

Report No.: 130715001SZN-001

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 4**

**EQUIPMENT PHOTOGRAPHS**

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: PSN3702-RX24  
Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

---

### 4.0 Equipment Photographs

For electronic filing, the photographs of the tested EUT are saved with filename: external photos.pdf & internal photos.pdf.

## **INTERTEK TESTING SERVICES**

---

---

### **EXHIBIT 5**

#### **PRODUCT LABELLING**

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: PSN3702-RX24  
Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

### 5.0 Product Labelling

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

# **INTERTEK TESTING SERVICES**

---

---

## **EXHIBIT 6**

### **TECHNICAL SPECIFICATIONS**

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: PSN3702-RX24  
Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematics of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 7**

**INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

**INTERTEK TESTING SERVICES**

---

---

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: PSN3702-RX24  
Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

### 8.0 Miscellaneous Information

This miscellaneous information includes details of the measured bandedge, the test procedure and calculation of factor such as pulse desensitization.

## INTERTEK TESTING SERVICES

---

### 8.1 Bandedge Plot

For electronic filing, the plot shows the fundamental emission when modulated is saved with filename: bandedge.pdf. From the plot, the field strength of any emissions outside of the specified frequency band are attenuated to the general radiated emission limits in section 15.209. It fulfils the requirement of 15.249(d).

#### Peak Measurement

Bandedge compliance is determined by applying marker-delta method, i.e (Bandedge Plot).

##### **(i) Lower channel 2403MHz:**

$$\begin{aligned}\text{Peak Resultant field strength} &= \text{Fundamental emissions (peak value)} - \text{delta from the bandedge plot} \\ &= 92.3 \text{ dB}\mu\text{v/m} - 32.2 \text{ dB} \\ &= 60.1 \text{ dB}\mu\text{v/m}\end{aligned}$$

$$\begin{aligned}\text{Average Resultant field strength} &= \text{Fundamental emissions (Average value)} - \text{delta from the bandedge plot} \\ &= 80.3 \text{ dB}\mu\text{v/m} - 32.2 \text{ dB} \\ &= 48.1 \text{ dB}\mu\text{v/m}\end{aligned}$$

##### **(ii) Upper channel 2471MHz:**

$$\begin{aligned}\text{Peak Resultant field strength} &= \text{Fundamental emissions (peak value)} - \text{delta from the bandedge plot} \\ &= 94.9 \text{ dB}\mu\text{v/m} - 44.6 \text{ dB} \\ &= 50.3 \text{ dB}\mu\text{v/m}\end{aligned}$$

$$\begin{aligned}\text{Average Resultant field strength} &= \text{Fundamental emissions (Average value)} - \text{delta from the bandedge plot} \\ &= 82.9 \text{ dB}\mu\text{v/m} - 44.6 \text{ dB} \\ &= 38.3 \text{ dB}\mu\text{v/m}\end{aligned}$$

The resultant field strength meets the general radiated emission limit in section 15.209, which does not exceed 74dB $\mu$ v/m (Peak Limit) and 54dB $\mu$ v/m (Average Limit).

## INTERTEK TESTING SERVICES

---

### 8.1 Bandedge Plot (cont'd)

Pursuant to FCC part 15 Section 15.215(c), the 20dB bandwidth of the emission was contained within the frequency band designated (mentioned as above) which the EUT operated. The effects, if any, from frequency sweeping, frequency hopping, other modulation techniques and frequency stability over expected variations in temperature and supply voltage were considered.

Figure 8.1 Bandwidth

## INTERTEK TESTING SERVICES

---

### 8.2 Discussion of Pulse Desensitization

Pulse desensitivity is not applicable for this device. The effective period ( $T_{eff}$ ) is approximately 0.21 ms for a digital "1" bit, as shown in the plots of Exhibit 8.3. With a resolution bandwidth (3 dB) of 100 kHz, the pulse desensitivity factor was 0 dB

## INTERTEK TESTING SERVICES

---

### 8.3 Calculation of Average Factor

Averaging factor in dB =  $20 \log_{10} (\text{duty cycle})$

The specification for output field strengths in accordance with the FCC rules specify measurements with an average detector. During testing, a spectrum analyzer incorporating a peak detector was used. Therefore, a reduction factor can be applied to the resultant peak signal level and compared to the limit for measurement instrumentation incorporating an average detector.

The time period over which the duty cycle is measured is 100 milliseconds, or the repetition cycle, whichever is a shorter time frame. The worst case (highest percentage on) duty cycle is used for the calculation. The duty cycle is measured by placing the spectrum analyzer in zero scan (receiver mode) and linear mode at maximum bandwidth (3 MHz at 3 dB down) and viewing the resulting time domain signal output from the analyzer on a Tektronix oscilloscope. The oscilloscope is used because of its superior time base and triggering facilities.

A plot of the worst-case duty cycle as detected in this manner are saved with filename: af.pdf

The duty cycle is simply the on-time divided by the period:

The duration of one cycle = 0.835ms

Effective period of the cycle = 0.210ms

DC = 0.210ms / 0.835ms = 0.251 or 25.1%

Therefore, the averaging factor is found by  $20 \log_{10} 0.251 = -12.0$  dB

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 2009.

The transmitting equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjust through all three orthogonal axes to obtain maximum emission levels. The antenna height and polarization are varied during the testing to search for maximum signal levels.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower.

## INTERTEK TESTING SERVICES

---

### 8.4 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

The IF bandwidth used for measurement of radiated signal strength was 10 kHz for emission below 30 MHz and 120 kHz for emission from 30 MHz to 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the restricted bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, but those measurements taken at a closer distance are so marked.

## **INTERTEK TESTING SERVICES**

---

---

### **EXHIBIT 9**

### **TEST EQUIPMENT LIST**

---

---

TRF No.: FCC 15C\_TX\_b  
FCC ID: PSN3702-RX24  
Report No.: 130715001SZN-001

## INTERTEK TESTING SERVICES

---

### 9.0 Test Equipment List

Equipment No.	Equipment	Manufacturer	Model No.	Serial No.	Cal. Date	Due Date
SZ061-04	BiConiLog Antenna	ETS	3142C	00066460	29-Jun-13	29-Jun-14
SZ185-01	EMI Receiver	R&S	ESCI	100547	12-Mar-13	12-Mar-14
SZ061-07	Pyramidal Horn Antenna	ETS	3160-09	00083067	21-Jul-13	21-Jan-14
SZ061-08	Horn Antenna	ETS	3115	00092346	03-Nov-12	03-Nov-13
SZ061-06	Active Loop Antenna	Electro-Metrics	EM-6876	217	12-Mar-13	12-Mar-14
SZ056-03	Spectrum Analyzer	R&S	FSP 30	101148	12-Mar-13	12-Mar-14
SZ181-04	Preamplifier	Agilent	8449B	3008A02474	12-Mar-13	12-Mar-14
SZ188-01	Anechoic Chamber	ETS	RFD-F/A-100	4102	02-Mar-13	02-Mar-14
SZ062-02	RF Cable	RADIALL	RG 213U	--	26-Feb-13	26-Aug-14
SZ062-06	RF Cable	RADIALL	0.04-26.5GHz	--	12-Mar-13	12-Mar-14
SZ062-12	RF Cable	RADIALL	0.04-26.5GHz	--	12-Mar-13	12-Mar-14
SZ067-04	Notch Filter	Micro-Tronics	BRM5070 2-02	--	12-Mar-13	12-Mar-14