



3301 E. Deseret Drive, St. George, UT 84790
www.wilsonelectronics.com • info@wilsonelectronics.com
phone 1-800-204-4104 • fax 1-435-656-2432

November 1, 2013
Subject: Antenna Kitting
Re: FCC ID: PWO460005
To Whom It May Concern:

The antenna kitting options for model 460005 signal booster were done for 27 Outside Antenna kit options and 14 Inside Antenna kit options. The order of the attached calculations is as follows:

Outside Antenna Kit Options:

1. Kit 314411-40075
2. Kit 314411-5825
3. Kit 314775-0630
4. Kit 301111-0675
5. Kit 301111-5850
6. Kit 301111-400170
7. Kit 311124-400100
8. Kit 311124-5840
9. Kit 311124-0660
10. Kit 311129-0650
11. Kit 311129-400100
12. Kit 311129-5830
13. Kit 311203-40020
14. Kit 311203-5820
15. Kit 311201-0620
16. Kit 301126
17. Kit 301111-11140
18. Kit 311201-1120
19. Kit 311124-11110
20. Kit 314475-1175
21. Kit 314453-5825

22. Kit 314453-40075
23. Kit 314473-0640
24. Kit 311141-0620
25. Kit 311129-1180
26. 311141-1120
27. 314473-1175

Inside Antenna Kit Options:

1. Kit 311135-40060
2. Kit 311155-40060
3. Kit 311135-5820
4. Kit 311155-0630
5. Kit 301121-40010
6. Kit 301151-0610
7. Kit 309900-50N
8. Kit 309902-75F
9. Kit 309903-75F
10. Kit 309904-75F
11. Kit 309905-50N
12. Kit 311155-1150
13. Kit 301151-1110
14. Kit 301213

Sincerely,

A handwritten signature in blue ink, appearing to read 'Patrick L. Cook'.

Patrick L. Cook
Senior Research and Development Engineer



Fixed Outside Antenna Kit Options

FCC ID: PWO460005

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	824-849	1850-1910
Uplink Output Power (dBm)	24.9	22.5

1 Wide Band Directional Antenna With 75' LMR 400 314411-40075

Antenna Gains (dBi)	7.8	9.1
Coax Loss (dB)	3.6	5.4
Final Gain less Loss (dB)	4.2	3.7
Output Power plus Final Gain (dBm EIRP)	29.09	26.2

2 Wide Band Directional Antenna With 25' RG-58 314411-5825

Antenna Gains (dBi)	7.8	9.1
Coax Loss (dB)	3.2	5.4
Final Gain less Loss (dB)	4.6	3.7
Output Power plus Final Gain (dBm EIRP)	29.5	26.2

3 Wide Band Directional Antenna With 30' RG-6 314775-0630

Antenna Gains (dBi)	7.8	9.1
Coax Loss (dB)	3.4	5.3
Final Gain less Loss (dB)	4.4	3.8
Output Power plus Final Gain (dBm EIRP)	29.3	26.3

4 Yagi Antenna 301111 With 75' RG-6 301111-0675

Antenna Gains (dBi)	10.8	14.9
Coax Loss (dB)	6.3	9.975
Final Gain less Loss (dB)	4.45	4.925
Output Power plus Final Gain (dBm EIRP)	29.3	27.4

5 Yagi Antenna 301111 With 50' RG-58 301111-5850

Antenna Gains (dBi)	10.8	-14.9
Coax Loss (dB)	6.5	10.7
Final Gain less Loss (dB)	4.3	-25.6
Output Power plus Final Gain (dBm EIRP)	29.2	-3.1

6 Yagi Antenna 301111 With 170' LMR 400 301111-400170

Antenna Gains (dBi)	10.8	-14.9
Coax Loss (dB)	6.3	9.8
Final Gain less Loss (dB)	4.45	-24.7
Output Power plus Final Gain (dBm EIRP)	29.3	-2.2



Fixed Outside Antenna Kit Options

FCC ID: PWO460005

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	824-849	1850-1910
Uplink Output Power (dBm)	24.9	22.5

7 Yagi Antenna 311124 With 100' LMR 400 311124-400100

Antenna Gains (dBi)	9.64	-11.97
Coax Loss (dB)	4.7	7.1
Final Gain less Loss (dB)	4.9	-19.07
Output Power plus Final Gain (dBm EIRP)	29.8	3.4

8 Yagi Antenna 311124 With 40' RG-58 311124-5840

Antenna Gains (dBi)	9.64	-11.97
Coax Loss (dB)	5.2	8.6
Final Gain less Loss (dB)	4.4	-20.6
Output Power plus Final Gain (dBm EIRP)	29.3	1.9

9 Yagi Antenna 311124 With 60' RG-6 311124-0660

Antenna Gains (dBi)	9.64	-11.97
Coax Loss (dB)	5.0	8.0
Final Gain less Loss (dB)	4.64	-19.95
Output Power plus Final Gain (dBm EIRP)	29.5	2.6

10 Yagi Antenna 311129 With 50' RG-6 311129-0650

Antenna Gains (dBi)	-23.4	10.9
Coax Loss (dB)	4.2	6.7
Final Gain less Loss (dB)	-27.60	4.25
Output Power plus Final Gain (dBm EIRP)	-2.7	26.8

Yagi Antenna 311129 With 100' LMR 400 311129-400100

Antenna Gains (dBi)	-23.4	10.9
Coax Loss (dB)	4.7	7.1
Final Gain less Loss (dB)	-28.1	3.8
Output Power plus Final Gain (dBm EIRP)	-3.21	26.3

12 Yagi Antenna 311129 With 30' RG-58 311129-5830

Antenna Gains (dBi)	-23.4	10.9
Coax Loss (dB)	3.9	6.4
Final Gain less Loss (dB)	-27.3	4.5
Output Power plus Final Gain (dBm EIRP)	-2.4	27.0



Fixed Outside Antenna Kit Options

FCC ID: PWO460005

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	824-849	1850-1915
Uplink Output Power (dBm)	24.9	22.5

13 Omni Directional Antenna 311203 With 20' LMR 400 311203-40020

Antenna Gains (dBi)	0.57	5.09
Coax Loss (dB)	0.7	1.1
Final Gain less Loss (dB)	-0.13	4.0
Output Power plus Final Gain (dBm EIRP)	24.8	26.5

14 Omni Directional Antenna 311203 With 20' RG-58 311203-5820

Antenna Gains (dBi)	0.57	5.09
Coax Loss (dB)	2.6	4.3
Final Gain less Loss (dB)	-2.03	0.79
Output Power plus Final Gain (dBm EIRP)	22.9	23.3

15 Omni Directional Antenna 311201 With 20' RG-6 311201-0620

Antenna Gains (dBi)	0.57	5.09
Coax Loss (dB)	1.7	2.7
Final Gain less Loss (dB)	-1.13	2.39
Output Power plus Final Gain (dBm EIRP)	23.8	24.9

16 Mini-Mag Antenna With 12.5' RG-174 301126

Antenna Gains (dBi)	1.97	6.89
Coax Loss (dB)	3.7	4.7
Final Gain less Loss (dB)	-1.73	2.19
Output Power plus Final Gain (dBm EIRP)	23.2	24.7

17 Yagi 301111 With 140' RG-11 301111-11140

Antenna Gains (dBi)	10.8	-14.6
Coax Loss (dB)	6.38	10.9
Final Gain less Loss (dB)	4.37	-25.5
Output Power plus Final Gain (dBm EIRP)	29.3	-3.0

18 Omni Directional Antenna 311201 With 20' RG-11 311201-1120

Antenna Gains (dBi)	0.57	5.09
Coax Loss (dB)	0.9	1.6
Final Gain less Loss (dB)	-0.3	3.5
Output Power plus Final Gain (dBm EIRP)	24.6	26.0

19 Yagi 311124 With 110' RG-11 311124-11110

Antenna Gains (dBi)	9.64	-11.97
Coax Loss (dB)	5	8.6
Final Gain less Loss (dB)	4.6	-20.6
Output Power plus Final Gain (dBm EIRP)	29.5	1.9

20 Wide Band Directional Antenna With 75' RG-11 314475-1175

Antenna Gains (dBi)	7.8	9.1
Coax Loss (dB)	3.4	5.9
Final Gain less Loss (dB)	4.4	3.2
Output Power plus Final Gain (dBm EIRP)	29.3	25.7



Fixed Outside Antenna Kit Options

FCC ID: PWO460005

Final Output Power Limited to 30 dBm EIRP in all frequency bands

Uplink Frequency (MHz)	824-849	1850-1915
Uplink Output Power (dBm)	24.9	22.5

21 Panel Antenna With 25' RG-58 314453-5825

Antenna Gains (dBi)	4.4	10.04
Coax Loss (dB)	3.2	5.4
Final Gain less Loss (dB)	1.2	4.6
Output Power plus Final Gain (dBm EIRP)	26.1	27.1

22 Panel Antenna With 75' LMR 400 314453-40075

Antenna Gains (dBi)	4.4	10.04
Coax Loss (dB)	3.6	5.4
Final Gain less Loss (dB)	0.8	4.64
Output Power plus Final Gain (dBm EIRP)	25.7	27.1

23 Panel Antenna With 40' RG-6 314473-0640

Antenna Gains (dBi)	4.4	10.04
Coax Loss (dB)	3.4	5.3
Final Gain less Loss (dB)	1.0	4.74
Output Power plus Final Gain (dBm EIRP)	25.9	27.2

24 Grey Panel With 20' RG-6 311141-0620

Antenna Gains (dBi)	1.2	5.5
Coax Loss (dB)	1.7	2.7
Final Gain less Loss (dB)	-0.5	2.8
Output Power plus Final Gain (dBm EIRP)	24.4	25.3

25 Yagi 311129 With 80' RG-11 311129-1180

Antenna Gains (dBi)	-23.4	10.9
Coax Loss (dB)	3.6	6.3
Final Gain less Loss (dB)	-27.0	4.6
Output Power plus Final Gain (dBm EIRP)	-2.1	27.1

26 Grey Panel With 20' RG-11 311141-1120

Antenna Gains (dBi)	1.2	5.5
Coax Loss (dB)	0.9	1.6
Final Gain less Loss (dB)	0.30	3.90
Output Power plus Final Gain (dBm EIRP)	25.2	26.4

27 Panel Antenna With 75' RG-11 314473-1175

Antenna Gains (dBi)	4.4	10.04
Coax Loss (dB)	3.4	5.9
Final Gain less Loss (dB)	1	4.1
Output Power plus Final Gain (dBm EIRP)	25.9	26.6



FCC ID: PWO460005

Uplink Frequency Band (MHz)	824-849	1850-1910
Measured Uplink Gain (dB)	59.50	65.90
Measured RSSI Shutoff (dBm/MHz)	-63.40	-68.80
MSCL Minimum (dB)	30.10	31.10
6' Separation Distance Path Loss (dB)	36.16	43.21
Polarity Loss	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	9.06	12.60

1 Inside Antenna Kit 311135-40060: Panel w/60' LMR 400

Antenna Gain Less Cable Loss (dB)	2.94	4.36
	-6.12	-8.24

2 Inside Antenna Kit 311155-40060: Panel w/60' LMR 400

Antenna Gain Less Cable Loss (dB)	2.94	4.36
	-6.12	-8.24

3 Inside Antenna Kit 311135-5820: Panel w/20' RG-58

Antenna Gain Less Cable Loss (dB)	1.82	5.75
	-7.24	-6.85

4 Inside Antenna Kit 311155-0630: Panel w/30' RG-6

Antenna Gain Less Cable Loss (dB)	1.88	6.05
	-7.18	-6.55

5 Inside Antenna Kit 301121-40010: Dome Antenna w/10' LMR 400

Antenna Gain Less Cable Loss (dB)	0.06	2.42
	-9.00	-10.18

6 Inside Antenna Kit 301151-0610: Dome Antenna w/10' RG-6

Antenna Gain Less Cable Loss (dB)	-0.08	2.02
	-9.14	-10.58

7 Inside Antenna Kit 309900-50N: 2 Panel Antennas and a 50 Ohm 3-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	1.33	7.49
Margin (dB)	-7.73	-5.11

8 Inside Antenna Kit 309902-75F: 2 Panel Antennas and a 75 Ohm 3-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	1.33	7.49
Margin (dB)	-7.73	-5.11

9 Inside Antenna Kit 309903-75F: 3 Panel Antennas and three 75 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	1.33	7.49
Margin (dB)	-7.73	-5.11

10 Inside Antenna Kit 309904-75F: 1 Panel Antenna and a 75 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	1.33	7.49
Margin (dB)	-7.73	-5.11

11 Inside Antenna Kit 309905-50N: 3 Panel Antennas and three 50 Ohm 2-Way Splitter

Antenna Gain Less Cable/Splitter Loss (dB)	1.33	7.49
Margin (dB)	-7.73	-5.11

12 Inside Antenna Kit 311155-1150: Panel w/50' RG-11

Antenna Gain Less Cable Loss (dB)	2.12	6.13
	-6.94	-6.47

13 Inside Antenna Kit 301151-1110: Dome Antenna w/10' RG-11

Antenna Gain Less Cable Loss (dB)	0.30	2.57
	-8.76	-10.03

Uplink Frequency Band (MHz)	824-849	1850-1910
Measured Uplink Gain (dB)	59.50	65.90
Measured RSSI Shutoff (dBm/MHz)	-63.94	-69.80
MSCL Minimum (dB)	29.56	30.10
4' Separation Distance Path Loss (dB)	32.64	39.68
Polarity Loss	3.0	3.0
Max Antenna Gain Less Cable Loss (dB)	6.08	12.58

14 Inside Antenna Kit 301213: Desktop Antenna w/5' RG-174

Antenna Gain Less Cable Loss (dB)	1.60	-5.50
	-4.48	-18.08