

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in § 1.1307(b)

FCC ID: **PXK-HL2021A**

EUT Specification

EUT	Bluetooth speaker
Frequency band (Operating)	☐ WLAN: 2.412GHz ~ 2.462GHz ☐ WLAN: 5.18GHz ~ 5.32GHz / 5.50GHz ~ 5.70GHz ☐ WLAN: 5.745GHz ~ 5825GHz ☒ Others
Device category	☐ Portable (<20cm separation) ☒ Mobile (>20cm separation) ☐ Others ____
Exposure classification	☐ Occupational/Controlled exposure (S = 5mW/cm ²) ☒ General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna diversity	☒ Single antenna ☐ Multiple antennas ☐ Tx diversity ☐ Rx diversity ☐ Tx/Rx diversity
Max. output power	-2.54dBm (0.000556W)
Antenna gain (Max)	0 dBi
Evaluation applied	☒ MPE Evaluation ☐ SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

P_d = Power density in mW/cm^2

P_{out} = output power to antenna in Mw

G = gain of antenna in linear scale

π = 3.1416

R = distance between observation point and center of the radiator in cm


P_d the limit of MPE, $1mW/cm^2$. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

Operating Mode	Channel Frequency (MHz)	Output Peak power (mW)	Antenna Gain (dBi)	Power density at 20cm (mW/cm^2)	Power density Limits (mW/cm^2)
op-mode 1	2402	0.556	0	1.106e-05	1
op-mode 2	2441	0.298	0	5.929e-05	1
op-mode 3	2480	0.085	0	1.691e-05	1
op-mode 6	2402	0.485	0	9.649e-05	1
op-mode 7	2441	0.265	0	5.272e-05	1
op-mode 8	2480	0.070	0	1.393e-05	1
op-mode 10	2402	0.491	0	9.768e-05	1
op-mode 11	2441	0.265	0	5.272e-05	1
op-mode 12	2480	0.070	0	1.393e-05	1

Note: The product has two RF modules, and both radios can be transmit at the same time, when both radio are turned on, the MPE is **1.858e-04**.

Signature



LC Liu

liuchengliu@ecorehyc.com

Tel: 0711-2383866

Fax: 0711-2383899

ECORE TECHNOLOGY COMPANY LIMITED

North of Bingang East Road, Huahu Development Zone, Ezhou, Hubei, China