

RF EXPOSURE REPORT

REPORT NO.: SA141106E03

MODEL NO.: C6250

FCC ID: PY314300292

RECEIVED: Oct. 06, 2014

TESTED: Nov. 19 to 20, 2014

ISSUED: Dec. 19, 2014

APPLICANT: NETGEAR, Inc.

ADDRESS: 350 East Plumeria Drive San Jose, CA 95134

ISSUED BY: Bureau Veritas Consumer Products Services (H.K.)
Ltd., Taoyuan Branch Hsin Chu Laboratory

LAB ADDRESS : No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen,
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,
R.O.C.

TEST LOCATION (1): No. 81-1, Lu Liao Keng, 9th Ling, Wu Lung Tsuen,
Chiung Lin Hsiang, Hsin Chu Hsien 307, Taiwan,
R.O.C.

TEST LOCATION (2): No. 49, Ln. 206, Wende Rd., Shangshan Tsuen, Chiung
Lin Hsiang, Hsin Chu Hsien 307, Taiwan, R.O.C.

This report should not be used by the client to claim
product certification, approval, or endorsement by any
government agencies.

This report is for your exclusive use. Any copying or replication of this report to or for any other person or entity, or use of our name or trademark, is permitted only with our prior written permission. This report sets forth our findings solely with respect to the test samples identified herein. The results set forth in this report are not indicative or representative of the quality or characteristics of the lot from which a test sample was taken or any similar or identical product unless specifically and expressly noted. Our report includes all of the tests requested by you and the results thereof based upon the information that you provided to us. You have 60 days from date of issuance of this report to notify us of any material error or omission caused by our negligence, provided, however, that such notice shall be in writing and shall specifically address the issue you wish to raise. A failure to raise such issue within the prescribed time shall constitute your unqualified acceptance of the completeness of this report, the tests conducted and the correctness of the report contents. Unless specific mention, the uncertainty of measurement has been explicitly taken into account to declare the compliance or non-compliance to the specification

TABLE OF CONTENTS

RELEASE CONTROL RECORD	3
1. CERTIFICATION.....	4
2. RF EXPOSURE LIMIT	5
3. MPE CALCULATION FORMULA.....	5
4. CLASSIFICATION.....	5
5. ANTENNA GAIN	6
6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER	7



RELEASE CONTROL RECORD

ISSUE NO.	REASON FOR CHANGE	DATE ISSUED
SA141106E03	Original release	Dec. 19, 2014

1. CERTIFICATION

PRODUCT: Wireless Cable Gateway
BRAND NAME: NETGEAR
MODEL NO.: C6250
TEST SAMPLE: ENGINEERING SAMPLE
APPLICANT: NETGEAR, Inc.
TESTED: Nov. 19 to 20, 2014
STANDARDS: FCC Part 2 (Section 2.1091)
KDB 447498 D03
IEEE C95.1

The above equipment (Model: C6250) has been tested by **Bureau Veritas Consumer Products Services (H.K.) Ltd., Taoyuan Branch**, and found compliance with the requirement of the above standards. The test record, data evaluation & Equipment Under Test (EUT) configurations represented herein are true and accurate accounts of the measurements of the sample's EMC characteristics under the conditions specified in this report.

Prepared By : C. Kuan , **Date:** Dec. 19, 2014
(Claire Kuan, Specialist)

Approved By : May Chen , **Date:** Dec. 19, 2014
(May Chen, Manager)

2. RF EXPOSURE LIMIT

LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

FREQUENCY RANGE (MHz)	ELECTRIC FIELD STRENGTH (V/m)	MAGNETIC FIELD STRENGTH (A/m)	POWER DENSITY (mW/cm ²)	AVERAGE TIME (minutes)
LIMITS FOR GENERAL POPULATION / UNCONTROLLED EXPOSURE				
300-1500	...	...	F/1500	30
1500-100,000	...	...	1.0	30

F = Frequency in MHz

3. MPE CALCULATION FORMULA

$$P_d = (P_{out} * G) / (4 * \pi * r^2)$$

where

P_d = power density in mW/cm²

P_{out} = output power to antenna in mW

G = gain of antenna in linear scale

π = 3.1416

r = distance between observation point and center of the radiator in cm

4. CLASSIFICATION

The antenna of this product, under normal use condition, is at least 24cm away from the body of the user. So, this device is classified as **Mobile Device**.

5. ANTENNA GAIN

The antennas provided to the EUT, please refer to the following table:

2.4GHz							
PCB Chain No.	Brand	Model	Antenna Gain(dBi) < including cable loss>	Frequency range	Antenna Type	Connector Type	Cable Length (mm)
Chain 0	Netgear	NA	3.8	2.4~2.4835 GHz	PCB	i-pex(MHF)	125
Chain 1	Netgear	NA	3.3	2.4~2.4835 GHz	PCB	i-pex(MHF)	250
5GHz							
PCB Chain No.	Brand	Model	Antenna Gain(dBi) < including cable loss>	Frequency range	Antenna Type	Connector Type	Cable Length (mm)
Chain 0	Netgear	NA	3.5	5.15~5.85 GHz	PCB	i-pex(MHF)	113
Chain 1	Netgear	NA	3.6	5.15~5.85 GHz	PCB	i-pex(MHF)	125
Chain 2	Netgear	NA	2.8	5.15~5.85 GHz	PCB	i-pex(MHF)	75

6. CALCULATION RESULT OF MAXIMUM CONDUCTED POWER

For 15.247(2.4GHz):

802.11b:

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
2412 ~ 2462	78.163	3.8	24	0.02590	1

802.11g:

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
2412 ~ 2462	144.901	6.56	24	0.09066	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.56\text{dBi}$

802.11n(HT20):

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
2412 ~ 2462	120.989	6.56	24	0.07570	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.56\text{dBi}$

802.11n(HT40):

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
2422 ~ 2452	35.396	6.56	24	0.02215	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20})^2 / 2] = 6.56\text{dBi}$

For 15.247(5GHz):

CDD Mode:

802.11a:

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5745 ~ 5825	594.541	8.08	24	0.52790	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$

Beamforming Mode:

802.11ac (VHT20)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5745 ~ 5825	596.397	8.08	24	0.52954	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$

802.11ac (VHT40)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5755 ~ 5795	583.372	8.08	24	0.51798	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$

802.11ac (VHT80)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5755	119.576	8.08	24	0.10617	1

Directional gain = $10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$

For 15.407(5GHz):

CDD Mode:

802.11a:

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5180 ~ 5240	295.272	8.08	24	0.26217	1

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$$

Beamforming Mode:

802.11ac (VHT20)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5180 ~ 5240	318.911	8.08	24	0.28316	1

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$$

802.11ac (VHT40)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5190 ~ 5230	372.052	8.08	24	0.33035	1

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$$

802.11ac (VHT80)

FREQUENCY (MHz)	CONDUCTED POWER (mW)	ANTENNA GAIN (dBi)	DISTANCE (cm)	POWER DENSITY (mW/cm ²)	LIMIT (mW/cm ²)
5210	63.742	8.08	24	0.05660	1

$$\text{Directional gain} = 10 \log[(10^{G1/20} + 10^{G2/20} + 10^{G3/20})^2 / 3] = 8.08\text{dBi}$$

CONCLUSION:

Both of the 2.4GHz and 5GHz WLAN can transmit simultaneously, the formula of calculated the MPE is:

$$\text{CPD}_1 / \text{LPD}_1 + \text{CPD}_2 / \text{LPD}_2 + \dots \text{etc.} < 1$$

CPD = Calculation power density

LPD = Limit of power density

Therefore, the worst-case situation is $0.09066 / 1 + 0.52954 / 1 = 0.6201$ which is less than "1". This confirmed that the device comply with FCC 1.1310 MPE limit.

--- END ---