

CEM compliance statement for Modular Transmitters (in Blue below)

§ 15.212 Modular transmitters.

(a) Single modular transmitters consist of a completely self-contained radiofrequency transmitter device that is typically incorporated into another product, host or device. Split modular transmitters consist of two components: a radio front end with antenna (or radio devices) and a transmitter control element (or specific hardware on which the software that controls the radio operation resides). All single or split modular transmitters are approved with an antenna. All of the following requirements apply, except as provided in paragraph (b) of this section.

(1) Single modular transmitters must meet the following requirements to obtain a modular transmitter approval.

(i) The radio elements of the modular transmitter must have their own shielding. The physical crystal and tuning capacitors may be located external to the shielded radio elements.

Shielding present -> Comply

(ii) The modular transmitter must have buffered modulation/data inputs (if such inputs are provided) to ensure that the module will comply with part 15 requirements under conditions of excessive data rates or over-modulation. **Comply**

(iii) The modular transmitter must have its own power supply regulation.

Yes, it has an inductor and capacitor to condition the regulated battery supply from the host unit Comply

(iv) The modular transmitter must comply with the antenna and transmission system requirements of §§ 15.203, 15.204(b) and 15.204(c). The antenna must either be permanently attached or employ a “unique” antenna coupler (at all connections between the module and the antenna, including the cable). The “professional installation” provision of § 15.203 is not applicable to modules but can apply to limited modular approvals under paragraph (b) of this section. **Antenna is pcb track ->Comply**

(v) The modular transmitter must be tested in a stand-alone configuration, i.e. , the module must not be inside another device during testing for compliance with part 15 requirements. Unless the transmitter module will be battery powered, it must comply with the AC line conducted requirements found in § 15.207. AC or DC power lines and data input/output lines connected to the module must not contain ferrites, unless they will be marketed with the module (see § 15.27(a)). The length of these lines shall be the length typical of actual use or, if that length is unknown, at least 10 centimeters to insure that there is no coupling between the case of the module and supporting equipment. Any accessories, peripherals, or support equipment connected to the module during testing shall be unmodified and commercially available (see § 15.31(i)). **Comply**

(vi) The modular transmitter must be equipped with either a permanently affixed label or must be capable of electronically displaying its FCC identification number. **Permanently affixed label fitted -> Comply**

(A) If using a permanently affixed label, the modular transmitter must be labelled with its own FCC identification number, and, if the FCC identification number is not visible when the module is installed inside another device, then the outside of the device into which the module is installed must also display a label referring to the enclosed module. This exterior label can use wording such as the following: “Contains Transmitter Module FCC ID: XYZMODEL1” or “Contains FCC ID: XYZMODEL1.” Any similar wording that expresses the same meaning may be used. The Grantee may either provide such a label, an example of which must be included in the application for equipment authorization, or, must provide adequate instructions along

with the module which explain this requirement. In the latter case, a copy of these instructions must be included in the application for equipment authorization. **Comply**

(B) If the modular transmitter uses an electronic display of the FCC identification number, the information must be readily accessible and visible on the modular transmitter or on the device in which it is installed. If the module is installed inside another device, then the outside of the device into which the module is installed must display a label referring to the enclosed module. This exterior label can use wording such as the following: "Contains FCC certified transmitter module(s)." Any similar wording that expresses the same meaning may be used. The user manual must include instructions on how to access the electronic display. A copy of these instructions must be included in the application for equipment authorization.

Electronic Display for FCC ID not used and external label fitted >Comply

(vii) The modular transmitter must comply with any specific rules or operating requirements that ordinarily apply to a complete transmitter and the manufacturer must provide adequate instructions along with the module to explain any such requirements. A copy of these instructions must be included in the application for equipment authorization.

Comply

(viii) The modular transmitter must comply with any applicable RF exposure requirements in its final configuration. **Comply**

(2) Split modular transmitters must meet the requirements in paragraph (a)(1) of this section, excluding paragraphs (a)(1)(i) and (a)(1)(v), and the following additional requirements to obtain a modular transmitter approval. **Not split module -> N/A**

(i) Only the radio front end must be shielded. The physical crystal and tuning capacitors may be located external to the shielded radio elements. The interface between the split sections of the modular system must be digital with a minimum signalling amplitude of 150 mV peak-to-peak. **Not split module -> N/A**

(ii) Control information and other data may be exchanged between the transmitter control elements and radio front end. **Not split module -> N/A**

(iii) The sections of a split modular transmitter must be tested installed in a host device(s) similar to that which is representative of the platform(s) intended for use. **Not split module -> N/A**

(iv) Manufacturers must ensure that only transmitter control elements and radio front end components that have been approved together are capable of operating together. The transmitter module must not operate unless it has verified that the installed transmitter control elements and radio front end have been authorized together. Manufacturers may use means including, but not limited to, coding in hardware and electronic signatures in software to meet these requirements, and must describe the methods in their application for equipment authorization. **Not split module -> N/A**

(b) A limited modular approval may be granted for single or split modular transmitters that do not comply with all of the above requirements, e.g., shielding, minimum signalling amplitude, buffered modulation/data inputs, or power supply regulation, if the manufacturer can demonstrate by alternative means in the application for equipment authorization that the modular transmitter meets all the applicable part 15 requirements under the operating conditions in which the transmitter will be used. Limited modular approval also may be granted in those instances where compliance with RF exposure rules is demonstrated only for particular product configurations. The applicant for certification must state how control of the

end product into which the module will be installed will be maintained such that full compliance of the end product is always ensured.

[List of hosts and control of the module](#)

Host Getac PS336

CEM Systems S3040 read head module assembly is made, assembled and tested in Northern Ireland by a local electronics manufacture for CEM Systems only. The manufactured units are then shipped to CEM Systems where they are mated to the Getac PS336 hand held unit and programmed with the firmware application and then given a final test before being packaged as a single unit in a single box. CEM Systems do not sell the S3040 read head module to any other manufacturer. The interface on the S3040 read head module is specifically designed to fit the Getac PS336 hand held unit and can not be fitted into anything else. Therefore the only configuration is for the S3040 Read Head module to be mated to the Getac PS336 hand held unit. CEM Systems will not be subcontracting manufacture out of our control. Comply!