

Block Diagram

The EUT-11W, EUT-15W, EUT-20W, EUT-24W, EUTS-11W, EUTS-15W, EUTS-20W, EUTS-24W, are the same, except the following component list different:

Models	Components/ rating										
	Tube	R4/R7	C5	C6	C7	C2	Fuse	L1	L2	Q1, 2	T1
EUT-11W	11W, 3U	10 Ω	473	332	222	10uF	750mA	L8 $\times$ 10, 0.23	EE16, 220T, 1.88mH	13003	2T: 4T: 4T
EUT-15W	15W, 3U	10 Ω	473	332	222	10uF	750mA	L8 $\times$ 10, 0.23	EE16, 195T, 1.82mH	13003	2T: 4T: 4T
EUT-20W	20W, 3U	15 Ω	104	222	682	22uF	1A	L9 $\times$ 12, 0.31	EE19, 160T, 1.38mH	13005	2T: 3T: 3T
EUT-24W	24W, 3U	15 Ω	104	222	682	22uF	1A	L9 $\times$ 12, 0.31	EE19, 150T, 1.22mH	13005	2T: 3T: 3T
EUTS-11W	11W, Spiral	10 Ω	473	332	222	10uF	750mA	L8 $\times$ 10, 0.23	EE16, 220T, 1.88mH	13003	2T: 4T: 4T
EUTS-15W	15W, Spiral	10 Ω	473	332	222	10uF	750mA	L8 $\times$ 10, 0.23	EE16, 180T, 1.80mH	13003	2T: 4T: 4T
EUTS-20W	20W, Spiral	15 Ω	104	222	682	22uF	1A	L9 $\times$ 12, 0.31	EE19, 160T, 1.38mH	13005	2T: 3T: 3T
EUTS-24W	24W, Spiral	15 Ω	104	222	682	22uF	1A	L9 $\times$ 12, 0.31	EE19, 150T, 1.22mH	13005	2T: 3T: 3T