

I-Tel Corporation

Application
For
Certification

5.8GHz/2.4GHz 40 Channel Analog Modulation Cordless Phone with
Caller ID - Handset

(FCC ID: QVF0701H)

07142322
KL/ ac
August 1, 2007

- The evaluation data of the report will be kept for 3 years from the date of issuance.
- This report is for the exclusive use of Intertek's Client and is provided pursuant to the agreement between Intertek and its Client. Intertek's responsibility and liability are limited to the terms and conditions of the agreement. Intertek assumes no liability to any party, other than to the Client in accordance with the agreement, for any loss, expense or damage occasioned by the use of this report. Only the Client is authorized to permit copying or distribution of this report and then only in its entirety. Any use of the Intertek name or one of its marks for the sale or advertisement of the tested material, product or service must first be approved in writing by Intertek. The observations and test results in this report are relevant only to the sample tested. This report by itself does not imply that the material, product, or service is or has ever been under an Intertek certification program.

Intertek Testing Services Hong Kong Ltd.

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.
Tel: (852) 2173 8888 Fax: (852) 2785 5487 Website: www.hk.intertek-etslsemko.com

INTERTEK TESTING SERVICES

LIST OF EXHIBITS

INTRODUCTION

| | |
|-------------------|---------------------------|
| <i>EXHIBIT 1:</i> | General Description |
| <i>EXHIBIT 2:</i> | System Test Configuration |
| <i>EXHIBIT 3:</i> | Emission Results |
| <i>EXHIBIT 4:</i> | Equipment Photographs |
| <i>EXHIBIT 5:</i> | Product Labelling |
| <i>EXHIBIT 6:</i> | Technical Specifications |
| <i>EXHIBIT 7:</i> | Instruction Manual |
| <i>EXHIBIT 8:</i> | Security Code Information |
| <i>EXHIBIT 9:</i> | Confidentiality Request |

INTERTEK TESTING SERVICES

MEASUREMENT/TECHNICAL REPORT

**I-Tel Corporation - MODEL: 35293-4, 35290, 35291, 35292,
MB5293, MB5290, MB5291, MB5292**

FCC ID: QVF0701H

This report concerns (check one:) Original Grant Class II Change

Equipment Type : DXT - Cordless Telephone

Deferred grant requested per 47 CFR
0.457(d)(1)(ii)? Yes No

If yes, defer until : _____
date

Company Name agrees to notify the Commission by:

date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37 ? Yes No

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [05-04-07]

Report prepared by: Lam Chun Cheong, Kenneth
Intertek Testing Services Hong Kong Ltd.
2/F., Garment Centre,
576 Castle Peak Road,
Kowloon, Hong Kong.
Phone : 852-2173-8474
Fax: 852-2741-1693

INTERTEK TESTING SERVICES

Table of Contents

| | |
|--|----|
| 1.0 General Description | 2 |
| 1.1 Product Description | 2 |
| 1.2 Related Submittal(s) Grants | 3 |
| 1.3 Test Methodology | 3 |
| 1.4 Test Facility | 3 |
| 2.0 System Test Configuration | 5 |
| 2.1 Justification | 5 |
| 2.2 EUT Exercising Software | 5 |
| 2.3 Support Equipment List and Description | 6 |
| 2.4 Measurement Uncertainty | 7 |
| 2.5 Equipment Modification | 7 |
| 3.0 Emission Results | 9 |
| 3.1 Field Strength Calculation | 10 |
| 3.2 Radiated Emission Configuration Photograph - Handset | 11 |
| 3.3 Radiated Emission Data - Handset | 12 |
| 3.4 Radiated Emission on the Bandedge | 15 |
| 4.0 Equipment Photographs | 17 |
| 5.0 Product Labelling | 19 |
| 6.0 Technical Specifications | 21 |
| 7.0 Instruction Manual | 23 |
| 8.0 Security Code Information | 25 |
| 9.0 Confidentiality Request | 27 |

INTERTEK TESTING SERVICES

List of attached file

| Exhibit type | File Description | filename |
|-----------------------|-------------------------------|---------------------|
| Cover Letter | Confidentiality Request | request.pdf |
| Test Report | Test Report | report.pdf |
| Operation Description | Technical Description | descri.pdf |
| Test Setup Photo | Radiated & Conducted Emission | config photos.doc |
| Test Report | Emission Plot | emission.pdf |
| External Photo | External Photo | external photos.doc |
| Internal Photo | Internal Photo | internal photos.doc |
| Block Diagram | Block Diagram | block.pdf |
| Schematics | Circuit Diagram | circuit.pdf |
| ID Label/Location | Label Artwork and Location | label.pdf |
| User Manual | User Manual | manual.pdf |

INTERTEK TESTING SERVICES

EXHIBIT 1
GENERAL DESCRIPTION

INTERTEK TESTING SERVICES

1.0 General Description

1.1 Product Description

The 35293-4 is a 5.8GHz/2.4GHz 40 Channel Analog Modulation Cordless Phone with Caller ID. Base Unit and handset operate at frequency of 5727.150MHz to 5733.000MHz and 2403.500MHz to 2407.400MHz respectively. The unit is capable of either tone or pulse dialing. The internal power supply's isolation is accomplished through a power transformer having an adequate dielectric rating. The circuit wiring is consistent under the requirement of part 68.

The handset unit consists of a keypad with twelve standard keys (0,...9,*,#), seven function keys (OFF, Redial/Pause, Channel/Delete, Flash/Edit, Memo, Menu, Call Transfer/Save). A Talk key is provided to control pick/release telephone line in a toggle base.

The base unit has a page key, which is used to page the handset unit.

The antennas used in base unit and handset are integral, and the tested sample is a prototype.

The Model: 35290, 35291, 35292, MB5293, MB5290, MB5291, and MB5292 are the same as the Model: 35293-4 in hardware aspect. The difference in model number serves marketing strategy.

The circuit description is saved with filename: descri.pdf

Connection between the device and the telephone network is accomplished through the use of USOC RJ11C in the 2-wire loop calling central office line.

INTERTEK TESTING SERVICES

1.2 Related Submittal(s) Grants

This is a single application for Certification of Handset of a cordless telephone system. The FCC ID of the associated base is FCC ID: QVF0701 and has been filed at the same time as this application. This specific report details the emission characteristics of a transmitter. A Verification report has been prepared for the digital device portion of each device. The device is also subject to Part 68 Registration.

1.3 Test Methodology

Radiated emission measurements was performed according to the procedures in ANSI C63.4 (2003). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

1.4 Test Facility

The open area test site used to collect the radiated data and conducted data are located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

INTERTEK TESTING SERVICES

EXHIBIT 2
SYSTEM TEST CONFIGURATION

INTERTEK TESTING SERVICES

2.0 System Test Configuration

2.1 Justification

For emissions testing, the equipment under test (EUT) was setup to transmit continuously to simplify the measurement methodology. Care was taken to ensure proper power supply voltages during testing. During testing, all cables were manipulated to produce worst case emissions. The handset was powered by a fully charged battery.

For the measurements, the EUT is attached to a plastic stand if necessary and placed on the wooden turntable. If the base unit attaches to peripherals, they are connected and operational (as typical as possible). The base unit is remotely located as far from the antenna and the handset as possible to ensure full power transmission from the handset. Else, the handset is wired to transmit full power without modulation.

The signal is maximized through rotation and placement in the three orthogonal axes. The antenna height and polarization are varied during the search for maximum signal level. The antenna height is varied from 1 to 4 meters. Radiated emissions are taken at three meters unless the signal level is too low for measurement at that distance. If necessary, a pre-amplifier is used and/or the test is conducted at a closer distance.

All readings are extrapolated back to the equivalent three meter reading using inverse scaling with distance. Analyzer resolution is 100 kHz or greater for frequencies below 1000 MHz. The resolution is 1 MHz or greater for frequencies above 1000 MHz. The spurious emissions more than 20 dB below the permissible value are not reported.

Radiated emission measurement were performed the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower.

2.2 EUT Exercising Software

The EUT exercise program used during radiated and conducted testing was designed to exercise the various system components in a manner similar to a typical use.

INTERTEK TESTING SERVICES

2.3 Support Equipment List and Description

The FCC ID's for all equipment, plus descriptions of all cables used in the tested system are:

HARDWARE:

A battery (provided with the unit) were used to power the device. Their description are listed below.

- (1) Handset: A "Ni-Cd" type rechargeable battery (3.6V 400mAh)

CABLES:

There are no special accessories necessary for compliance of this product.

OTHERS:

There are no special accessories necessary for compliance of this product.

INTERTEK TESTING SERVICES

2.4 Measurement Uncertainty

When determining of the test conclusion, the Measurement Uncertainty test has been considered.

Uncertainty and Compliance - Unless the standard specifically states that measured values are to be extended by the measurement uncertainty in determining compliance, all compliance determinations are based on the actual measured value.

2.5 Equipment Modification

Any modifications installed previous to testing by I-Tel Corporation will be incorporated in each production model sold/leased in the United States.

No modifications were installed by ETL Division, Intertek Testing Services Hong Kong Ltd.

All the items listed under section 2.0 of this report are confirmed by:

Confirmed by:

*Lam Chun Cheong, Kenneth
Assistant Supervisor
Intertek Testing Services
Agent for I-Tel Corporation*



Signature

August 1, 2007 Date

INTERTEK TESTING SERVICES

EXHIBIT 3
EMISSION RESULTS

INTERTEK TESTING SERVICES

3.0 Emission Results

Data is included of the worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

INTERTEK TESTING SERVICES

3.1 Field Strength Calculation

The field strength is calculated by adding the Antenna Factor and Cable Factor, and subtracting the Amplifier Gain (if any) from the measured reading. The basic equation with a sample calculation is as follows:

$$FS = RA + AF + CF - AG$$

where FS = Field Strength in $\text{dB}\mu\text{V}/\text{m}$

RA = Receiver Amplitude (including preamplifier) in $\text{dB}\mu\text{V}$

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

In the following table(s), the reading shown on the data table reflects the preamplifier gain. An example for the calculations in the following table is as follows:-

$$FS = RR + LF$$

where FS = Field Strength in $\text{dB}\mu\text{V}/\text{m}$

RR = $RA - AG$ in $\text{dB}\mu\text{V}$

LF = $CF + AF$ in dB

Assume a receiver reading of 52.0 $\text{dB}\mu\text{V}$ is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted, giving a field strength of 32 $\text{dB}\mu\text{V}/\text{m}$. This value in $\text{dB}\mu\text{V}/\text{m}$ was converted to its corresponding level in $\mu\text{V}/\text{m}$.

$$RA = 52.0 \text{ dB}\mu\text{V}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$FS = RR + LF$$

$$FS = 23 + 9 = 32 \text{ dB}\mu\text{V}/\text{m}$$

$$RR = 23.0 \text{ dB}\mu\text{V}$$

$$LF = 9.0 \text{ dB}$$

$$\text{Level in } \mu\text{V}/\text{m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V}/\text{m})/20] = 39.8 \mu\text{V}/\text{m}$$

INTERTEK TESTING SERVICES

3.2 Radiated Emission Configuration Photograph - Handset

Worst Case Radiated Emission

at 4807.000 MHz

For electronic filing, the worst case radiated emission configuration photographs are saved with filename: config photos.doc

INTERTEK TESTING SERVICES

3.3 Radiated Emission Data - Handset

The data on the following pages list the significant emission frequencies, the limit and the margin of compliance.

Judgement : Passed by 1.6 dB

TEST PERSONNEL:



Tester Signature

Jess Tang, Lead Engineer
Typed/Printed Name

August 1, 2007
Date

INTERTEK TESTING SERVICES

Company: I-Tel Corporation
Model: 35293-4
Mode : TX-Channel 1

Date of Test: June 26-July 9, 2007

Table 1, Handset

Radiated Emissions

| Polarization | Frequency (MHz) | Reading (dB μ V) | Pre-Amp (dB) | Antenna Factor (dB) | Net at 3m (dB μ V/m) | Limit at 3m (dB μ V/m) | Margin (dB) |
|--------------|-----------------|----------------------|--------------|---------------------|--------------------------|----------------------------|-------------|
| V | 2403.500 | 89.6 | 33 | 29.4 | 86.0 | 94 | -8.0 |
| H | *4807.000 | 50.5 | 33 | 34.9 | 52.4 | 54 | -1.6 |
| H | 7210.500 | 44.3 | 33 | 37.9 | 49.2 | 54 | -4.8 |
| H | 9614.000 | 41.2 | 33 | 40.4 | 48.6 | 54 | -5.4 |
| H | *12017.500 | 40.7 | 33 | 40.5 | 48.2 | 54 | -5.8 |

NOTES: 1. Peak detector is used for the emission measurement.

2. All measurements were made at 3 meters. Radiated emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other radiated emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

5. Emissions radiated outside of the specified frequency bands, except harmonics, are attenuated by 50 dB below the level of the fundamental or to the general radiated emission limits in Section 15.209, whichever is the lesser attenuation, which meet the requirement of part 15.249(d).

* Emission within the restricted band meets the requirement of part 15.205.

Test Engineer: Jess Tang

INTERTEK TESTING SERVICES

Company: I-Tel Corporation
Model: 35293-4
Mode : TX-Channel 40

Date of Test: June 26-July 9, 2007

Table 2, Handset

Radiated Emissions

| Polarization | Frequency (MHz) | Reading (dB μ V) | Pre-Amp (dB) | Antenna Factor (dB) | Net at 3m (dB μ V/m) | Limit at 3m (dB μ V/m) | Margin (dB) |
|--------------|-----------------|----------------------|--------------|---------------------|--------------------------|----------------------------|-------------|
| V | 2407.400 | 89.4 | 33 | 29.4 | 85.8 | 94 | -8.2 |
| H | *4814.800 | 50.4 | 33 | 34.9 | 52.3 | 54 | -1.7 |
| H | 7222.200 | 44.4 | 33 | 37.9 | 49.3 | 54 | -4.7 |
| H | 9629.600 | 41.1 | 33 | 40.4 | 48.5 | 54 | -5.5 |
| H | *12037.000 | 40.7 | 33 | 40.5 | 48.2 | 54 | -5.8 |

NOTES: 1. Peak detector is used for the emission measurement.

2. All measurements were made at 3 meters. Radiated emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other radiated emissions than those reported were detected at a test distance of 0.3-meter.

3. Negative value in the margin column shows emission below limit.

4. Horn antenna is used for the emission over 1000MHz.

5. Emissions radiated outside of the specified frequency bands, except harmonics, are attenuated by 50 dB below the level of the fundamental or to the general radiated emission limits in Section 15.209, whichever is the lesser attenuation, which meet the requirement of part 15.249(d).

* Emission within the restricted band meets the requirement of part 15.205.

Test Engineer: Jess Tang

INTERTEK TESTING SERVICES

3.4 Radiated Emission on the Bandedge

From the following plots, they show that the fundamental emissions are confined in the specified band (2400MHz and 2483.5MHz). In case of the fundamental emissions are within two standard bandwidths from the bandedge, the delta measurement technique is used for determining bandedge compliance. Standard bandwidth is the bandwidth specified by ANSI C63.4 (2003) for frequency being measured.

Emissions radiated outside of the specified frequency bands, except harmonics, are attenuated by 50 dB below the level of the fundamental or to the general radiated emission limits in Section 15.209, whichever is the lesser attenuation, which meet the requirement of part 15.249(d).

Please refer to the following plots for radiated emission on the bandedge:

Plot H1A: Handset - Low Channel Emissions

Plot H1B: Handset - High Channel Emissions

For electronic filing, the above plots are saved with filename: emission.pdf

INTERTEK TESTING SERVICES

EXHIBIT 4
EQUIPMENT PHOTOGRAPHS

INTERTEK TESTING SERVICES

4.0 Equipment Photographs

For electronic filing, the photographs are saved with filename: external photos.doc & internal photos.doc

INTERTEK TESTING SERVICES

EXHIBIT 5
PRODUCT LABELLING

INTERTEK TESTING SERVICES

5.0 Product Labelling

For electronic filing, the FCC ID label artwork and location is saved with filename: label.pdf

INTERTEK TESTING SERVICES

EXHIBIT 6
TECHNICAL SPECIFICATIONS

INTERTEK TESTING SERVICES

6.0 Technical Specifications

For electronic filing, the block diagram and circuit diagram are saved with filename: block.pdf and circuit.pdf respectively.

INTERTEK TESTING SERVICES

EXHIBIT 7
INSTRUCTION MANUAL

INTERTEK TESTING SERVICES

7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

The required FCC Information to the User is stated on P.9-10 of the Instruction Manual.

This manual will be provided to the end-user with each unit sold/leased in the United States.

INTERTEK TESTING SERVICES

EXHIBIT 8
SECURITY CODE INFORMATION

INTERTEK TESTING SERVICES

8.0 Security Code Information

These models have an internal security code with 65,000 possible combination. Each time the HANDSET is placed on the BASE UNIT, the code is randomly set to a new combination.

The code allows your base and handset to recognize each other so that other cordless telephones will not make calls on your line.

If the AC adaptor is disconnected or a loss of power occurs while the handset is away from the base unit, the security code will be lost and the phone will be inoperable. If this occurs, reconnect the AC adaptor and return the handset to the base unit so that the security code is reset.

Digital security coding will also eliminate the "false" ringing associated with cordless telephones not equipped with this feature.

INTERTEK TESTING SERVICES

EXHIBIT 9
CONFIDENTIALITY REQUEST

INTERTEK TESTING SERVICES

9.0 **Confidentiality Request**

For electronic filing, a preliminary copy of the Confidentiality Request is saved with filename: request.pdf