

**BAO Limited**

Application  
For  
Certification  
**(FCC ID: QWS8226)**

Transmitter

Sample Description : Smart Talking Truck  
Model : 8226

We hereby certify that the sample of the above item is considered to comply with the requirements of FCC Part 15, Subpart C for Intentional Radiator, mention 47 CFR [12-8-2003]

0408440  
WN/at  
June 30, 2004

- The test results reported in this report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

FCC ID : QWS8226

## INTERTEK TESTING SERVICES

---

---

### LIST OF EXHIBITS

#### *INTRODUCTION*

<i>EXHIBIT 1:</i>	General Description
<i>EXHIBIT 2:</i>	System Test Configuration
<i>EXHIBIT 3:</i>	Emission Results
<i>EXHIBIT 4:</i>	Equipment Photographs
<i>EXHIBIT 5:</i>	Product Labelling
<i>EXHIBIT 6:</i>	Technical Specifications
<i>EXHIBIT 7:</i>	Instruction Manual
<i>EXHIBIT 8:</i>	Miscellaneous Information

# INTERTEK TESTING SERVICES

---

## MEASUREMENT/TECHNICAL REPORT

**BAO Limited - MODEL: 8226**  
**FCC ID: QWS8226**

**June 30, 2004**

This report concerns (check one:)      Original Grant       Class II Change

Equipment Type: Low Power Transmitter (example: computer, printer, modem, etc.)

---

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)?      Yes       No

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37?      Yes       No

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [12-8-2003 Edition] provision.

Report prepared by:

Wilbur Ng  
Intertek Testing Services  
2/F., Garment Center,  
576, Castle Peak Road,  
HONG KONG  
Phone: 852-2173-8502  
Fax: 852-2742-9149

# INTERTEK TESTING SERVICES

---

---

## Table of Contents

<b>1.0</b>	<b><u>General Description</u></b>	2
1.1	Product Description	2
1.2	Related Submittal(s) Grants	2
1.3	Test Methodology	3
1.4	Test Facility	3
<b>2.0</b>	<b><u>System Test Configuration</u></b>	5
2.1	Justification	5
2.2	EUT Exercising Software	5
2.3	Special Accessories	5
2.4	Equipment Modification	6
2.5	Support Equipment List and Description	6
<b>3.0</b>	<b><u>Emission Results</u></b>	8
3.1	Field Strength Calculation	9
3.1	Field Strength Calculation (cont'd)	10
3.2	Radiated Emission Configuration Photograph	11
3.3	Radiated Emission Data	12
<b>4.0</b>	<b><u>Equipment Photographs</u></b>	16
<b>5.0</b>	<b><u>Product Labelling</u></b>	18
<b>6.0</b>	<b><u>Technical Specifications</u></b>	20
<b>7.0</b>	<b><u>Instruction Manual</u></b>	22
<b>8.0</b>	<b><u>Miscellaneous Information</u></b>	24
8.1	Measured Bandwidth	25
8.2	Emission Test Procedures	26
8.2	Emission Test Procedures (Cont'd)	27

## INTERTEK TESTING SERVICES

---

---

### List of attached file

Exhibit type	File Description	filename
Test Report	Test Report	report.pdf
Operation Description	Technical Description	descri.pdf
Test Setup Photo	Radiated Emission	radiated photos.pdf
Test Report	Bandwidth Plot	bw.pdf
External Photo	External Photo	external photos.pdf
Internal Photo	Internal Photo	Internal photos1-2.pdf Internal photos2-2.pdf
Block Diagram	Block Diagram	block.pdf
Schematics	Circuit Diagram	circuit.pdf
ID Label/Location	Label Artwork and Location	label.pdf
User Manual	User Manual	manual.pdf

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 1**

**GENERAL DESCRIPTION**

# INTERTEK TESTING SERVICES

---

## 1.0 General Description

### 1.1 Product Description

The equipment under test (EUT) is a transmitter for an Inductive Toy operating at 13.56 MHz which is controlled by a crystal. The EUT includes a Truck and Four Cars with tag inside. The Truck is powered by four AA batteries, it has a power switch and five buttons. When the power switch is “ON”, the biggest blue button is to generate the truck engine sound. When one of the remain buttons is pressed, the Truck will generate a RF energy to the car where places on it. Then, the car will transmit a signal back to the Truck and Truck will generate various sound effect depend on the game mode selected. The detail is shown in the following. When the green button is pressed, the truck will count the number of cars where place on it and reports to the user. When the yellow button is pressed, the truck will generate various engine sound depend on the car places on it. When the blue button is pressed, the truck will instruct the user to park the assigned colour of car on it. When the red button is pressed, the truck will instruct the user to park the car on the parking ramp.

The brief circuit description is saved with filename : descri.pdf

### 1.2 Related Submittal(s) Grants

The receiver for this transmitter is exempted form the Part 15 technical rules per 15.101(b).

## INTERTEK TESTING SERVICES

---

---

### 1.3 Test Methodology

The radiated emission measurements were performed according to the procedures in ANSI C63.4 (2001). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the "**Justification Section**" of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the emission data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 2**

**SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2001).

The truck was powered by four new AA batteries during test.

The tag was powered by the emitted electromagnetic radiation from the truck.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The truck was operated with the four cars (four tags) which were directly placed on top of the truck. The whole system was placed in the center of the turntable.

The whole system was placed in the center of the ground plane.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT were placed on the ground and rotate through 360°, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes.

The measurement results indicated that only one tag (the green car) placed on the truck produced the highest emission.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device.

#### 2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by BAO Limited will be incorporated in each production model sold/leased in the United States.

Modifications were installed by Intertek Testing Services.

### 2.5 Support Equipment List and Description

This product was tested in a standalone configuration.

All the items listed under section 2.0 of this report are

*Confirmed by:*

*Wilbur Ng  
Manager  
Intertek Testing Services  
Agent for BAO Limited*



\_\_\_\_\_  
Signature

June 30, 2004 \_\_\_\_\_ Date

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 3**

**EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

---

### 3.0 **Emission Results**

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in  $\text{dB}\mu\text{V}/\text{m}$

RA = Receiver Amplitude (including preamplifier) in  $\text{dB}\mu\text{V}$

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation (cont'd)

#### Example

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 62.0 \text{ dB}\mu\text{V}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$PD = 0 \text{ dB}$$

$$AV = -10 \text{ dB}$$

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32 \text{ dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

## **INTERTEK TESTING SERVICES**

---

---

### **3.2 Radiated Emission Configuration Photograph**

**Worst Case Radiated Emission**

**108.529 and 135.642 MHz**

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.pdf

## INTERTEK TESTING SERVICES

---

---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 9.0 dB

### ***TEST PERSONNEL:***



---

*Signature*

Ivan Y. M. Wong, Compliance Engineer

*Typed/Printed Name*

June 30, 2004

*Date*

## INTERTEK TESTING SERVICES

---

Applicant: BAO Limited  
Model: 8226

Date of Test: June 3, 2004

Table 1  
**Radiated Emissions**

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Distance Factor (-dB)	Net at 3m (dB $\mu$ V/m)	Calculated at 30m (dB $\mu$ V/m)	Limit at 30m (dB $\mu$ V/m)	Margin (dB)
O	13.561	44.1	9.3	16.0	40.0	37.4	-2.6	84.0	-86.6
O	27.109	31.8	14.0	16.0	40.0	29.8	-10.2	29.5	-39.7

Table 2  
**Radiated Emissions**

Polarization	Frequency (MHz)	Reading (dB $\mu$ V)	Antenna Factor (dB)	Pre-Amp Gain (dB)	Net at 3m (dB $\mu$ V/m)	Limit at 3m (dB $\mu$ V/m)	Margin (dB)
V	40.581	34.5	10	16.0	28.5	40.0	-11.5
V	54.254	33.4	11	16.0	28.4	40.0	-11.6
V	67.851	35.8	8	16.0	27.8	40.0	-12.2
H	81.390	38.6	7	16.0	29.6	40.0	-10.4
H	108.529	37.5	13	16.0	34.5	43.5	-9.0
H	122.078	34.7	13	16.0	31.7	43.5	-11.8
H	135.642	37.5	13	16.0	34.5	43.5	-9.0
H	149.201	33.7	13	16.0	30.7	43.5	-12.8

Notes:

1. Peak Detector Data unless otherwise stated.
2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3 meter distance were measured at 0.3 meter and an inverse proportional extrapolation was performed to compare the signal level to the 3 meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3 meter.
3. Negative value in the margin column shows emission below limit.
4. Loop antenna are used for emissions below 30 MHz.
5. Worst case emissions were measured.

\*Emission within the restricted band meets the requirement of part 15.205. The corresponding limit as per 15.209 is based on Quasi peak detector data for frequencies below 1000 MHz and peak detector data with average factor for frequencies over 1000 MHz.

Test Engineer: Ivan Y. M. Wong

## INTERTEK TESTING SERVICES

---

Applicant: BAO Limited  
Model: 8226

Date of Test: June 3, 2004

### FCC Part 15 Section 15.225(C)

**Data Table**  
**Frequency tolerance of Transmitter**  
**(Temperature Variation : -20°C to +50°C)**

Operating frequency			13.563778 MHz	
Test Voltage (V)	Temperature (°C)	Measured frequency (MHz)	Frequency shift (%)	Limit (%)
6	+50	13.563688	-0.00066	±0.01
6	+40	13.563733	-0.00033	±0.01
6	+30	13.563768	-0.00007	±0.01
6	+20	13.563778	0	±0.01
6	+10	13.563788	+0.00007	±0.01
6	0	13.563798	+0.00015	±0.01
6	-10	13.563793	+0.00011	±0.01
6	-20	13.563753	-0.00018	±0.01

We found that the EUT met the requirement of FCC Part 15 Section 15.225(C).

---

Test Engineer: Ivan Y. M. Wong

---

FCC ID: QWS8226

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 4**

**EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

---

### 4.0 Equipment Photographs

For electronic filing, the photographs are saved with filename:  
external photos.pdf, internal photos1-2.pdf and internal photos2-2.pdf

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 5**

**PRODUCT LABELLING**

## INTERTEK TESTING SERVICES

---

---

### 5.0 Product Labelling

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 6**

**TECHNICAL SPECIFICATIONS**

## INTERTEK TESTING SERVICES

---

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematics are saved with filename: block.pdf and circuit.pdf

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 7**

**INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf

---

---

**INTERTEK TESTING SERVICES**

---

**EXHIBIT 8**

**MISCELLANEOUS INFORMATION**

## INTERTEK TESTING SERVICES

---

---

### 8.0 Miscellaneous Information

This miscellaneous information includes details of the measured bandwidth and the test procedure.

## INTERTEK TESTING SERVICES

---

---

### 8.1 Measured Bandwidth

The plot saved in bw.pdf which shows the fundamental emission is confined in the specified band. The emission of the fundamental is  $-2.6 \text{ dB}\mu\text{V/m}$  and it is below the limit of  $50.5 \text{ dB}\mu\text{V/m}$  in the range of (13.410 – 13.553 MHz) and (13.710 - 14.010 MHz) and the limit of  $40.5 \text{ dB}\mu\text{V/m}$  in the frequency range of (13.110 – 14.410 MHz) and (13.710 – 14.010 MHz). In the frequency range from 13.110 – 14.010 MHz, we cannot find any emission higher than the fundamental emission. Therefore they meet the requirement of Section 15.225(a), (b), (c), & (d).

Figure 8.1 Bandwidth

## INTERTEK TESTING SERVICES

---

### 8.2 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 2001.

The transmitting equipment under test (EUT) is placed on the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The antenna height and polarization are varied during the testing to search for maximum signal levels.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 150 kHz to 30 MHz.

## INTERTEK TESTING SERVICES

---

### 8.2 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements are made as described in ANSI C63.4 - 2001.

The IF bandwidth used for measurement of radiated signal strength was 10 kHz for emission below 30 MHz and 120 kHz for emission from 30 MHz to 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.2). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the restricted bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, but those measurements taken at a closer distance are so marked.

When determining the test result, the Measurement Uncertainty of the test has been considered.