































Appendix B. AC Conducted Emission Test Results





Test Engineer :	Nathon	Temperature :	22~24°C
		Relative Humidity :	44~50%
Test Voltage :	120Vac / 60Hz	Phase :	Neutral
Remark :	All emissions not reported here are more than 10 dB below the prescribed limit.		



Site : CO02-SZ
Condition : FCC 15E_QP LISN_2025-N NEUTRAL

	Freq	Level	Over	Limit	Read	LISN	Cable	Remark
	MHz	dBuV	Limit	Line	Level	Factor	Loss	
			dB	dBuV	dBuV	dB	dB	
1	0.16	32.10	-23.55	55.65	12.29	9.62	10.19	Average
2 *	0.16	51.90	-13.75	65.65	32.09	9.62	10.19	QP
3	0.18	32.19	-22.14	54.33	12.20	9.81	10.18	Average
4	0.18	47.59	-16.74	64.33	27.60	9.81	10.18	QP
5	0.23	27.82	-24.53	52.35	8.00	9.63	10.19	Average
6	0.23	40.32	-22.03	62.35	20.50	9.63	10.19	QP
7	0.31	27.82	-22.11	49.93	7.80	9.81	10.21	Average
8	0.31	38.52	-21.41	59.93	18.50	9.81	10.21	QP
9	0.50	27.25	-18.76	46.01	7.40	9.61	10.24	Average
10	0.50	37.45	-18.56	56.01	17.60	9.61	10.24	QP
11	0.55	28.26	-17.74	46.00	8.39	9.63	10.24	Average
12	0.55	36.46	-19.54	56.00	16.59	9.63	10.24	QP

Note:

- Level(dBμV) = Read Level(dBμV) + LISN Factor(dB) + Cable Loss(dB)
- Over Limit(dB) = Level(dBμV) – Limit Line(dBμV)



Appendix C. Radiated Spurious Emission

Test Engineer :	ZhangXu	Relative Humidity :	48~49%
		Temperature :	24°C~25°C

Radiated Spurious Emission Test Modes

Mode	Band	Band (GHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 1	U-NII-1	5.15-5.25	CDD8+9	802.11a	36	5180	6Mbps	-	-
Mode 2	U-NII-1	5.15-5.25	CDD8+9	802.11a	44	5220	6Mbps	-	-
Mode 3	U-NII-1	5.15-5.25	CDD8+9	802.11a	48	5240	6Mbps	-	-
Mode 4	U-NII-2A	5.25-5.35	CDD8+9	802.11a	52	5260	6Mbps	-	-
Mode 5	U-NII-2A	5.25-5.35	CDD8+9	802.11a	60	5300	6Mbps	-	-
Mode 6	U-NII-2A	5.25-5.35	CDD8+9	802.11a	64	5320	6Mbps	-	-
Mode 7	U-NII-2C	5.47-5.725	CDD8+9	802.11a	100	5500	6Mbps	-	-
Mode 8	U-NII-2C	5.47-5.725	CDD8+9	802.11a	116	5580	6Mbps	-	-
Mode 9	U-NII-2C	5.47-5.725	CDD8+9	802.11a	140	5700	6Mbps	-	-
Mode 10	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE20	36	5180	MCS0	-	-
Mode 11	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE20	44	5220	MCS0	-	-
Mode 12	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE20	48	5240	MCS0	-	-
Mode 13	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE20	52	5260	MCS0	-	-
Mode 14	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE20	60	5300	MCS0	-	-
Mode 15	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE20	64	5320	MCS0	-	-
Mode 16	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE20	100	5500	MCS0	-	-
Mode 17	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE20	116	5580	MCS0	-	-
Mode 18	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE20	140	5700	MCS0	-	-
Mode 19	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE40	38	5190	MCS0	-	-
Mode 20	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE40	46	5230	MCS0	-	-
Mode 21	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE40	54	5270	MCS0	-	-
Mode 22	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE40	62	5310	MCS0	-	-
Mode 23	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE40	102	5510	MCS0	-	-
Mode 24	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE40	134	5670	MCS0	-	-
Mode 25	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE80	42	5210	MCS0	-	-
Mode 26	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE80	58	5290	MCS0	-	-
Mode 27	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE80	106	5530	MCS0	-	-
Mode 28	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE80	122	5610	MCS0	-	-
Mode 29	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE160	50	5250	MCS0	-	-
Mode 30	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE160	114	5570	MCS0	-	-
Mode 31	U-NII-3	5.725-5.85	CDD8+9	802.11a	149	5745	6Mbps	-	-



Mode 32	U-NII-3	5.725-5.85	CDD8+9	802.11a	157	5785	6Mbps	-	-
Mode 33	U-NII-3	5.725-5.85	CDD8+9	802.11a	165	5825	6Mbps	-	-
Mode 34	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE20	149	5745	MCS0	-	-
Mode 35	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE20	157	5785	MCS0	-	-
Mode 36	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE20	165	5825	MCS0	-	-
Mode 37	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE40	151	5755	MCS0	-	-
Mode 38	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE40	159	5795	MCS0	-	-
Mode 39	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE80	155	5775	MCS0	-	-
Mode 40	U-NII-1	5.15-5.25	CDD8+9	802.11ax HE20	36	5180	MCS0	Partial RU 106/53	-
Mode 41	U-NII-2A	5.25-5.35	CDD8+9	802.11ax HE20	64	5320	MCS0	Partial RU 26/8	-
Mode 42	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE20	100	5500	MCS0	Partial RU 26/0	-
Mode 43	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE20	140	5700	MCS0	Partial RU 26/8	-
Mode 44	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE20	149	5745	MCS0	Partial RU 106/53	-
Mode 45	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE20	165	5825	MCS0	Partial RU 26/8	-
Mode 46	U-NII-2C	5.47-5.725	CDD8+9	802.11ax HE80-LF	106	5530	MCS0	-	-
Mode 47	U-NII-3	5.725-5.85	CDD8+9	802.11ax HE80-LF	155	5775	MCS0	-	-
Mode 48 CO-TX	-	5.47-5.725	9	802.11ax HE80	106	5530	MCS0	-	-
		2400-2483.5	12	802.11ax HE20	11	2462	MCS0	-	-
		LTE	1	B13 link					-
Mode 49 CO-TX	-	5.47-5.725	CDD8+9	802.11ax HE80	106	5530	MCS0	-	-
		2400-2483.5	12	Bluetooth-LE_GSKF	38	2478	2Mbps	-	-
		LTE	1	B13 link					-



Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	Remark
1	802.11a	36	-	-	-	-	-	-	-	Band Edge
1	802.11a	36	10360.00	61.90	68.30	-6.40	H	Peak	Pass	Harmonic
2	802.11a	44	-	-	-	-	-	-	-	Band Edge
2	802.11a	44	10440.00	62.08	68.30	-6.22	H	Peak	Pass	Harmonic
3	802.11a	48	-	-	-	-	-	-	-	Band Edge
3	802.11a	48	10480.00	62.03	68.30	-6.27	H	Peak	Pass	Harmonic
4	802.11a	52	-	-	-	-	-	-	-	Band Edge
4	802.11a	52	10520.00	62.11	68.30	-6.19	H	Peak	Pass	Harmonic
5	802.11a	60	-	-	-	-	-	-	-	Band Edge
5	802.11a	60	10600.00	47.51	54.00	-6.49	H	Average	Pass	Harmonic
6	802.11a	64	-	-	-	-	-	-	-	Band Edge
6	802.11a	64	10640.00	47.71	54.00	-6.29	H	Average	Pass	Harmonic
7	802.11a	100	-	-	-	-	-	-	-	Band Edge
7	802.11a	100	11000.00	45.16	54.00	-8.84	H	Average	Pass	Harmonic
8	802.11a	116	-	-	-	-	-	-	-	Band Edge
8	802.11a	116	11160.00	47.58	54.00	-6.42	H	Average	Pass	Harmonic
9	802.11a	140	-	-	-	-	-	-	-	Band Edge
9	802.11a	140	11400.00	47.54	54.00	-6.46	H	Average	Pass	Harmonic
10	802.11ax HE20	36	5148.32	43.00	54.00	-11.00	V	AVERAGE	Pass	Band Edge
10	802.11ax HE20	36	10360.00	62.14	68.30	-6.16	H	Peak	Pass	Harmonic
11	802.11ax HE20	44	-	-	-	-	-	-	-	Band Edge
11	802.11ax HE20	44	10440.00	61.97	68.30	-6.33	H	Peak	Pass	Harmonic
12	802.11ax HE20	48	5093.12	42.15	54.00	-11.85	V	AVERAGE	Pass	Band Edge
12	802.11ax HE20	48	10480.00	61.92	68.30	-6.38	H	Peak	Pass	Harmonic
13	802.11ax HE20	52	5103.22	41.93	54.00	-12.07	H	AVERAGE	Pass	Band Edge
13	802.11ax HE20	52	10520.00	61.91	68.30	-6.39	H	Peak	Pass	Harmonic
14	802.11ax HE20	60	-	-	-	-	-	-	-	Band Edge
14	802.11ax HE20	60	10600.00	47.53	54.00	-6.47	H	Average	Pass	Harmonic
15	802.11ax HE20	64	5355.84	43.37	54.00	-10.63	V	AVERAGE	Pass	Band Edge
15	802.11ax HE20	64	10640.00	47.31	54.00	-6.69	H	Average	Pass	Harmonic
16	802.11ax HE20	100	5459.35	42.37	54.00	-11.63	V	AVERAGE	Pass	Band Edge
16	802.11ax HE20	100	11000.00	44.45	54.00	-9.55	H	Average	Pass	Harmonic
17	802.11ax HE20	116	-	-	-	-	-	-	-	Band Edge
17	802.11ax HE20	116	11160.00	46.83	54.00	-7.17	H	Average	Pass	Harmonic
18	802.11ax HE20	140	5751.29	51.98	68.30	-16.32	V	PEAK	Pass	Band Edge
18	802.11ax HE20	140	11400.00	47.69	54.00	-6.31	H	Average	Pass	Harmonic





19	802.11ax HE40	38	5148.77	44.70	54.00	-9.30	V	AVERAGE	Pass	Band Edge
19	802.11ax HE40	38	-	-	-	-	-	-	-	Harmonic
20	802.11ax HE40	46	5003.91	43.04	54.00	-10.96	V	AVERAGE	Pass	Band Edge
20	802.11ax HE40	46	-	-	-	-	-	-	-	Harmonic
21	802.11ax HE40	54	5000.27	43.31	54.00	-10.69	V	AVERAGE	Pass	Band Edge
21	802.11ax HE40	54	10540.00	58.31	68.30	-9.99	H	Peak	Pass	Harmonic
22	802.11ax HE40	62	5350.35	43.49	54.00	-10.51	H	AVERAGE	Pass	Band Edge
22	802.11ax HE40	62	10620.00	47.40	54.00	-6.60	H	Average	Pass	Harmonic
23	802.11ax HE40	102	5458.48	44.33	54.00	-9.67	V	AVERAGE	Pass	Band Edge
23	802.11ax HE40	102	11020.00	45.93	54.00	-8.07	H	Average	Pass	Harmonic
24	802.11ax HE40	134	5458.80	42.77	54.00	-11.23	H	AVERAGE	Pass	Band Edge
24	802.11ax HE40	134	11340.00	47.96	54.00	-6.04	H	Average	Pass	Harmonic
25	802.11ax HE80	42	5149.73	48.81	54.00	-5.19	V	AVERAGE	Pass	Band Edge
25	802.11ax HE80	42	-	-	-	-	-	-	-	Harmonic
26	802.11ax HE80	58	5350.35	45.41	54.00	-8.59	V	AVERAGE	Pass	Band Edge
26	802.11ax HE80	58	-	-	-	-	-	-	-	Harmonic
27	802.11ax HE80	106	5444.86	48.90	54.00	-5.10	V	AVERAGE	Pass	Band Edge
27	802.11ax HE80	106	16590.00	47.72	68.30	-20.58	V	Peak	Pass	Harmonic
28	802.11ax HE80	122	5452.44	45.28	54.00	-8.72	H	AVERAGE	Pass	Band Edge
28	802.11ax HE80	122	-	-	-	-	-	-	-	Harmonic
29	802.11ax HE160	50	5001.00	44.29	54.00	-9.71	H	AVERAGE	Pass	Band Edge
29	802.11ax HE160	50	-	-	-	-	-	-	-	Harmonic
30	802.11ax HE160	114	5447.46	47.07	54.00	-6.93	H	AVERAGE	Pass	Band Edge
30	802.11ax HE160	114	-	-	-	-	-	-	-	Harmonic
31	802.11a	149	-	-	-	-	-	-	-	Band Edge
31	802.11a	149	11490.00	47.84	54.00	-6.16	V	Average	Pass	Harmonic
32	802.11a	157	-	-	-	-	-	-	-	Band Edge
32	802.11a	157	11570.00	47.89	54.00	-6.11	V	Average	Pass	Harmonic
33	802.11a	165	-	-	-	-	-	-	-	Band Edge
33	802.11a	165	11650.00	47.86	54.00	-6.14	V	Average	Pass	Harmonic
34	802.11ax HE20	149	5625.23	52.29	68.30	-16.01	V	PEAK	Pass	Band Edge
34	802.11ax HE20	149	11490.00	47.19	54.00	-6.81	V	Average	Pass	Harmonic
35	802.11ax HE20	157	-	-	-	-	-	-	-	Band Edge
35	802.11ax HE20	157	11570.00	47.70	54.00	-6.30	V	Average	Pass	Harmonic
36	802.11ax HE20	165	5938.88	53.57	68.30	-14.73	H	PEAK	Pass	Band Edge
36	802.11ax HE20	165	11650.00	47.80	54.00	-6.20	V	Average	Pass	Harmonic
37	802.11ax HE40	151	5645.57	51.77	68.30	-16.53	H	PEAK	Pass	Band Edge
37	802.11ax HE40	151	11510.00	47.79	54.00	-6.21	V	Average	Pass	Harmonic
38	802.11ax HE40	159	5942.41	52.97	68.30	-15.33	V	PEAK	Pass	Band Edge





38	802.11ax HE40	159	11590.00	47.88	54.00	-6.12	V	Average	Pass	Harmonic
39	802.11ax HE80	155	5649.00	58.65	68.30	-9.65	H	PEAK	Pass	Band Edge
39	802.11ax HE80	155	11550.00	47.74	54.00	-6.26	V	Average	Pass	Harmonic
40	802.11ax HE20	36	5000.72	42.63	54.00	-11.37	V	AVERAGE	Pass	Band Edge
40	802.11ax HE20	36	-	-	-	-	-	-	-	Harmonic
41	802.11ax HE20	64	5451.74	42.12	54.00	-11.88	H	AVERAGE	Pass	Band Edge
41	802.11ax HE20	64	-	-	-	-	-	-	-	Harmonic
42	802.11ax HE20	100	5458.60	42.25	54.00	-11.75	V	AVERAGE	Pass	Band Edge
42	802.11ax HE20	100	-	-	-	-	-	-	-	Harmonic
43	802.11ax HE20	140	5753.17	51.94	68.30	-16.36	H	PEAK	Pass	Band Edge
43	802.11ax HE20	140	-	-	-	-	-	-	-	Harmonic
44	802.11ax HE20	149	5650.17	52.90	68.43	-15.53	H	PEAK	Pass	Band Edge
44	802.11ax HE20	149	-	-	-	-	-	-	-	Harmonic
45	802.11ax HE20	165	5928.50	53.30	68.30	-15.00	H	PEAK	Pass	Band Edge
45	802.11ax HE20	165	-	-	-	-	-	-	-	Harmonic
46	802.11ax HE80-LF	106	32.91	26.70	40.00	-13.30	V	PEAK	Pass	LF
47	802.11ax HE80-LF	155	951.50	32.81	46.00	-13.19	V	PEAK	Pass	LF
48 CO-TX	802.11ax HE80	106	5432.32	48.56	54.00	-5.44	V	Average	Pass	Band Edge
	802.11ax HE80	106	16590.00	48.07	68.30	-20.23	V	Peak	Pass	Harmonic
49 CO-TX	802.11ax HE80	106	5452.48	48.79	54.00	-5.21	V	Average	Pass	Band Edge
	802.11ax HE80	106	16590.00	47.95	68.30	-20.35	V	Peak	Pass	Harmonic





Mode	1																																																																																																											
	Harmonic																																																																																																											
	U-NII-1_5.15-5.25_802.11a_CH36_5180MHz																																																																																																											
ANT	CDD8+9																																																																																																											
Pol.	Horizontal					Vertical																																																																																																						
Peak Avg																																																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10360.00</td><td>61.90</td><td>68.30</td><td>-6.40</td><td>75.13</td><td>38.47</td><td>12.06</td><td>63.76</td><td>188</td><td>0 Peak</td></tr><tr><td>2 15540.00</td><td>47.60</td><td>74.00</td><td>-26.40</td><td>56.08</td><td>41.32</td><td>14.58</td><td>64.38</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10360.00	61.90	68.30	-6.40	75.13	38.47	12.06	63.76	188	0 Peak	2 15540.00	47.60	74.00	-26.40	56.08	41.32	14.58	64.38	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 10360.00</td><td>60.69</td><td>68.30</td><td>-7.61</td><td>73.92</td><td>38.47</td><td>12.06</td><td>63.76</td><td>363</td><td>352 Peak</td></tr><tr><td>2 15540.00</td><td>46.63</td><td>74.00</td><td>-27.37</td><td>55.11</td><td>41.32</td><td>14.58</td><td>64.38</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10360.00	60.69	68.30	-7.61	73.92	38.47	12.06	63.76	363	352 Peak	2 15540.00	46.63	74.00	-27.37	55.11	41.32	14.58	64.38	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1 10360.00	61.90	68.30	-6.40	75.13	38.47	12.06	63.76	188	0 Peak																																																																																																			
2 15540.00	47.60	74.00	-26.40	56.08	41.32	14.58	64.38	---	---	Peak																																																																																																		
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																				
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																			
1 10360.00	60.69	68.30	-7.61	73.92	38.47	12.06	63.76	363	352 Peak																																																																																																			
2 15540.00	46.63	74.00	-27.37	55.11	41.32	14.58	64.38	---	---	Peak																																																																																																		





Mode	2																																																															
	Harmonic																																																															
	U-NII-1_5.15-5.25_802.11a_CH44_5220MHz																																																															
ANT	CDD8+9																																																															
Pol.	Horizontal						Vertical																																																									
Peak Avg																																																																
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>62.08</td><td>68.30</td><td>-6.22</td><td>75.19</td><td>38.49</td><td>12.12</td><td>63.72</td><td>125</td><td>32</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>46.20</td><td>74.00</td><td>-27.80</td><td>54.62</td><td>41.40</td><td>14.64</td><td>64.46</td><td>---</td><td>---</td><td>Peak</td></tr></table>													Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	62.08	68.30	-6.22	75.19	38.49	12.12	63.72	125	32	Peak	2	15660.00	46.20	74.00	-27.80	54.62	41.40	14.64	64.46	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																							
1	10440.00	62.08	68.30	-6.22	75.19	38.49	12.12	63.72	125	32	Peak																																																					
2	15660.00	46.20	74.00	-27.80	54.62	41.40	14.64	64.46	---	---	Peak																																																					
																																																																
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>61.93</td><td>68.30</td><td>-6.37</td><td>75.04</td><td>38.49</td><td>12.12</td><td>63.72</td><td>369</td><td>342</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>46.53</td><td>74.00</td><td>-27.47</td><td>54.95</td><td>41.40</td><td>14.64</td><td>64.46</td><td>---</td><td>---</td><td>Peak</td></tr></table>													Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	61.93	68.30	-6.37	75.04	38.49	12.12	63.72	369	342	Peak	2	15660.00	46.53	74.00	-27.47	54.95	41.40	14.64	64.46	---	---	Peak	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																							
1	10440.00	61.93	68.30	-6.37	75.04	38.49	12.12	63.72	369	342	Peak																																																					
2	15660.00	46.53	74.00	-27.47	54.95	41.40	14.64	64.46	---	---	Peak																																																					





Mode	3																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-1_5.15-5.25_802.11a_CH48_5240MHz																																																																																																																			
ANT	CDD8+9																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>10480.00</td><td>62.03</td><td>68.30</td><td>-6.27</td><td>75.09</td><td>38.50</td><td>12.15</td><td>63.71</td><td>207</td><td>349</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>47.17</td><td>74.00</td><td>-26.83</td><td>55.58</td><td>41.43</td><td>14.66</td><td>64.50</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10480.00	62.03	68.30	-6.27	75.09	38.50	12.15	63.71	207	349	Peak	2	15720.00	47.17	74.00	-26.83	55.58	41.43	14.66	64.50	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr></thead><tbody><tr><td></td><td>MHz</td><td>dBuV/m</td><td>dBuV/m</td><td>dB</td><td>dBuV</td><td>dB/m</td><td>dB</td><td>cm</td><td>deg</td></tr><tr><td>1</td><td>10480.00</td><td>59.16</td><td>68.30</td><td>-9.14</td><td>72.22</td><td>38.50</td><td>12.15</td><td>63.71</td><td>398</td><td>353</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>46.64</td><td>74.00</td><td>-27.36</td><td>55.05</td><td>41.43</td><td>14.66</td><td>64.50</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10480.00	59.16	68.30	-9.14	72.22	38.50	12.15	63.71	398	353	Peak	2	15720.00	46.64	74.00	-27.36	55.05	41.43	14.66	64.50	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10480.00	62.03	68.30	-6.27	75.09	38.50	12.15	63.71	207	349	Peak																																																																																																									
2	15720.00	47.17	74.00	-26.83	55.58	41.43	14.66	64.50	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10480.00	59.16	68.30	-9.14	72.22	38.50	12.15	63.71	398	353	Peak																																																																																																									
2	15720.00	46.64	74.00	-27.36	55.05	41.43	14.66	64.50	---	---	Peak																																																																																																									



Mode	4																																																																																											
	Harmonic																																																																																											
	U-NII-2A_5.25-5.35_802.11a_CH52_5260MHz																																																																																											
ANT	CDD8+9																																																																																											
Pol.	Horizontal						Vertical																																																																																					
Peak Avg																																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th></tr><tr><td>1</td><td>10520.00</td><td>62.11</td><td>68.30</td><td>-6.19</td><td>75.12</td><td>38.50</td><td>12.18</td></tr><tr><td>2</td><td>15780.00</td><td>47.04</td><td>74.00</td><td>-26.96</td><td>55.43</td><td>41.47</td><td>14.69</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	10520.00	62.11	68.30	-6.19	75.12	38.50	12.18	2	15780.00	47.04	74.00	-26.96	55.43	41.47	14.69	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th></tr><tr><td>1</td><td>10520.00</td><td>61.20</td><td>68.30</td><td>-7.10</td><td>74.21</td><td>38.50</td><td>12.18</td></tr><tr><td>2</td><td>15780.00</td><td>47.50</td><td>74.00</td><td>-26.50</td><td>55.89</td><td>41.47</td><td>14.69</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	1	10520.00	61.20	68.30	-7.10	74.21	38.50	12.18	2	15780.00	47.50	74.00	-26.50	55.89	41.47	14.69
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																					
1	10520.00	62.11	68.30	-6.19	75.12	38.50	12.18																																																																																					
2	15780.00	47.04	74.00	-26.96	55.43	41.47	14.69																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																					
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB																																																																																					
1	10520.00	61.20	68.30	-7.10	74.21	38.50	12.18																																																																																					
2	15780.00	47.50	74.00	-26.50	55.89	41.47	14.69																																																																																					
<table><tr><th></th><th>Remark</th></tr><tr><td>1</td><td>Peak</td></tr><tr><td>2</td><td>Peak</td></tr></table>							Remark	1	Peak	2	Peak	<table><tr><th></th><th>Remark</th></tr><tr><td>1</td><td>Peak</td></tr><tr><td>2</td><td>Peak</td></tr></table>							Remark	1	Peak	2	Peak																																																																					
	Remark																																																																																											
1	Peak																																																																																											
2	Peak																																																																																											
	Remark																																																																																											
1	Peak																																																																																											
2	Peak																																																																																											





Mode	5																																																																																																																																										
	Harmonic																																																																																																																																										
	U-NII-2A_5.25-5.35_802.11a_CH60_5300MHz																																																																																																																																										
ANT	CDD8+9																																																																																																																																										
Pol.	Horizontal										Vertical																																																																																																																																
Peak Avg																																																																																																																																											
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10600.00</td><td>57.71</td><td>74.00</td><td>-16.29</td><td>70.62</td><td>38.52</td><td>12.23</td><td>63.66</td><td>199</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>10600.00</td><td>47.51</td><td>54.00</td><td>-6.49</td><td>60.42</td><td>38.52</td><td>12.23</td><td>63.66</td><td>199</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>15900.00</td><td>45.42</td><td>74.00</td><td>-28.58</td><td>53.76</td><td>41.54</td><td>14.75</td><td>64.63</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10600.00	57.71	74.00	-16.29	70.62	38.52	12.23	63.66	199	360	Peak	2	10600.00	47.51	54.00	-6.49	60.42	38.52	12.23	63.66	199	360	Average	3	15900.00	45.42	74.00	-28.58	53.76	41.54	14.75	64.63	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10600.00</td><td>55.84</td><td>74.00</td><td>-18.16</td><td>68.75</td><td>38.52</td><td>12.23</td><td>63.66</td><td>376</td><td>344</td><td>Peak</td></tr><tr><td>2</td><td>10600.00</td><td>47.24</td><td>54.00</td><td>-6.76</td><td>60.15</td><td>38.52</td><td>12.23</td><td>63.66</td><td>376</td><td>344</td><td>Average</td></tr><tr><td>3</td><td>15900.00</td><td>45.89</td><td>74.00</td><td>-28.11</td><td>54.23</td><td>41.54</td><td>14.75</td><td>64.63</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10600.00	55.84	74.00	-18.16	68.75	38.52	12.23	63.66	376	344	Peak	2	10600.00	47.24	54.00	-6.76	60.15	38.52	12.23	63.66	376	344	Average	3	15900.00	45.89	74.00	-28.11	54.23	41.54	14.75	64.63	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																			
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																		
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																		
1	10600.00	57.71	74.00	-16.29	70.62	38.52	12.23	63.66	199	360	Peak																																																																																																																																
2	10600.00	47.51	54.00	-6.49	60.42	38.52	12.23	63.66	199	360	Average																																																																																																																																
3	15900.00	45.42	74.00	-28.58	53.76	41.54	14.75	64.63	---	---	Peak																																																																																																																																
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																		
1	10600.00	55.84	74.00	-18.16	68.75	38.52	12.23	63.66	376	344	Peak																																																																																																																																
2	10600.00	47.24	54.00	-6.76	60.15	38.52	12.23	63.66	376	344	Average																																																																																																																																
3	15900.00	45.89	74.00	-28.11	54.23	41.54	14.75	64.63	---	---	Peak																																																																																																																																





Mode	6																																																																										
	Harmonic																																																																										
	U-NII-2A_5.25-5.35_802.11a_CH64_5320MHz																																																																										
ANT	CDD8+9																																																																										
Pol.	Horizontal																																																																										
Peak Avg																																																																											
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>57.37</td><td>74.00</td><td>-16.63</td><td>70.22</td><td>38.53</td><td>12.26</td><td>63.64</td><td>191</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>10640.00</td><td>47.71</td><td>54.00</td><td>-6.29</td><td>60.56</td><td>38.53</td><td>12.26</td><td>63.64</td><td>191</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>15960.00</td><td>45.73</td><td>74.00</td><td>-28.27</td><td>54.05</td><td>41.58</td><td>14.77</td><td>64.67</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	57.37	74.00	-16.63	70.22	38.53	12.26	63.64	191	360	Peak	2	10640.00	47.71	54.00	-6.29	60.56	38.53	12.26	63.64	191	360	Average	3	15960.00	45.73	74.00	-28.27	54.05	41.58	14.77	64.67	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																			
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																		
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	10640.00	57.37	74.00	-16.63	70.22	38.53	12.26	63.64	191	360	Peak																																																																
2	10640.00	47.71	54.00	-6.29	60.56	38.53	12.26	63.64	191	360	Average																																																																
3	15960.00	45.73	74.00	-28.27	54.05	41.58	14.77	64.67	---	---	Peak																																																																
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>56.07</td><td>74.00</td><td>-17.93</td><td>68.92</td><td>38.53</td><td>12.26</td><td>63.64</td><td>395</td><td>323</td><td>Peak</td></tr><tr><td>2</td><td>10640.00</td><td>47.37</td><td>54.00</td><td>-6.63</td><td>60.22</td><td>38.53</td><td>12.26</td><td>63.64</td><td>395</td><td>323</td><td>Average</td></tr><tr><td>3</td><td>15960.00</td><td>46.21</td><td>74.00</td><td>-27.79</td><td>54.53</td><td>41.58</td><td>14.77</td><td>64.67</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	56.07	74.00	-17.93	68.92	38.53	12.26	63.64	395	323	Peak	2	10640.00	47.37	54.00	-6.63	60.22	38.53	12.26	63.64	395	323	Average	3	15960.00	46.21	74.00	-27.79	54.53	41.58	14.77	64.67	---	---	Peak	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	10640.00	56.07	74.00	-17.93	68.92	38.53	12.26	63.64	395	323	Peak																																																																
2	10640.00	47.37	54.00	-6.63	60.22	38.53	12.26	63.64	395	323	Average																																																																
3	15960.00	46.21	74.00	-27.79	54.53	41.58	14.77	64.67	---	---	Peak																																																																
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>56.07</td><td>74.00</td><td>-17.93</td><td>68.92</td><td>38.53</td><td>12.26</td><td>63.64</td><td>395</td><td>323</td><td>Peak</td></tr><tr><td>2</td><td>10640.00</td><td>47.37</td><td>54.00</td><td>-6.63</td><td>60.22</td><td>38.53</td><td>12.26</td><td>63.64</td><td>395</td><td>323</td><td>Average</td></tr><tr><td>3</td><td>15960.00</td><td>46.21</td><td>74.00</td><td>-27.79</td><td>54.53</td><td>41.58</td><td>14.77</td><td>64.67</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	56.07	74.00	-17.93	68.92	38.53	12.26	63.64	395	323	Peak	2	10640.00	47.37	54.00	-6.63	60.22	38.53	12.26	63.64	395	323	Average	3	15960.00	46.21	74.00	-27.79	54.53	41.58	14.77	64.67	---	---	Peak	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	10640.00	56.07	74.00	-17.93	68.92	38.53	12.26	63.64	395	323	Peak																																																																
2	10640.00	47.37	54.00	-6.63	60.22	38.53	12.26	63.64	395	323	Average																																																																
3	15960.00	46.21	74.00	-27.79	54.53	41.58	14.77	64.67	---	---	Peak																																																																





Mode	7																																																																																																																																			
	Harmonic																																																																																																																																			
	U-NII-2C_5.47-5.725_802.11a_CH100_5500MHz																																																																																																																																			
ANT	CDD8+9																																																																																																																																			
Pol.	Horizontal	Vertical																																																																																																																																		
Peak Avg	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11000.00</td><td>55.58</td><td>74.00</td><td>-18.42</td><td>67.96</td><td>38.60</td><td>12.52</td><td>63.50</td><td>189</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>11000.00</td><td>45.16</td><td>54.00</td><td>-8.84</td><td>57.54</td><td>38.60</td><td>12.52</td><td>63.50</td><td>189</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>16500.00</td><td>47.11</td><td>68.30</td><td>-21.19</td><td>54.74</td><td>41.95</td><td>15.17</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11000.00	55.58	74.00	-18.42	67.96	38.60	12.52	63.50	189	360	Peak	2	11000.00	45.16	54.00	-8.84	57.54	38.60	12.52	63.50	189	360	Average	3	16500.00	47.11	68.30	-21.19	54.74	41.95	15.17	64.75	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11000.00</td><td>52.84</td><td>74.00</td><td>-21.16</td><td>65.22</td><td>38.60</td><td>12.52</td><td>63.50</td><td>397</td><td>347</td><td>Peak</td></tr><tr><td>2</td><td>11000.00</td><td>44.35</td><td>54.00</td><td>-9.65</td><td>56.73</td><td>38.60</td><td>12.52</td><td>63.50</td><td>397</td><td>347</td><td>Average</td></tr><tr><td>3</td><td>16500.00</td><td>46.50</td><td>68.30</td><td>-21.80</td><td>54.13</td><td>41.95</td><td>15.17</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11000.00	52.84	74.00	-21.16	65.22	38.60	12.52	63.50	397	347	Peak	2	11000.00	44.35	54.00	-9.65	56.73	38.60	12.52	63.50	397	347	Average	3	16500.00	46.50	68.30	-21.80	54.13	41.95	15.17	64.75	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	11000.00	55.58	74.00	-18.42	67.96	38.60	12.52	63.50	189	360	Peak																																																																																																																									
2	11000.00	45.16	54.00	-8.84	57.54	38.60	12.52	63.50	189	360	Average																																																																																																																									
3	16500.00	47.11	68.30	-21.19	54.74	41.95	15.17	64.75	---	---	Peak																																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																										
1	11000.00	52.84	74.00	-21.16	65.22	38.60	12.52	63.50	397	347	Peak																																																																																																																									
2	11000.00	44.35	54.00	-9.65	56.73	38.60	12.52	63.50	397	347	Average																																																																																																																									
3	16500.00	46.50	68.30	-21.80	54.13	41.95	15.17	64.75	---	---	Peak																																																																																																																									







Mode	8																																																																																																																																																			
	Harmonic																																																																																																																																																			
	U-NII-2C_5.47-5.725_802.11a_CH116_5580MHz																																																																																																																																																			
ANT	CDD8+9																																																																																																																																																			
Pol.	Horizontal										Vertical																																																																																																																																									
Peak Avg																																																																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11160.00</td><td>56.15</td><td>74.00</td><td>-17.85</td><td>68.33</td><td>38.79</td><td>12.64</td><td>63.61</td><td>181</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>11160.00</td><td>47.58</td><td>54.00</td><td>-6.42</td><td>59.76</td><td>38.79</td><td>12.64</td><td>63.61</td><td>181</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>16740.00</td><td>46.79</td><td>68.30</td><td>-21.51</td><td>54.09</td><td>42.12</td><td>15.35</td><td>64.77</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11160.00	56.15	74.00	-17.85	68.33	38.79	12.64	63.61	181	360	Peak	2	11160.00	47.58	54.00	-6.42	59.76	38.79	12.64	63.61	181	360	Average	3	16740.00	46.79	68.30	-21.51	54.09	42.12	15.35	64.77	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11160.00</td><td>53.04</td><td>74.00</td><td>-20.96</td><td>65.22</td><td>38.79</td><td>12.64</td><td>63.61</td><td>396</td><td>325</td><td>Peak</td></tr><tr><td>2</td><td>11160.00</td><td>45.25</td><td>54.00</td><td>-8.75</td><td>57.43</td><td>38.79</td><td>12.64</td><td>63.61</td><td>396</td><td>325</td><td>Average</td></tr><tr><td>3</td><td>16740.00</td><td>45.45</td><td>68.30</td><td>-22.85</td><td>52.75</td><td>42.12</td><td>15.35</td><td>64.77</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11160.00	53.04	74.00	-20.96	65.22	38.79	12.64	63.61	396	325	Peak	2	11160.00	45.25	54.00	-8.75	57.43	38.79	12.64	63.61	396	325	Average	3	16740.00	45.45	68.30	-22.85	52.75	42.12	15.35	64.77	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																												
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																											
1	11160.00	56.15	74.00	-17.85	68.33	38.79	12.64	63.61	181	360	Peak																																																																																																																																									
2	11160.00	47.58	54.00	-6.42	59.76	38.79	12.64	63.61	181	360	Average																																																																																																																																									
3	16740.00	46.79	68.30	-21.51	54.09	42.12	15.35	64.77	---	---	Peak																																																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																												
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																											
1	11160.00	53.04	74.00	-20.96	65.22	38.79	12.64	63.61	396	325	Peak																																																																																																																																									
2	11160.00	45.25	54.00	-8.75	57.43	38.79	12.64	63.61	396	325	Average																																																																																																																																									
3	16740.00	45.45	68.30	-22.85	52.75	42.12	15.35	64.77	---	---	Peak																																																																																																																																									



Mode	9																																																																																																																															
	Harmonic																																																																																																																															
	U-NII-2C_5.47-5.725_802.11a_CH140_5700MHz																																																																																																																															
ANT	CDD8+9																																																																																																																															
Pol.	Horizontal					Vertical																																																																																																																										
Peak Avg																																																																																																																																
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11400.00</td><td>55.99</td><td>74.00</td><td>-18.01</td><td>67.88</td><td>39.08</td><td>12.81</td><td>63.78</td><td>190</td><td>351 Peak</td></tr><tr><td>2 11400.00</td><td>47.54</td><td>54.00</td><td>-6.46</td><td>59.43</td><td>39.08</td><td>12.81</td><td>63.78</td><td>190</td><td>351 Average</td></tr><tr><td>3 17100.00</td><td>46.74</td><td>68.30</td><td>-21.56</td><td>53.62</td><td>42.41</td><td>15.62</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11400.00	55.99	74.00	-18.01	67.88	39.08	12.81	63.78	190	351 Peak	2 11400.00	47.54	54.00	-6.46	59.43	39.08	12.81	63.78	190	351 Average	3 17100.00	46.74	68.30	-21.56	53.62	42.41	15.62	64.91	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11400.00</td><td>48.24</td><td>74.00</td><td>-25.76</td><td>60.13</td><td>39.08</td><td>12.81</td><td>63.78</td><td>387</td><td>350 Peak</td></tr><tr><td>2 11400.00</td><td>43.75</td><td>54.00</td><td>-10.25</td><td>55.64</td><td>39.08</td><td>12.81</td><td>63.78</td><td>387</td><td>350 Average</td></tr><tr><td>3 17100.00</td><td>46.34</td><td>68.30</td><td>-21.96</td><td>53.22</td><td>42.41</td><td>15.62</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11400.00	48.24	74.00	-25.76	60.13	39.08	12.81	63.78	387	350 Peak	2 11400.00	43.75	54.00	-10.25	55.64	39.08	12.81	63.78	387	350 Average	3 17100.00	46.34	68.30	-21.96	53.22	42.41	15.62	64.91	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1 11400.00	55.99	74.00	-18.01	67.88	39.08	12.81	63.78	190	351 Peak																																																																																																																							
2 11400.00	47.54	54.00	-6.46	59.43	39.08	12.81	63.78	190	351 Average																																																																																																																							
3 17100.00	46.74	68.30	-21.56	53.62	42.41	15.62	64.91	---	---	Peak																																																																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																								
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1 11400.00	48.24	74.00	-25.76	60.13	39.08	12.81	63.78	387	350 Peak																																																																																																																							
2 11400.00	43.75	54.00	-10.25	55.64	39.08	12.81	63.78	387	350 Average																																																																																																																							
3 17100.00	46.34	68.30	-21.96	53.22	42.41	15.62	64.91	---	---	Peak																																																																																																																						





Mode	10																																																																																									
	Band Edge																																																																																									
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_5180MHz																																																																																									
ANT	CDD8+9																																																																																									
Pol.	Horizontal					Fundamental																																																																																				
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5014.40</td><td>52.82</td><td>74.00</td><td>-21.18</td><td>41.33</td><td>36.69</td><td>8.30</td><td>33.50</td><td>316</td><td>33</td><td>PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5014.40	52.82	74.00	-21.18	41.33	36.69	8.30	33.50	316	33	PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>106.73</td><td>-----</td><td>-----</td><td>95.05</td><td>36.56</td><td>8.58</td><td>33.46</td><td>316</td><td>33</td><td>PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	106.73	-----	-----	95.05	36.56	8.58	33.46	316	33	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5014.40	52.82	74.00	-21.18	41.33	36.69	8.30	33.50	316	33	PEAK																																																																															
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5180.00	106.73	-----	-----	95.05	36.56	8.58	33.46	316	33	PEAK																																																																															
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5148.32</td><td>42.43</td><td>54.00</td><td>-11.57</td><td>30.79</td><td>36.58</td><td>8.53</td><td>33.47</td><td>316</td><td>33</td><td>AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5148.32	42.43	54.00	-11.57	30.79	36.58	8.53	33.47	316	33	AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>97.89</td><td>-----</td><td>-----</td><td>86.21</td><td>36.56</td><td>8.58</td><td>33.46</td><td>316</td><td>33</td><td>AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	97.89	-----	-----	86.21	36.56	8.58	33.46	316	33	AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5148.32	42.43	54.00	-11.57	30.79	36.58	8.53	33.47	316	33	AVERAGE																																																																															
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																			
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5180.00	97.89	-----	-----	86.21	36.56	8.58	33.46	316	33	AVERAGE																																																																															





Mode	10																																																																																										
	Band Edge																																																																																										
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_5180MHz																																																																																										
ANT	CDD8+9																																																																																										
Pol.	Vertical						Fundamental																																																																																				
Peak	Date: 2025-03-20						Date: 2025-03-20																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5127.98</td><td>52.88</td><td>74.00</td><td>-21.12</td><td>41.26</td><td>36.60</td><td>8.49</td><td>33.47</td><td>351 280 PEAK</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5127.98	52.88	74.00	-21.12	41.26	36.60	8.49	33.47	351 280 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>107.24</td><td>-----</td><td>-----</td><td>95.56</td><td>36.56</td><td>8.58</td><td>33.46</td><td>351 280 PEAK</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	107.24	-----	-----	95.56	36.56	8.58	33.46
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5127.98	52.88	74.00	-21.12	41.26	36.60	8.49	33.47	351 280 PEAK																																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5180.00	107.24	-----	-----	95.56	36.56	8.58	33.46	351 280 PEAK																																																																																		
Avg	Date: 2025-03-20						Date: 2025-03-20																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5148.32</td><td>43.00</td><td>54.00</td><td>-11.00</td><td>31.36</td><td>36.58</td><td>8.53</td><td>33.47</td><td>351 280 AVERAGE</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5148.32	43.00	54.00	-11.00	31.36	36.58	8.53	33.47	351 280 AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5180.00</td><td>98.27</td><td>-----</td><td>-----</td><td>86.59</td><td>36.55</td><td>8.59</td><td>33.46</td><td>351 280 AVERAGE</td></tr></tbody></table>							Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5180.00	98.27	-----	-----	86.59	36.55	8.59	33.46
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5148.32	43.00	54.00	-11.00	31.36	36.58	8.53	33.47	351 280 AVERAGE																																																																																		
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																		
1	5180.00	98.27	-----	-----	86.59	36.55	8.59	33.46	351 280 AVERAGE																																																																																		



Mode	10																																																																																																	
	Harmonic																																																																																																	
	U-NII-1_5.15-5.25_802.11ax HE20_CH36_5180MHz																																																																																																	
ANT	CDD8+9																																																																																																	
Pol.	Horizontal	Vertical																																																																																																
Peak Avg	 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Apos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10360.00</td><td>62.14</td><td>68.30</td><td>-6.16</td><td>75.37</td><td>38.47</td><td>12.06</td><td>63.76</td><td>185</td><td>352 Peak</td></tr><tr><td>2 15540.00</td><td>45.78</td><td>74.00</td><td>-28.22</td><td>54.26</td><td>41.32</td><td>14.58</td><td>64.38</td><td>---</td><td>--- Peak</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Apos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10360.00	62.14	68.30	-6.16	75.37	38.47	12.06	63.76	185	352 Peak	2 15540.00	45.78	74.00	-28.22	54.26	41.32	14.58	64.38	---	--- Peak	 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Apos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 10360.00</td><td>60.20</td><td>68.30</td><td>-8.10</td><td>73.43</td><td>38.47</td><td>12.06</td><td>63.76</td><td>394</td><td>334 Peak</td></tr><tr><td>2 15540.00</td><td>46.24</td><td>74.00</td><td>-27.76</td><td>54.72</td><td>41.32</td><td>14.58</td><td>64.38</td><td>---</td><td>--- Peak</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Apos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 10360.00	60.20	68.30	-8.10	73.43	38.47	12.06	63.76	394	334 Peak	2 15540.00	46.24	74.00	-27.76	54.72	41.32	14.58	64.38	---	--- Peak
		Limit	Read	Ant	Cable	Preamp	Apos	TPos	Remark																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10360.00	62.14	68.30	-6.16	75.37	38.47	12.06	63.76	185	352 Peak																																																																																									
2 15540.00	45.78	74.00	-28.22	54.26	41.32	14.58	64.38	---	--- Peak																																																																																									
	Limit	Read	Ant	Cable	Preamp	Apos	TPos	Remark																																																																																										
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1 10360.00	60.20	68.30	-8.10	73.43	38.47	12.06	63.76	394	334 Peak																																																																																									
2 15540.00	46.24	74.00	-27.76	54.72	41.32	14.58	64.38	---	--- Peak																																																																																									



Mode	11																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-1_5.15-5.25_802.11ax HE20_CH44_5220MHz																																																																																																																			
ANT	CDD8+9																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>61.97</td><td>68.30</td><td>-6.33</td><td>75.08</td><td>38.49</td><td>12.12</td><td>63.72</td><td>185</td><td>352</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>46.21</td><td>74.00</td><td>-27.79</td><td>54.63</td><td>41.40</td><td>14.64</td><td>64.46</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	61.97	68.30	-6.33	75.08	38.49	12.12	63.72	185	352	Peak	2	15660.00	46.21	74.00	-27.79	54.63	41.40	14.64	64.46	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10440.00</td><td>60.76</td><td>68.30</td><td>-7.54</td><td>73.87</td><td>38.49</td><td>12.12</td><td>63.72</td><td>400</td><td>346</td><td>Peak</td></tr><tr><td>2</td><td>15660.00</td><td>44.83</td><td>74.00</td><td>-29.17</td><td>53.25</td><td>41.40</td><td>14.64</td><td>64.46</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10440.00	60.76	68.30	-7.54	73.87	38.49	12.12	63.72	400	346	Peak	2	15660.00	44.83	74.00	-29.17	53.25	41.40	14.64	64.46	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10440.00	61.97	68.30	-6.33	75.08	38.49	12.12	63.72	185	352	Peak																																																																																																									
2	15660.00	46.21	74.00	-27.79	54.63	41.40	14.64	64.46	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10440.00	60.76	68.30	-7.54	73.87	38.49	12.12	63.72	400	346	Peak																																																																																																									
2	15660.00	44.83	74.00	-29.17	53.25	41.40	14.64	64.46	---	---	Peak																																																																																																									



		12									
Mode		Band Edge - L									
		U-NII-1_5.15-5.25_802.11ax HE20_CH48_5240MHz									
ANT		CDD8+9									
Pol.		Horizontal					Fundamental				
Peak	Level (dBuV/m) Date: 2025-03-20										





Mode	12									
	Band Edge - R									
	U-NII-1_5.15-5.25_802.11ax HE20_CH48_5240MHz									
ANT	CDD8+9									
Pol.	Horizontal					Fundamental				
Peak										





		12																																																																																																
Mode		Band Edge - L																																																																																																
		U-NII-1_5.15-5.25_802.11ax HE20_CH48_5240MHz																																																																																																
ANT		CDD8+9																																																																																																
Pol.		Vertical					Fundamental																																																																																											
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5112.32</td><td>51.44</td><td>74.00</td><td>-22.56</td><td>39.84</td><td>36.61</td><td>8.47</td><td>33.48</td><td>226</td><td>103 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5112.32	51.44	74.00	-22.56	39.84	36.61	8.47	33.48	226	103 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5240.00</td><td>108.36</td><td>-----</td><td>-----</td><td>96.49</td><td>36.51</td><td>8.81</td><td>33.45</td><td>226</td><td>103 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5240.00	108.36	-----	-----	96.49	36.51	8.81	33.45	226	103 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5112.32	51.44	74.00	-22.56	39.84	36.61	8.47	33.48	226	103 PEAK																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5240.00	108.36	-----	-----	96.49	36.51	8.81	33.45	226	103 PEAK																																																																																								
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5093.12</td><td>42.15</td><td>54.00</td><td>-11.85</td><td>30.57</td><td>36.63</td><td>8.43</td><td>33.48</td><td>226</td><td>103 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5093.12	42.15	54.00	-11.85	30.57	36.63	8.43	33.48	226	103 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5240.00</td><td>100.19</td><td>-----</td><td>-----</td><td>88.36</td><td>36.51</td><td>8.77</td><td>33.45</td><td>226</td><td>103 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark		Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg		1	5240.00	100.19	-----	-----	88.36	36.51	8.77	33.45	226	103 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5093.12	42.15	54.00	-11.85	30.57	36.63	8.43	33.48	226	103 AVERAGE																																																																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5240.00	100.19	-----	-----	88.36	36.51	8.77	33.45	226	103 AVERAGE																																																																																								







Mode	12																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ax HE20_CH48_5240MHz																																										
ANT	CDD8+9																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5450.10</td><td>50.62</td><td>74.00</td><td>-23.38</td><td>38.01</td><td>36.34</td><td>9.68</td><td>33.41</td><td>226</td><td>103 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5450.10	50.62	74.00	-23.38	38.01	36.34	9.68	33.41	226	103 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5450.10	50.62	74.00	-23.38	38.01	36.34	9.68	33.41	226	103 PEAK																																	
Avg	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5414.02</td><td>41.59</td><td>54.00</td><td>-12.41</td><td>28.98</td><td>36.37</td><td>9.66</td><td>33.42</td><td>226</td><td>103 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5414.02	41.59	54.00	-12.41	28.98	36.37	9.66	33.42	226	103 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5414.02	41.59	54.00	-12.41	28.98	36.37	9.66	33.42	226	103 AVERAGE																																	



Mode	12																																																																																																																																	
	Harmonic																																																																																																																																	
	U-NII-1_5.15-5.25_802.11ax HE20_CH48_5240MHz																																																																																																																																	
ANT	CDD8+9																																																																																																																																	
Pol.	Horizontal						Vertical																																																																																																																											
Peak Avg																																																																																																																																		
	<table><thead><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>10480.00</td><td>61.92</td><td>68.30</td><td>-6.38</td><td>74.98</td><td>38.50</td><td>12.15</td><td>63.71</td><td>206</td><td>348</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>45.47</td><td>74.00</td><td>-28.53</td><td>53.88</td><td>41.43</td><td>14.66</td><td>64.50</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10480.00	61.92	68.30	-6.38	74.98	38.50	12.15	63.71	206	348	Peak	2	15720.00	45.47	74.00	-28.53	53.88	41.43	14.66	64.50	---	---	Peak	<table><thead><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>10480.00</td><td>60.49</td><td>68.30</td><td>-7.81</td><td>73.55</td><td>38.50</td><td>12.15</td><td>63.71</td><td>398</td><td>352</td><td>Peak</td></tr><tr><td>2</td><td>15720.00</td><td>44.91</td><td>74.00</td><td>-29.09</td><td>53.32</td><td>41.43</td><td>14.66</td><td>64.50</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg			1	10480.00	60.49	68.30	-7.81	73.55	38.50	12.15	63.71	398	352	Peak	2	15720.00	44.91	74.00	-29.09	53.32	41.43	14.66	64.50	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																						
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10480.00	61.92	68.30	-6.38	74.98	38.50	12.15	63.71	206	348	Peak																																																																																																																							
2	15720.00	45.47	74.00	-28.53	53.88	41.43	14.66	64.50	---	---	Peak																																																																																																																							
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																							
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																											
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																									
1	10480.00	60.49	68.30	-7.81	73.55	38.50	12.15	63.71	398	352	Peak																																																																																																																							
2	15720.00	44.91	74.00	-29.09	53.32	41.43	14.66	64.50	---	---	Peak																																																																																																																							







		13									
Mode		Band Edge - L									
		U-NII-2A_5.25-5.35_802.11ax HE20_CH52_5260MHz									
ANT		CDD8+9									
Pol.		Horizontal					Fundamental				
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) 1 5036.92 52.03 74.00 -21.97 40.52 36.67 8.33 33.49 328 35 PEAK					 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) 1 5260.00 106.83 ----- 94.89 36.49 8.90 33.45 328 35 PEAK					
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg					Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg					
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) 1 5103.22 41.93 54.00 -12.07 30.34 36.62 8.45 33.48 328 35 AVERAGE					 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) 1 5260.00 98.59 ----- 86.65 36.49 8.90 33.45 328 35 AVERAGE					
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg					Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg					





Mode	13																																																		
	Band Edge - R																																																		
	U-NII-2A_5.25-5.35_802.11ax HE20_CH52_5260MHz																																																		
ANT	CDD8+9																																																		
Pol.	Horizontal					Fundamental																																													
Peak	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5449.20</td><td>51.25</td><td>74.00</td><td>-22.75</td><td>38.64</td><td>36.34</td><td>9.68</td><td>33.41</td><td>328</td><td>35 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5449.20	51.25	74.00	-22.75	38.64	36.34	9.68	33.41	328	35 PEAK	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5449.20	51.25	74.00	-22.75	38.64	36.34	9.68	33.41	328	35 PEAK																																									
Avg	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5361.00</td><td>41.91</td><td>54.00</td><td>-12.09</td><td>29.51</td><td>36.41</td><td>9.42</td><td>33.43</td><td>328</td><td>35 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5361.00	41.91	54.00	-12.09	29.51	36.41	9.42	33.43	328	35 AVERAGE	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																										
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																										
1	5361.00	41.91	54.00	-12.09	29.51	36.41	9.42	33.43	328	35 AVERAGE																																									





Mode	13																																																																																	
	Band Edge - L																																																																																	
	U-NII-2A_5.25-5.35_802.11ax HE20_CH52_5260MHz																																																																																	
ANT	CDD8+9																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5023.40</td><td>51.49</td><td>74.00</td><td>-22.51</td><td>40.01</td><td>36.68</td><td>8.30</td><td>33.50</td><td>100</td><td>255 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5023.40	51.49	74.00	-22.51	40.01	36.68	8.30	33.50	100	255 PEAK	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5260.00</td><td>104.05</td><td>-----</td><td>-----</td><td>92.11</td><td>36.49</td><td>8.90</td><td>33.45</td><td>100</td><td>255 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5260.00	104.05	-----	-----	92.11	36.49	8.90	33.45	100	255 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5023.40	51.49	74.00	-22.51	40.01	36.68	8.30	33.50	100	255 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5260.00	104.05	-----	-----	92.11	36.49	8.90	33.45	100	255 PEAK																																																																									
Avg	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5105.82</td><td>41.90</td><td>54.00</td><td>-12.10</td><td>30.31</td><td>36.62</td><td>8.45</td><td>33.48</td><td>100</td><td>255 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5105.82	41.90	54.00	-12.10	30.31	36.62	8.45	33.48	100	255 AVERAGE	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5260.00</td><td>96.26</td><td>-----</td><td>-----</td><td>84.32</td><td>36.49</td><td>8.90</td><td>33.45</td><td>100</td><td>255 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5260.00	96.26	-----	-----	84.32	36.49	8.90	33.45	100	255 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5105.82	41.90	54.00	-12.10	30.31	36.62	8.45	33.48	100	255 AVERAGE																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																									
1 5260.00	96.26	-----	-----	84.32	36.49	8.90	33.45	100	255 AVERAGE																																																																									





Mode	13																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ax HE20_CH52_5260MHz																																										
ANT	CDD8+9																																										
Pol.	Vertical	Fundamental																																									
Peak	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5435.40</td><td>51.10</td><td>74.00</td><td>-22.90</td><td>38.49</td><td>36.35</td><td>9.67</td><td>33.41</td><td>100</td><td>255 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5435.40	51.10	74.00	-22.90	38.49	36.35	9.67	33.41	100	255 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5435.40	51.10	74.00	-22.90	38.49	36.35	9.67	33.41	100	255 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-20  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5359.80</td><td>41.72</td><td>54.00</td><td>-12.28</td><td>29.32</td><td>36.41</td><td>9.42</td><td>33.43</td><td>100</td><td>255 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5359.80	41.72	54.00	-12.28	29.32	36.41	9.42	33.43	100	255 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5359.80	41.72	54.00	-12.28	29.32	36.41	9.42	33.43	100	255 AVERAGE																																	









Mode	13																																																																																																																			
	Harmonic																																																																																																																			
	U-NII-2A_5.25-5.35_802.11ax HE20_CH52_5260MHz																																																																																																																			
ANT	CDD8+9																																																																																																																			
Pol.	Horizontal						Vertical																																																																																																													
Peak Avg																																																																																																																				
	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10520.00</td><td>61.91</td><td>68.30</td><td>-6.39</td><td>74.92</td><td>38.50</td><td>12.18</td><td>63.69</td><td>191</td><td>354</td><td>Peak</td></tr><tr><td>2</td><td>15780.00</td><td>44.47</td><td>74.00</td><td>-29.53</td><td>52.86</td><td>41.47</td><td>14.69</td><td>64.55</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10520.00	61.91	68.30	-6.39	74.92	38.50	12.18	63.69	191	354	Peak	2	15780.00	44.47	74.00	-29.53	52.86	41.47	14.69	64.55	---	---	Peak	<table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>10520.00</td><td>60.37</td><td>68.30</td><td>-7.93</td><td>73.38</td><td>38.50</td><td>12.18</td><td>63.69</td><td>394</td><td>338</td><td>Peak</td></tr><tr><td>2</td><td>15780.00</td><td>45.50</td><td>74.00</td><td>-28.50</td><td>53.89</td><td>41.47</td><td>14.69</td><td>64.55</td><td>---</td><td>---</td><td>Peak</td></tr></tbody></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	10520.00	60.37	68.30	-7.93	73.38	38.50	12.18	63.69	394	338	Peak	2	15780.00	45.50	74.00	-28.50	53.89	41.47	14.69	64.55	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																												
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10520.00	61.91	68.30	-6.39	74.92	38.50	12.18	63.69	191	354	Peak																																																																																																									
2	15780.00	44.47	74.00	-29.53	52.86	41.47	14.69	64.55	---	---	Peak																																																																																																									
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																																																																																											
1	10520.00	60.37	68.30	-7.93	73.38	38.50	12.18	63.69	394	338	Peak																																																																																																									
2	15780.00	45.50	74.00	-28.50	53.89	41.47	14.69	64.55	---	---	Peak																																																																																																									



Mode	14																																																																																																																																														
	Harmonic																																																																																																																																														
	U-NII-2A_5.25-5.35_802.11ax HE20_CH60_5300MHz																																																																																																																																														
ANT	CDD8+9																																																																																																																																														
Pol.	Horizontal						Vertical																																																																																																																																								
Peak Avg																																																																																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>10600.00</td><td>57.02</td><td>74.00</td><td>-16.98</td><td>69.93</td><td>38.52</td><td>12.23</td><td>63.66</td><td>207</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>10600.00</td><td>47.53</td><td>54.00</td><td>-6.47</td><td>60.44</td><td>38.52</td><td>12.23</td><td>63.66</td><td>207</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>15900.00</td><td>44.80</td><td>74.00</td><td>-29.20</td><td>53.14</td><td>41.54</td><td>14.75</td><td>64.63</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	10600.00	57.02	74.00	-16.98	69.93	38.52	12.23	63.66	207	360	Peak	2	10600.00	47.53	54.00	-6.47	60.44	38.52	12.23	63.66	207	360	Average	3	15900.00	44.80	74.00	-29.20	53.14	41.54	14.75	64.63	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>10600.00</td><td>56.73</td><td>74.00</td><td>-17.27</td><td>69.64</td><td>38.52</td><td>12.23</td><td>63.66</td><td>400</td><td>331</td><td>Peak</td></tr><tr><td>2</td><td>10600.00</td><td>46.56</td><td>54.00</td><td>-7.44</td><td>59.47</td><td>38.52</td><td>12.23</td><td>63.66</td><td>400</td><td>331</td><td>Average</td></tr><tr><td>3</td><td>15900.00</td><td>45.44</td><td>74.00</td><td>-28.56</td><td>53.78</td><td>41.54</td><td>14.75</td><td>64.63</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	10600.00	56.73	74.00	-17.27	69.64	38.52	12.23	63.66	400	331	Peak	2	10600.00	46.56	54.00	-7.44	59.47	38.52	12.23	63.66	400	331	Average	3	15900.00	45.44	74.00	-28.56	53.78	41.54	14.75	64.63	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																							
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																					
1	10600.00	57.02	74.00	-16.98	69.93	38.52	12.23	63.66	207	360	Peak																																																																																																																																				
2	10600.00	47.53	54.00	-6.47	60.44	38.52	12.23	63.66	207	360	Average																																																																																																																																				
3	15900.00	44.80	74.00	-29.20	53.14	41.54	14.75	64.63	---	---	Peak																																																																																																																																				
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																							
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																					
1	10600.00	56.73	74.00	-17.27	69.64	38.52	12.23	63.66	400	331	Peak																																																																																																																																				
2	10600.00	46.56	54.00	-7.44	59.47	38.52	12.23	63.66	400	331	Average																																																																																																																																				
3	15900.00	45.44	74.00	-28.56	53.78	41.54	14.75	64.63	---	---	Peak																																																																																																																																				





		15																																																																																		
Mode	Band Edge																																																																																			
	U-NII-2A_5.25-5.35_802.11ax HE20_CH64_5320MHz																																																																																			
ANT	CDD8+9																																																																																			
Pol.	Horizontal					Fundamental																																																																														
Peak	Level (dBuV/m) Date: 2025-03-20  532053485376540454325460 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5448.38</td><td>51.20</td><td>74.00</td><td>-22.80</td><td>38.59</td><td>36.34</td><td>9.68</td><td>33.41</td><td>300 31 PEAK</td></tr></table> <td colspan="5"> Level (dBuV/m) Date: 2025-03-20  100022003400460058007000 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5320.00</td><td>105.61</td><td>-----</td><td>-----</td><td>93.40</td><td>36.44</td><td>9.21</td><td>33.44</td><td>300 31 PEAK</td></tr></table> </td>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5448.38	51.20	74.00	-22.80	38.59	36.34	9.68	33.41	300 31 PEAK	Level (dBuV/m) Date: 2025-03-20  100022003400460058007000 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5320.00</td><td>105.61</td><td>-----</td><td>-----</td><td>93.40</td><td>36.44</td><td>9.21</td><td>33.44</td><td>300 31 PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5320.00	105.61	-----	-----	93.40	36.44	9.21	33.44	300 31 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5448.38	51.20	74.00	-22.80	38.59	36.34	9.68	33.41	300 31 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5320.00	105.61	-----	-----	93.40	36.44	9.21	33.44	300 31 PEAK																																																																											
Avg	Level (dBuV/m) Date: 2025-03-20  532053485376540454325460 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.80</td><td>42.44</td><td>54.00</td><td>-11.56</td><td>30.08</td><td>36.42</td><td>9.37</td><td>33.43</td><td>300 31 AVERAGE</td></tr></table> <td colspan="5"> Level (dBuV/m) Date: 2025-03-20  100022003400460058007000 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5320.00</td><td>97.09</td><td>-----</td><td>-----</td><td>84.88</td><td>36.44</td><td>9.21</td><td>33.44</td><td>300 31 AVERAGE</td></tr></table> </td>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.80	42.44	54.00	-11.56	30.08	36.42	9.37	33.43	300 31 AVERAGE	Level (dBuV/m) Date: 2025-03-20  100022003400460058007000 <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5320.00</td><td>97.09</td><td>-----</td><td>-----</td><td>84.88</td><td>36.44</td><td>9.21</td><td>33.44</td><td>300 31 AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5320.00	97.09	-----	-----	84.88	36.44	9.21	33.44	300 31 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5350.80	42.44	54.00	-11.56	30.08	36.42	9.37	33.43	300 31 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5320.00	97.09	-----	-----	84.88	36.44	9.21	33.44	300 31 AVERAGE																																																																											



		15																																																																																								
Mode		Band Edge																																																																																								
		U-NII-2A_5.25-5.35_802.11ax HE20_CH64_5320MHz																																																																																								
ANT		CDD8+9																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1 5450.48</td><td>51.47</td><td>74.00</td><td>-22.53</td><td>38.86</td><td>36.34</td><td>9.68</td><td>33.41</td><td>300</td><td>95 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1 5450.48	51.47	74.00	-22.53	38.86	36.34	9.68	33.41	300	95 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1 5320.00</td><td>106.32</td><td>-----</td><td>-----</td><td>94.13</td><td>36.45</td><td>9.18</td><td>33.44</td><td>300</td><td>95 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1 5320.00	106.32	-----	-----	94.13	36.45	9.18	33.44	300	95 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1 5450.48	51.47	74.00	-22.53	38.86	36.34	9.68	33.41	300	95 PEAK																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1 5320.00	106.32	-----	-----	94.13	36.45	9.18	33.44	300	95 PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1 5355.84</td><td>43.37</td><td>54.00</td><td>-10.63</td><td>30.98</td><td>36.42</td><td>9.40</td><td>33.43</td><td>300</td><td>95 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1 5355.84	43.37	54.00	-10.63	30.98	36.42	9.40	33.43	300	95 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1 5320.00</td><td>99.00</td><td>-----</td><td>-----</td><td>86.79</td><td>36.44</td><td>9.21</td><td>33.44</td><td>300</td><td>95 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1 5320.00	99.00	-----	-----	86.79	36.44	9.21	33.44	300	95 AVERAGE
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1 5355.84	43.37	54.00	-10.63	30.98	36.42	9.40	33.43	300	95 AVERAGE																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor			Remark																																																																																	
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																		
1 5320.00	99.00	-----	-----	86.79	36.44	9.21	33.44	300	95 AVERAGE																																																																																	



Mode	15																																																																																																																																					
	Harmonic																																																																																																																																					
	U-NII-2A_5.25-5.35_802.11ax HE20_CH64_5320MHz																																																																																																																																					
ANT	CDD8+9																																																																																																																																					
Pol.	Horizontal										Vertical																																																																																																																											
Peak Avg																																																																																																																																						
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>54.01</td><td>74.00</td><td>-19.99</td><td>66.86</td><td>38.53</td><td>12.26</td><td>63.64</td><td>180</td><td>354 Peak</td></tr><tr><td>2</td><td>10640.00</td><td>47.31</td><td>54.00</td><td>-6.69</td><td>60.16</td><td>38.53</td><td>12.26</td><td>63.64</td><td>180</td><td>354 Average</td></tr><tr><td>3</td><td>15960.00</td><td>44.12</td><td>74.00</td><td>-29.88</td><td>52.44</td><td>41.58</td><td>14.77</td><td>64.67</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	54.01	74.00	-19.99	66.86	38.53	12.26	63.64	180	354 Peak	2	10640.00	47.31	54.00	-6.69	60.16	38.53	12.26	63.64	180	354 Average	3	15960.00	44.12	74.00	-29.88	52.44	41.58	14.77	64.67	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10640.00</td><td>53.67</td><td>74.00</td><td>-20.33</td><td>66.52</td><td>38.53</td><td>12.26</td><td>63.64</td><td>400</td><td>352 Peak</td></tr><tr><td>2</td><td>10640.00</td><td>45.77</td><td>54.00</td><td>-8.23</td><td>58.62</td><td>38.53</td><td>12.26</td><td>63.64</td><td>400</td><td>352 Average</td></tr><tr><td>3</td><td>15960.00</td><td>42.65</td><td>74.00</td><td>-31.35</td><td>50.97</td><td>41.58</td><td>14.77</td><td>64.67</td><td>---</td><td>---</td><td>Peak</td></tr></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10640.00	53.67	74.00	-20.33	66.52	38.53	12.26	63.64	400	352 Peak	2	10640.00	45.77	54.00	-8.23	58.62	38.53	12.26	63.64	400	352 Average	3	15960.00	42.65	74.00	-31.35	50.97	41.58	14.77	64.67	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																													
1	10640.00	54.01	74.00	-19.99	66.86	38.53	12.26	63.64	180	354 Peak																																																																																																																												
2	10640.00	47.31	54.00	-6.69	60.16	38.53	12.26	63.64	180	354 Average																																																																																																																												
3	15960.00	44.12	74.00	-29.88	52.44	41.58	14.77	64.67	---	---	Peak																																																																																																																											
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																													
1	10640.00	53.67	74.00	-20.33	66.52	38.53	12.26	63.64	400	352 Peak																																																																																																																												
2	10640.00	45.77	54.00	-8.23	58.62	38.53	12.26	63.64	400	352 Average																																																																																																																												
3	15960.00	42.65	74.00	-31.35	50.97	41.58	14.77	64.67	---	---	Peak																																																																																																																											



	16																																																																																		
Mode	Band Edge																																																																																		
	U-NII-2C_5.47-5.725_802.11ax HE20_CH100_5500MHz																																																																																		
ANT	CDD8+9																																																																																		
Pol.	Horizontal	Fundamental																																																																																	
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5414.35</td><td>51.89</td><td>74.00</td><td>-22.11</td><td>39.28</td><td>36.37</td><td>9.66</td><td>33.42</td><td>240 31 PEAK</td></tr><tr><td>2 5468.95</td><td>51.16</td><td>68.30</td><td>-17.14</td><td>38.56</td><td>36.32</td><td>9.69</td><td>33.41</td><td>240 31 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5414.35	51.89	74.00	-22.11	39.28	36.37	9.66	33.42	240 31 PEAK	2 5468.95	51.16	68.30	-17.14	38.56	36.32	9.69	33.41	240 31 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5500.00</td><td>103.40</td><td>-----</td><td>-----</td><td>90.79</td><td>36.30</td><td>9.71</td><td>33.40</td><td>240 31 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5500.00	103.40	-----	-----	90.79	36.30	9.71	33.40	240 31 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Level	Factor	Loss Factor																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5414.35	51.89	74.00	-22.11	39.28	36.37	9.66	33.42	240 31 PEAK																																																																											
2 5468.95	51.16	68.30	-17.14	38.56	36.32	9.69	33.41	240 31 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	Level	Factor	Loss Factor																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5500.00	103.40	-----	-----	90.79	36.30	9.71	33.40	240 31 PEAK																																																																											
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5458.30</td><td>42.34</td><td>54.00</td><td>-11.66</td><td>29.73</td><td>36.33</td><td>9.69</td><td>33.41</td><td>240 31 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5458.30	42.34	54.00	-11.66	29.73	36.33	9.69	33.41	240 31 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5500.00</td><td>94.10</td><td>-----</td><td>-----</td><td>81.49</td><td>36.30</td><td>9.71</td><td>33.40</td><td>240 31 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5500.00	94.10	-----	-----	81.49	36.30	9.71	33.40	240 31 AVERAGE									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																										
Freq	Level	Line	Level	Factor	Loss Factor																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5458.30	42.34	54.00	-11.66	29.73	36.33	9.69	33.41	240 31 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	Level	Factor	Loss Factor																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																											
1 5500.00	94.10	-----	-----	81.49	36.30	9.71	33.40	240 31 AVERAGE																																																																											





		16																																																																																																		
Mode		Band Edge																																																																																																		
		U-NII-2C_5.47-5.725_802.11ax HE20_CH100_5500MHz																																																																																																		
ANT		CDD8+9																																																																																																		
Pol.		Vertical					Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5449.75</td><td>51.30</td><td>74.00</td><td>-22.70</td><td>38.69</td><td>36.34</td><td>9.68</td><td>33.41</td><td>306</td><td>252</td><td>PEAK</td></tr><tr><td>2</td><td>5464.75</td><td>51.49</td><td>68.30</td><td>-16.81</td><td>38.88</td><td>36.33</td><td>9.69</td><td>33.41</td><td>306</td><td>252</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5449.75	51.30	74.00	-22.70	38.69	36.34	9.68	33.41	306	252	PEAK	2	5464.75	51.49	68.30	-16.81	38.88	36.33	9.69	33.41	306	252	PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5500.00</td><td>101.64</td><td>-----</td><td>-----</td><td>89.02</td><td>36.31</td><td>9.71</td><td>33.40</td><td>306</td><td>252</td><td>PEAK</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5500.00	101.64	-----	-----	89.02	36.31	9.71	33.40	306	252	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5449.75	51.30	74.00	-22.70	38.69	36.34	9.68	33.41	306	252	PEAK																																																																																									
2	5464.75	51.49	68.30	-16.81	38.88	36.33	9.69	33.41	306	252	PEAK																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5500.00	101.64	-----	-----	89.02	36.31	9.71	33.40	306	252	PEAK																																																																																									
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5459.35</td><td>42.37</td><td>54.00</td><td>-11.63</td><td>29.76</td><td>36.33</td><td>9.69</td><td>33.41</td><td>306</td><td>252</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5459.35	42.37	54.00	-11.63	29.76	36.33	9.69	33.41	306	252	AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5500.00</td><td>94.49</td><td>-----</td><td>-----</td><td>81.88</td><td>36.30</td><td>9.71</td><td>33.40</td><td>306</td><td>252</td><td>AVERAGE</td></tr></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5500.00	94.49	-----	-----	81.88	36.30	9.71	33.40	306	252	AVERAGE												
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5459.35	42.37	54.00	-11.63	29.76	36.33	9.69	33.41	306	252	AVERAGE																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5500.00	94.49	-----	-----	81.88	36.30	9.71	33.40	306	252	AVERAGE																																																																																									



Mode	16																																																																																																																														
	Harmonic																																																																																																																														
	U-NII-2C_5.47-5.725_802.11ax HE20_CH100_5500MHz																																																																																																																														
ANT	CDD8+9																																																																																																																														
Pol.	Horizontal					Vertical																																																																																																																									
Peak Avg																																																																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11000.00</td><td>50.75</td><td>74.00</td><td>-23.25</td><td>63.13</td><td>38.60</td><td>12.52</td><td>63.50</td><td>218</td><td>351 Peak</td></tr><tr><td>2 11000.00</td><td>44.45</td><td>54.00</td><td>-9.55</td><td>56.83</td><td>38.60</td><td>12.52</td><td>63.50</td><td>218</td><td>351 Average</td></tr><tr><td>3 16500.00</td><td>43.88</td><td>68.30</td><td>-24.42</td><td>51.51</td><td>41.95</td><td>15.17</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11000.00	50.75	74.00	-23.25	63.13	38.60	12.52	63.50	218	351 Peak	2 11000.00	44.45	54.00	-9.55	56.83	38.60	12.52	63.50	218	351 Average	3 16500.00	43.88	68.30	-24.42	51.51	41.95	15.17	64.75	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11000.00</td><td>50.01</td><td>74.00</td><td>-23.99</td><td>62.39</td><td>38.60</td><td>12.52</td><td>63.50</td><td>389</td><td>350 Peak</td></tr><tr><td>2 11000.00</td><td>44.01</td><td>54.00</td><td>-9.99</td><td>56.39</td><td>38.60</td><td>12.52</td><td>63.50</td><td>389</td><td>350 Average</td></tr><tr><td>3 16500.00</td><td>46.15</td><td>68.30</td><td>-22.15</td><td>53.78</td><td>41.95</td><td>15.17</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11000.00	50.01	74.00	-23.99	62.39	38.60	12.52	63.50	389	350 Peak	2 11000.00	44.01	54.00	-9.99	56.39	38.60	12.52	63.50	389	350 Average	3 16500.00	46.15	68.30	-22.15	53.78	41.95	15.17	64.75	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																						
1 11000.00	50.75	74.00	-23.25	63.13	38.60	12.52	63.50	218	351 Peak																																																																																																																						
2 11000.00	44.45	54.00	-9.55	56.83	38.60	12.52	63.50	218	351 Average																																																																																																																						
3 16500.00	43.88	68.30	-24.42	51.51	41.95	15.17	64.75	---	---	Peak																																																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																						
1 11000.00	50.01	74.00	-23.99	62.39	38.60	12.52	63.50	389	350 Peak																																																																																																																						
2 11000.00	44.01	54.00	-9.99	56.39	38.60	12.52	63.50	389	350 Average																																																																																																																						
3 16500.00	46.15	68.30	-22.15	53.78	41.95	15.17	64.75	---	---	Peak																																																																																																																					



Mode	17																																																																																																																																											
	Harmonic																																																																																																																																											
	U-NII-2C_5.47-5.725_802.11ax HE20_CH116_5580MHz																																																																																																																																											
ANT	CDD8+9																																																																																																																																											
Pol.	Horizontal						Vertical																																																																																																																																					
Peak Avg																																																																																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11160.00</td><td>54.39</td><td>74.00</td><td>-19.61</td><td>66.57</td><td>38.79</td><td>12.64</td><td>63.61</td><td>206</td><td>360</td><td>Peak</td></tr><tr><td>2</td><td>11160.00</td><td>46.83</td><td>54.00</td><td>-7.17</td><td>59.01</td><td>38.79</td><td>12.64</td><td>63.61</td><td>206</td><td>360</td><td>Average</td></tr><tr><td>3</td><td>16740.00</td><td>43.71</td><td>68.30</td><td>-24.59</td><td>51.01</td><td>42.12</td><td>15.35</td><td>64.77</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11160.00	54.39	74.00	-19.61	66.57	38.79	12.64	63.61	206	360	Peak	2	11160.00	46.83	54.00	-7.17	59.01	38.79	12.64	63.61	206	360	Average	3	16740.00	43.71	68.30	-24.59	51.01	42.12	15.35	64.77	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11160.00</td><td>48.84</td><td>74.00</td><td>-25.16</td><td>61.02</td><td>38.79</td><td>12.64</td><td>63.61</td><td>400</td><td>349</td><td>Peak</td></tr><tr><td>2</td><td>11160.00</td><td>42.54</td><td>54.00</td><td>-11.46</td><td>54.72</td><td>38.79</td><td>12.64</td><td>63.61</td><td>400</td><td>349</td><td>Average</td></tr><tr><td>3</td><td>16740.00</td><td>46.66</td><td>68.30</td><td>-21.64</td><td>53.96</td><td>42.12</td><td>15.35</td><td>64.77</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11160.00	48.84	74.00	-25.16	61.02	38.79	12.64	63.61	400	349	Peak	2	11160.00	42.54	54.00	-11.46	54.72	38.79	12.64	63.61	400	349	Average	3	16740.00	46.66	68.30	-21.64	53.96	42.12	15.35	64.77	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																		
1	11160.00	54.39	74.00	-19.61	66.57	38.79	12.64	63.61	206	360	Peak																																																																																																																																	
2	11160.00	46.83	54.00	-7.17	59.01	38.79	12.64	63.61	206	360	Average																																																																																																																																	
3	16740.00	43.71	68.30	-24.59	51.01	42.12	15.35	64.77	---	---	Peak																																																																																																																																	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																		
1	11160.00	48.84	74.00	-25.16	61.02	38.79	12.64	63.61	400	349	Peak																																																																																																																																	
2	11160.00	42.54	54.00	-11.46	54.72	38.79	12.64	63.61	400	349	Average																																																																																																																																	
3	16740.00	46.66	68.30	-21.64	53.96	42.12	15.35	64.77	---	---	Peak																																																																																																																																	





Mode	18									
	Band Edge									
	U-NII-2C_5.47-5.725_802.11ax HE20_CH140_5700MHz									
ANT	CDD8+9									
Pol.	Horizontal					Fundamental				
Peak	Level (dBuV/m) </									







Mode	18																																																																																	
	Band Edge																																																																																	
	U-NII-2C_5.47-5.725_802.11ax HE20_CH140_5700MHz																																																																																	
ANT	CDD8+9																																																																																	
Pol.	Vertical	Fundamental																																																																																
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5751.29</td><td>51.98</td><td>68.30</td><td>-16.32</td><td>38.81</td><td>36.55</td><td>10.07</td><td>33.45</td><td>327 267 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5751.29	51.98	68.30	-16.32	38.81	36.55	10.07	33.45	327 267 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>105.46</td><td>-----</td><td>92.44</td><td>36.50</td><td>9.96</td><td>33.44</td><td>327</td><td>267 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	105.46	-----	92.44	36.50	9.96	33.44	327	267 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5751.29	51.98	68.30	-16.32	38.81	36.55	10.07	33.45	327 267 PEAK																																																																									
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5700.00	105.46	-----	92.44	36.50	9.96	33.44	327	267 PEAK																																																																									
Avg	Blank	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5700.00</td><td>98.58</td><td>-----</td><td>85.56</td><td>36.50</td><td>9.96</td><td>33.44</td><td>327</td><td>267 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor					MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5700.00	98.58	-----	85.56	36.50	9.96	33.44	327	267 AVERAGE																																								
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																												
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																									
1	5700.00	98.58	-----	85.56	36.50	9.96	33.44	327	267 AVERAGE																																																																									



Mode	18																																																																																																																															
	Harmonic																																																																																																																															
	U-NII-2C_5.47-5.725_802.11ax HE20_CH140_5700MHz																																																																																																																															
ANT	CDD8+9																																																																																																																															
Pol.	Horizontal					Vertical																																																																																																																										
Peak Avg																																																																																																																																
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11400.00</td><td>54.71</td><td>74.00</td><td>-19.29</td><td>66.60</td><td>39.08</td><td>12.81</td><td>63.78</td><td>180</td><td>8 Peak</td></tr><tr><td>2 11400.00</td><td>47.69</td><td>54.00</td><td>-6.31</td><td>59.58</td><td>39.08</td><td>12.81</td><td>63.78</td><td>180</td><td>8 Average</td></tr><tr><td>3 17100.00</td><td>45.26</td><td>68.30</td><td>-23.04</td><td>52.14</td><td>42.41</td><td>15.62</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11400.00	54.71	74.00	-19.29	66.60	39.08	12.81	63.78	180	8 Peak	2 11400.00	47.69	54.00	-6.31	59.58	39.08	12.81	63.78	180	8 Average	3 17100.00	45.26	68.30	-23.04	52.14	42.41	15.62	64.91	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11400.00</td><td>51.38</td><td>74.00</td><td>-22.62</td><td>63.27</td><td>39.08</td><td>12.81</td><td>63.78</td><td>400</td><td>352 Peak</td></tr><tr><td>2 11400.00</td><td>44.48</td><td>54.00</td><td>-9.52</td><td>56.37</td><td>39.08</td><td>12.81</td><td>63.78</td><td>400</td><td>352 Average</td></tr><tr><td>3 17100.00</td><td>46.64</td><td>68.30</td><td>-21.66</td><td>53.52</td><td>42.41</td><td>15.62</td><td>64.91</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11400.00	51.38	74.00	-22.62	63.27	39.08	12.81	63.78	400	352 Peak	2 11400.00	44.48	54.00	-9.52	56.37	39.08	12.81	63.78	400	352 Average	3 17100.00	46.64	68.30	-21.66	53.52	42.41	15.62	64.91	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1 11400.00	54.71	74.00	-19.29	66.60	39.08	12.81	63.78	180	8 Peak																																																																																																																							
2 11400.00	47.69	54.00	-6.31	59.58	39.08	12.81	63.78	180	8 Average																																																																																																																							
3 17100.00	45.26	68.30	-23.04	52.14	42.41	15.62	64.91	---	---	Peak																																																																																																																						
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																								
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1 11400.00	51.38	74.00	-22.62	63.27	39.08	12.81	63.78	400	352 Peak																																																																																																																							
2 11400.00	44.48	54.00	-9.52	56.37	39.08	12.81	63.78	400	352 Average																																																																																																																							
3 17100.00	46.64	68.30	-21.66	53.52	42.41	15.62	64.91	---	---	Peak																																																																																																																						







		19																																																																																		
Mode		Band Edge - L																																																																																		
		U-NII-1_5.15-5.25_802.11ax HE40_CH38_5190MHz																																																																																		
ANT		CDD8+9																																																																																		
Pol.		Horizontal					Fundamental																																																																													
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5000.76</td><td>52.75</td><td>74.00</td><td>-21.25</td><td>41.21</td><td>36.70</td><td>8.34</td><td>33.50</td><td>383 208 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5000.76	52.75	74.00	-21.25	41.21	36.70	8.34	33.50	383 208 PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>100.39</td><td>-----</td><td>-----</td><td>88.69</td><td>36.55</td><td>8.61</td><td>33.46</td><td>383 208 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	100.39	-----	-----	88.69	36.55	8.61	33.46	383 208 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5000.76	52.75	74.00	-21.25	41.21	36.70	8.34	33.50	383 208 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5190.00	100.39	-----	-----	88.69	36.55	8.61	33.46	383 208 PEAK																																																																											
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5016.15</td><td>42.96</td><td>54.00</td><td>-11.04</td><td>31.48</td><td>36.69</td><td>8.29</td><td>33.50</td><td>383 208 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5016.15	42.96	54.00	-11.04	31.48	36.69	8.29	33.50	383 208 AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>93.18</td><td>-----</td><td>-----</td><td>81.48</td><td>36.55</td><td>8.61</td><td>33.46</td><td>383 208 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5190.00	93.18	-----	-----	81.48	36.55	8.61	33.46	383 208 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5016.15	42.96	54.00	-11.04	31.48	36.69	8.29	33.50	383 208 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5190.00	93.18	-----	-----	81.48	36.55	8.61	33.46	383 208 AVERAGE																																																																											



Mode	19																																										
	Band Edge - R																																										
	U-NII-1_5.15-5.25_802.11ax HE40_CH38_5190MHz																																										
ANT	CDD8+9																																										
Pol.	Horizontal	Fundamental																																									
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5408.70</td><td>51.40</td><td>74.00</td><td>-22.60</td><td>38.79</td><td>36.37</td><td>9.66</td><td>33.42</td><td>383</td><td>208 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5408.70	51.40	74.00	-22.60	38.79	36.37	9.66	33.42	383	208 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5408.70	51.40	74.00	-22.60	38.79	36.37	9.66	33.42	383	208 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5441.10</td><td>42.77</td><td>54.00</td><td>-11.23</td><td>30.15</td><td>36.35</td><td>9.68</td><td>33.41</td><td>383</td><td>208 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5441.10	42.77	54.00	-11.23	30.15	36.35	9.68	33.41	383	208 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5441.10	42.77	54.00	-11.23	30.15	36.35	9.68	33.41	383	208 AVERAGE																																	







		19																																																																																						
Mode		Band Edge - L																																																																																						
		U-NII-1_5.15-5.25_802.11ax HE40_CH38_5190MHz																																																																																						
ANT		CDD8+9																																																																																						
Pol.		Vertical					Fundamental																																																																																	
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5148.39</td><td>52.24</td><td>74.00</td><td>-21.76</td><td>40.60</td><td>36.58</td><td>8.53</td><td>33.47</td><td>246</td><td>91 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5148.39	52.24	74.00	-21.76	40.60	36.58	8.53	33.47	246	91 PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>103.46</td><td>-----</td><td>-----</td><td>91.76</td><td>36.54</td><td>8.62</td><td>33.46</td><td>246</td><td>91 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5190.00	103.46	-----	-----	91.76	36.54	8.62	33.46	246	91 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5148.39	52.24	74.00	-21.76	40.60	36.58	8.53	33.47	246	91 PEAK																																																																														
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5190.00	103.46	-----	-----	91.76	36.54	8.62	33.46	246	91 PEAK																																																																														
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5148.77</td><td>44.70</td><td>54.00</td><td>-9.30</td><td>33.06</td><td>36.58</td><td>8.53</td><td>33.47</td><td>246</td><td>91 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5148.77	44.70	54.00	-9.30	33.06	36.58	8.53	33.47	246	91 AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5190.00</td><td>94.22</td><td>-----</td><td>-----</td><td>82.52</td><td>36.55</td><td>8.61</td><td>33.46</td><td>246</td><td>91 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5190.00	94.22	-----	-----	82.52	36.55	8.61	33.46	246	91 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																															
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5148.77	44.70	54.00	-9.30	33.06	36.58	8.53	33.47	246	91 AVERAGE																																																																														
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																															
1	5190.00	94.22	-----	-----	82.52	36.55	8.61	33.46	246	91 AVERAGE																																																																														



Mode	19																																		
	Band Edge - R																																		
	U-NII-1_5.15-5.25_802.11ax HE40_CH38_5190MHz																																		
ANT	CDD8+9																																		
Pol.	Vertical	Fundamental																																	
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 5408.16</td><td>50.62</td><td>74.00</td><td>-23.38</td><td>38.01</td><td>36.37</td><td>9.66</td><td>33.42</td><td>246</td><td>91</td><td>PEAK</td></tr></table>	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg		1 5408.16	50.62	74.00	-23.38	38.01	36.37	9.66	33.42	246	91	PEAK	Blank
Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																									
MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg																										
1 5408.16	50.62	74.00	-23.38	38.01	36.37	9.66	33.42	246	91	PEAK																									
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Freq</th><th>Level</th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 5455.14</td><td>42.48</td><td>54.00</td><td>-11.52</td><td>29.87</td><td>36.34</td><td>9.68</td><td>33.41</td><td>246</td><td>91</td><td>AVERAGE</td></tr></table>	Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg		1 5455.14	42.48	54.00	-11.52	29.87	36.34	9.68	33.41	246	91	AVERAGE	Blank
Freq	Level	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																									
MHz	dBuV/m	dBuV/m	(dB)	Level	Factor	Loss	Factor	cm	deg																										
1 5455.14	42.48	54.00	-11.52	29.87	36.34	9.68	33.41	246	91	AVERAGE																									







		20																																																																																		
Mode		Band Edge - L																																																																																		
		U-NII-1_5.15-5.25_802.11ax HE40_CH46_5230MHz																																																																																		
ANT		CDD8+9																																																																																		
Pol.		Horizontal					Fundamental																																																																													
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5018.86</td><td>51.49</td><td>74.00</td><td>-22.51</td><td>40.02</td><td>36.68</td><td>8.29</td><td>33.50</td><td>254 47 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5018.86	51.49	74.00	-22.51	40.02	36.68	8.29	33.50	254 47 PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5230.00</td><td>100.22</td><td>-----</td><td>-----</td><td>88.39</td><td>36.51</td><td>8.77</td><td>33.45</td><td>254 47 PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	100.22	-----	-----	88.39	36.51	8.77	33.45	254 47 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5018.86	51.49	74.00	-22.51	40.02	36.68	8.29	33.50	254 47 PEAK																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5230.00	100.22	-----	-----	88.39	36.51	8.77	33.45	254 47 PEAK																																																																											
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5000.23</td><td>42.98</td><td>54.00</td><td>-11.02</td><td>31.44</td><td>36.70</td><td>8.34</td><td>33.50</td><td>254 47 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5000.23	42.98	54.00	-11.02	31.44	36.70	8.34	33.50	254 47 AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5230.00</td><td>92.65</td><td>-----</td><td>-----</td><td>80.84</td><td>36.52</td><td>8.74</td><td>33.45</td><td>254 47 AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5230.00	92.65	-----	-----	80.84	36.52	8.74	33.45	254 47 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5000.23	42.98	54.00	-11.02	31.44	36.70	8.34	33.50	254 47 AVERAGE																																																																											
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																												
1	5230.00	92.65	-----	-----	80.84	36.52	8.74	33.45	254 47 AVERAGE																																																																											



Mode	20																																									
	Band Edge - R																																									
	U-NII-1_5.15-5.25_802.11ax HE40_CH46_5230MHz																																									
ANT	CDD8+9																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5365.24</td><td>50.51</td><td>74.00</td><td>-23.49</td><td>38.09</td><td>36.41</td><td>9.44</td><td>33.43</td><td>254 47 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5365.24	50.51	74.00	-23.49	38.09	36.41	9.44	33.43	254 47 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5365.24	50.51	74.00	-23.49	38.09	36.41	9.44	33.43	254 47 PEAK																																	
Avg	Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.85</td><td>42.51</td><td>54.00</td><td>-11.49</td><td>29.90</td><td>36.33</td><td>9.69</td><td>33.41</td><td>254 47 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.85	42.51	54.00	-11.49	29.90	36.33	9.69	33.41	254 47 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5458.85	42.51	54.00	-11.49	29.90	36.33	9.69	33.41	254 47 AVERAGE																																	



		20																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-1_5.15-5.25_802.11ax HE40_CH46_5230MHz																																																																																								
ANT		CDD8+9																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5102.12</td><td>52.30</td><td>74.00</td><td>-21.70</td><td>40.71</td><td>36.62</td><td>8.45</td><td>33.48</td><td>225</td><td>87 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5102.12	52.30	74.00	-21.70	40.71	36.62	8.45	33.48	225	87 PEAK	 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5230.00</td><td>102.57</td><td>-----</td><td>-----</td><td>90.76</td><td>36.52</td><td>8.74</td><td>33.45</td><td>225</td><td>87 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	102.57	-----	-----	90.76	36.52	8.74	33.45	225	87 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1 5102.12	52.30	74.00	-21.70	40.71	36.62	8.45	33.48	225	87 PEAK																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1 5230.00	102.57	-----	-----	90.76	36.52	8.74	33.45	225	87 PEAK																																																																																	
Avg	 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5003.91</td><td>43.04</td><td>54.00</td><td>-10.96</td><td>31.51</td><td>36.70</td><td>8.33</td><td>33.50</td><td>225</td><td>87 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5003.91	43.04	54.00	-10.96	31.51	36.70	8.33	33.50	225	87 AVERAGE	 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5230.00</td><td>95.87</td><td>-----</td><td>-----</td><td>84.06</td><td>36.52</td><td>8.74</td><td>33.45</td><td>225</td><td>87 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5230.00	95.87	-----	-----	84.06	36.52	8.74	33.45	225	87 AVERAGE
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1 5003.91	43.04	54.00	-10.96	31.51	36.70	8.33	33.50	225	87 AVERAGE																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1 5230.00	95.87	-----	-----	84.06	36.52	8.74	33.45	225	87 AVERAGE																																																																																	



Mode	21																																																																											
	Band Edge - L																																																																											
	U-NII-2A_5.25-5.35_802.11ax HE40_CH54_5270MHz																																																																											
ANT	CDD8+9																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5109.08</td><td>51.55</td><td>74.00</td><td>-22.45</td><td>39.96</td><td>36.61</td><td>8.46</td><td>33.48</td><td>323 29 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5109.08	51.55	74.00	-22.45	39.96	36.61	8.46	33.48	323 29 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>101.79</td><td>-----</td><td>-----</td><td>89.80</td><td>36.48</td><td>8.96</td><td>33.45</td><td>323 29 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5270.00	101.79	-----	-----	89.80	36.48	8.96	33.45	323 29 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																						
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5109.08	51.55	74.00	-22.45	39.96	36.61	8.46	33.48	323 29 PEAK																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																						
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5270.00	101.79	-----	-----	89.80	36.48	8.96	33.45	323 29 PEAK																																																																			
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5000.54</td><td>42.86</td><td>54.00</td><td>-11.14</td><td>31.32</td><td>36.70</td><td>8.34</td><td>33.50</td><td>323 29 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5000.54	42.86	54.00	-11.14	31.32	36.70	8.34	33.50	323 29 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5270.00</td><td>94.72</td><td>-----</td><td>-----</td><td>82.73</td><td>36.48</td><td>8.96</td><td>33.45</td><td>323 29 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5270.00	94.72	-----	-----	82.73	36.48	8.96	33.45	323 29 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																						
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5000.54	42.86	54.00	-11.14	31.32	36.70	8.34	33.50	323 29 AVERAGE																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																						
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5270.00	94.72	-----	-----	82.73	36.48	8.96	33.45	323 29 AVERAGE																																																																			



Mode	21																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ax HE40_CH54_5270MHz																																										
ANT	CDD8+9																																										
Pol.	Horizontal	Fundamental																																									
Peak	Date: 2025-03-20 Level (dBuV/m) Frequency (MHz) PART 15.407 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5457.15</td><td>51.61</td><td>74.00</td><td>-22.39</td><td>39.00</td><td>36.33</td><td>9.69</td><td>33.41</td><td>323</td><td>29 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5457.15	51.61	74.00	-22.39	39.00	36.33	9.69	33.41	323	29 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5457.15	51.61	74.00	-22.39	39.00	36.33	9.69	33.41	323	29 PEAK																																	
Avg	Date: 2025-03-20 Level (dBuV/m) Frequency (MHz) PART 15.407 AVG <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.37</td><td>42.87</td><td>54.00</td><td>-11.13</td><td>30.51</td><td>36.42</td><td>9.37</td><td>33.43</td><td>323</td><td>29 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.37	42.87	54.00	-11.13	30.51	36.42	9.37	33.43	323	29 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.37	42.87	54.00	-11.13	30.51	36.42	9.37	33.43	323	29 AVERAGE																																	





Mode	21																																																																									
	Band Edge - L																																																																									
	U-NII-2A_5.25-5.35_802.11ax HE40_CH54_5270MHz																																																																									
ANT	CDD8+9																																																																									
Pol.	Vertical	Fundamental																																																																								
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5029.70</td><td>51.84</td><td>74.00</td><td>-22.16</td><td>40.34</td><td>36.68</td><td>8.31</td><td>33.49</td><td>224 86 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5029.70	51.84	74.00	-22.16	40.34	36.68	8.31	33.49	224 86 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5270.00</td><td>102.92</td><td>-----</td><td>-----</td><td>90.93</td><td>36.48</td><td>8.96</td><td>33.45</td><td>224 86 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5270.00	102.92	-----	-----	90.93	36.48	8.96	33.45	224 86 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																				
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5029.70	51.84	74.00	-22.16	40.34	36.68	8.31	33.49	224 86 PEAK																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																				
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5270.00	102.92	-----	-----	90.93	36.48	8.96	33.45	224 86 PEAK																																																																		
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5000.27</td><td>43.31</td><td>54.00</td><td>-10.69</td><td>31.77</td><td>36.70</td><td>8.34</td><td>33.50</td><td>224 86 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5000.27	43.31	54.00	-10.69	31.77	36.70	8.34	33.50	224 86 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5270.00</td><td>96.31</td><td>-----</td><td>-----</td><td>84.32</td><td>36.48</td><td>8.96</td><td>33.45</td><td>224 86 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1 5270.00	96.31	-----	-----	84.32	36.48	8.96	33.45	224 86 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																				
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5000.27	43.31	54.00	-10.69	31.77	36.70	8.34	33.50	224 86 AVERAGE																																																																		
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																				
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																		
1 5270.00	96.31	-----	-----	84.32	36.48	8.96	33.45	224 86 AVERAGE																																																																		



Mode	21																																									
	Band Edge - R																																									
	U-NII-2A_5.25-5.35_802.11ax HE40_CH54_5270MHz																																									
ANT	CDD8+9																																									
Pol.	Vertical	Fundamental																																								
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5378.49</td><td>50.97</td><td>74.00</td><td>-23.03</td><td>38.48</td><td>36.40</td><td>9.51</td><td>33.42</td><td>224 86 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5378.49	50.97	74.00	-23.03	38.48	36.40	9.51	33.42	224 86 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5378.49	50.97	74.00	-23.03	38.48	36.40	9.51	33.42	224 86 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5420.67</td><td>42.83</td><td>54.00</td><td>-11.17</td><td>30.22</td><td>36.36</td><td>9.67</td><td>33.42</td><td>224 86 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5420.67	42.83	54.00	-11.17	30.22	36.36	9.67	33.42	224 86 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																	
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5420.67	42.83	54.00	-11.17	30.22	36.36	9.67	33.42	224 86 AVERAGE																																	



Mode	21																																																																																																																											
	Harmonic																																																																																																																											
	U-NII-2A_5.25-5.35_802.11ax HE40_CH54_5270MHz																																																																																																																											
ANT	CDD8+9																																																																																																																											
Pol.	Horizontal						Vertical																																																																																																																					
Peak Avg																																																																																																																												
	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 10540.00</td><td>58.31</td><td>68.30</td><td>-9.99</td><td>71.29</td><td>38.51</td><td>12.19</td><td>63.68</td><td>182</td><td>360</td><td>Peak</td></tr><tr><td>2 15810.00</td><td>43.78</td><td>74.00</td><td>-30.22</td><td>52.15</td><td>41.49</td><td>14.71</td><td>64.57</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1 10540.00	58.31	68.30	-9.99	71.29	38.51	12.19	63.68	182	360	Peak	2 15810.00	43.78	74.00	-30.22	52.15	41.49	14.71	64.57	---	---	Peak	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1 10540.00</td><td>56.21</td><td>68.30</td><td>-12.09</td><td>69.19</td><td>38.51</td><td>12.19</td><td>63.68</td><td>363</td><td>339</td><td>Peak</td></tr><tr><td>2 15810.00</td><td>45.34</td><td>74.00</td><td>-28.66</td><td>53.71</td><td>41.49</td><td>14.71</td><td>64.57</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1 10540.00	56.21	68.30	-12.09	69.19	38.51	12.19	63.68	363	339	Peak	2 15810.00	45.34	74.00	-28.66	53.71	41.49	14.71	64.57	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																			
1 10540.00	58.31	68.30	-9.99	71.29	38.51	12.19	63.68	182	360	Peak																																																																																																																		
2 15810.00	43.78	74.00	-30.22	52.15	41.49	14.71	64.57	---	---	Peak																																																																																																																		
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																	
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																			
1 10540.00	56.21	68.30	-12.09	69.19	38.51	12.19	63.68	363	339	Peak																																																																																																																		
2 15810.00	45.34	74.00	-28.66	53.71	41.49	14.71	64.57	---	---	Peak																																																																																																																		







Mode	22																																																																											
	Band Edge - L																																																																											
	U-NII-2A_5.25-5.35_802.11ax HE40_CH62_5310MHz																																																																											
ANT	CDD8+9																																																																											
Pol.	Horizontal	Fundamental																																																																										
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5031.93</td><td>51.94</td><td>74.00</td><td>-22.06</td><td>40.44</td><td>36.67</td><td>8.32</td><td>33.49</td><td>320 36 PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5031.93	51.94	74.00	-22.06	40.44	36.67	8.32	33.49	320 36 PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5310.00</td><td>101.51</td><td>-----</td><td>-----</td><td>89.32</td><td>36.45</td><td>9.18</td><td>33.44</td><td>320 36 PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5310.00	101.51	-----	-----	89.32	36.45	9.18	33.44	320 36 PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5031.93	51.94	74.00	-22.06	40.44	36.67	8.32	33.49	320 36 PEAK																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5310.00	101.51	-----	-----	89.32	36.45	9.18	33.44	320 36 PEAK																																																																			
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5003.41</td><td>43.16</td><td>54.00</td><td>-10.84</td><td>31.63</td><td>36.70</td><td>8.33</td><td>33.50</td><td>320 36 AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5003.41	43.16	54.00	-10.84	31.63	36.70	8.33	33.50	320 36 AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5310.00</td><td>93.97</td><td>-----</td><td>-----</td><td>81.78</td><td>36.45</td><td>9.18</td><td>33.44</td><td>320 36 AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5310.00	93.97	-----	-----	81.78	36.45	9.18	33.44	320 36 AVERAGE
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5003.41	43.16	54.00	-10.84	31.63	36.70	8.33	33.50	320 36 AVERAGE																																																																			
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																				
1	5310.00	93.97	-----	-----	81.78	36.45	9.18	33.44	320 36 AVERAGE																																																																			



Mode	22									
	Band Edge - R									
	U-NII-2A_5.25-5.35_802.11ax HE40_CH62_5310MHz									
ANT	CDD8+9									
Pol.	Horizontal					Fundamental				
Peak	</									





		22																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-2A_5.25-5.35_802.11ax HE40_CH62_5310MHz																																																																																								
ANT		CDD8+9																																																																																								
Pol.		Vertical					Fundamental																																																																																			
Peak	 Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5090.21</td><td>51.32</td><td>74.00</td><td>-22.68</td><td>39.74</td><td>36.63</td><td>8.43</td><td>33.48</td><td>322 82 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5090.21	51.32	74.00	-22.68	39.74	36.63	8.43	33.48	322 82 PEAK	 Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5310.00</td><td>103.65</td><td>-----</td><td>-----</td><td>91.49</td><td>36.45</td><td>9.15</td><td>33.44</td><td>322 82 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5310.00	103.65	-----	-----	91.49	36.45	9.15	33.44	322 82 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5090.21	51.32	74.00	-22.68	39.74	36.63	8.43	33.48	322 82 PEAK																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5310.00	103.65	-----	-----	91.49	36.45	9.15	33.44	322 82 PEAK																																																																																	
Avg	 Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5000.31</td><td>42.77</td><td>54.00</td><td>-11.23</td><td>31.23</td><td>36.70</td><td>8.34</td><td>33.50</td><td>322 82 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5000.31	42.77	54.00	-11.23	31.23	36.70	8.34	33.50	322 82 AVERAGE	 Date: 2025-03-20 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5310.00</td><td>95.85</td><td>-----</td><td>-----</td><td>83.69</td><td>36.45</td><td>9.15</td><td>33.44</td><td>322 82 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5310.00	95.85	-----	-----	83.69	36.45	9.15	33.44	322 82 AVERAGE
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5000.31	42.77	54.00	-11.23	31.23	36.70	8.34	33.50	322 82 AVERAGE																																																																																	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5310.00	95.85	-----	-----	83.69	36.45	9.15	33.44	322 82 AVERAGE																																																																																	



Mode	22																																										
	Band Edge - R																																										
	U-NII-2A_5.25-5.35_802.11ax HE40_CH62_5310MHz																																										
ANT	CDD8+9																																										
Pol.	Vertical	Fundamental																																									
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5375.70</td><td>50.71</td><td>74.00</td><td>-23.29</td><td>38.23</td><td>36.40</td><td>9.50</td><td>33.42</td><td>322</td><td>82 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5375.70	50.71	74.00	-23.29	38.23	36.40	9.50	33.42	322	82 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5375.70	50.71	74.00	-23.29	38.23	36.40	9.50	33.42	322	82 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.95</td><td>43.27</td><td>54.00</td><td>-10.73</td><td>30.91</td><td>36.42</td><td>9.37</td><td>33.43</td><td>322</td><td>82 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5350.95	43.27	54.00	-10.73	30.91	36.42	9.37	33.43	322	82 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5350.95	43.27	54.00	-10.73	30.91	36.42	9.37	33.43	322	82 AVERAGE																																	







Mode	22																																																																																																																																					
	Harmonic																																																																																																																																					
	U-NII-2A_5.25-5.35_802.11ax HE40_CH62_5310MHz																																																																																																																																					
ANT	CDD8+9																																																																																																																																					
Pol.	Horizontal						Vertical																																																																																																																															
Peak Avg																																																																																																																																						
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10620.00</td><td>53.18</td><td>74.00</td><td>-20.82</td><td>66.06</td><td>38.52</td><td>12.25</td><td>63.65</td><td>185</td><td>9 Peak</td></tr><tr><td>2</td><td>10620.00</td><td>47.40</td><td>54.00</td><td>-6.60</td><td>60.28</td><td>38.52</td><td>12.25</td><td>63.65</td><td>185</td><td>9 Average</td></tr><tr><td>3</td><td>15930.00</td><td>41.59</td><td>74.00</td><td>-32.41</td><td>49.92</td><td>41.56</td><td>14.76</td><td>64.65</td><td>---</td><td>---</td><td>Peak</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10620.00	53.18	74.00	-20.82	66.06	38.52	12.25	63.65	185	9 Peak	2	10620.00	47.40	54.00	-6.60	60.28	38.52	12.25	63.65	185	9 Average	3	15930.00	41.59	74.00	-32.41	49.92	41.56	14.76	64.65	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>10620.00</td><td>47.66</td><td>74.00</td><td>-26.34</td><td>60.54</td><td>38.52</td><td>12.25</td><td>63.65</td><td>386</td><td>348 Peak</td></tr><tr><td>2</td><td>10620.00</td><td>42.76</td><td>54.00</td><td>-11.24</td><td>55.64</td><td>38.52</td><td>12.25</td><td>63.65</td><td>386</td><td>348 Average</td></tr><tr><td>3</td><td>15930.00</td><td>44.86</td><td>74.00</td><td>-29.14</td><td>53.19</td><td>41.56</td><td>14.76</td><td>64.65</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	10620.00	47.66	74.00	-26.34	60.54	38.52	12.25	63.65	386	348 Peak	2	10620.00	42.76	54.00	-11.24	55.64	38.52	12.25	63.65	386	348 Average	3	15930.00	44.86	74.00	-29.14	53.19	41.56	14.76	64.65	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																													
1	10620.00	53.18	74.00	-20.82	66.06	38.52	12.25	63.65	185	9 Peak																																																																																																																												
2	10620.00	47.40	54.00	-6.60	60.28	38.52	12.25	63.65	185	9 Average																																																																																																																												
3	15930.00	41.59	74.00	-32.41	49.92	41.56	14.76	64.65	---	---	Peak																																																																																																																											
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																													
1	10620.00	47.66	74.00	-26.34	60.54	38.52	12.25	63.65	386	348 Peak																																																																																																																												
2	10620.00	42.76	54.00	-11.24	55.64	38.52	12.25	63.65	386	348 Average																																																																																																																												
3	15930.00	44.86	74.00	-29.14	53.19	41.56	14.76	64.65	---	---	Peak																																																																																																																											




Mode	23																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11ax HE40_CH102_5510MHz																																																																																											
ANT	CDD8+9																																																																																											
Pol.	Horizontal	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5455.44</td><td>52.15</td><td>74.00</td><td>-21.85</td><td>39.54</td><td>36.34</td><td>9.68</td><td>33.41</td><td>200</td><td>38</td><td>PEAK</td></tr><tr><td>2</td><td>5465.04</td><td>52.76</td><td>68.30</td><td>-15.54</td><td>40.15</td><td>36.33</td><td>9.69</td><td>33.41</td><td>200</td><td>38</td><td>PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5455.44	52.15	74.00	-21.85	39.54	36.34	9.68	33.41	200	38	PEAK	2	5465.04	52.76	68.30	-15.54	40.15	36.33	9.69	33.41	200	38	PEAK	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>100.67</td><td>-----</td><td>-----</td><td>88.05</td><td>36.31</td><td>9.71</td><td>33.40</td><td>200</td><td>38</td><td>PEAK</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	100.67	-----	-----	88.05	36.31	9.71	33.40	200	38	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5455.44	52.15	74.00	-21.85	39.54	36.34	9.68	33.41	200	38	PEAK																																																																																	
2	5465.04	52.76	68.30	-15.54	40.15	36.33	9.69	33.41	200	38	PEAK																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5510.00	100.67	-----	-----	88.05	36.31	9.71	33.40	200	38	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5445.20</td><td>43.93</td><td>54.00</td><td>-10.07</td><td>31.32</td><td>36.34</td><td>9.68</td><td>33.41</td><td>200</td><td>38</td><td>AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5445.20	43.93	54.00	-10.07	31.32	36.34	9.68	33.41	200	38	AVERAGE	Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>93.21</td><td>-----</td><td>-----</td><td>80.59</td><td>36.31</td><td>9.71</td><td>33.40</td><td>200</td><td>38</td><td>AVERAGE</td></tr></tbody></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	93.21	-----	-----	80.59	36.31	9.71	33.40	200	38	AVERAGE												
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5445.20	43.93	54.00	-10.07	31.32	36.34	9.68	33.41	200	38	AVERAGE																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5510.00	93.21	-----	-----	80.59	36.31	9.71	33.40	200	38	AVERAGE																																																																																	





		23																																																																																																		
Mode		Band Edge - L																																																																																																		
		U-NII-2C_5.47-5.725_802.11ax HE40_CH102_5510MHz																																																																																																		
ANT		CDD8+9																																																																																																		
Pol.		Vertical					Fundamental																																																																																													
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5437.36</td><td>52.60</td><td>74.00</td><td>-21.40</td><td>39.98</td><td>36.35</td><td>9.68</td><td>33.41</td><td>300</td><td>285</td><td>PEAK</td></tr><tr><td>2</td><td>5468.40</td><td>54.26</td><td>68.30</td><td>-14.04</td><td>41.65</td><td>36.33</td><td>9.69</td><td>33.41</td><td>300</td><td>285</td><td>PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5437.36	52.60	74.00	-21.40	39.98	36.35	9.68	33.41	300	285	PEAK	2	5468.40	54.26	68.30	-14.04	41.65	36.33	9.69	33.41	300	285	PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>103.72</td><td>-----</td><td>-----</td><td>91.10</td><td>36.31</td><td>9.71</td><td>33.40</td><td>300</td><td>285</td><td>PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	103.72	-----	-----	91.10	36.31	9.71	33.40	300	285	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5437.36	52.60	74.00	-21.40	39.98	36.35	9.68	33.41	300	285	PEAK																																																																																									
2	5468.40	54.26	68.30	-14.04	41.65	36.33	9.69	33.41	300	285	PEAK																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5510.00	103.72	-----	-----	91.10	36.31	9.71	33.40	300	285	PEAK																																																																																									
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.48</td><td>44.33</td><td>54.00</td><td>-9.67</td><td>31.72</td><td>36.33</td><td>9.69</td><td>33.41</td><td>300</td><td>285</td><td>AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.48	44.33	54.00	-9.67	31.72	36.33	9.69	33.41	300	285	AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5510.00</td><td>96.36</td><td>-----</td><td>-----</td><td>83.74</td><td>36.31</td><td>9.71</td><td>33.40</td><td>300</td><td>285</td><td>AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5510.00	96.36	-----	-----	83.74	36.31	9.71	33.40	300	285	AVERAGE												
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5458.48	44.33	54.00	-9.67	31.72	36.33	9.69	33.41	300	285	AVERAGE																																																																																									
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5510.00	96.36	-----	-----	83.74	36.31	9.71	33.40	300	285	AVERAGE																																																																																									







Mode	23																																																			
	Band Edge - R																																																			
	U-NII-2C_5.47-5.725_802.11ax HE40_CH102_5510MHz																																																			
ANT	CDD8+9																																																			
Pol.	Vertical	Fundamental																																																		
Peak	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5735.42</td><td>51.47</td><td>68.30</td><td>-16.83</td><td>38.34</td><td>36.54</td><td>10.04</td><td>33.45</td><td>300</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>285 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5735.42	51.47	68.30	-16.83	38.34	36.54	10.04	33.45	300										285 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																												
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																											
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																											
1	5735.42	51.47	68.30	-16.83	38.34	36.54	10.04	33.45	300																																											
									285 PEAK																																											



Mode	23																																																																											
	Harmonic																																																																											
	U-NII-2C_5.47-5.725_802.11ax HE40_CH102_5510MHz																																																																											
ANT	CDD8+9																																																																											
Pol.	Horizontal																																																																											
Peak Avg																																																																												
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11020.00</td><td>50.97</td><td>74.00</td><td>-23.03</td><td>63.32</td><td>38.62</td><td>12.54</td><td>63.51</td><td>181</td><td>17</td><td>Peak</td></tr><tr><td>2</td><td>11020.00</td><td>45.93</td><td>54.00</td><td>-8.07</td><td>58.28</td><td>38.62</td><td>12.54</td><td>63.51</td><td>181</td><td>17</td><td>Average</td></tr><tr><td>3</td><td>16530.00</td><td>44.65</td><td>68.30</td><td>-23.65</td><td>52.24</td><td>41.97</td><td>15.19</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11020.00	50.97	74.00	-23.03	63.32	38.62	12.54	63.51	181	17	Peak	2	11020.00	45.93	54.00	-8.07	58.28	38.62	12.54	63.51	181	17	Average	3	16530.00	44.65	68.30	-23.65	52.24	41.97	15.19	64.75	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	11020.00	50.97	74.00	-23.03	63.32	38.62	12.54	63.51	181	17	Peak																																																																	
2	11020.00	45.93	54.00	-8.07	58.28	38.62	12.54	63.51	181	17	Average																																																																	
3	16530.00	44.65	68.30	-23.65	52.24	41.97	15.19	64.75	---	---	Peak																																																																	
Vertical																																																																												
																																																																												
<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11020.00</td><td>49.01</td><td>74.00</td><td>-24.99</td><td>61.36</td><td>38.62</td><td>12.54</td><td>63.51</td><td>400</td><td>350</td><td>Peak</td></tr><tr><td>2</td><td>11020.00</td><td>41.28</td><td>54.00</td><td>-12.72</td><td>53.63</td><td>38.62</td><td>12.54</td><td>63.51</td><td>400</td><td>350</td><td>Average</td></tr><tr><td>3</td><td>16530.00</td><td>46.79</td><td>68.30</td><td>-21.51</td><td>54.38</td><td>41.97</td><td>15.19</td><td>64.75</td><td>---</td><td>---</td><td>Peak</td></tr></table>												Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11020.00	49.01	74.00	-24.99	61.36	38.62	12.54	63.51	400	350	Peak	2	11020.00	41.28	54.00	-12.72	53.63	38.62	12.54	63.51	400	350	Average	3	16530.00	46.79	68.30	-21.51	54.38	41.97	15.19	64.75	---	---	Peak	
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																				
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	11020.00	49.01	74.00	-24.99	61.36	38.62	12.54	63.51	400	350	Peak																																																																	
2	11020.00	41.28	54.00	-12.72	53.63	38.62	12.54	63.51	400	350	Average																																																																	
3	16530.00	46.79	68.30	-21.51	54.38	41.97	15.19	64.75	---	---	Peak																																																																	







		24																																																																																															
Mode		Band Edge - L																																																																																															
		U-NII-2C_5.47-5.725_802.11ax HE40_CH134_5670MHz																																																																																															
ANT		CDD8+9																																																																																															
Pol.		Horizontal					Fundamental																																																																																										
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5449.84</td><td>51.36</td><td>74.00</td><td>-22.64</td><td>38.75</td><td>36.34</td><td>9.68</td><td>33.41</td><td>294</td><td>0° PEAK</td></tr><tr><td>2</td><td>5467.44</td><td>51.11</td><td>68.30</td><td>-17.19</td><td>38.50</td><td>36.33</td><td>9.69</td><td>33.41</td><td>294</td><td>0° PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5449.84	51.36	74.00	-22.64	38.75	36.34	9.68	33.41	294	0° PEAK	2	5467.44	51.11	68.30	-17.19	38.50	36.33	9.69	33.41	294	0° PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>102.63</td><td>-----</td><td>-----</td><td>89.69</td><td>36.47</td><td>9.90</td><td>33.43</td><td>294</td><td>0° PEAK</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5670.00	102.63	-----	-----	89.69	36.47	9.90	33.43	294	0° PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5449.84	51.36	74.00	-22.64	38.75	36.34	9.68	33.41	294	0° PEAK																																																																																							
2	5467.44	51.11	68.30	-17.19	38.50	36.33	9.69	33.41	294	0° PEAK																																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5670.00	102.63	-----	-----	89.69	36.47	9.90	33.43	294	0° PEAK																																																																																							
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5458.80</td><td>42.77</td><td>54.00</td><td>-11.23</td><td>30.16</td><td>36.33</td><td>9.69</td><td>33.41</td><td>294</td><td>0° AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.80	42.77	54.00	-11.23	30.16	36.33	9.69	33.41	294	0° AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>94.76</td><td>-----</td><td>-----</td><td>81.81</td><td>36.47</td><td>9.91</td><td>33.43</td><td>294</td><td>0° AVERAGE</td></tr></tbody></table>					Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5670.00	94.76	-----	-----	81.81	36.47	9.91	33.43	294	0° AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																								
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5458.80	42.77	54.00	-11.23	30.16	36.33	9.69	33.41	294	0° AVERAGE																																																																																							
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																										
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																									
1	5670.00	94.76	-----	-----	81.81	36.47	9.91	33.43	294	0° AVERAGE																																																																																							



Mode	24																																																											
	Band Edge - R																																																											
	U-NII-2C_5.47-5.725_802.11ax HE40_CH134_5670MHz																																																											
ANT	CDD8+9																																																											
Pol.	Horizontal					Fundamental																																																						
Peak	Date: 2025-03-20 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5730.52</td><td>51.64</td><td>68.30</td><td>-16.66</td><td>38.53</td><td>36.53</td><td>10.03</td><td>33.45</td><td>294</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>0° PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5730.52	51.64	68.30	-16.66	38.53	36.53	10.03	33.45	294										0° PEAK	Blank				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																																			
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																			
1	5730.52	51.64	68.30	-16.66	38.53	36.53	10.03	33.45	294																																																			
									0° PEAK																																																			





		24																																																																																																					
Mode		Band Edge - L																																																																																																					
		U-NII-2C_5.47-5.725_802.11ax HE40_CH134_5670MHz																																																																																																					
ANT		CDD8+9																																																																																																					
Pol.		Vertical					Fundamental																																																																																																
Peak	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5457.20</td><td>51.89</td><td>74.00</td><td>-22.11</td><td>39.28</td><td>36.33</td><td>9.69</td><td>33.41</td><td>300</td><td>257 PEAK</td></tr><tr><td>2</td><td>5464.24</td><td>49.86</td><td>68.30</td><td>-18.44</td><td>37.25</td><td>36.33</td><td>9.69</td><td>33.41</td><td>300</td><td>257 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5457.20	51.89	74.00	-22.11	39.28	36.33	9.69	33.41	300	257 PEAK	2	5464.24	49.86	68.30	-18.44	37.25	36.33	9.69	33.41	300	257 PEAK	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>104.70</td><td>-----</td><td>-----</td><td>91.75</td><td>36.47</td><td>9.91</td><td>33.43</td><td>300</td><td>257 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	104.70	-----	-----	91.75	36.47	9.91	33.43	300	257 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5457.20	51.89	74.00	-22.11	39.28	36.33	9.69	33.41	300	257 PEAK																																																																																													
2	5464.24	49.86	68.30	-18.44	37.25	36.33	9.69	33.41	300	257 PEAK																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5670.00	104.70	-----	-----	91.75	36.47	9.91	33.43	300	257 PEAK																																																																																													
Avg	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5408.88</td><td>42.75</td><td>54.00</td><td>-11.25</td><td>30.14</td><td>36.37</td><td>9.66</td><td>33.42</td><td>300</td><td>257 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5408.88	42.75	54.00	-11.25	30.14	36.37	9.66	33.42	300	257 AVERAGE	 Level (dBuV/m) Date: 2025-03-20 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5670.00</td><td>98.50</td><td>-----</td><td>-----</td><td>85.55</td><td>36.47</td><td>9.91</td><td>33.43</td><td>300</td><td>257 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5670.00	98.50	-----	-----	85.55	36.47	9.91	33.43	300	257 AVERAGE											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5408.88	42.75	54.00	-11.25	30.14	36.37	9.66	33.42	300	257 AVERAGE																																																																																													
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																														
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																	
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																														
1	5670.00	98.50	-----	-----	85.55	36.47	9.91	33.43	300	257 AVERAGE																																																																																													



Mode	24																																										
	Band Edge - R																																										
	U-NII-2C_5.47-5.725_802.11ax HE40_CH134_5670MHz																																										
ANT	CDD8+9																																										
Pol.	Vertical	Fundamental																																									
Peak	Date: 2025-03-20 Level (dBuV/m) Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5739.35</td><td>52.95</td><td>68.30</td><td>-15.35</td><td>39.81</td><td>36.54</td><td>10.05</td><td>33.45</td><td>300</td><td>257 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5739.35	52.95	68.30	-15.35	39.81	36.54	10.05	33.45	300	257 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5739.35	52.95	68.30	-15.35	39.81	36.54	10.05	33.45	300	257 PEAK																																	



		24																																																																				
Mode		Harmonic																																																																				
		U-NII-2C_5.47-5.725_802.11ax HE40_CH134_5670MHz																																																																				
ANT		CDD8+9																																																																				
Pol.		Horizontal					Vertical																																																															
Peak Avg																																																																						
		<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11340.00</td><td>54.14</td><td>74.00</td><td>-19.86</td><td>66.10</td><td>39.01</td><td>12.77</td><td>63.74</td><td>207</td><td>360 Peak</td></tr><tr><td>2 11340.00</td><td>47.96</td><td>54.00</td><td>-6.04</td><td>59.92</td><td>39.01</td><td>12.77</td><td>63.74</td><td>207</td><td>360 Average</td></tr><tr><td>3 17010.00</td><td>45.55</td><td>68.30</td><td>-22.75</td><td>52.50</td><td>42.31</td><td>15.55</td><td>64.81</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11340.00	54.14	74.00	-19.86	66.10	39.01	12.77	63.74	207	360 Peak	2 11340.00	47.96	54.00	-6.04	59.92	39.01	12.77	63.74	207	360 Average	3 17010.00	45.55	68.30	-22.75	52.50	42.31	15.55	64.81	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																													
1 11340.00	54.14	74.00	-19.86	66.10	39.01	12.77	63.74	207	360 Peak																																																													
2 11340.00	47.96	54.00	-6.04	59.92	39.01	12.77	63.74	207	360 Average																																																													
3 17010.00	45.55	68.30	-22.75	52.50	42.31	15.55	64.81	---	---	Peak																																																												
																																																																						
		<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11340.00</td><td>51.91</td><td>74.00</td><td>-22.09</td><td>63.87</td><td>39.01</td><td>12.77</td><td>63.74</td><td>284</td><td>325 Peak</td></tr><tr><td>2 11340.00</td><td>46.30</td><td>54.00</td><td>-7.70</td><td>58.26</td><td>39.01</td><td>12.77</td><td>63.74</td><td>284</td><td>325 Average</td></tr><tr><td>3 17010.00</td><td>47.89</td><td>68.30</td><td>-20.41</td><td>54.84</td><td>42.31</td><td>15.55</td><td>64.81</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11340.00	51.91	74.00	-22.09	63.87	39.01	12.77	63.74	284	325 Peak	2 11340.00	46.30	54.00	-7.70	58.26	39.01	12.77	63.74	284	325 Average	3 17010.00	47.89	68.30	-20.41	54.84	42.31	15.55	64.81	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																															
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																														
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																													
1 11340.00	51.91	74.00	-22.09	63.87	39.01	12.77	63.74	284	325 Peak																																																													
2 11340.00	46.30	54.00	-7.70	58.26	39.01	12.77	63.74	284	325 Average																																																													
3 17010.00	47.89	68.30	-20.41	54.84	42.31	15.55	64.81	---	---	Peak																																																												







		25																																																																																			
Mode		Band Edge - L																																																																																			
		U-NII-1_5.15-5.25_802.11ax HE80_CH42_5210MHz																																																																																			
ANT		CDD8+9																																																																																			
Pol.		Horizontal					Fundamental																																																																														
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21 Frequency (MHz)																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5008.61</td><td>51.48</td><td>74.00</td><td>-22.52</td><td>39.97</td><td>36.69</td><td>8.32</td><td>33.50</td><td>100</td><td>223 PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 5008.61	51.48	74.00	-22.52	39.97	36.69	8.32	33.50	100	223 PEAK	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5210.00</td><td>89.88</td><td>-----</td><td>-----</td><td>78.18</td><td>36.54</td><td>8.62</td><td>33.46</td><td>100</td><td>223 PEAK</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 5210.00	89.88	-----	-----	78.18	36.54	8.62	33.46	100
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																												
1 5008.61	51.48	74.00	-22.52	39.97	36.69	8.32	33.50	100	223 PEAK																																																																												
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																												
1 5210.00	89.88	-----	-----	78.18	36.54	8.62	33.46	100	223 PEAK																																																																												
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21 Frequency (MHz)																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5117.39</td><td>44.52</td><td>54.00</td><td>-9.48</td><td>32.91</td><td>36.61</td><td>8.48</td><td>33.48</td><td>100</td><td>223 AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 5117.39	44.52	54.00	-9.48	32.91	36.61	8.48	33.48	100	223 AVERAGE	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 5210.00</td><td>83.22</td><td>-----</td><td>-----</td><td>71.51</td><td>36.54</td><td>8.63</td><td>33.46</td><td>100</td><td>223 AVERAGE</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 5210.00	83.22	-----	-----	71.51	36.54	8.63	33.46	100
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																												
1 5117.39	44.52	54.00	-9.48	32.91	36.61	8.48	33.48	100	223 AVERAGE																																																																												
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																													
Freq	Level	Line	Margin	Level	Factor	Loss Factor																																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																												
1 5210.00	83.22	-----	-----	71.51	36.54	8.63	33.46	100	223 AVERAGE																																																																												



Mode	25																																									
	Band Edge - R																																									
	U-NII-1_5.15-5.25_802.11ax HE80_CH42_5210MHz																																									
ANT	CDD8+9																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2025-03-21 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5405.75</td><td>51.23</td><td>74.00</td><td>-22.77</td><td>38.62</td><td>36.38</td><td>9.65</td><td>33.42</td><td>100</td><td>223</td><td>PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	5405.75	51.23	74.00	-22.77	38.62	36.38	9.65	33.42	100	223	PEAK	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																	
1	5405.75	51.23	74.00	-22.77	38.62	36.38	9.65	33.42	100	223	PEAK																															
Avg	Date: 2025-03-21 <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5456.25</td><td>44.30</td><td>54.00</td><td>-9.70</td><td>31.69</td><td>36.33</td><td>9.69</td><td>33.41</td><td>100</td><td>223</td><td>AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	5456.25	44.30	54.00	-9.70	31.69	36.33	9.69	33.41	100	223	AVERAGE	Blank
	Limit	Read	Ant	Cable	Preamp	APos	TPos	Remark																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																	
1	5456.25	44.30	54.00	-9.70	31.69	36.33	9.69	33.41	100	223	AVERAGE																															







Mode	25																																																																																															
	Band Edge - L																																																																																															
	U-NII-1_5.15-5.25_802.11ax HE80_CH42_5210MHz																																																																																															
ANT	CDD8+9																																																																																															
Pol.	Vertical						Fundamental																																																																																									
Peak	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5149.94</td><td>55.16</td><td>74.00</td><td>-18.84</td><td>43.51</td><td>36.58</td><td>8.54</td><td>33.47</td><td>360</td><td>266</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	5149.94	55.16	74.00	-18.84	43.51	36.58	8.54	33.47	360	266	PEAK	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5210.00</td><td>98.38</td><td>-----</td><td>-----</td><td>86.70</td><td>36.55</td><td>8.59</td><td>33.46</td><td>360</td><td>266</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	5210.00	98.38	-----	-----	86.70	36.55	8.59	33.46	360	266	PEAK
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5149.94	55.16	74.00	-18.84	43.51	36.58	8.54	33.47	360	266	PEAK																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5210.00	98.38	-----	-----	86.70	36.55	8.59	33.46	360	266	PEAK																																																																																					
Avg	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5149.73</td><td>48.81</td><td>54.00</td><td>-5.19</td><td>37.16</td><td>36.58</td><td>8.54</td><td>33.47</td><td>360</td><td>266</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	5149.73	48.81	54.00	-5.19	37.16	36.58	8.54	33.47	360	266	AVERAGE	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>5210.00</td><td>90.44</td><td>-----</td><td>-----</td><td>78.76</td><td>36.55</td><td>8.59</td><td>33.46</td><td>360</td><td>266</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	5210.00	90.44	-----	-----	78.76	36.55	8.59	33.46	360	266	AVERAGE
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5149.73	48.81	54.00	-5.19	37.16	36.58	8.54	33.47	360	266	AVERAGE																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																									
Freq	Level	Line	Margin	Level	Factor	Loss Factor		Remark																																																																																								
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																						
1	5210.00	90.44	-----	-----	78.76	36.55	8.59	33.46	360	266	AVERAGE																																																																																					



Mode	25																																																			
	Band Edge - R																																																			
	U-NII-1_5.15-5.25_802.11ax HE80_CH42_5210MHz																																																			
ANT	CDD8+9																																																			
Pol.	Vertical						Fundamental																																													
Peak	Date: 2025-03-21 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5426.00</td><td>50.56</td><td>74.00</td><td>-23.44</td><td>37.94</td><td>36.36</td><td>9.67</td><td>33.41</td><td>360</td><td>266</td><td>PEAK</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5426.00	50.56	74.00	-23.44	37.94	36.36	9.67	33.41	360	266	PEAK	Blank					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																											
1	5426.00	50.56	74.00	-23.44	37.94	36.36	9.67	33.41	360	266	PEAK																																									
Avg	Date: 2025-03-21 <table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5412.50</td><td>43.82</td><td>54.00</td><td>-10.18</td><td>31.21</td><td>36.37</td><td>9.66</td><td>33.42</td><td>360</td><td>266</td><td>AVERAGE</td></tr></table>							Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg	1	5412.50	43.82	54.00	-10.18	31.21	36.37	9.66	33.42	360	266	AVERAGE	Blank					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																													
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																												
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	cm	deg																																											
1	5412.50	43.82	54.00	-10.18	31.21	36.37	9.66	33.42	360	266	AVERAGE																																									



		26																																																																																								
Mode		Band Edge - L																																																																																								
		U-NII-2A_5.25-5.35_802.11ax HE80_CH58_5290MHz																																																																																								
ANT		CDD8+9																																																																																								
Pol.		Horizontal					Fundamental																																																																																			
Peak	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)																																																																																				
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5076.27</td><td>51.83</td><td>74.00</td><td>-22.17</td><td>40.27</td><td>36.64</td><td>8.40</td><td>33.48</td><td>379</td><td>1 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5076.27	51.83	74.00	-22.17	40.27	36.64	8.40	33.48	379	1 PEAK	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5290.00</td><td>92.12</td><td>-----</td><td>79.96</td><td>36.45</td><td>9.15</td><td>33.44</td><td>379</td><td>1 PEAK</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5290.00	92.12	-----	79.96	36.45	9.15	33.44	379
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5076.27	51.83	74.00	-22.17	40.27	36.64	8.40	33.48	379	1 PEAK																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	92.12	-----	79.96	36.45	9.15	33.44	379	1 PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)																																																																																				
	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5006.96</td><td>43.88</td><td>54.00</td><td>-10.12</td><td>32.37</td><td>36.69</td><td>8.32</td><td>33.50</td><td>379</td><td>1 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5006.96	43.88	54.00	-10.12	32.37	36.69	8.32	33.50	379	1 AVERAGE	<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5290.00</td><td>85.29</td><td>-----</td><td>73.08</td><td>36.44</td><td>9.21</td><td>33.44</td><td>379</td><td>1 AVERAGE</td></tr></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5290.00	85.29	-----	73.08	36.44	9.21	33.44	379
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5006.96	43.88	54.00	-10.12	32.37	36.69	8.32	33.50	379	1 AVERAGE																																																																																
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																	
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																				
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	5290.00	85.29	-----	73.08	36.44	9.21	33.44	379	1 AVERAGE																																																																																	



Mode	26																																								
	Band Edge - R																																								
	U-NII-2A_5.25-5.35_802.11ax HE80_CH58_5290MHz																																								
ANT	CDD8+9																																								
Pol.	Horizontal	Fundamental																																							
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5416.99</td><td>51.13</td><td>74.00</td><td>-22.87</td><td>38.51</td><td>36.37</td><td>9.67</td><td>33.42</td><td>379</td><td>1 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5416.99	51.13	74.00	-22.87	38.51	36.37	9.67	33.42	379	1 PEAK	Blank
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																
1	5416.99	51.13	74.00	-22.87	38.51	36.37	9.67	33.42	379	1 PEAK																															
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5350.18</td><td>45.12</td><td>54.00</td><td>-8.88</td><td>32.76</td><td>36.42</td><td>9.37</td><td>33.43</td><td>379</td><td>1 AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5350.18	45.12	54.00	-8.88	32.76	36.42	9.37	33.43	379	1 AVERAGE	Blank
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																	
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																
1	5350.18	45.12	54.00	-8.88	32.76	36.42	9.37	33.43	379	1 AVERAGE																															







Mode	26	
	Band Edge - L	
	U-NII-2A_5.25-5.35_802.11ax HE80_CH58_5290MHz	
ANT	CDD8+9	
Pol.	Vertical	Fundamental
Peak	Level (dBuV/m) Date: 2025-03-21 1 5038.28 51.46 74.00 -22.54 39.95 36.67 8.33 33.49 300 241 PEAK	Level (dBuV/m) Date: 2025-03-21 1 5290.00 93.43 ----- 81.27 36.45 9.15 33.44 300 241 PEAK
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg 1 5038.28 51.46 74.00 -22.54 39.95 36.67 8.33 33.49 300 241 PEAK	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg 1 5290.00 93.43 ----- 81.27 36.45 9.15 33.44 300 241 PEAK
Avg	Level (dBuV/m) Date: 2025-03-21 1 5000.58 44.24 54.00 -9.76 32.70 36.70 8.34 33.50 300 241 AVERAGE	Level (dBuV/m) Date: 2025-03-21 1 5290.00 86.20 ----- 73.99 36.44 9.21 33.44 300 241 AVERAGE
	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg 1 5000.58 44.24 54.00 -9.76 32.70 36.70 8.34 33.50 300 241 AVERAGE	Limit Margin Read Ant Cable Preamp APos TPos Freq Level Line (dB) Level Factor Loss Factor Remark MHz dBuV/m dBuV/m dBuV dB/m dB dB cm deg 1 5290.00 86.20 ----- 73.99 36.44 9.21 33.44 300 241 AVERAGE



Mode	26	
	Band Edge - R	
	U-NII-2A_5.25-5.35_802.11ax HE80_CH58_5290MHz	
ANT	CDD8+9	
Pol.	Vertical	Fundamental
Peak	<	



		27																																																																															
Mode		Band Edge - L																																																																															
		U-NII-2C_5.47-5.725_802.11ax HE80_CH106_5530MHz																																																																															
ANT		CDD8+9																																																																															
Pol.		Horizontal					Fundamental																																																																										
Peak	 Level (dBuV/m) vs Frequency (MHz) for Horizontal polarization. The plot shows a blue signal line with two peaks labeled 1 and 2. A red limit line is at 70.0 dBuV/m. The date is 2025-03-21.					 Level (dBuV/m) vs Frequency (MHz) for Fundamental polarization. The plot shows a blue signal line with a single peak labeled 1. A red limit line is at 70.0 dBuV/m. The date is 2025-03-21.																																																																											
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg	1	5446.12	54.36	74.00	-19.64	41.75	36.34	9.68	33.41	228	235 PEAK	2	5465.74	54.02	68.30	-14.28	41.41	36.33	9.69	33.41	228	235 PEAK		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg	1	5530.00	94.74	-----	-----	82.13	36.30	9.71	33.40	228	235 PEAK				
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg																																																																							
1	5446.12	54.36	74.00	-19.64	41.75	36.34	9.68	33.41	228	235 PEAK																																																																							
2	5465.74	54.02	68.30	-14.28	41.41	36.33	9.69	33.41	228	235 PEAK																																																																							
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg																																																																							
1	5530.00	94.74	-----	-----	82.13	36.30	9.71	33.40	228	235 PEAK																																																																							
Avg	 Level (dBuV/m) vs Frequency (MHz) for Horizontal polarization. The plot shows a blue signal line with an average peak labeled 1. A red limit line is at 52.5 dBuV/m. The date is 2025-03-21.					 Level (dBuV/m) vs Frequency (MHz) for Fundamental polarization. The plot shows a blue signal line with an average peak labeled 1. A red limit line is at 52.5 dBuV/m. The date is 2025-03-21.																																																																											
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg	1	5444.86	48.17	54.00	-5.83	35.56	36.34	9.68	33.41	228	235 AVERAGE		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos			Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg	1	5530.00	87.34	-----	-----	74.72	36.31	9.71	33.40	228	235 AVERAGE															
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg																																																																							
1	5444.86	48.17	54.00	-5.83	35.56	36.34	9.68	33.41	228	235 AVERAGE																																																																							
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																																									
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		cm	deg																																																																							
1	5530.00	87.34	-----	-----	74.72	36.31	9.71	33.40	228	235 AVERAGE																																																																							



Mode	27																																									
	Band Edge - R																																									
	U-NII-2C_5.47-5.725_802.11ax HE80_CH106_5530MHz																																									
ANT	CDD8+9																																									
Pol.	Horizontal	Fundamental																																								
Peak	Date: 2025-03-21 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5743.62</td><td>51.70</td><td>68.30</td><td>-16.60</td><td>38.55</td><td>36.54</td><td>10.06</td><td>33.45</td><td>228</td><td>235</td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5743.62	51.70	68.30	-16.60	38.55	36.54	10.06	33.45	228	235	PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																		
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																	
1	5743.62	51.70	68.30	-16.60	38.55	36.54	10.06	33.45	228	235	PEAK																															





		27																																																																																																		
Mode		Band Edge - L																																																																																																		
		U-NII-2C_5.47-5.725_802.11ax HE80_CH106_5530MHz																																																																																																		
ANT		CDD8+9																																																																																																		
Pol.		Vertical					Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5441.08</td><td>54.51</td><td>74.00</td><td>-19.49</td><td>41.89</td><td>36.35</td><td>9.68</td><td>33.41</td><td>286 246 PEAK</td></tr><tr><td>2</td><td>5469.52</td><td>55.35</td><td>68.30</td><td>-12.95</td><td>42.75</td><td>36.32</td><td>9.69</td><td>33.41</td><td>286 246 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5441.08	54.51	74.00	-19.49	41.89	36.35	9.68	33.41	286 246 PEAK	2	5469.52	55.35	68.30	-12.95	42.75	36.32	9.69	33.41	286 246 PEAK	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>97.14</td><td>-----</td><td>-----</td><td>84.53</td><td>36.30</td><td>9.71</td><td>33.40</td><td>286 246 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5530.00	97.14	-----	-----	84.53	36.30	9.71	33.40	286 246 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5441.08	54.51	74.00	-19.49	41.89	36.35	9.68	33.41	286 246 PEAK																																																																																											
2	5469.52	55.35	68.30	-12.95	42.75	36.32	9.69	33.41	286 246 PEAK																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5530.00	97.14	-----	-----	84.53	36.30	9.71	33.40	286 246 PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5444.86</td><td>48.90</td><td>54.00</td><td>-5.10</td><td>36.29</td><td>36.34</td><td>9.68</td><td>33.41</td><td>286 246 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5444.86	48.90	54.00	-5.10	36.29	36.34	9.68	33.41	286 246 AVERAGE	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr></thead><tbody><tr><td>1</td><td>5530.00</td><td>89.43</td><td>-----</td><td>-----</td><td>76.82</td><td>36.30</td><td>9.71</td><td>33.40</td><td>286 246 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor			MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg		1	5530.00	89.43	-----	-----	76.82	36.30	9.71	33.40	286 246 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5444.86	48.90	54.00	-5.10	36.29	36.34	9.68	33.41	286 246 AVERAGE																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																													
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																												
1	5530.00	89.43	-----	-----	76.82	36.30	9.71	33.40	286 246 AVERAGE																																																																																											



Mode	27																																																	
	Band Edge - R																																																	
	U-NII-2C_5.47-5.725_802.11ax HE80_CH106_5530MHz																																																	
ANT	CDD8+9																																																	
Pol.	Vertical	Fundamental																																																
Peak	Date: 2025-03-21 Level (dBuV/m) Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th></tr><tr><td>1</td><td>5727.40</td><td>51.26</td><td>68.30</td><td>-17.04</td><td>38.16</td><td>36.53</td><td>10.02</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td>33.45</td><td></td><td>286</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>246 PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	5727.40	51.26	68.30	-17.04	38.16	36.53	10.02						33.45		286								246 PEAK	Blank
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																											
Freq	Level	Line	Level	Factor	Loss	Factor	Remark																																											
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																											
1	5727.40	51.26	68.30	-17.04	38.16	36.53	10.02																																											
					33.45		286																																											
							246 PEAK																																											



Mode	27																																																																																																																															
	Harmonic																																																																																																																															
	U-NII-2C_5.47-5.725_802.11ax HE80_CH106_5530MHz																																																																																																																															
ANT	CDD8+9																																																																																																																															
Pol.	Horizontal						Vertical																																																																																																																									
Peak Avg																																																																																																																																
	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>11060.00</td><td>44.51</td><td>74.00</td><td>-29.49</td><td>56.81</td><td>38.67</td><td>12.57</td><td>63.54</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16590.00</td><td>45.64</td><td>68.30</td><td>-22.66</td><td>53.16</td><td>42.01</td><td>15.23</td><td>64.76</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	11060.00	44.51	74.00	-29.49	56.81	38.67	12.57	63.54	---	---	Peak	2	16590.00	45.64	68.30	-22.66	53.16	42.01	15.23	64.76	---	---	Peak	<table><tr><th colspan="2"></th><th colspan="2">Limit</th><th colspan="2">Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th rowspan="2">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th></tr><tr><td>1</td><td>11060.00</td><td>45.81</td><td>74.00</td><td>-28.19</td><td>58.11</td><td>38.67</td><td>12.57</td><td>63.54</td><td>---</td><td>---</td><td>Peak</td></tr><tr><td>2</td><td>16590.00</td><td>47.72</td><td>68.30</td><td>-20.58</td><td>55.24</td><td>42.01</td><td>15.23</td><td>64.76</td><td>---</td><td>---</td><td>Peak</td></tr></table>								Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg		1	11060.00	45.81	74.00	-28.19	58.11	38.67	12.57	63.54	---	---	Peak	2	16590.00	47.72	68.30	-20.58	55.24	42.01	15.23	64.76	---	---	Peak
			Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1	11060.00	44.51	74.00	-29.49	56.81	38.67	12.57	63.54	---	---	Peak																																																																																																																					
2	16590.00	45.64	68.30	-22.66	53.16	42.01	15.23	64.76	---	---	Peak																																																																																																																					
		Limit		Read		Ant	Cable	Preamp	APos	TPos	Remark																																																																																																																					
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																																																																									
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																							
1	11060.00	45.81	74.00	-28.19	58.11	38.67	12.57	63.54	---	---	Peak																																																																																																																					
2	16590.00	47.72	68.30	-20.58	55.24	42.01	15.23	64.76	---	---	Peak																																																																																																																					



Mode	28																																																																																																			
	Band Edge - L																																																																																																			
	U-NII-2C_5.47-5.725_802.11ax HE80_CH122_5610MHz																																																																																																			
ANT	CDD8+9																																																																																																			
Pol.	Horizontal					Fundamental																																																																																														
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5441.00</td><td>51.61</td><td>74.00</td><td>-22.39</td><td>38.99</td><td>36.35</td><td>9.68</td><td>33.41</td><td>200</td><td>45 PEAK</td></tr><tr><td>2 5465.96</td><td>51.69</td><td>68.30</td><td>-16.61</td><td>39.08</td><td>36.33</td><td>9.69</td><td>33.41</td><td>200</td><td>45 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5441.00	51.61	74.00	-22.39	38.99	36.35	9.68	33.41	200	45 PEAK	2 5465.96	51.69	68.30	-16.61	39.08	36.33	9.69	33.41	200	45 PEAK	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5610.00</td><td>98.46</td><td>-----</td><td>-----</td><td>85.58</td><td>36.45</td><td>9.86</td><td>33.43</td><td>200</td><td>45 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5610.00	98.46	-----	-----	85.58	36.45	9.86	33.43	200	45 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5441.00	51.61	74.00	-22.39	38.99	36.35	9.68	33.41	200	45 PEAK																																																																																											
2 5465.96	51.69	68.30	-16.61	39.08	36.33	9.69	33.41	200	45 PEAK																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5610.00	98.46	-----	-----	85.58	36.45	9.86	33.43	200	45 PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5452.44</td><td>45.28</td><td>54.00</td><td>-8.72</td><td>32.67</td><td>36.34</td><td>9.68</td><td>33.41</td><td>200</td><td>45 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5452.44	45.28	54.00	-8.72	32.67	36.34	9.68	33.41	200	45 AVERAGE	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5610.00</td><td>90.23</td><td>-----</td><td>-----</td><td>77.43</td><td>36.42</td><td>9.80</td><td>33.42</td><td>200</td><td>45 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5610.00	90.23	-----	-----	77.43	36.42	9.80	33.42	200	45 AVERAGE										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5452.44	45.28	54.00	-8.72	32.67	36.34	9.68	33.41	200	45 AVERAGE																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5610.00	90.23	-----	-----	77.43	36.42	9.80	33.42	200	45 AVERAGE																																																																																											





Mode	28																																																																																											
	Band Edge - L																																																																																											
	U-NII-2C_5.47-5.725_802.11ax HE80_CH122_5610MHz																																																																																											
ANT	CDD8+9																																																																																											
Pol.	Vertical	Fundamental																																																																																										
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5454.78</td><td>52.22</td><td>74.00</td><td>-21.78</td><td>39.61</td><td>36.34</td><td>9.68</td><td>33.41</td><td>301</td><td>257</td><td>PEAK</td></tr><tr><td>2</td><td>5468.82</td><td>52.27</td><td>68.30</td><td>-16.03</td><td>39.67</td><td>36.32</td><td>9.69</td><td>33.41</td><td>301</td><td>257</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5454.78	52.22	74.00	-21.78	39.61	36.34	9.68	33.41	301	257	PEAK	2	5468.82	52.27	68.30	-16.03	39.67	36.32	9.69	33.41	301	257	PEAK	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5610.00</td><td>99.33</td><td>-----</td><td>-----</td><td>86.51</td><td>36.43</td><td>9.82</td><td>33.43</td><td>301</td><td>257</td><td>PEAK</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5610.00	99.33	-----	-----	86.51	36.43	9.82	33.43	301	257	PEAK
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5454.78	52.22	74.00	-21.78	39.61	36.34	9.68	33.41	301	257	PEAK																																																																																	
2	5468.82	52.27	68.30	-16.03	39.67	36.32	9.69	33.41	301	257	PEAK																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5610.00	99.33	-----	-----	86.51	36.43	9.82	33.43	301	257	PEAK																																																																																	
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5458.68</td><td>44.81</td><td>54.00</td><td>-9.19</td><td>32.20</td><td>36.33</td><td>9.69</td><td>33.41</td><td>301</td><td>257</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5458.68	44.81	54.00	-9.19	32.20	36.33	9.69	33.41	301	257	AVERAGE	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5610.00</td><td>92.81</td><td>-----</td><td>-----</td><td>79.99</td><td>36.43</td><td>9.82</td><td>33.43</td><td>301</td><td>257</td><td>AVERAGE</td></tr></table>	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5610.00	92.81	-----	-----	79.99	36.43	9.82	33.43	301	257	AVERAGE												
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5458.68	44.81	54.00	-9.19	32.20	36.33	9.69	33.41	301	257	AVERAGE																																																																																	
Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																				
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor																																																																																					
MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																																																																				
1	5610.00	92.81	-----	-----	79.99	36.43	9.82	33.43	301	257	AVERAGE																																																																																	



Mode	28																																																							
	Band Edge - R																																																							
	U-NII-2C_5.47-5.725_802.11ax HE80_CH122_5610MHz																																																							
ANT	CDD8+9																																																							
Pol.	Vertical	Fundamental																																																						
Peak	Date: 2025-03-21 <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th></tr><tr><td>1</td><td>5727.65</td><td>51.81</td><td>68.30</td><td>-16.49</td><td>38.71</td><td>36.53</td><td>10.02</td><td>33.45</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>301</td><td>257</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	1	5727.65	51.81	68.30	-16.49	38.71	36.53	10.02	33.45								301	257									PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																																
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor	Remark																																																
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm																																																
1	5727.65	51.81	68.30	-16.49	38.71	36.53	10.02	33.45																																																
							301	257																																																
								PEAK																																																



		29																																																									
Mode	Band Edge - L																																																										
	U-NII-2C_5.47-5.725_802.11ax HE160_CH50_5250MHz																																																										
ANT	CDD8+9																																																										
Pol.	Horizontal																																																										
Peak	Fundamental																																																										
	Date: 2025-03-21																																																										
																																																											
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="3"></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr><tr><td>1 5106.00</td><td>53.42</td><td>74.00</td><td>-20.58</td><td>41.83</td><td>36.62</td><td>8.45</td><td>33.48</td><td>231</td><td>26</td><td colspan="2">PEAK</td></tr></table>													Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark			Freq	Level	Line	(dB)	Level	Factor	Loss Factor						MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg			1 5106.00	53.42	74.00	-20.58	41.83	36.62	8.45	33.48	231	26	PEAK	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																					
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																		
1 5106.00	53.42	74.00	-20.58	41.83	36.62	8.45	33.48	231	26	PEAK																																																	
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="3"></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr><tr><td>1 5250.00</td><td>88.35</td><td>-----</td><td>-----</td><td>76.43</td><td>36.50</td><td>8.87</td><td>33.45</td><td>231</td><td>26</td><td colspan="2">PEAK</td></tr></table>													Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark			Freq	Level	Line	(dB)	Level	Factor	Loss Factor						MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg			1 5250.00	88.35	-----	-----	76.43	36.50	8.87	33.45	231	26	PEAK	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																					
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																		
1 5250.00	88.35	-----	-----	76.43	36.50	8.87	33.45	231	26	PEAK																																																	
Avg	Horizontal																																																										
	Date: 2025-03-21																																																										
																																																											
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="3"></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr><tr><td>1 5001.00</td><td>44.29</td><td>54.00</td><td>-9.71</td><td>32.75</td><td>36.70</td><td>8.34</td><td>33.50</td><td>231</td><td>26</td><td colspan="2">AVERAGE</td></tr></table>													Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark			Freq	Level	Line	(dB)	Level	Factor	Loss Factor						MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg			1 5001.00	44.29	54.00	-9.71	32.75	36.70	8.34	33.50	231	26	AVERAGE	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																					
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																		
1 5001.00	44.29	54.00	-9.71	32.75	36.70	8.34	33.50	231	26	AVERAGE																																																	
<table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th colspan="3">Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th colspan="3"></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th colspan="2"></th></tr><tr><td>1 5250.00</td><td>81.67</td><td>-----</td><td>-----</td><td>69.84</td><td>36.51</td><td>8.77</td><td>33.45</td><td>231</td><td>26</td><td colspan="2">AVERAGE</td></tr></table>													Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark			Freq	Level	Line	(dB)	Level	Factor	Loss Factor						MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg			1 5250.00	81.67	-----	-----	69.84	36.51	8.77	33.45	231	26	AVERAGE	
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																		
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																					
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																		
1 5250.00	81.67	-----	-----	69.84	36.51	8.77	33.45	231	26	AVERAGE																																																	



Mode	29																																										
	Band Edge - R																																										
	U-NII-2C_5.47-5.725_802.11ax HE160_CH50_5250MHz																																										
ANT	CDD8+9																																										
Pol.	Horizontal	Fundamental																																									
Peak	Date: 2025-03-21 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5403.72</td><td>51.61</td><td>74.00</td><td>-22.39</td><td>39.01</td><td>36.38</td><td>9.64</td><td>33.42</td><td>231</td><td>26 PEAK</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5403.72	51.61	74.00	-22.39	39.01	36.38	9.64	33.42	231	26 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5403.72	51.61	74.00	-22.39	39.01	36.38	9.64	33.42	231	26 PEAK																																	
Avg	Date: 2025-03-21 <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5416.74</td><td>43.98</td><td>54.00</td><td>-10.02</td><td>31.37</td><td>36.37</td><td>9.66</td><td>33.42</td><td>231</td><td>26 AVERAGE</td></tr></tbody></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark		MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg	1	5416.74	43.98	54.00	-10.02	31.37	36.37	9.66	33.42	231	26 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
	MHz	dBuV/m	dBuV/m	dBuV	dB/m	dB	dB	cm	deg																																		
1	5416.74	43.98	54.00	-10.02	31.37	36.37	9.66	33.42	231	26 AVERAGE																																	







		29									
Mode		Band Edge - L									
		U-NII-2C_5.47-5.725_802.11ax HE160_CH50_5250MHz									
ANT		CDD8+9									
Pol.		Vertical					Fundamental				
Peak		Level (dBuV/m) Date: 2025-03-21									



Mode	29																																										
	Band Edge - R																																										
	U-NII-2C_5.47-5.725_802.11ax HE160_CH50_5250MHz																																										
ANT	CDD8+9																																										
Pol.	Vertical	Fundamental																																									
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5387.76</td><td>50.99</td><td>74.00</td><td>-23.01</td><td>38.46</td><td>36.39</td><td>9.56</td><td>33.42</td><td>200</td><td>206 PEAK</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5387.76	50.99	74.00	-23.01	38.46	36.39	9.56	33.42	200	206 PEAK	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																		
1	5387.76	50.99	74.00	-23.01	38.46	36.39	9.56	33.42	200	206 PEAK																																	
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>5439.21</td><td>43.98</td><td>54.00</td><td>-10.02</td><td>31.36</td><td>36.35</td><td>9.68</td><td>33.41</td><td>200</td><td>206 AVERAGE</td></tr></table>		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark	MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5439.21	43.98	54.00	-10.02	31.36	36.35	9.68	33.41	200	206 AVERAGE	Blank
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos																																			
Freq	Level	Line	(dB)	Level	Factor	Loss	Factor		Remark																																		
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																		
1	5439.21	43.98	54.00	-10.02	31.36	36.35	9.68	33.41	200	206 AVERAGE																																	





		30																																																																																																				
Mode		Band Edge - L																																																																																																				
		U-NII-2C_5.47-5.725_802.11ax HE160_CH114_5570MHz																																																																																																				
ANT		CDD8+9																																																																																																				
Pol.		Horizontal					Fundamental																																																																																															
Peak	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)																																																																																																
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5447.24</td><td>52.90</td><td>74.00</td><td>-21.10</td><td>40.29</td><td>36.34</td><td>9.68</td><td>33.41</td><td>378</td><td>25 PEAK</td></tr><tr><td>2</td><td>5463.74</td><td>52.98</td><td>68.30</td><td>-15.32</td><td>40.37</td><td>36.33</td><td>9.69</td><td>33.41</td><td>378</td><td>25 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5447.24	52.90	74.00	-21.10	40.29	36.34	9.68	33.41	378	25 PEAK	2	5463.74	52.98	68.30	-15.32	40.37	36.33	9.69	33.41	378	25 PEAK	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5570.00</td><td>90.36</td><td>-----</td><td>-----</td><td>77.65</td><td>36.38</td><td>9.75</td><td>33.42</td><td>378</td><td>25 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	90.36	-----	-----	77.65	36.38	9.75	33.42	378
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	5447.24	52.90	74.00	-21.10	40.29	36.34	9.68	33.41	378	25 PEAK																																																																																												
2	5463.74	52.98	68.30	-15.32	40.37	36.33	9.69	33.41	378	25 PEAK																																																																																												
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	5570.00	90.36	-----	-----	77.65	36.38	9.75	33.42	378	25 PEAK																																																																																												
Avg	Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)					Level (dBuV/m) Date: 2025-03-21  Frequency (MHz)																																																																																																
	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5447.46</td><td>47.07</td><td>54.00</td><td>-6.93</td><td>34.46</td><td>36.34</td><td>9.68</td><td>33.41</td><td>378</td><td>25 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5447.46	47.07	54.00	-6.93	34.46	36.34	9.68	33.41	378	25 AVERAGE	<table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>5570.00</td><td>81.90</td><td>-----</td><td>-----</td><td>69.18</td><td>36.39</td><td>9.75</td><td>33.42</td><td>378</td><td>25 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1	5570.00	81.90	-----	-----	69.18	36.39	9.75	33.42	378	25 AVERAGE										
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	5447.46	47.07	54.00	-6.93	34.46	36.34	9.68	33.41	378	25 AVERAGE																																																																																												
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																													
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																																
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																													
1	5570.00	81.90	-----	-----	69.18	36.39	9.75	33.42	378	25 AVERAGE																																																																																												





		30																																																																																																		
Mode		Band Edge - L																																																																																																		
		U-NII-2C_5.47-5.725_802.11ax HE160_CH114_5570MHz																																																																																																		
ANT		CDD8+9																																																																																																		
Pol.		Vertical					Fundamental																																																																																													
Peak	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5449.88</td><td>53.00</td><td>74.00</td><td>-21.00</td><td>40.39</td><td>36.34</td><td>9.68</td><td>33.41</td><td>236</td><td>97 PEAK</td></tr><tr><td>2 5464.40</td><td>52.89</td><td>68.30</td><td>-15.41</td><td>40.28</td><td>36.33</td><td>9.69</td><td>33.41</td><td>236</td><td>97 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5449.88	53.00	74.00	-21.00	40.39	36.34	9.68	33.41	236	97 PEAK	2 5464.40	52.89	68.30	-15.41	40.28	36.33	9.69	33.41	236	97 PEAK	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5570.00</td><td>89.49</td><td>-----</td><td>-----</td><td>76.88</td><td>36.30</td><td>9.71</td><td>33.40</td><td>236</td><td>97 PEAK</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5570.00	89.49	-----	-----	76.88	36.30	9.71	33.40	236	97 PEAK
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5449.88	53.00	74.00	-21.00	40.39	36.34	9.68	33.41	236	97 PEAK																																																																																											
2 5464.40	52.89	68.30	-15.41	40.28	36.33	9.69	33.41	236	97 PEAK																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5570.00	89.49	-----	-----	76.88	36.30	9.71	33.40	236	97 PEAK																																																																																											
Avg	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5454.50</td><td>46.81</td><td>54.00</td><td>-7.19</td><td>34.20</td><td>36.34</td><td>9.68</td><td>33.41</td><td>236</td><td>97 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5454.50	46.81	54.00	-7.19	34.20	36.34	9.68	33.41	236	97 AVERAGE	Level (dBuV/m) Date: 2025-03-21 Frequency (MHz) <table><thead><tr><th></th><th>Limit</th><th>Margin</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>(dB)</th><th>Level</th><th>Factor</th><th>Loss Factor</th><th></th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th></th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1 5570.00</td><td>82.97</td><td>-----</td><td>-----</td><td>70.35</td><td>36.31</td><td>9.71</td><td>33.40</td><td>236</td><td>97 AVERAGE</td></tr></tbody></table>						Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark	Freq	Level	Line	(dB)	Level	Factor	Loss Factor				MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg	1 5570.00	82.97	-----	-----	70.35	36.31	9.71	33.40	236	97 AVERAGE										
		Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																										
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5454.50	46.81	54.00	-7.19	34.20	36.34	9.68	33.41	236	97 AVERAGE																																																																																											
	Limit	Margin	Read	Ant	Cable	Preamp	APos	TPos	Remark																																																																																											
Freq	Level	Line	(dB)	Level	Factor	Loss Factor																																																																																														
MHz	dBuV/m	dBuV/m		dBuV	dB/m	dB	dB	cm	deg																																																																																											
1 5570.00	82.97	-----	-----	70.35	36.31	9.71	33.40	236	97 AVERAGE																																																																																											





Mode	31																																																																																																																														
	Harmonic																																																																																																																														
	U-NII-3_5.725-5.85_802.11a_CH149_5745MHz																																																																																																																														
ANT	CDD8+9																																																																																																																														
Pol.	Horizontal					Vertical																																																																																																																									
Peak Avg																																																																																																																															
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11490.00</td><td>50.88</td><td>74.00</td><td>-23.12</td><td>62.66</td><td>39.19</td><td>12.87</td><td>63.84</td><td>125</td><td>17 Peak</td></tr><tr><td>2 11490.00</td><td>44.39</td><td>54.00</td><td>-9.61</td><td>56.17</td><td>39.19</td><td>12.87</td><td>63.84</td><td>125</td><td>17 Average</td></tr><tr><td>3 17235.00</td><td>48.05</td><td>68.30</td><td>-20.25</td><td>54.83</td><td>42.56</td><td>15.72</td><td>65.06</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11490.00	50.88	74.00	-23.12	62.66	39.19	12.87	63.84	125	17 Peak	2 11490.00	44.39	54.00	-9.61	56.17	39.19	12.87	63.84	125	17 Average	3 17235.00	48.05	68.30	-20.25	54.83	42.56	15.72	65.06	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1 11490.00</td><td>54.75</td><td>74.00</td><td>-19.25</td><td>66.53</td><td>39.19</td><td>12.87</td><td>63.84</td><td>190</td><td>0 Peak</td></tr><tr><td>2 11490.00</td><td>47.84</td><td>54.00</td><td>-6.16</td><td>59.62</td><td>39.19</td><td>12.87</td><td>63.84</td><td>190</td><td>0 Average</td></tr><tr><td>3 17235.00</td><td>47.84</td><td>68.30</td><td>-20.46</td><td>54.62</td><td>42.56</td><td>15.72</td><td>65.06</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1 11490.00	54.75	74.00	-19.25	66.53	39.19	12.87	63.84	190	0 Peak	2 11490.00	47.84	54.00	-6.16	59.62	39.19	12.87	63.84	190	0 Average	3 17235.00	47.84	68.30	-20.46	54.62	42.56	15.72	65.06	---	---
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																						
1 11490.00	50.88	74.00	-23.12	62.66	39.19	12.87	63.84	125	17 Peak																																																																																																																						
2 11490.00	44.39	54.00	-9.61	56.17	39.19	12.87	63.84	125	17 Average																																																																																																																						
3 17235.00	48.05	68.30	-20.25	54.83	42.56	15.72	65.06	---	---	Peak																																																																																																																					
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																								
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																							
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																						
1 11490.00	54.75	74.00	-19.25	66.53	39.19	12.87	63.84	190	0 Peak																																																																																																																						
2 11490.00	47.84	54.00	-6.16	59.62	39.19	12.87	63.84	190	0 Average																																																																																																																						
3 17235.00	47.84	68.30	-20.46	54.62	42.56	15.72	65.06	---	---	Peak																																																																																																																					



		32																																																																									
Mode		Harmonic																																																																									
		U-NII-3_5.725-5.85_802.11a_CH157_5785MHz																																																																									
ANT		CDD8+9																																																																									
Pol.		Horizontal					Vertical																																																																				
Peak Avg																																																																											
																																																																											
		<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11570.00</td><td>50.92</td><td>74.00</td><td>-23.08</td><td>62.61</td><td>39.28</td><td>12.93</td><td>63.90</td><td>130</td><td>18</td><td>Peak</td></tr><tr><td>2</td><td>11570.00</td><td>44.96</td><td>54.00</td><td>-9.04</td><td>56.65</td><td>39.28</td><td>12.93</td><td>63.90</td><td>130</td><td>18</td><td>Average</td></tr><tr><td>3</td><td>17355.00</td><td>47.06</td><td>68.30</td><td>-21.24</td><td>53.75</td><td>42.69</td><td>15.81</td><td>65.19</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11570.00	50.92	74.00	-23.08	62.61	39.28	12.93	63.90	130	18	Peak	2	11570.00	44.96	54.00	-9.04	56.65	39.28	12.93	63.90	130	18	Average	3	17355.00	47.06	68.30	-21.24	53.75	42.69	15.81	65.19	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	11570.00	50.92	74.00	-23.08	62.61	39.28	12.93	63.90	130	18	Peak																																																																
2	11570.00	44.96	54.00	-9.04	56.65	39.28	12.93	63.90	130	18	Average																																																																
3	17355.00	47.06	68.30	-21.24	53.75	42.69	15.81	65.19	---	---	Peak																																																																
		<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11570.00</td><td>55.07</td><td>74.00</td><td>-18.93</td><td>66.76</td><td>39.28</td><td>12.93</td><td>63.90</td><td>187</td><td>0</td><td>Peak</td></tr><tr><td>2</td><td>11570.00</td><td>47.89</td><td>54.00</td><td>-6.11</td><td>59.58</td><td>39.28</td><td>12.93</td><td>63.90</td><td>187</td><td>0</td><td>Average</td></tr><tr><td>3</td><td>17355.00</td><td>47.38</td><td>68.30</td><td>-20.92</td><td>54.07</td><td>42.69</td><td>15.81</td><td>65.19</td><td>---</td><td>---</td><td>Peak</td></tr></table>											Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11570.00	55.07	74.00	-18.93	66.76	39.28	12.93	63.90	187	0	Peak	2	11570.00	47.89	54.00	-6.11	59.58	39.28	12.93	63.90	187	0	Average	3	17355.00	47.38	68.30	-20.92	54.07	42.69	15.81	65.19	---	---	Peak
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																				
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																		
1	11570.00	55.07	74.00	-18.93	66.76	39.28	12.93	63.90	187	0	Peak																																																																
2	11570.00	47.89	54.00	-6.11	59.58	39.28	12.93	63.90	187	0	Average																																																																
3	17355.00	47.38	68.30	-20.92	54.07	42.69	15.81	65.19	---	---	Peak																																																																



Mode	33																																																																																																																																									
	Harmonic																																																																																																																																									
	U-NII-3_5.725-5.85_802.11a_CH165_5825MHz																																																																																																																																									
ANT	CDD8+9																																																																																																																																									
Pol.	Horizontal					Vertical																																																																																																																																				
Peak Avg																																																																																																																																										
	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11650.00</td><td>52.05</td><td>74.00</td><td>-21.95</td><td>63.63</td><td>39.38</td><td>12.99</td><td>63.95</td><td>140</td><td>22</td><td>Peak</td></tr><tr><td>2</td><td>11650.00</td><td>43.54</td><td>54.00</td><td>-10.46</td><td>55.12</td><td>39.38</td><td>12.99</td><td>63.95</td><td>140</td><td>22</td><td>Average</td></tr><tr><td>3</td><td>17475.00</td><td>47.12</td><td>68.30</td><td>-21.18</td><td>53.72</td><td>42.82</td><td>15.90</td><td>65.32</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11650.00	52.05	74.00	-21.95	63.63	39.38	12.99	63.95	140	22	Peak	2	11650.00	43.54	54.00	-10.46	55.12	39.38	12.99	63.95	140	22	Average	3	17475.00	47.12	68.30	-21.18	53.72	42.82	15.90	65.32	---	---	Peak	<table><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>APos</th><th>TPos</th><th></th></tr><tr><th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Remark</th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr><tr><td>1</td><td>11650.00</td><td>54.56</td><td>74.00</td><td>-19.44</td><td>66.14</td><td>39.38</td><td>12.99</td><td>63.95</td><td>154</td><td>0</td><td>Peak</td></tr><tr><td>2</td><td>11650.00</td><td>47.86</td><td>54.00</td><td>-6.14</td><td>59.44</td><td>39.38</td><td>12.99</td><td>63.95</td><td>154</td><td>0</td><td>Average</td></tr><tr><td>3</td><td>17475.00</td><td>46.53</td><td>68.30</td><td>-21.77</td><td>53.13</td><td>42.82</td><td>15.90</td><td>65.32</td><td>---</td><td>---</td><td>Peak</td></tr></table>						Limit	Read	Ant	Cable	Preamp	APos	TPos		Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	11650.00	54.56	74.00	-19.44	66.14	39.38	12.99	63.95	154	0	Peak	2	11650.00	47.86	54.00	-6.14	59.44	39.38	12.99	63.95	154	0	Average	3	17475.00	46.53	68.30	-21.77	53.13	42.82	15.90	65.32	---	---	Peak
		Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																		
	Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																	
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																	
1	11650.00	52.05	74.00	-21.95	63.63	39.38	12.99	63.95	140	22	Peak																																																																																																																															
2	11650.00	43.54	54.00	-10.46	55.12	39.38	12.99	63.95	140	22	Average																																																																																																																															
3	17475.00	47.12	68.30	-21.18	53.72	42.82	15.90	65.32	---	---	Peak																																																																																																																															
	Limit	Read	Ant	Cable	Preamp	APos	TPos																																																																																																																																			
Freq	Level	Line	Margin	Level	Factor	Loss	Factor	Remark																																																																																																																																		
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																																																																	
1	11650.00	54.56	74.00	-19.44	66.14	39.38	12.99	63.95	154	0	Peak																																																																																																																															
2	11650.00	47.86	54.00	-6.14	59.44	39.38	12.99	63.95	154	0	Average																																																																																																																															
3	17475.00	46.53	68.30	-21.77	53.13	42.82	15.90	65.32	---	---	Peak																																																																																																																															