

RF EXPOSURE EVALUATION

According to FCC 1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency(RF) Radiation as specified in §1.1307(b)

FCC ID: **RG2-YC300**

EUT Specification

EUT	Portable wireless recorder
Frequency band (Operating)	☐ WLAN: 2.412GHz ~ 2.462GHz ☒ WLAN: 5.18GHz ~ 5.24GHz ☐ Others: 2.402GHz~2.480GHz (BT4.2)
Device category	☐ Portable (<20cm separation) ☒ Mobile (>20cm separation) ☐ Others ____
Exposure classification	☐ Occupational/Controlled exposure (S = 5mW/cm ²) ☒ General Population/Uncontrolled exposure (S=1mW/cm ²)
Antenna diversity	☐ Single antenna ☒ Multiple antennas ☐ Tx diversity ☐ Rx diversity ☐ Tx/Rx diversity
Antenna gain (Max)	ANT1 & ANT2 & ANT3 & ANT4: 0 dBi
Evaluation applied	☒ MPE Evaluation ☐ SAR Evaluation

Limits for Maximum Permissible Exposure(MPE)

Frequency Range(MHz)	Electric Field Strength(V/m)	Magnetic Field Strength(A/m)	Power Density(mW/cm ²)	Average Time
(A) Limits for Occupational/Control Exposures				
300-1500	--	--	F/300	6
1500-100000	--	--	5	6
(B) Limits for General Population/Uncontrol Exposures				
300-1500	--	--	F/1500	6
1500-100000	--	--	1	30

Friis transmission formula: $P_d = (P_{out} * G) / (4 * \pi * R^2)$

Where

P_d = Power density in mW/cm^2

P_{out} = output power to antenna in Mw

G = gain of antenna in linear scale

$\pi = 3.1416$

R = distance between observation point and center of the radiator in cm

P_d the limit of MPE, $1mW/cm^2$. If we know the maximum gain of the antenna and total power input to the antenna, through the calculation, we will know the distance where the MPE limit is reached.

Measurement Result

ANT1:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/ cm ²)	(mW/cm ²)
5G	5180	9.66	9.66±1	10.66	0	0.0023	1
	5200	12.12	12.12±1	13.12	0	0.0041	1
	5240	12.07	12.07±1	13.07	0	0.0040	1

ANT2:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/ cm ²)	(mW/cm ²)
5G	5180	9.44	9.44±1	10.44	0	0.0022	1
	5200	11.42	11.42±1	12.42	0	0.0035	1
	5240	10.89	10.89±1	11.89	0	0.0031	1

ANT3:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/ cm ²)	(mW/cm ²)
5G	5180	10.10	10.10±1	11.10	0	0.0026	1
	5200	10.96	10.96±1	11.96	0	0.0031	1
	5240	11.95	11.95±1	12.95	0	0.0039	1

ANT4:

Operating Mode	Channel Frequency	Measured Power	Tune up tolerance	Max. Tune up Power	Antenna Gain	Power density at 20cm	Power density Limits
	(MHz)	(dBm)	(dBm)	(dBm)	(dBi)	(mW/ cm ²)	(mW/cm ²)
5G	5180	9.56	9.56±1	10.56	0	0.0023	1
	5200	10.99	10.99±1	11.99	0	0.0031	1
	5240	11.61	11.61±1	12.61	0	0.0036	1

ANT1+ANT2+ANT3+ANT4:

Operating Mode	Channel Frequency (MHz)	ANT 1 Power density at 20cm (mW/ cm ²)	ANT 2 Power density at 20cm (mW/ cm ²)	ANT 3 Power density at 20cm (mW/ cm ²)	ANT 4 Power density at 20cm (mW/ cm ²)	Power density at 20cm (mW/ cm ²)	Power density Limits (mW/cm ²)
5G	5180	0.0023	0.0022	0.0026	0.0023	0.0094	1
	5200	0.0041	0.0035	0.0031	0.0031	0.0138	1
	5240	0.0040	0.0031	0.0039	0.0036	0.0146	1