

Product specifications

Operating frequency range	ISM 2.402 to 2.480GHz
Support for Bluetooth Profiles	Headset & Handsfree and A2DP & AVRCP Profiles
Transmit power	Class 2
Scope of wireless connection	10m
Charger output specifications	DC 5V 100mA
Built in rechargeable lithium battery	Polymer lithium battery 85mAh
Charging socket	Micro USB
Standby current	≤0.6mA
Talking current	≤20mA
Shutdown current	≤5μA
Loudspeaker	Φ8mm
Microphone	-42dBm 4015
Normal charging time	≤2.5H
Maximum time of call	6H
The biggest music playback time	7 H
Maximum idle time	170 H
Outline dimensions	8*35*35mm
Weight	12 g

Operation procedures:

1 started to use:

Use your Bluetooth hands-free products, please refer to the following steps:

(a) the product is used for the first time, please charge the battery.

(b) add the charger is connected with the power socket, the other end is connected to the charging interface Bluetooth hands-free products. When charging, please remove automatic charger charging

interface.

(c) in pairs, please make sure that the Bluetooth hands-free products and Bluetooth devices in the 0.5 meters distance.

(d) when using this product, please make sure that the mobile phone and the distance in 10 meters of the induction distance, if there are obstacles, the induction distance will be shortened.

Prompt.

(a): normal charging time for the full battery charge time of about 2-3 hours.

(b) charging instructions : the product when charging, product red light will light up; full after the red light will be extinguished, blue light.

(c) low power indication: when battery power is low, the product will prompt, please immediately product charge. In order to maintain the life of the battery, when the battery power is low when the product, the product will automatically shutdown.

The LED directive will have the following two ways:

(1) product in the connected state: blue light flash 2 times every 30 seconds.

(2) products are not connected to state: red light flashing 1 times every 5 seconds.

2 boot and shutdown:

(1): starting in the off state, long press the function key, until the blue indicator light, to release the button, horn has a boot voice tone.

(2): shutdown in on state, long press the function key, until the indicator lights up red went out after the release button, horn, the boot voice tone.

3 and Bluetooth mobile phone pairing with connection:

(a) products and mobile phone distance control within 0.5 meters.

(b) determine the products in the power off state.

(c) the boot and press to red and blue lights flash alternately, means the products into pairing mode.

(d) according to the Bluetooth mobile phone instructions, open " Bluetooth search " or " add new equipment " function, in search of the Bluetooth equipment choice for this product, confirmation, if the mobile phone input prompt pairing password, enter "0000 " after the confirmation, the product and the mobile phone has been successful pairing, not every mobile phone needs to input pair password. Pairing is complete, blue exhibit of lanterns flash 2 times, and is accompanied by the voice prompt sound, this product will be placed in a standby state, LED flash every 30 seconds 2 blue light.

4 recovery products and mobile phone connection:

Paired with link is completed, the product is in a standby mode, before using the product if the mobile phone screen does not appear icon Bluetooth headphones or marking, please follow the below steps to restore the Bluetooth connection

(a) with mobile phone: mobile phone pairing list of "Kandie " to connect.

(b) use headphones: short press the function key, in the mobile phone screen and select " accept connection ". Please note that some mobile phone screen will display " accept connections ".

Prompt.

(a) when the Bluetooth connection is lost or removed, and mobile phone screen to see the Bluetooth logo or link symbol, for example: mobile phone earphone or shut down after the boot, or more than 10 meters of the induction distance according to the instructions, please reply.

(b) this product has an energy saving device, once the Bluetooth link removed more than 15 minutes (approximately), the headset will enter shutdown state, to restore the link, in 15 minutes. Please press the function key, or operating mobile phone restore connections.

(c) the headset after shutdown, starting up again, in most cases, the headset will automatically and finally connected the mobile phone connection, if not automatically connect, in accordance with the above described operation mobile phone or headset restoring the connection, this also applies to the double connection state.

Note: if your headset connected to two mobile phone, mobile phone off and then boot, will not automatically return link, please choose a mobile phone pairing list of "Kandie " return connection.

(d) headphones are not connected to the standby condition, short press the function key, products will be automatically and the last connection of mobile phone connections.

5 remove the connection:

By the following method disconnect products and mobile phone connection:

(a) shutdown: will the headphones or mobile phone shutdown.

(b) operation: mobile phone mobile phone Bluetooth device is connected from the menu " disconnect " connection.

Note: headphones and mobile phone outside the 10m range disconnected, for most Bluetooth hands-free mobile phone, 15 minutes back to the range will be automatically connected, disconnected for more than 15 minutes after had not returned to the range is connected with the mobile phone headset will enter shutdown state.

6 the use of Bluetooth headset:

(a) to answer the phone

When the call came in, Bluetooth headset send ringtones, short press the function key or using a mobile phone incoming call answering key.

(b) hang up the phone

When the Bluetooth headset during a call state, short press the function key or the use of mobile phone keys to terminate the telephone call.

(c) the voice dialing

Bluetooth headset in the standby state (connected mobile phone), press the function key to tone, mobile phone sound prompting voice, now say voice volume can realize voice dialing.

Prompt.

In use the voice dialing before, we must first determine the mobile phone has a voice dialing function, the specific use please refer to mobile phone use, due to differences in some mobile phone mobile phone, voice dialing without prompt tone.

(d) the last number redial

In the standby mode, click redial function keys: connecting mobile phone last allocated numbers. Voice: "di "

(E) abort dial

When the dialed number, the other is not connected, short press the function key abort dial. Voice: "di"
"

(f) a two function

The first and the first mobile phone to complete the pair, the Bluetooth headset off, again with second mobile phone to complete the pair, then the Bluetooth headset shutdown, the Bluetooth headset boot will automatically with the first and second mobile phone connection.

(g) the voice prompt language switching: the headphone support (English, in the west, France and Germany, in five languages), in the paired condition according to the function keys (horn " beep" two seconds) after the release, voice prompt circulatory changes, when the switch to the language, press the function key to confirm you can.

In 5, long-term storage conditions: closed headphones, not exposed to moisture or heat

FCC ID Note:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment