



User's Manual

- S1[1] ON** ☐ Large detector area like an EAS antenna
S1[1] OFF ☐ Small detector area like the GuardPost detector
S1[2] ON ☐ Narrow distance between the detectors (less than 1.2 - 1.4 meter)
S1[2] OFF ☐ Wide distance between the detectors (greater than 1.2 - 1.4 meter)
S1[3] ON ☐ Detector size adjustment preset 2
S1[3] OFF ☐ Detector size adjustment preset 1
S1[4] ON ☐ High metal sensitivity
S1[4] OFF ☐ Normal metal sensitivity
S1[5] ON ☐ AM filter OFF
S1[5] OFF ☐ AM filter ON

- S2[1] ON** ☐ Trolley rejection disabled (Alarm delay = 0.1 second)
S2[1] OFF ☐ Trolley rejection enabled (Alarm delay = 1 second)
S2[2] ON ☐ Trolley blanking enabled
S2[2] OFF ☐ Trolley blanking disabled
S2[3] ON ☐ 3 detectors
S2[3] OFF ☐ 2 detectors
S2[4] ON ☐ Slave
S2[4] OFF ☐ Master

- "ANT SIZE"** Fine tuning of the correction to the detector size
"DIST" Adjustment of the sensitivity to the distance between the antennas
"THRESHOLD" Adjustment of the threshold level for the AM filter
 Use an oscilloscope at TP601 when adjusting
"MOVE" Adjustment of the blocking function to movement of the top of the antenna
"METAL" Adjustment of the alarm sensitivity to metal bags
"TROLLEY" Adjustment of the rejection of large metal items such as trolleys
"TIME" Adjustment of the alarm time
"CHANNEL" Selection of channels



TP400 ○

TP500 ○

TP401 ○

MOVE ☐


METAL ☐

TROLLEY ☐

TIME ☐

S2 ☐

TP501 ○



Federal Communications Commission and Industry Canada Statement

This device complies with part 15 of the FCC Rules and RSS-210 of the Canadian Rules.

Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation of the device.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by tuning the equipment off and on, the user is encouraged to try to correct the interference by one of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help.

WARNING!

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

This User Manual is valid for the following products: FCC ID: S8OMDET3320 and S8OMDET3380 - IC ID: 5849A-MDET3320 and IC ID: 5849A-MDET3380