



## **Certification Exhibit**

**FCC ID: SDBR100NA**

**FCC Rule Part: 47 CFR Part 2.1091**

**TÜV SÜD Project Number: 72159520**

Manufacturer: Sensus USA, Inc.  
Model: **R100NA (with Amphenol antenna BCD-87010)**

## **RF Exposure Multiple Transmitters**

**General Information:**

Applicant: Sensus USA, Inc.  
 Device Category: Fixed  
 Environment: General Population/Uncontrolled Exposure

The R100NA can be installed into the 53963437000XX host with 2 additional wireless transceivers. Transceiver 1 is a WIFI device and a second is a single cellular modem. Simultaneous transmission is possible with the WIFI (FCC ID: Z64-WL18DBMOD), and cellular radio modem (FCC ID: RI7LE910NA or RI7LE910SV) and the native R100NA Flexnet transmitter. This document covers the present model combined with the Amphenol antenna.

The high-gain antenna for the R100NA is only applicable with the unit operated in the base station / fixed frequency bands of operation (930-931 MHz, 940-941 MHz, 941-941.5 MHz, 952-953 MHz and 959.85-960 MHz).

**Technical Information:****Using RI7LE910SV cellular modem****Table 1: Technical Information**

	Telit Communications LE910SV	SDBR100NA	Texas Instruments WL18DBMOD
<b>Frequency Bands (MHz)</b>	Band 13:777MHz-787MHz	901 to 960 MHz	2412 to 2462 MHz
	Band 4:1710.7MHz- 1754.3MHz		
	Band 2:1850.7MHz- 1909.3MHz		
<b>Antenna Type(s)</b>	Band 13: Vertical	Fiberglass Omnidirectional Antenna	Vertical Dipole
	Band 4: Vertical		
	Band 2: Vertical		
<b>Antenna Gain (dBi)</b>	Band 13: 0.97	12.15	2.0
	Band 4: 0.68		
	Band 2: 0.68		
<b>Conducted Power (dBm)</b>	Band 13: 24	35.8	23.86
	Band 4: 24		
	Band2: 24		

**The LE910SV cellular modem has several modulation formats the worst case was selected for each frequency band.**

**MPE Calculation:**

The Power Density (mW/cm<sup>2</sup>) is calculated as follows:

$$S = \frac{PG}{4\pi R^2}$$

Where:

S = power density (in appropriate units, e.g. mW/cm<sup>2</sup>)

P = power input to the antenna (in appropriate units, e.g., mW)

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna (appropriate units, e.g., cm)

**Table 2: MPE Calculation (Including Collocated Devices)**

Transmit Frequency (MHz)	Radio Power (dBm)	Power Density Limit (mW/cm <sup>2</sup> )	Radio Power (mW)	Antenna Gain (dBi)	Antenna Gain (mW eq.)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Radio
777	24	0.52	251.19	0.96	1.247	92	0.003	A
1710.7	24	1.00	251.19	0.68	1.169	92	0.003	B
1850.7	24	1.00	251.19	0.68	1.169	92	0.003	C
2412	23.86	1.00	243.22	2	1.585	92	0.004	D
901	35.8	0.60	3801.89	12.15	16.406	92	0.586	E

**Summation of MPE ratios – Simultaneous Transmissions**

This device contains multiple transmitters which can operate simultaneously; therefore the maximum RF exposure is determined by the summation of MPE ratios. The limit is such that the summation of MPE ratios is  $\leq 1.0$ .

**Table 3: Summation of MPE Ratios**

	Scenario 1	Scenario 2	Scenario 3
Radio A (Telit Band 13)	x		
Radio B (Telit Band 4)		x	
Radio C (Telit Band 2)			x
Radio D (WIFI)	x	x	x
Radio E(R100NA)	x	x	x
Radio A MPE Ratio	0.00568702		
Radio B MPE Ratio		0.002761942	
Radio C MPE Ratio			0.002761942
Radio D MPE Ratio	0.003624219	0.003624219	0.003624219
Radio E MPE Ratio	0.97629474	0.97629474	0.97629474
MPE Ratio Summation:	0.985605979	0.982680901	0.982680901

## Using RI7LE910NA cellular modem

Table 4: Technical Information

	Telit Communications, S.p.A. LTE modem Model LE910-NA FCC ID: RI7LE910NA	SDBR100NA	Texas Instruments WL18DBMOD
<b>Frequency Bands (MHz) &amp; Conducted Power (dBm)</b>	LTE Band 17: 706.5 MHz - 713.5 MHz Conducted Power = 25.00 dBm	901 to 960 MHz Conducted Power = 35.8 dBm	
	UMTS/HSPA: 826.4 MHz – 846.6 MHz Conducted Power = 25.00 dBm		2412 to 2462 MHz Conducted Power = 23.86 dBm
	LTE Band 5: 826.5 MHz – 846.5 MHz Conducted Power = 25.00 dBm		
	GSM 850: 824.2MHz-848.2MHz Conducted Power = 33.5dBm		
	LTE Band 4: 1712.5 MHz – 1752.5 MHz Conducted Power = 25.00 dBm		
	UMTS/HSPA: 1852.4 MHz – 1907.6 MHz Conducted Power = 25.00 dBm		
	LTE Band 2: 1852.5 MHz – 1907.5 MHz Conducted Power = 25.00 dBm		
	GSM 1900: 1850.2 MHz – 1909.8 MHz Conducted Power = 30.50 dBm		
	SanteFe SFT-LTE-002		
<b>Antenna Type(s)</b>		Fiberglass Omnidirectional Antenna	Vertical Dipole
<b>Antenna Gain (dBi)</b>	700MHz Band = 0.97	12.15	2.0
	800MHz Band = 0.97		
	1700MHz Band = 0.68		
	1900MHz Band = 0.68		

**MPE Calculation:**

The Power Density (mW/cm<sup>2</sup>) is calculated as follows:

$$S = \frac{PG}{4\pi R^2}$$

Where:

S = power density (in appropriate units, e.g. mW/cm<sup>2</sup>)

P = power input to the antenna (in appropriate units, e.g., mW)

G = power gain of the antenna in the direction of interest relative to an isotropic radiator

R = distance to the center of radiation of the antenna (appropriate units, e.g., cm)

**Table 5: MPE Calculation (Including Collocated Devices)**

Transmit Frequency (MHz)	Radio Power (dBm)	Power Density Limit (mW/cm <sup>2</sup> )	Radio Power (mW)	Antenna Gain (dBi)	Antenna Gain (mW eq.)	Distance (cm)	Power Density (mW/cm <sup>2</sup> )	Radio
706.5	25	0.47	316.23	0.96	1.247	93	0.004	A
824.2	33.5	0.55	559.68	0.96	1.247	93	0.026	B
1712.5	25	1.00	316.23	0.68	1.169	93	0.003	C
1850.2	25	1.00	316.23	0.68	1.169	93	0.003	D
2412	23.86	1.00	243.22	2	1.585	93	0.004	E
901	35.8	0.60	3801.89	12.1	16.218	93	0.567	F

\*The Telit RF Exposure report filed with FCC ID RI7LE910NA was used to determine the worst case for each frequency band.

\*\*Peak output power for GSM850 is 33.5 dBm with a 25% duty cycle. 559.68 mW is the source-based time-averaging power.

#### **Summation of MPE ratios – Simultaneous Transmissions**

This device contains multiple transmitters which can operate simultaneously; therefore the maximum RF exposure is determined by the summation of MPE ratios. The limit is such that the summation of MPE ratios is  $\leq 1.0$ .

**Table 6: Summation of MPE Ratios**

	Scenario 1	Scenario 2	Scenario 3	Scenario 4
Radio A (Telit LTE Band 17)	x			
Radio B (Telit GSM850)		x		
Radio C (Telit LTE Band 4)			x	
Radio D (Telit LTE Band 2)				x
Radio E (WIFI)	x	x	x	x
Radio F (R100NA)	x	x	x	x
Radio A MPE Ratio	0.007705544			
Radio B MPE Ratio		0.046760903		
Radio C MPE Ratio			0.003402705	
Radio D MPE Ratio				0.003402705
Radio E MPE Ratio	0.003546698	0.003546698	0.003546698	0.003546698
Radio F MPE Ratio	0.944475522	0.944475522	0.944475522	0.944475522
MPE Ratio Summation:	0.955727765	0.994783123	0.951424925	0.951424925