



FCC RADIO TEST REPORT

FCC ID : SZGGNN2Z
Equipment : Wireless Device
Model Name : GNN2Z
Applicant : Weifang Goertek Electronics Co., Ltd
Gaoxin 2 Road, Free Trade Zone, Weifang,
Shandong, 261205, P.R.China
Standard : FCC Part 15 Subpart C §15.247

The product was received on Dec. 09, 2024 and testing was performed from Dec. 20, 2024 to Jan. 25, 2025. We, Sporton International Inc. Wensan Laboratory, would like to declare that the tested sample has been evaluated in accordance with the test procedures and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval from Sporton International Inc. Wensan Laboratory, the test report shall not be reproduced except in full.

Approved by: Louis Wu

Sportun International Inc. Wensan Laboratory

No.58, Aly. 75, Ln. 564, Wenhua 3rd, Rd., Guishan Dist., Taoyuan City 333010, Taiwan (R.O.C.)



Table of Contents

History of this test report.....	3
Summary of Test Result.....	4
1 General Description.....	5
1.1 Product Feature of Equipment Under Test.....	5
1.2 Modification of EUT	5
1.3 Testing Location	6
1.4 Applicable Standards.....	6
2 Test Configuration of Equipment Under Test.....	7
2.1 Carrier Frequency Channel	7
2.2 Test Mode.....	8
2.3 Connection Diagram of Test System	9
2.4 Support Unit used in test configuration and system	10
2.5 EUT Operation Test Setup	10
2.6 Measurement Results Explanation Example.....	10
3 Test Result.....	11
3.1 6dB and 99% Bandwidth Measurement	11
3.2 Output Power Measurement.....	12
3.3 Power Spectral Density Measurement	13
3.4 Conducted Band Edges and Spurious Emission Measurement	14
3.5 Radiated Band Edges and Spurious Emission Measurement	15
3.6 AC Conducted Emission Measurement.....	19
3.7 Antenna Requirements.....	21
4 List of Measuring Equipment	22
5 Measurement Uncertainty	23
Appendix A. Conducted Test Results	
Appendix B. AC Conducted Emission Test Result	
Appendix C. Radiated Spurious Emission Test Data	
Appendix D. Duty Cycle Plots	
Appendix E. Setup Photographs	



History of this test report



Summary of Test Result

Report Clause	Ref Std. Clause	Test Items	Result (PASS/FAIL)	Remark
3.1	15.247(a)(2)	6dB Bandwidth	Pass	-
3.1	2.1049	99% Occupied Bandwidth	Pass	-
3.2	15.247(b)(3) 15.247(b)(4)	Output Power	Pass	-
3.3	15.247(e)	Power Spectral Density	Pass	-
3.4	15.247(d)	Conducted Band Edges and Spurious Emission	Pass	-
3.5	15.247(d)	Radiated Band Edges and Spurious Emission	Pass	-
3.6	15.207	AC Conducted Emission	Pass	-
3.7	15.203	Antenna Requirement	Pass	-

Remark: Except Conducted and Radiated Band Edges and Radiated Spurious Emission are carrying out, The FR4N2022C report reuses test data from the FR4N2548B report.

Conformity Assessment Condition:
1. The test results (PASS/FAIL) with all measurement uncertainty excluded are presented against the regulation limits or in accordance with the requirements stipulated by the applicant/manufacturer who shall bear all the risks of non-compliance that may potentially occur if measurement uncertainty is taken into account.
2. The measurement uncertainty please refer to each test result in the section "Measurement Uncertainty".
Disclaimer:
The product specifications of the EUT presented in the test report that may affect the test assessments are declared by the manufacturer who shall take full responsibility for the authenticity.

Reviewed by: Duko Chen

Report Producer: Mila Chen



1 General Description

1.1 Product Feature of Equipment Under Test

Product Feature	
General Specs Bluetooth-LE, BLE ASK and BLE GFSK.	
Antenna Type Bluetooth-LE, BLE ASK and BLE GFSK: PCB Antenna	

EUT Information List	
S/N	Performed Test Item
M14AFC1794	RF Conducted Measurement
4A23C7560	Radiated Spurious Emission
4A31LZACOL6416 4A31LZACOR6448	Conducted Emission
Antenna information	
2400 MHz ~ 2483.5 MHz	Peak Gain (dBi) 0.2

Remark: The EUT's information above is declared by manufacturer. Please refer to Disclaimer in report summary.

1.2 Modification of EUT

No modifications made to the EUT during the testing.



1.3 Testing Location

Test Site	Sportun International Inc. Wensan Laboratory
Test Site Location	No.58, Aly. 75, Ln. 564, Wenhua 3rd, Rd., Guishan Dist., Taoyuan City 333010, Taiwan (R.O.C.) TEL: +886-3-327-0868 FAX: +886-3-327-0855
Test Site No.	Sportun Site No. TH05-HY, CO07-HY, 03CH20-HY

Note: The test site complies with ANSI C63.4 2014 requirement.

FCC designation No.: TW3786

1.4 Applicable Standards

According to the specifications declared by the manufacturer, the EUT must comply with the requirements of the following standards:

- ♦ FCC Part 15 Subpart C §15.247
- ♦ FCC KDB Publication No. 558074 D01 15.247 Meas Guidance v05r02
- ♦ FCC KDB 414788 D01 Radiated Test Site v01r01
- ♦ ANSI C63.10-2013

Remark:

1. All the test items were validated and recorded in accordance with the standards without any modification during the testing.
2. The TAF code is not including all the FCC KDB listed without accreditation.



2 Test Configuration of Equipment Under Test

2.1 Carrier Frequency Channel

Frequency Band	Channel	Freq. (MHz)	Channel	Freq. (MHz)	Channel	Freq. (MHz)
2400-2483.5 MHz	-	-	27	2429	54	2456
	-	-	28	2430	55	2457
	2	2404	29	2431	56	2458
	3	2405	30	2432	57	2459
	4	2406	31	2433	58	2460
	5	2407	32	2434	59	2461
	6	2408	33	2435	60	2462
	7	2409	34	2436	61	2463
	8	2410	35	2437	62	2464
	9	2411	36	2438	63	2465
	10	2412	37	2439	64	2466
	11	2413	38	2440	65	2467
	12	2414	39	2441	66	2468
	13	2415	40	2442	67	2469
	14	2416	41	2443	68	2470
	15	2417	42	2444	69	2471
	16	2418	43	2445	70	2472
	17	2419	44	2446	71	2473
	18	2420	45	2447	72	2474
	19	2421	46	2448	73	2475
	20	2422	47	2449	74	2476
	21	2423	48	2450	75	2477
	22	2424	49	2451	76	2478
	-	-	50	2452	-	-
	-	-	51	2453	-	-
	-	-	52	2454	-	-
	26	2428	53	2455	-	-



2.2 Test Mode


- a. The EUT has been associated with peripherals and configuration operated in a manner tended to maximize its emission characteristics in a typical application. Frequency range investigated: conduction emission (150 kHz to 30 MHz), radiation emission (9 kHz to the 10th harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower). For radiated measurement, the measured emission level of the EUT was maximized by rotating the EUT on a turntable, adjusting the orientation of the EUT and EUT antenna in three orthogonal axis (X: flat, Y: portrait, Z: landscape), and accessory (Adapter or Earphone), and adjusting the measurement antenna orientation, following C63.10 exploratory test procedures and only the worst case emissions were reported in this report.
- b. AC power line Conducted Emission was tested under maximum output power.

The following summary table is showing all test modes to demonstrate in compliance with the standard.


Summary table of Test Cases	
Test Item	Data Rate / Modulation
Conducted Test Cases	Bluetooth – LE / GFSK
	Mode 1: Bluetooth Tx CH02_2404 MHz_1Mbps
	Mode 2: Bluetooth Tx CH38_2440 MHz_1Mbps
	Mode 3: Bluetooth Tx CH76_2478 MHz_1Mbps
AC Conducted Emission	Mode 1: Bluetooth Link + MP3 + Battery + Wireless Device + USB Cable (Charging from Adapter)
Remark:	
1. For radiation spurious emission, the modulation and the data rate picked for testing are determined by the Max. RF conducted power.	
2. The detailed Radiated test modes are shown in Appendix C.	

2.3 Connection Diagram of Test System

<AC Conducted Emission Mode>



<Bluetooth-LE GFSK Tx Mode>





2.4 Support Unit used in test configuration and system

Item	Equipment	Brand Name	Model Name	FCC ID	Data Cable	Power Cord
1.	Phone	N/A	N/A	N/A	N/A	N/A
2.	Adapter	N/A	N/A	N/A	N/A	N/A
3.	USB Cable	N/A	N/A	N/A	N/A	N/A

2.5 EUT Operation Test Setup

The RF test items, utility “BDT 5.7.4” was installed in Notebook which was programmed in order to make the EUT get into the engineering modes to provide channel selection, power level, data rate and the application type and for continuous transmitting signals.

2.6 Measurement Results Explanation Example

For all conducted test items:

The offset level is set in the spectrum analyzer to compensate the RF cable loss and attenuator factor between EUT conducted output port and spectrum analyzer. With the offset compensation, the spectrum analyzer reading level is exactly the EUT RF output level.

Example :

The spectrum analyzer offset is derived from RF cable loss and attenuator factor.

Offset = RF cable loss + attenuator factor.

Following shows an offset computation example with cable loss 4.2 dB and 10 dB attenuator.

Offset(dB) = RF cable loss(dB) + attenuator factor(dB).

$$= 4.2 + 10 = 14.2 \text{ (dB)}$$

3 Test Result

3.1 6dB and 99% Bandwidth Measurement

3.1.1 Limit of 6dB and 99% Bandwidth

The minimum 6 dB bandwidth shall be at least 500 kHz.


3.1.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.1.3 Test Procedures

1. The testing follows the ANSI C63.10 Section 6.9.3 (OBW) and 11.8.1 (6dB BW).
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 100 kHz. Set the Video bandwidth (VBW) = 300 kHz. In order to make an accurate measurement. The 6dB bandwidth must be greater than 500 kHz.
5. For 99% Bandwidth Measurement, the spectrum analyzer's resolution bandwidth (RBW) is set 1-5% of the emission bandwidth and set the Video bandwidth (VBW) $\geq 3 * \text{RBW}$.
6. Measure and record the results in the test report.

3.1.4 Test Setup



3.1.5 Test Result of 6dB Bandwidth

Please refer to Appendix A.

3.1.6 Test Result of 99% Occupied Bandwidth

Please refer to Appendix A.

3.2 Output Power Measurement

3.2.1 Limit of Output Power

For systems using digital modulation in the 2400-2483.5 MHz, the limit for output power is 30 dBm. If transmitting antenna of directional gain greater than 6 dBi is used, the peak output power from the intentional radiator shall be reduced below the above stated value by the amount in dB that the directional gain of the antenna exceeds 6 dBi. In case of point-to-point operation, the limit has to be reduced by 1 dB for every 3 dB that the directional gain of the antenna exceeds 6 dBi.


3.2.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.2.3 Test Procedures

1. For Average Power, the testing follows ANSI C63.10 Section 11.9.2.3.2 Method AVGPM-G
2. The RF output of EUT is connected to the power meter by RF cable and attenuator.
3. The path loss is compensated to the results for each measurement.
4. Set the maximum power setting and enable the EUT to transmit continuously.
5. Measure the conducted output power and record the results in the test report.

3.2.4 Test Setup



3.2.5 Test Result of Average Output Power

Please refer to Appendix A.

3.3 Power Spectral Density Measurement

3.3.1 Limit of Power Spectral Density

The peak power spectral density shall not be greater than 8 dBm in any 3 kHz band at any time interval of continuous transmission.


3.3.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.3.3 Test Procedures

1. The testing follows the ANSI C63.10 Section 11.10.2 Method PKPSD.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Make the measurement with the spectrum analyzer's resolution bandwidth (RBW) = 3 kHz. Video bandwidth (VBW) = 10 kHz. In order to make an accurate measurement, set the span to 1.5 times DTS Channel Bandwidth. (6 dB BW)
5. Detector = peak, Sweep time = auto couple, Trace mode = max hold, Allow trace to fully stabilize. Use the peak marker function to determine the maximum power level.
6. Measure and record the results in the test report.
7. The Measured power density (dBm)/ 100 kHz is a reference level and is used as 20 dBc down limit line for Conducted Band Edges and Conducted Spurious Emission.

3.3.4 Test Setup



3.3.5 Test Result of Power Spectral Density

Please refer to Appendix A.

3.4 Conducted Band Edges and Spurious Emission Measurement

3.4.1 Limit of Conducted Band Edges and Spurious Emission

All harmonics/spurious must be at least 30 dB down from the highest emission level within the authorized band.


3.4.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.4.3 Test Procedure

1. The testing follows the ANSI C63.10 Section 11.11.3 Emission level measurement.
2. The RF output of EUT is connected to the spectrum analyzer by RF cable and attenuator. The path loss is compensated to the results for each measurement.
3. Set the maximum power setting and enable the EUT to transmit continuously.
4. Set RBW = 100 kHz, VBW = 300 kHz, Peak Detector. Unwanted Emissions measured in any 100 kHz bandwidth outside of the authorized frequency band shall be attenuated by at least 20 dB relative to the maximum in-band peak PSD level in 100 kHz when maximum peak conducted output power procedure is used. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, the attenuation required under this paragraph shall be 30 dB instead of 20 dB.
5. Measure and record the results in the test report.
6. The RF fundamental frequency should be excluded against the limit line in the operating frequency band.

3.4.4 Test Setup



3.4.5 Test Result of Conducted Band Edges Plots

Please refer to Appendix A.

3.4.6 Test Result of Conducted Spurious Emission Plots

Please refer to Appendix A.



3.5 Radiated Band Edges and Spurious Emission Measurement

3.5.1 Limit of Radiated Band Edges and Spurious Emission

In any 100 kHz bandwidth outside the intentional radiator frequency band, all harmonics/spurious must be at least 20 dB below the highest emission level within the authorized band. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, the attenuation required shall be 30 dB instead of 20 dB. In addition, radiated emissions which fall in the restricted bands must also comply with the limits as below.

Frequency (MHz)	Field Strength (microvolts/meter)	Measurement Distance (meters)
0.009 – 0.490	2400/F(kHz)	300
0.490 – 1.705	24000/F(kHz)	30
1.705 – 30.0	30	30
30 – 88	100	3
88 – 216	150	3
216 - 960	200	3
Above 960	500	3

3.5.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.



3.5.3 Test Procedures


1. The testing follows the ANSI C63.10 Section 11.12.1 Radiated emission measurements.
2. The EUT is arranged to its worst case and then tune the antenna tower (from 1 m to 4 m) and turntable (from 0 degree to 360 degrees) to find the maximum reading. A pre-amp and a high pass filter are used for the test in order to get better signal level.
3. The EUT is placed on a turntable with 0.8 meter for frequency below 1 GHz and 1.5 meter for frequency above 1 GHz respectively above ground.
4. The EUT is set 3 meters away from the receiving antenna, which is mounted on the top of a variable height antenna tower.
5. Corrected Reading: Antenna Factor + Cable Loss + Read Level - Preamp Factor = Level
6. Radiated testing below 1 GHz is performed by adjusting the antenna tower from 1 m to 4 m and by rotating the turn table from 0 degree to 360 degrees to find the peak maximum hold reading. When there is no suspected emission found and the emission level is with at least 6 dB margin against QP limit line, the position is marked as “-”.
7. Radiated testing above 1 GHz is performed by adjusting the antenna tower from 1 m to 4 m and by rotating the turn table from 0 degree to 360 degrees to find the peak maximum hold reading for scanning all frequencies. When there is no suspected emission found and the harmonic emission level is with at least 6 dB margin against average limit line, the position is marked as “-”.
8. Use the following spectrum analyzer settings:
 - (1) Span shall wide enough to fully capture the emission being measured;
 - (2) Set RBW = 100 kHz for $f < 1$ GHz; VBW \geq RBW; Sweep = auto; Detector function = peak; Trace = max hold;
 - (3) Set RBW = 1 MHz, VBW = 3 MHz for $f \geq 1$ GHz for peak measurement.

For average measurement:


 - VBW = 10 Hz, when duty cycle is no less than 98 percent.
 - VBW $\geq 1/T$, when duty cycle is less than 98 percent where T is the minimum transmission duration over which the transmitter is on and is transmitting at its maximum power control level for the tested mode of operation.

3.5.4 Test Setup


For radiated test below 30MHz




For radiated test from 30MHz to 1GHz



For radiated test from 1GHz to 18GHz



For radiated test above 18GHz



3.5.5 Test Results of Radiated Spurious Emissions (9 kHz ~ 30 MHz)

The low frequency, which starts from 9 kHz to 30 MHz, is pre-scanned and the result which is 20 dB lower than the limit line is not reported.

There is adequate comparison measurement of both open-field test site and alternative test site - semi-Anechoic chamber according to 414788 D01 Radiated Test Site v01r01, and the result comes out very similar.

3.5.6 Test Result of Radiated Spurious at Band Edges

Please refer to Appendix C.

3.5.7 Duty Cycle

Please refer to Appendix D.

3.5.8 Test Result of Radiated Spurious Emission (30 MHz ~ 10th Harmonic)

Please refer to Appendix C.



3.6 AC Conducted Emission Measurement

3.6.1 Limit of AC Conducted Emission

For equipment that is designed to be connected to the public utility (AC) power line, the radio frequency voltage that is conducted back onto the AC power line on any frequency or frequencies within the band 150 kHz to 30 MHz shall not exceed the limits in the following table.

Frequency of emission (MHz)	Conducted limit (dB μ V)	
	Quasi-peak	Average
0.15-0.5	66 to 56*	56 to 46*
0.5-5	56	46
5-30	60	50

*Decreases with the logarithm of the frequency.


3.6.2 Measuring Instruments

Please refer to the measuring equipment list in this test report.

3.6.3 Test Procedures

1. The EUT is placed 0.4 meter away from the conducting wall of the shielding room, and is kept at least 80 centimeters from any other grounded conducting surface.
2. Connect EUT to the power mains through a line impedance stabilization network (LISN).
3. All the support units are connecting to the other LISN.
4. The LISN provides 50 ohm coupling impedance for the measuring instrument.
5. The FCC states that a 50 ohm, 50 microhenry LISN shall be used.
6. Both Line and Neutral shall be tested in order to find out the maximum conducted emission.
7. The frequency range from 150 kHz to 30 MHz is scanned.
8. Set the test-receiver system to Peak Detect Function and specified bandwidth (IF Bandwidth = 9 kHz) with Maximum Hold Mode. Then measurement is also conducted by Average Detector and Quasi-Peak Detector Function respectively.

3.6.4 Test Setup



3.6.5 Test Result of AC Conducted Emission

Please refer to Appendix B.



3.7 Antenna Requirements

3.7.1 Standard Applicable

An intentional radiator shall be designed to ensure that no antenna other than that furnished by the responsible party shall be used with the device. The use of a permanently attached antenna or of an antenna that uses a unique coupling to the intentional radiator shall be considered sufficient to comply with the provisions of this section. The manufacturer may design the unit so that a broken antenna can be replaced by the user, but the use of a standard antenna jack or electrical connector is prohibited. This requirement does not apply to carrier current devices or to devices operated under the provisions of § 15.211, 15.213, 15.217, 15.219, 15.221, or § 15.236. Further, this requirement does not apply to intentional radiators that must be professionally installed, such as perimeter protection systems and some field disturbance sensors, or to other intentional radiators which, in accordance with § 15.31(d), must be measured at the installation site. However, the installer shall be responsible for ensuring that the proper antenna is employed so that the limits in this part are not exceeded.

3.7.2 Antenna Anti-Replacement Construction

Antenna permanently attached.



4 List of Measuring Equipment

Instrument	Brand Name	Model No.	Serial No.	Characteristics	Calibration Date	Test Date	Due Date	Remark
Hygrometer	TECPHEL	DTM-303A	TP201996	N/A	Nov. 01, 2024	Dec. 20, 2024~ Dec. 26, 2024	Oct. 31, 2025	Conducted (TH05-HY)
Power Sensor	DARE	RPR3006W	17I00015SNO 35 (NO:109)	10MHz~6GHz	Jan. 15, 2024	Dec. 20, 2024~ Dec. 26, 2024	Jan. 14, 2025	Conducted (TH05-HY)
Signal Analyzer	Rohde & Schwarz	FSV40	101566	10Hz~40GHz	Aug. 23, 2024	Dec. 20, 2024~ Dec. 26, 2024	Aug. 22, 2025	Conducted (TH05-HY)
Switch Control Mainframe	Burgeon	ETF-058	EC1300484 (BOX3)	N/A	May 20, 2024	Dec. 20, 2024~ Dec. 26, 2024	May 19, 2025	Conducted (TH05-HY)
Software	Sportun	BTWIFI_Final_V ersion_241211	N/A	Conducted Other Test Item	N/A	Dec. 20, 2024~ Dec. 26, 2024	N/A	Conducted (TH05-HY)
EMI Test Receiver	Keysight	N9038A(MXE)	MY54130085	N/A	Oct. 16, 2024	Jan. 17, 2025~ Jan. 25, 2025	Oct. 15, 2025	Radiation (03CH20-HY)
Loop Antenna	Rohde & Schwarz	HFH2-Z2	100488	9 kHz~30 MHz	Aug. 29, 2024	Jan. 17, 2025~ Jan. 25, 2025	Aug. 28, 2025	Radiation (03CH20-HY)
Preamplifier	EMEC	EM18G40G	060715	18GHz~40GHz	Dec. 02, 2024	Jan. 17, 2025~ Jan. 25, 2025	Dec. 01, 2025	Radiation (03CH20-HY)
Controller	ChainTek	3000-1	N/A	Control Turn table & Ant Mast	N/A	Jan. 17, 2025~ Jan. 25, 2025	N/A	Radiation (03CH20-HY)
Antenna Mast	ChainTek	MBS-520-1	N/A	1m~4m	N/A	Jan. 17, 2025~ Jan. 25, 2025	N/A	Radiation (03CH20-HY)
Turn Table	ChainTek	T-200-S-1	N/A	0~360 Degree	N/A	Jan. 17, 2025~ Jan. 25, 2025	N/A	Radiation (03CH20-HY)
Signal Analyzer	Keysight	N9010B	MY60240520	N/A	Dec. 09, 2024	Jan. 17, 2025~ Jan. 25, 2025	Dec. 08, 2025	Radiation (03CH20-HY)
Bilog Antenna	TESEQ	CBL 6111D&00802N 1D01N-06	55606 & 08	30MHz~1GHz	Nov. 27, 2024	Jan. 17, 2025~ Jan. 25, 2025	Nov. 26, 2025	Radiation (03CH20-HY)
Horn Antenna	SCHWARZBECK	BBHA 9120 D	02360	1GHz-18GHz	Nov. 01, 2024	Jan. 17, 2025~ Jan. 25, 2025	Oct. 31, 2025	Radiation (03CH20-HY)
SHF-EHF Horn Antenna	SCHWARZBECK	BBHA 9170	1224	18GHz-40GHz	Jun. 24, 2024	Jan. 17, 2025~ Jan. 25, 2025	Jun. 23, 2025	Radiation (03CH20-HY)
Preamplifier	COM-POWER	PAM-103	18020201	1MHz-1000MHz	Dec. 31, 2024	Jan. 17, 2025~ Jan. 25, 2025	Dec. 30, 2025	Radiation (03CH20-HY)
Amplifier	EMCI	EMC118A45SE	980792	N/A	Nov. 12, 2024	Jan. 17, 2025~ Jan. 25, 2025	Nov. 11, 2025	Radiation (03CH20-HY)
RF Cable	HUBER + SUHNER	SUCOFLEX 102	519229/2,8040 15/2,804027/2	N/A	Jan. 16, 2025	Jan. 17, 2025~ Jan. 25, 2025	Jan. 15, 2026	Radiation (03CH20-HY)
Hygrometer	TECPHEL	DTM-303A	TP211382	N/A	Mar. 27, 2024	Jan. 17, 2025~ Jan. 25, 2025	Mar. 26, 2025	Radiation (03CH20-HY)
Software	Audix	N/A	RK-002156	N/A	N/A	Jan. 17, 2025~ Jan. 25, 2025	N/A	Radiation (03CH20-HY)
AC Power Source	ACPOWER	AFC-11003G	F317040033	N/A	N/A	Jan. 09, 2025	N/A	Conduction (CO07-HY)
Software	Rohde & Schwarz	EMC32 V10.30	N/A	N/A	N/A	Jan. 09, 2025	N/A	Conduction (CO07-HY)
Pulse Limiter	SCHWARZBECK	VTSD 9561-F N	9561-F N00373	9kHz-200MHz	Oct. 23, 2024	Jan. 09, 2025	Oct. 22, 2025	Conduction (CO07-HY)
RF Cable	HUBER + SUHNER	RG 214/U	1358175	9kHz~30MHz	Mar. 14, 2024	Jan. 09, 2025	Mar. 13, 2025	Conduction (CO07-HY)
Two-Line V-Network	TESEQ	NNB 51	45051	N/A	Mar. 10, 2024	Jan. 09, 2025	Mar. 09, 2025	Conduction (CO07-HY)
EMI Test Receiver	Rohde & Schwarz	ESR3	102317	9kHz~3.6GHz	Sep. 23, 2024	Jan. 09, 2025	Sep. 22, 2025	Conduction (CO07-HY)



5 Measurement Uncertainty

Uncertainty of Conducted Emission Measurement (150 kHz ~ 30 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{C(y)}$)	3.7 dB
---	--------

Uncertainty of Radiated Emission Measurement (30 MHz ~ 1000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{C(y)}$)	6.7 dB
---	--------

Uncertainty of Radiated Emission Measurement (1000 MHz ~ 6000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{C(y)}$)	5.4 dB
---	--------

Uncertainty of Radiated Emission Measurement (6000 MHz ~ 18000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{C(y)}$)	5.6 dB
---	--------

Uncertainty of Radiated Emission Measurement (18000 MHz ~ 40000 MHz)

Measuring Uncertainty for a Level of Confidence of 95% ($U = 2U_{C(y)}$)	5.7 dB
---	--------

Appendix A. Test Result of Conducted Test Items

Test Engineer:	Mina Liu			Temperature:	21~25		°C
Test Date:	2024/12/20~2024/12/26			Relative Humidity:	51~54		%

<u>TEST RESULTS DATA</u> <u>6dB and 99% Occupied Bandwidth</u>									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	99% Occupied BW (MHz)	6dB BW (MHz)	6dB BW Limit (MHz)	Pass/Fail	
BLE GFSK	1Mbps	1	02	2404	1.023	0.677	0.50	Pass	
BLE GFSK	1Mbps	1	38	2440	1.028	0.691	0.50	Pass	
BLE GFSK	1Mbps	1	76	2478	1.024	0.673	0.50	Pass	




<u>TEST RESULTS DATA</u> <u>Average Power Table</u>									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	Average Conducted Power (dBm)	Conducted Power Limit (dBm)	DG (dBi)	EIRP Power (dBm)	EIRP Power Limit (dBm)
BLE GFSK	1Mbps	1	02	2404	6.22	30.00	0.20	6.42	36.00
BLE GFSK	1Mbps	1	38	2440	6.13	30.00	0.20	6.33	36.00
BLE GFSK	1Mbps	1	76	2478	6.24	30.00	0.20	6.44	36.00

<u>TEST RESULTS DATA</u> <u>Peak Power Density</u>									
Mod.	Data Rate	NTX	CH.	Freq. (MHz)	Peak PSD (dBm /100kHz)	Peak PSD (dBm /3kHz)	DG (dBi)	Peak PSD Limit (dBm /3kHz)	Pass/Fail
BLE GFSK	1Mbps	1	02	2404	5.92	-2.88	0.20	8.00	Pass
BLE GFSK	1Mbps	1	38	2440	5.68	-4.55	0.20	8.00	Pass
BLE GFSK	1Mbps	1	76	2478	5.95	-3.50	0.20	8.00	Pass

Note: PSD (dBm/ 100kHz) is a reference level used for Conducted Band Edges and Conducted Spurious Emission 30dBc limit.




**6dB Bandwidth**

<GFSK>

6 dB Bandwidth Plot on Channel 02**6 dB Bandwidth Plot on Channel 38****6 dB Bandwidth Plot on Channel 76**


**99% Occupied Bandwidth**

<GFSK>

99% Occupied Bandwidth Plot on Channel 02**99% Occupied Bandwidth Plot on Channel 38****99% Occupied Bandwidth Plot on Channel 76**


**Power Spectral Density (dBm/3kHz)**


<GFSK>




**Band Edge and Conducted Spurious Emission**

<GFSK>










Appendix B. AC Conducted Emission Test Results

Test Engineer :	Louis Chung	Temperature :	18.2~20.3°C
		Relative Humidity :	40.2~47.6%

EUT Information

Test Mode : Mode 1
 Test Voltage : 120Vac/60Hz
 Phase : Line

Full Spectrum



Final Result


Frequency (MHz)	QuasiPeak (dBuV)	CAverage (dBuV)	Limit (dBuV)	Margin (dB)	Line	PE	Corr. (dB)
0.156278	39.39	---	65.66	26.27	L1	FLO	19.9
0.156278	---	22.42	55.66	33.24	L1	FLO	19.9
0.165750	37.28	---	65.17	27.89	L1	FLO	19.9
0.165750	---	19.58	55.17	35.59	L1	FLO	19.9
0.177810	37.44	---	64.59	27.15	L1	FLO	19.9
0.177810	---	19.22	54.59	35.37	L1	FLO	19.9
0.204000	31.13	---	63.45	32.32	L1	FLO	19.9
0.204000	---	16.66	53.45	36.79	L1	FLO	19.9
0.269070	27.46	---	61.15	33.69	L1	FLO	19.9
0.269070	---	21.66	51.15	29.49	L1	FLO	19.9
0.299040	27.54	---	60.27	32.73	L1	FLO	19.9
0.299040	---	14.81	50.27	35.46	L1	FLO	19.9
0.408030	28.52	---	57.69	29.17	L1	FLO	19.9
0.408030	---	19.91	47.69	27.78	L1	FLO	19.9
0.678930	29.33	---	56.00	26.67	L1	FLO	19.9
0.678930	---	18.08	46.00	27.92	L1	FLO	19.9
1.169610	28.31	---	56.00	27.69	L1	FLO	19.9
1.169610	---	17.17	46.00	28.83	L1	FLO	19.9
1.221180	29.24	---	56.00	26.76	L1	FLO	19.9

1.221180	---	19.17	46.00	26.83	L1	FLO	19.9
1.302000	28.90	---	56.00	27.10	L1	FLO	19.9
1.302000	---	17.64	46.00	28.36	L1	FLO	19.9
21.859080	21.51	---	60.00	38.49	L1	FLO	20.2
21.859080	---	18.10	50.00	31.90	L1	FLO	20.2

EUT Information

Test Mode : Mode 1
 Test Voltage : 120Vac/60Hz
 Phase : Neutral

Full Spectrum



Final Result

Frequency (MHz)	QuasiPeak (dBuV)	CAverage (dBuV)	Limit (dBuV)	Margin (dB)	Line	PE	Corr. (dB)
0.153578	---	23.73	55.80	32.07	N	FLO	20.0
0.153578	39.26	---	65.80	26.54	N	FLO	20.0
0.165750	---	19.75	55.17	35.42	N	FLO	19.9
0.165750	36.93	---	65.17	28.24	N	FLO	19.9
0.185460	---	18.42	54.24	35.82	N	FLO	19.9
0.185460	34.17	---	64.24	30.07	N	FLO	19.9
0.201750	---	16.68	53.54	36.86	N	FLO	19.9
0.201750	28.69	---	63.54	34.85	N	FLO	19.9
0.294000	---	14.59	50.41	35.82	N	FLO	19.9
0.294000	26.85	---	60.41	33.56	N	FLO	19.9
0.391200	---	18.95	48.04	29.09	N	FLO	19.9
0.391200	30.79	---	58.04	27.25	N	FLO	19.9
0.404250	---	21.00	47.77	26.77	N	FLO	19.9
0.404250	25.17	---	57.77	32.60	N	FLO	19.9
0.674250	---	18.72	46.00	27.28	N	FLO	19.9
0.674250	28.97	---	56.00	27.03	N	FLO	19.9
1.173120	---	16.07	46.00	29.93	N	FLO	20.0
1.173120	28.98	---	56.00	27.02	N	FLO	20.0
1.218750	---	18.29	46.00	27.71	N	FLO	20.0

1.218750	28.63	---	56.00	27.37	N	FLO	20.0
1.293090	---	17.51	46.00	28.49	N	FLO	20.0
1.293090	28.51	---	56.00	27.49	N	FLO	20.0
2.931180	---	16.93	46.00	29.07	N	FLO	20.0
2.931180	19.42	---	56.00	36.58	N	FLO	20.0
21.425100	---	18.71	50.00	31.29	N	FLO	20.2
21.425100	22.29	---	60.00	37.71	N	FLO	20.2



Appendix C. Radiated Spurious Emission Test Data

Test Engineer :	John Chuang, David Dai and Sam Chou	Temperature :	19.1~22.2°C
		Relative Humidity :	65.4~70.5%

Note symbol

-L	Low channel location
-R	High channel location





C1. Radiated Spurious Emission Test Modes

Mode	Band (MHz)	Antenna	Modulation	Channel	Frequency	Data Rate	RU	Remark
Mode 9	2400-2483.5	1	Bluetooth BR_GFSK	02	2404	1Mbps	-	-
Mode 10	2400-2483.5	1	Bluetooth BR_GFSK	38	2440	1Mbps	-	-
Mode 11	2400-2483.5	1	Bluetooth BR_GFSK	76	2478	1Mbps	-	-
Mode 12	2400-2483.5	1	Bluetooth BR_GFSK	02	2404	1Mbps	-	LF
Mode 13	2400-2483.5	1	Bluetooth BR_GFSK	02	2404	1Mbps	-	SHF





C2. Summary of each worse mode

Mode	Modulation	Ch.	Freq. (MHz)	Level (dBuV/m)	Limit (dBuV/m)	Margin (dB)	Pol.	Peak Avg.	Result	RU	Remark
9	Bluetooth BR_GFSK	02	2355.97	38.37	54.00	-15.63	H	Avg.	Pass	-	Band Edge
	Bluetooth BR_GFSK	02	4808.00	48.74	54.00	-5.26	H	Avg.	Pass	-	Harmonic
10	Bluetooth BR_GFSK	38	2488.00	39.29	54.00	-14.71	H	Avg.	Pass	-	Band Edge
	Bluetooth BR_GFSK	38	4880.00	48.51	54.00	-5.49	H	Avg.	Pass	-	Harmonic
11	Bluetooth BR_GFSK	76	2483.52	39.13	54.00	-14.87	H	Avg.	Pass	-	Band Edge
	Bluetooth BR_GFSK	76	4956.00	47.34	54.00	-6.66	H	Avg.	Pass	-	Harmonic
12	LF	02	50.37	32.95	40.00	-7.05	V	Peak	Pass	-	LF
13	SHF	02	24580.00	43.41	74.00	-30.59	V	Peak	Pass	-	SHF






Mode	9																																																																									
	Band Edge																																																																									
	2400-2483.5_Bluetooth BR_GFSK_CH02_2404MHz																																																																									
ANT	1																																																																									
Pol.	Horizontal	Fundamental																																																																								
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2316.86</td><td>50.07</td><td>74.00</td><td>-23.93</td><td>40.85</td><td>27.30</td><td>8.49</td><td>36.25 9.68 200 198 PEAK</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg	1	2316.86	50.07	74.00	-23.93	40.85	27.30	8.49	36.25 9.68 200 198 PEAK	 <p>Site : 03CH20-HY Condition: PEAK_74_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2404.00</td><td>101.10</td><td>-----</td><td>-----</td><td>91.60</td><td>27.44</td><td>8.65</td><td>36.27 9.68 200 198 PEAK</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg	1	2404.00	101.10	-----	-----	91.60	27.44	8.65	36.27 9.68 200 198 PEAK
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																			
MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg																																																																		
1	2316.86	50.07	74.00	-23.93	40.85	27.30	8.49	36.25 9.68 200 198 PEAK																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																			
MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg																																																																		
1	2404.00	101.10	-----	-----	91.60	27.44	8.65	36.27 9.68 200 198 PEAK																																																																		
 <p>Site : 03CH20-HY Condition: AVG_BE_54_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2355.97</td><td>38.37</td><td>54.00</td><td>-15.63</td><td>29.09</td><td>27.30</td><td>8.56</td><td>36.26 9.68 200 198 AVERAGE</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg	1	2355.97	38.37	54.00	-15.63	29.09	27.30	8.56	36.26 9.68 200 198 AVERAGE	 <p>Site : 03CH20-HY Condition: AVG_54_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line</th><th>Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th></th></tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2404.00</td><td>100.67</td><td>-----</td><td>-----</td><td>91.17</td><td>27.44</td><td>8.65</td><td>36.27 9.68 200 198 AVERAGE</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line	Margin	Level	Factor	Loss	Factor		MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg	1	2404.00	100.67	-----	-----	91.17	27.44	8.65	36.27 9.68 200 198 AVERAGE	
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																			
MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg																																																																		
1	2355.97	38.37	54.00	-15.63	29.09	27.30	8.56	36.26 9.68 200 198 AVERAGE																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line	Margin	Level	Factor	Loss	Factor																																																																			
MHz	dBm	dBm	dB	dB	/m	dB	dB	cm deg																																																																		
1	2404.00	100.67	-----	-----	91.17	27.44	8.65	36.27 9.68 200 198 AVERAGE																																																																		







Mode	9																																																																									
	Band Edge																																																																									
	2400-2483.5_Bluetooth BR_GFSK_CH02_2404MHz																																																																									
ANT	1																																																																									
Pol.	Vertical	Fundamental																																																																								
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2377.49</td><td>50.11</td><td>74.00</td><td>-23.89</td><td>40.86</td><td>27.23</td><td>8.60</td><td>36.26 9.68 101 178 PEAK</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBm	dBm	dB	dB	dB	cm	deg		1	2377.49	50.11	74.00	-23.89	40.86	27.23	8.60	36.26 9.68 101 178 PEAK	 <p>Site : 03CH20-HY Condition: PEAK_74_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2404.00</td><td>98.76</td><td>-----</td><td>-----</td><td>89.26</td><td>27.44</td><td>8.65</td><td>36.27 9.68 101 178 PEAK</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBm	dBm	dB	dB	dB	cm	deg		1	2404.00	98.76	-----	-----	89.26	27.44	8.65	36.27 9.68 101 178 PEAK
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBm	dBm	dB	dB	dB	cm	deg																																																																			
1	2377.49	50.11	74.00	-23.89	40.86	27.23	8.60	36.26 9.68 101 178 PEAK																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBm	dBm	dB	dB	dB	cm	deg																																																																			
1	2404.00	98.76	-----	-----	89.26	27.44	8.65	36.27 9.68 101 178 PEAK																																																																		
 <p>Site : 03CH20-HY Condition: AVG_BE_54_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2356.06</td><td>38.14</td><td>54.00</td><td>-15.86</td><td>28.86</td><td>27.30</td><td>8.56</td><td>36.26 9.68 101 178 AVERAGE</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBm	dBm	dB	dB	dB	cm	deg		1	2356.06	38.14	54.00	-15.86	28.86	27.30	8.56	36.26 9.68 101 178 AVERAGE	 <p>Site : 03CH20-HY Condition: AVG_54_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBm</th><th>dBm</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2404.00</td><td>98.28</td><td>-----</td><td>-----</td><td>88.78</td><td>27.44</td><td>8.65</td><td>36.27 9.68 101 178 AVERAGE</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBm	dBm	dB	dB	dB	cm	deg		1	2404.00	98.28	-----	-----	88.78	27.44	8.65	36.27 9.68 101 178 AVERAGE	
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBm	dBm	dB	dB	dB	cm	deg																																																																			
1	2356.06	38.14	54.00	-15.86	28.86	27.30	8.56	36.26 9.68 101 178 AVERAGE																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBm	dBm	dB	dB	dB	cm	deg																																																																			
1	2404.00	98.28	-----	-----	88.78	27.44	8.65	36.27 9.68 101 178 AVERAGE																																																																		





Mode	9																																																																																										
	Harmonic																																																																																										
	2400-2483.5_Bluetooth BR_GFSK_CH02_2404MHz																																																																																										
ANT	1																																																																																										
Pol.	Horizontal																																																																																										
Peak																																																																																											
	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 HORIZONTAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4808.00</td><td>52.53</td><td>74.00</td><td>-21.47</td><td>44.72</td><td>32.26</td><td>12.25</td><td>37.52</td><td>0.82</td><td>115</td><td>176 PEAK</td></tr><tr><td>2</td><td>4808.00</td><td>48.74</td><td>54.00</td><td>-5.26</td><td>40.93</td><td>32.26</td><td>12.25</td><td>37.52</td><td>0.82</td><td>115</td><td>176 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4808.00	52.53	74.00	-21.47	44.72	32.26	12.25	37.52	0.82	115	176 PEAK	2	4808.00	48.74	54.00	-5.26	40.93	32.26	12.25	37.52	0.82	115	176 Average	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 VERTICAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th></tr></thead><tbody><tr><td>1</td><td>4808.00</td><td>50.86</td><td>74.00</td><td>-23.14</td><td>43.05</td><td>32.26</td><td>12.25</td><td>37.52</td><td>0.82</td><td>100</td><td>242 PEAK</td></tr><tr><td>2</td><td>4808.00</td><td>46.63</td><td>54.00</td><td>-7.37</td><td>38.82</td><td>32.26</td><td>12.25</td><td>37.52</td><td>0.82</td><td>100</td><td>242 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	4808.00	50.86	74.00	-23.14	43.05	32.26	12.25	37.52	0.82	100	242 PEAK	2	4808.00	46.63	54.00	-7.37	38.82	32.26	12.25	37.52	0.82	100
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	4808.00	52.53	74.00	-21.47	44.72	32.26	12.25	37.52	0.82	115	176 PEAK																																																																																
2	4808.00	48.74	54.00	-5.26	40.93	32.26	12.25	37.52	0.82	115	176 Average																																																																																
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																		
	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																																																	
1	4808.00	50.86	74.00	-23.14	43.05	32.26	12.25	37.52	0.82	100	242 PEAK																																																																																
2	4808.00	46.63	54.00	-7.37	38.82	32.26	12.25	37.52	0.82	100	242 Average																																																																																









Mode	10																																																																															
	Band Edge - L																																																																															
	2400-2483.5_Bluetooth BR_GFSK_CH38_2440MHz																																																																															
ANT	1																																																																															
Pol.	Horizontal	Fundamental																																																																														
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2384.88</td><td>50.05</td><td>74.00</td><td>-23.95</td><td>40.73</td><td>27.30</td><td>8.61</td><td>36.27</td><td>9.68</td><td>200</td><td>200 PEAK</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg		1	2384.88	50.05	74.00	-23.95	40.73	27.30	8.61	36.27	9.68	200	200 PEAK	 <p>Site : 03CH20-HY Condition: PEAK_74_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2440.00</td><td>102.72</td><td>-----</td><td>-----</td><td>93.01</td><td>27.60</td><td>8.71</td><td>36.28</td><td>9.68</td><td>200</td><td>200 PEAK</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg		1	2440.00	102.72	-----	-----	93.01	27.60	8.71	36.28	9.68	200	200 PEAK
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg																																																																									
1	2384.88	50.05	74.00	-23.95	40.73	27.30	8.61	36.27	9.68	200	200 PEAK																																																																					
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg																																																																									
1	2440.00	102.72	-----	-----	93.01	27.60	8.71	36.28	9.68	200	200 PEAK																																																																					
 <p>Site : 03CH20-HY Condition: AVG_BE_54_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2389.04</td><td>38.06</td><td>54.00</td><td>-15.94</td><td>28.65</td><td>27.38</td><td>8.62</td><td>36.27</td><td>9.68</td><td>200</td><td>AVERAGE</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg		1	2389.04	38.06	54.00	-15.94	28.65	27.38	8.62	36.27	9.68	200	AVERAGE	 <p>Site : 03CH20-HY Condition: AVG_54_3m_HF_91200_02360_241101_HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th><th></th> </tr> </thead> <tbody> <tr> <td>1</td><td>2440.00</td><td>102.21</td><td>-----</td><td>-----</td><td>92.50</td><td>27.60</td><td>8.71</td><td>36.28</td><td>9.68</td><td>200</td><td>AVERAGE</td> </tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg		1	2440.00	102.21	-----	-----	92.50	27.60	8.71	36.28	9.68	200	AVERAGE	
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg																																																																									
1	2389.04	38.06	54.00	-15.94	28.65	27.38	8.62	36.27	9.68	200	AVERAGE																																																																					
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																											
MHz	dBuV/m	dBuV/m	dB	dB	dB	cm	deg																																																																									
1	2440.00	102.21	-----	-----	92.50	27.60	8.71	36.28	9.68	200	AVERAGE																																																																					





Mode	10																																									
	Band Edge - R																																									
	2400-2483.5_Bluetooth BR_GFSK_CH38_2440MHz																																									
ANT	1																																									
Pol.	Horizontal	Fundamental																																								
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm deg</th></tr></thead><tbody><tr><td>1</td><td>2484.52</td><td>50.01</td><td>74.00</td><td>-23.99</td><td>39.88</td><td>27.95</td><td>8.80</td><td>36.30</td><td>9.68 200 PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm deg	1	2484.52	50.01	74.00	-23.99	39.88	27.95	8.80	36.30	9.68 200 PEAK	Blank
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																	
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm deg																																	
1	2484.52	50.01	74.00	-23.99	39.88	27.95	8.80	36.30	9.68 200 PEAK																																	
Avg	 <p>Site : 03CH20-HY Condition: AVG_BE_54 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr><tr><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>dB</th><th>cm deg</th></tr></thead><tbody><tr><td>1</td><td>2488.00</td><td>39.29</td><td>54.00</td><td>-14.71</td><td>29.13</td><td>27.98</td><td>8.80</td><td>36.30</td><td>9.68 200 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor			MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm deg	1	2488.00	39.29	54.00	-14.71	29.13	27.98	8.80	36.30	9.68 200 AVERAGE	Blank
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																	
Freq	Level	Line Margin	Level	Factor	Loss	Factor	Factor																																			
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	dB	cm deg																																	
1	2488.00	39.29	54.00	-14.71	29.13	27.98	8.80	36.30	9.68 200 AVERAGE																																	




Mode	10																																																													
	Band Edge - L																																																													
	2400-2483.5_Bluetooth BR_GFSK_CH38_2440MHz																																																													
ANT	1																																																													
Pol.	Vertical	Fundamental																																																												
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2350.02</td><td>50.33</td><td>74.00</td><td>-23.67</td><td>41.09</td><td>27.30</td><td>8.51</td><td>36.25</td><td>9.68 100 175 PEAK</td> </tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2350.02	50.33	74.00	-23.67	41.09	27.30	8.51	36.25	9.68 100 175 PEAK	 <p>Site : 03CH20-HY Condition: PEAK_74_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2440.00</td><td>99.59</td><td>-----</td><td>-----</td><td>89.88</td><td>27.60</td><td>8.71</td><td>36.28</td><td>9.68 100 175 PEAK</td> </tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2440.00	99.59	-----	-----	89.88	27.60	8.71	36.28	9.68 100 175 PEAK
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																					
1	2350.02	50.33	74.00	-23.67	41.09	27.30	8.51	36.25	9.68 100 175 PEAK																																																					
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																					
1	2440.00	99.59	-----	-----	89.88	27.60	8.71	36.28	9.68 100 175 PEAK																																																					
 <p>Site : 03CH20-HY Condition: AVG_BE_54_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2389.82</td><td>38.12</td><td>54.00</td><td>-15.88</td><td>28.69</td><td>27.40</td><td>8.62</td><td>36.27</td><td>9.68 100 175 AVERAGE</td> </tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2389.82	38.12	54.00	-15.88	28.69	27.40	8.62	36.27	9.68 100 175 AVERAGE	 <p>Site : 03CH20-HY Condition: AVG_54_3m_HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2440.00</td><td>99.16</td><td>-----</td><td>-----</td><td>89.45</td><td>27.60</td><td>8.71</td><td>36.28</td><td>9.68 100 175 AVERAGE</td> </tr> </tbody> </table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2440.00	99.16	-----	-----	89.45	27.60	8.71	36.28	9.68 100 175 AVERAGE	
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																					
1	2389.82	38.12	54.00	-15.88	28.69	27.40	8.62	36.27	9.68 100 175 AVERAGE																																																					
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																					
1	2440.00	99.16	-----	-----	89.45	27.60	8.71	36.28	9.68 100 175 AVERAGE																																																					







Mode	10																															
	Band Edge - R																															
	2400-2483.5_Bluetooth BR_GFSK_CH38_2440MHz																															
ANT	1																															
Pol.	Vertical	Fundamental																														
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr></thead><tbody><tr><td>1</td><td>2498.86</td><td>50.20</td><td>74.00</td><td>-23.88</td><td>40.00</td><td>28.00</td><td>8.82</td><td>36.30</td><td>9.68 100 175 PEAK</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2498.86	50.20	74.00	-23.88	40.00	28.00	8.82	36.30	9.68 100 175 PEAK	Blank
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																							
Freq	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																							
1	2498.86	50.20	74.00	-23.88	40.00	28.00	8.82	36.30	9.68 100 175 PEAK																							
Avg	 <p>Site : 03CH20-HY Condition: AVG_BE_54 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr></thead><tbody><tr><td>1</td><td>2487.94</td><td>38.99</td><td>54.00</td><td>-15.01</td><td>28.83</td><td>27.98</td><td>8.80</td><td>36.30</td><td>9.68 100 175 AVERAGE</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2487.94	38.99	54.00	-15.01	28.83	27.98	8.80	36.30	9.68 100 175 AVERAGE	Blank
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																							
Freq	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																							
1	2487.94	38.99	54.00	-15.01	28.83	27.98	8.80	36.30	9.68 100 175 AVERAGE																							



Mode	10																																																																																																																								
	Harmonic																																																																																																																								
	2400-2483.5_Bluetooth BR_GFSK_CH38_2440MHz																																																																																																																								
ANT	1																																																																																																																								
Pol.	Horizontal																																																																																																																								
Peak																																																																																																																									
	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 HORIZONTAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>4880.00</td><td>52.71</td><td>74.00</td><td>-21.29</td><td>44.50</td><td>32.72</td><td>12.39</td><td>37.57</td><td>0.67 106 174 PEAK</td></tr><tr><td>2</td><td>4880.00</td><td>48.51</td><td>54.00</td><td>-5.49</td><td>40.30</td><td>32.72</td><td>12.39</td><td>37.57</td><td>0.67 106 174 Average</td></tr><tr><td>3</td><td>7320.00</td><td>53.88</td><td>74.00</td><td>-20.12</td><td>39.85</td><td>36.78</td><td>15.38</td><td>38.48</td><td>0.35 100 297 Peak</td></tr><tr><td>4</td><td>7320.00</td><td>45.01</td><td>54.00</td><td>-8.99</td><td>30.98</td><td>36.78</td><td>15.38</td><td>38.48</td><td>0.35 100 297 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4880.00	52.71	74.00	-21.29	44.50	32.72	12.39	37.57	0.67 106 174 PEAK	2	4880.00	48.51	54.00	-5.49	40.30	32.72	12.39	37.57	0.67 106 174 Average	3	7320.00	53.88	74.00	-20.12	39.85	36.78	15.38	38.48	0.35 100 297 Peak	4	7320.00	45.01	54.00	-8.99	30.98	36.78	15.38	38.48	0.35 100 297 Average	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 VERTICAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>4880.00</td><td>50.89</td><td>74.00</td><td>-23.11</td><td>42.68</td><td>32.72</td><td>12.39</td><td>37.57</td><td>0.67 100 241 PEAK</td></tr><tr><td>2</td><td>4880.00</td><td>46.54</td><td>54.00</td><td>-7.46</td><td>38.33</td><td>32.72</td><td>12.39</td><td>37.57</td><td>0.67 100 241 Average</td></tr><tr><td>3</td><td>7320.00</td><td>50.47</td><td>74.00</td><td>-23.53</td><td>36.44</td><td>36.78</td><td>15.38</td><td>38.48</td><td>0.35 200 198 PEAK</td></tr><tr><td>4</td><td>7320.00</td><td>42.50</td><td>54.00</td><td>-11.50</td><td>28.47</td><td>36.78</td><td>15.38</td><td>38.48</td><td>0.35 200 198 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4880.00	50.89	74.00	-23.11	42.68	32.72	12.39	37.57	0.67 100 241 PEAK	2	4880.00	46.54	54.00	-7.46	38.33	32.72	12.39	37.57	0.67 100 241 Average	3	7320.00	50.47	74.00	-23.53	36.44	36.78	15.38	38.48	0.35 200 198 PEAK	4	7320.00	42.50	54.00	-11.50	28.47	36.78	15.38	38.48
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																				
1	4880.00	52.71	74.00	-21.29	44.50	32.72	12.39	37.57	0.67 106 174 PEAK																																																																																																																
2	4880.00	48.51	54.00	-5.49	40.30	32.72	12.39	37.57	0.67 106 174 Average																																																																																																																
3	7320.00	53.88	74.00	-20.12	39.85	36.78	15.38	38.48	0.35 100 297 Peak																																																																																																																
4	7320.00	45.01	54.00	-8.99	30.98	36.78	15.38	38.48	0.35 100 297 Average																																																																																																																
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																				
1	4880.00	50.89	74.00	-23.11	42.68	32.72	12.39	37.57	0.67 100 241 PEAK																																																																																																																
2	4880.00	46.54	54.00	-7.46	38.33	32.72	12.39	37.57	0.67 100 241 Average																																																																																																																
3	7320.00	50.47	74.00	-23.53	36.44	36.78	15.38	38.48	0.35 200 198 PEAK																																																																																																																
4	7320.00	42.50	54.00	-11.50	28.47	36.78	15.38	38.48	0.35 200 198 Average																																																																																																																






Mode	11																																																																							
	Band Edge																																																																							
	2400-2483.5_Bluetooth BR_GFSK_CH76_2478MHz																																																																							
ANT	1																																																																							
Pol.	Horizontal						Fundamental																																																																	
Peak	 <p>Site : 03CH20-HY Condition: PEAK_BE_74 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2483.81</td><td>51.06</td><td>74.00</td><td>-22.94</td><td>40.94</td><td>27.94</td><td>8.80</td><td>36.30</td><td>9.68 112 86 PEAK</td> </tr> </tbody> </table>						Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.81	51.06	74.00	-22.94	40.94	27.94	8.80	36.30	9.68 112 86 PEAK	 <p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2478.00</td><td>103.22</td><td>-----</td><td>-----</td><td>93.17</td><td>27.88</td><td>8.78</td><td>36.29</td><td>9.68 112 86 PEAK</td> </tr> </tbody> </table>						Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2478.00	103.22	-----	-----	93.17	27.88	8.78	36.29	9.68 112 86 PEAK
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																															
1	2483.81	51.06	74.00	-22.94	40.94	27.94	8.80	36.30	9.68 112 86 PEAK																																																															
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																															
1	2478.00	103.22	-----	-----	93.17	27.88	8.78	36.29	9.68 112 86 PEAK																																																															
 <p>Site : 03CH20-HY Condition: AVG_BE_54 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2483.52</td><td>39.13</td><td>54.00</td><td>-14.87</td><td>29.02</td><td>27.94</td><td>8.79</td><td>36.30</td><td>9.68 112 86 AVERAGE</td> </tr> </tbody> </table>						Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2483.52	39.13	54.00	-14.87	29.02	27.94	8.79	36.30	9.68 112 86 AVERAGE	 <p>Site : 03CH20-HY Condition: AVG_54 3m HF_91200_02360_241101 HORIZONTAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th> </tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm</th><th>deg</th> </tr> </thead> <tbody> <tr> <td>1</td><td>2478.00</td><td>102.80</td><td>-----</td><td>-----</td><td>92.75</td><td>27.88</td><td>8.78</td><td>36.29</td><td>9.68 112 86 AVERAGE</td> </tr> </tbody> </table>						Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg	1	2478.00	102.80	-----	-----	92.75	27.88	8.78	36.29	9.68 112 86 AVERAGE	
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																															
1	2483.52	39.13	54.00	-14.87	29.02	27.94	8.79	36.30	9.68 112 86 AVERAGE																																																															
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																															
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm	deg																																																															
1	2478.00	102.80	-----	-----	92.75	27.88	8.78	36.29	9.68 112 86 AVERAGE																																																															





Mode	11																																																																									
	Band Edge																																																																									
	2400-2483.5_Bluetooth BR_GFSK_CH76_2478MHz																																																																									
ANT	1																																																																									
Pol.	Vertical	Fundamental																																																																								
Peak	<p>Site : 03CH20-HY Condition: PEAK_BE_74 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th></tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2490.52</td><td>50.77</td><td>74.00</td><td>-23.23</td><td>40.58</td><td>28.00</td><td>8.81</td><td>36.30 9.68 100 181 PEAK</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2490.52	50.77	74.00	-23.23	40.58	28.00	8.81	36.30 9.68 100 181 PEAK	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:3000.000kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th></tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2478.00</td><td>99.40</td><td>-----</td><td>-----</td><td>89.35</td><td>27.88</td><td>8.78</td><td>36.29 9.68 100 181 PEAK</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2478.00	99.40	-----	-----	89.35	27.88	8.78	36.29 9.68 100 181 PEAK
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																																																																		
1	2490.52	50.77	74.00	-23.23	40.58	28.00	8.81	36.30 9.68 100 181 PEAK																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																																																																		
1	2478.00	99.40	-----	-----	89.35	27.88	8.78	36.29 9.68 100 181 PEAK																																																																		
<p>Site : 03CH20-HY Condition: AVG_BE_54 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th></tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2483.61</td><td>38.90</td><td>54.00</td><td>-15.10</td><td>28.79</td><td>27.94</td><td>8.79</td><td>36.30 9.68 100 181 AVERAGE</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2483.61	38.90	54.00	-15.10	28.79	27.94	8.79	36.30 9.68 100 181 AVERAGE	<p>Site : 03CH20-HY Condition: AVG_54 3m HF_91200_02360_241101 VERTICAL : RBW:1000.000kHz VBW:0.010kHz SWT:Auto</p> <table border="1"> <thead> <tr> <th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr> <tr> <th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th></tr> <tr> <th>MHz</th><th>dBuV/m</th><th>dBuV/m</th><th>dB</th><th>dBuV</th><th>dB/m</th><th>dB</th><th>dB</th><th>cm deg</th></tr> </thead> <tbody> <tr> <td>1</td><td>2478.00</td><td>99.04</td><td>-----</td><td>-----</td><td>88.99</td><td>27.88</td><td>8.78</td><td>36.29 9.68 100 181 AVERAGE</td></tr> </tbody> </table>	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor				MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg	1	2478.00	99.04	-----	-----	88.99	27.88	8.78	36.29 9.68 100 181 AVERAGE	
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																																																																		
1	2483.61	38.90	54.00	-15.10	28.79	27.94	8.79	36.30 9.68 100 181 AVERAGE																																																																		
Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																		
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																					
MHz	dBuV/m	dBuV/m	dB	dBuV	dB/m	dB	dB	cm deg																																																																		
1	2478.00	99.04	-----	-----	88.99	27.88	8.78	36.29 9.68 100 181 AVERAGE																																																																		





Mode	11																																																																																																																								
	Harmonic																																																																																																																								
	2400-2483.5_Bluetooth BR_GFSK_CH76_2478MHz																																																																																																																								
ANT	1																																																																																																																								
Pol.	Horizontal																																																																																																																								
Peak																																																																																																																									
	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 HORIZONTAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>4956.00</td><td>51.57</td><td>74.00</td><td>+22.43</td><td>43.02</td><td>33.14</td><td>12.53</td><td>37.63</td><td>0.51 100 160 PEAK</td></tr><tr><td>2</td><td>4956.00</td><td>47.34</td><td>54.00</td><td>-6.66</td><td>38.79</td><td>33.14</td><td>12.53</td><td>37.63</td><td>0.51 100 160 Average</td></tr><tr><td>3</td><td>7434.00</td><td>52.87</td><td>74.00</td><td>-21.13</td><td>39.37</td><td>36.23</td><td>15.51</td><td>38.57</td><td>0.33 100 299 PEAK</td></tr><tr><td>4</td><td>7434.00</td><td>46.52</td><td>54.00</td><td>-7.48</td><td>33.02</td><td>36.23</td><td>15.51</td><td>38.57</td><td>0.33 100 299 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4956.00	51.57	74.00	+22.43	43.02	33.14	12.53	37.63	0.51 100 160 PEAK	2	4956.00	47.34	54.00	-6.66	38.79	33.14	12.53	37.63	0.51 100 160 Average	3	7434.00	52.87	74.00	-21.13	39.37	36.23	15.51	38.57	0.33 100 299 PEAK	4	7434.00	46.52	54.00	-7.48	33.02	36.23	15.51	38.57	0.33 100 299 Average	<p>Site : 03CH20-HY Condition: PEAK_74 3m HF_91200_02360_241101 VERTICAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>4956.00</td><td>49.71</td><td>74.00</td><td>+24.29</td><td>41.16</td><td>33.14</td><td>12.53</td><td>37.63</td><td>0.51 100 242 PEAK</td></tr><tr><td>2</td><td>4956.00</td><td>44.76</td><td>54.00</td><td>-9.24</td><td>36.21</td><td>33.14</td><td>12.53</td><td>37.63</td><td>0.51 100 242 Average</td></tr><tr><td>3</td><td>7434.00</td><td>50.40</td><td>74.00</td><td>-23.60</td><td>36.90</td><td>36.23</td><td>15.51</td><td>38.57</td><td>0.33 100 65 PEAK</td></tr><tr><td>4</td><td>7434.00</td><td>42.87</td><td>54.00</td><td>-11.13</td><td>29.37</td><td>36.23</td><td>15.51</td><td>38.57</td><td>0.33 100 65 Average</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	4956.00	49.71	74.00	+24.29	41.16	33.14	12.53	37.63	0.51 100 242 PEAK	2	4956.00	44.76	54.00	-9.24	36.21	33.14	12.53	37.63	0.51 100 242 Average	3	7434.00	50.40	74.00	-23.60	36.90	36.23	15.51	38.57	0.33 100 65 PEAK	4	7434.00	42.87	54.00	-11.13	29.37	36.23	15.51	38.57
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																				
1	4956.00	51.57	74.00	+22.43	43.02	33.14	12.53	37.63	0.51 100 160 PEAK																																																																																																																
2	4956.00	47.34	54.00	-6.66	38.79	33.14	12.53	37.63	0.51 100 160 Average																																																																																																																
3	7434.00	52.87	74.00	-21.13	39.37	36.23	15.51	38.57	0.33 100 299 PEAK																																																																																																																
4	7434.00	46.52	54.00	-7.48	33.02	36.23	15.51	38.57	0.33 100 299 Average																																																																																																																
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																				
1	4956.00	49.71	74.00	+24.29	41.16	33.14	12.53	37.63	0.51 100 242 PEAK																																																																																																																
2	4956.00	44.76	54.00	-9.24	36.21	33.14	12.53	37.63	0.51 100 242 Average																																																																																																																
3	7434.00	50.40	74.00	-23.60	36.90	36.23	15.51	38.57	0.33 100 65 PEAK																																																																																																																
4	7434.00	42.87	54.00	-11.13	29.37	36.23	15.51	38.57	0.33 100 65 Average																																																																																																																






Mode	12																																																																																																																																																																
	LF																																																																																																																																																																
	2400-2483.5_Bluetooth BR_GFSK_CH02_2404MHz																																																																																																																																																																
ANT	1																																																																																																																																																																
Pol.	Horizontal																																																																																																																																																																
QP/ Peak																																																																																																																																																																	
	<p>Site : 03CH20-HY Condition: QP 3m Bilog_55606 & 08_241127 HORIZONTAL</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>30.97</td><td>24.01</td><td>40.00</td><td>-15.99</td><td>34.41</td><td>24.12</td><td>0.98</td><td>35.75</td><td>0.25</td></tr><tr><td>2</td><td>197.81</td><td>29.46</td><td>43.50</td><td>-14.04</td><td>47.23</td><td>15.03</td><td>2.51</td><td>35.51</td><td>0.20</td></tr><tr><td>3</td><td>263.77</td><td>32.05</td><td>46.00</td><td>-13.95</td><td>44.01</td><td>20.34</td><td>2.88</td><td>35.37</td><td>0.19</td></tr><tr><td>4</td><td>297.72</td><td>30.37</td><td>46.00</td><td>-15.63</td><td>43.08</td><td>19.33</td><td>3.06</td><td>35.29</td><td>0.19</td></tr><tr><td>5</td><td>737.13</td><td>33.11</td><td>46.00</td><td>-12.89</td><td>34.16</td><td>27.94</td><td>4.80</td><td>33.94</td><td>0.15</td></tr><tr><td>6</td><td>935.01</td><td>34.42</td><td>46.00</td><td>-11.58</td><td>32.20</td><td>29.92</td><td>5.39</td><td>33.21</td><td>0.12</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	30.97	24.01	40.00	-15.99	34.41	24.12	0.98	35.75	0.25	2	197.81	29.46	43.50	-14.04	47.23	15.03	2.51	35.51	0.20	3	263.77	32.05	46.00	-13.95	44.01	20.34	2.88	35.37	0.19	4	297.72	30.37	46.00	-15.63	43.08	19.33	3.06	35.29	0.19	5	737.13	33.11	46.00	-12.89	34.16	27.94	4.80	33.94	0.15	6	935.01	34.42	46.00	-11.58	32.20	29.92	5.39	33.21	0.12	<p>Site : 03CH20-HY Condition: QP 3m Bilog_55606 & 08_241127 VERTICAL</p> <table><thead><tr><th></th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th>Freq</th><th>Level</th><th>Line Margin</th><th>Level Factor</th><th>Loss Factor</th><th>Factor</th><th></th><th></th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>50.37</td><td>32.95</td><td>40.00</td><td>-7.05</td><td>52.73</td><td>14.46</td><td>1.25</td><td>35.74</td><td>0.25</td></tr><tr><td>2</td><td>155.13</td><td>28.04</td><td>43.50</td><td>-15.46</td><td>44.18</td><td>17.04</td><td>2.22</td><td>35.59</td><td>0.19</td></tr><tr><td>3</td><td>224.97</td><td>33.80</td><td>46.00</td><td>-12.20</td><td>50.62</td><td>15.78</td><td>2.66</td><td>35.46</td><td>0.20</td></tr><tr><td>4</td><td>505.30</td><td>28.85</td><td>46.00</td><td>-17.15</td><td>35.49</td><td>24.02</td><td>3.96</td><td>34.75</td><td>0.13</td></tr><tr><td>5</td><td>734.22</td><td>34.28</td><td>46.00</td><td>-11.72</td><td>35.43</td><td>27.86</td><td>4.79</td><td>33.95</td><td>0.15</td></tr><tr><td>6</td><td>959.26</td><td>36.82</td><td>46.00</td><td>-9.18</td><td>33.33</td><td>31.07</td><td>5.45</td><td>33.12</td><td>0.09</td></tr></tbody></table>		Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark	Freq	Level	Line Margin	Level Factor	Loss Factor	Factor					1	50.37	32.95	40.00	-7.05	52.73	14.46	1.25	35.74	0.25	2	155.13	28.04	43.50	-15.46	44.18	17.04	2.22	35.59	0.19	3	224.97	33.80	46.00	-12.20	50.62	15.78	2.66	35.46	0.20	4	505.30	28.85	46.00	-17.15	35.49	24.02	3.96	34.75	0.13	5	734.22	34.28	46.00	-11.72	35.43	27.86	4.79	33.95	0.15	6	959.26	36.82	46.00	-9.18	33.33	31.07	5.45	33.12
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																																																												
1	30.97	24.01	40.00	-15.99	34.41	24.12	0.98	35.75	0.25																																																																																																																																																								
2	197.81	29.46	43.50	-14.04	47.23	15.03	2.51	35.51	0.20																																																																																																																																																								
3	263.77	32.05	46.00	-13.95	44.01	20.34	2.88	35.37	0.19																																																																																																																																																								
4	297.72	30.37	46.00	-15.63	43.08	19.33	3.06	35.29	0.19																																																																																																																																																								
5	737.13	33.11	46.00	-12.89	34.16	27.94	4.80	33.94	0.15																																																																																																																																																								
6	935.01	34.42	46.00	-11.58	32.20	29.92	5.39	33.21	0.12																																																																																																																																																								
	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																																																																																																								
Freq	Level	Line Margin	Level Factor	Loss Factor	Factor																																																																																																																																																												
1	50.37	32.95	40.00	-7.05	52.73	14.46	1.25	35.74	0.25																																																																																																																																																								
2	155.13	28.04	43.50	-15.46	44.18	17.04	2.22	35.59	0.19																																																																																																																																																								
3	224.97	33.80	46.00	-12.20	50.62	15.78	2.66	35.46	0.20																																																																																																																																																								
4	505.30	28.85	46.00	-17.15	35.49	24.02	3.96	34.75	0.13																																																																																																																																																								
5	734.22	34.28	46.00	-11.72	35.43	27.86	4.79	33.95	0.15																																																																																																																																																								
6	959.26	36.82	46.00	-9.18	33.33	31.07	5.45	33.12	0.09																																																																																																																																																								



Mode	13																																																																																
	SHF																																																																																
	2400-2483.5_Bluetooth BR_GFSK_CH02_2404MHz																																																																																
ANT	1																																																																																
Pol.	Horizontal																																																																																
Peak																																																																																	
	<p>Site : 03CH20-HY Condition: PEAK_74 1m BBHA9170_1224_240624 HORIZONTAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>23334.00</td><td>42.23</td><td>74.00</td><td>-31.77</td><td>37.92</td><td>38.84</td><td>28.08</td><td>53.07</td><td>-9.54</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>-- Peak</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Level	Line Margin	Level	Factor	Loss	Factor	Factor			1	23334.00	42.23	74.00	-31.77	37.92	38.84	28.08	53.07	-9.54										-- Peak	<p>Site : 03CH20-HY Condition: PEAK_74 1m BBHA9170_1224_240624 VERTICAL</p> <table><thead><tr><th>Freq</th><th>Limit</th><th>Read</th><th>Ant</th><th>Cable</th><th>Preamp</th><th>Aux</th><th>APos</th><th>TPos</th><th>Remark</th></tr><tr><th></th><th>Level</th><th>Line Margin</th><th>Level</th><th>Factor</th><th>Loss</th><th>Factor</th><th>Factor</th><th></th><th></th></tr></thead><tbody><tr><td>1</td><td>24580.00</td><td>43.41</td><td>74.00</td><td>-30.59</td><td>37.63</td><td>39.36</td><td>28.88</td><td>52.92</td><td>-9.54</td></tr><tr><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td></td><td>-- Peak</td></tr></tbody></table>	Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark		Level	Line Margin	Level	Factor	Loss	Factor	Factor			1	24580.00	43.41	74.00	-30.59	37.63	39.36	28.88	52.92	-9.54									
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
	Level	Line Margin	Level	Factor	Loss	Factor	Factor																																																																										
1	23334.00	42.23	74.00	-31.77	37.92	38.84	28.08	53.07	-9.54																																																																								
									-- Peak																																																																								
Freq	Limit	Read	Ant	Cable	Preamp	Aux	APos	TPos	Remark																																																																								
	Level	Line Margin	Level	Factor	Loss	Factor	Factor																																																																										
1	24580.00	43.41	74.00	-30.59	37.63	39.36	28.88	52.92	-9.54																																																																								
									-- Peak																																																																								

Appendix D. Duty Cycle Plots

Band	Duty Cycle(%)	T(us)	1/T(kHz)	VBW Setting
Bluetooth - LE for 1Mbps	100.00	-	-	10Hz



THE END