

**Soehnle-Waagen GmbH & Co. KG**

Application  
For  
Certification  
**(FCC ID: TDV-BB01001)**

Transmitter

0527837  
DL/ Sandy Lee  
March 14, 2006

- The test results reported in this test report shall refer only to the sample actually tested and shall not refer or be deemed to refer to bulk from which such a sample may be said to have been obtained.
- This report shall not be reproduced except in full without prior authorization from Intertek Testing Services Hong Kong Limited.
- For Terms And Conditions of the services, it can be provided upon request.
- The evaluation data of the report will be kept for 3 years from the date of issuance.

**Intertek Testing Services Hong Kong Ltd.**

2/F., Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong.  
Tel: (852) 2173 8888 Fax: (852) 2371 0521 Website: [www.hk.intertek-etlsemko.com](http://www.hk.intertek-etlsemko.com)

## INTERTEK TESTING SERVICES

---

### LIST OF EXHIBITS

#### *INTRODUCTION*

|                   |                           |
|-------------------|---------------------------|
| <i>EXHIBIT 1:</i> | General Description       |
| <i>EXHIBIT 2:</i> | System Test Configuration |
| <i>EXHIBIT 3:</i> | Emission Results          |
| <i>EXHIBIT 4:</i> | Equipment Photographs     |
| <i>EXHIBIT 5:</i> | Product Labelling         |
| <i>EXHIBIT 6:</i> | Technical Specifications  |
| <i>EXHIBIT 7:</i> | Instruction Manual        |
| <i>EXHIBIT 8:</i> | Miscellaneous Information |

# INTERTEK TESTING SERVICES

## MEASUREMENT/TECHNICAL REPORT

Soehnle-Waagen GmbH & Co. KG - MODEL: Soehnle BB COMFORT F5

FCC ID: TDV-BB01001

March 14, 2006

This report concerns (check one:) Original Grant ☒ Class II Change \_\_\_\_\_

Equipment Type: Low Power Transmitter (example: computer, printer, modem, etc.)

Deferred grant requested per 47 CFR 0.457(d)(1)(ii)? Yes \_\_\_\_\_ No ☒

If yes, defer until: \_\_\_\_\_  
date

Company Name agrees to notify the Commission by: \_\_\_\_\_  
date

of the intended date of announcement of the product so that the grant can be issued on that date.

Transition Rules Request per 15.37? Yes \_\_\_\_\_ No ☒

If no, assumed Part 15, Subpart C for intentional radiator - the new 47 CFR [10-01-04 Edition] provision.

Report prepared by:

Derek Leung  
Intertek Testing Services  
2/F., Garment Center,  
576, Castle Peak Road,  
Kowloon, Hong Kong.  
Phone: 852-2173-8539  
Fax: 852-2371-0521

# INTERTEK TESTING SERVICES

---

## Table of Contents

|                                                      |    |
|------------------------------------------------------|----|
| 1.0 <b><u>General Description</u></b> .....          | 2  |
| 1.1 Product Description .....                        | 2  |
| 1.2 Related Submittal(s) Grants .....                | 2  |
| 1.3 Test Methodology .....                           | 3  |
| 1.4 Test Facility .....                              | 3  |
| 2.0 <b><u>System Test Configuration</u></b> .....    | 5  |
| 2.1 Justification .....                              | 5  |
| 2.2 EUT Exercising Software .....                    | 5  |
| 2.3 Special Accessories .....                        | 5  |
| 2.4 Equipment Modification .....                     | 6  |
| 2.5 Measurement Uncertainty .....                    | 6  |
| 2.6 Support Equipment List and Description .....     | 6  |
| 3.0 <b><u>Emission Results</u></b> .....             | 8  |
| 3.1 Field Strength Calculation .....                 | 9  |
| 3.2 Radiated Emission Configuration Photograph ..... | 11 |
| 3.3 Radiated Emission Data .....                     | 12 |
| 4.0 <b><u>Equipment Photographs</u></b> .....        | 15 |
| 5.0 <b><u>Product Labelling</u></b> .....            | 17 |
| 6.0 <b><u>Technical Specifications</u></b> .....     | 19 |
| 7.0 <b><u>Instruction Manual</u></b> .....           | 21 |
| 8.0 <b><u>Miscellaneous Information</u></b> .....    | 23 |
| 8.1 Bandwidth Plot .....                             | 24 |
| 8.2 Discussion of Pulse Desensitization .....        | 25 |
| 8.3 Emissions Test Procedures .....                  | 26 |

---

## INTERTEK TESTING SERVICES

---

### List of attached file

| Exhibit type          | File Description           | filename            |
|-----------------------|----------------------------|---------------------|
| Test Report           | Test Report                | report.pdf          |
| Operation Description | Technical Description      | descri.pdf          |
| Test Setup Photo      | Radiated Emission          | radiated photos.doc |
| Test Report           | Bandwidth Plot             | bw.pdf              |
| External Photo        | External Photo             | external photos.doc |
| Internal Photo        | Internal Photo             | internal photos.doc |
| Block Diagram         | Block Diagram              | block.pdf           |
| Schematics            | Circuit Diagram            | circuit.pdf         |
| ID Label/Location     | Label Artwork and Location | label.pdf           |
| User Manual           | User Manual                | manual.pdf          |

# **INTERTEK TESTING SERVICES**

---

## **EXHIBIT 1**

### **GENERAL DESCRIPTION**

## INTERTEK TESTING SERVICES

---

### 1.0 **General Description**

#### 1.1 Product Description

The Equipment Under Test (EUT) is a Transmitter operating at 2440.000MHz. The EUT is powered by 6V d.c. (4 x 1.5V "AA" battery). It measures weight and transmits the reading to the corresponding receiver. The reading will be shown on the display accordingly.

Antenna Type : Internal, Integral

For electronic filing, the brief circuit description is saved with filename: descri.pdf.

#### 1.2 Related Submittal(s) Grants

This is an application for certification of a transmitter. The receiver, associated with this transmitter, exempted from technical requirement of the FCC Part 15 standard.

## INTERTEK TESTING SERVICES

---

### 1.3 Test Methodology

Radiated emission measurements were performed according to the procedures in ANSI C63.4 (2003). All measurements were performed in Open Area Test Sites. Preliminary scans were performed in the Open Area Test Sites only to determine worst case modes. For each scan, the procedure for maximizing emissions in Appendices D and E were followed. All Radiated tests were performed at an antenna to EUT distance of 3 meters, unless stated otherwise in the “**Justification Section**” of this Application.

### 1.4 Test Facility

The open area test site and conducted measurement facility used to collect the emission data is located at Garment Centre, 576 Castle Peak Road, Kowloon, Hong Kong. This test facility and site measurement data have been fully placed on file with the FCC.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 2**

### **SYSTEM TEST CONFIGURATION**

## INTERTEK TESTING SERVICES

---

### 2.0 **System Test Configuration**

#### 2.1 Justification

The system was configured for testing in a typical fashion (as a customer would normally use it), and in the confines as outlined in ANSI C63.4 (2003).

The EUT was powered from 4 x 1.5V new "AA" battery.

For maximizing emissions, the EUT was rotated through 360°, the antenna height was varied from 1 meter to 4 meters above the ground plane, and the antenna polarization was changed. This step by step procedure for maximizing emissions led to the data reported in Exhibit 3.0.

The unit was operated standalone and placed in the center of the turntable.

The equipment under test (EUT) was configured for testing in a typical fashion (as a customer would normally use it). The EUT was placed on turntable, which enabled the engineer to maximize emissions through its placement in the three orthogonal axes. For simplicity of testing, the unit was wired to transmit continuously.

The frequency range from 9kHz to 24.4GHz was searched for spurious emissions from the device. Only those emissions reported were detected. All other emissions were at least 20 dB below the applicable limits.

#### 2.2 EUT Exercising Software

There was no special software to exercise the device. Once the button is depressed, the unit transmits the typical signal. For simplicity of testing, the unit was wired to transmit continuously.

#### 2.3 Special Accessories

There are no special accessories necessary for compliance of this product.

## INTERTEK TESTING SERVICES

---

### 2.4 Equipment Modification

Any modifications installed previous to testing by Soehnle-Waagen GmbH & Co. KG will be incorporated in each production model sold/leased in the United States.

No modifications were installed by Intertek Testing Services.

### 2.5 Measurement Uncertainty

When determining the test conclusion, the Measurement Uncertainty of test has been considered.

### 2.6 Support Equipment List and Description

This product was tested in a standalone configuration.

All the items listed under section 2.0 of this report are

*Confirmed by:*

*Derek Leung  
Assistant Manager  
Intertek Testing Services Hong Kong Ltd.  
Agent for Soehnle-Waagen GmbH & Co. KG*



\_\_\_\_\_  
Signature

\_\_\_\_\_  
March 14, 2006      Date

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 3**

### **EMISSION RESULTS**

## INTERTEK TESTING SERVICES

---

### 3.0 Emission Results

Data is included worst case configuration (the configuration which resulted in the highest emission levels). A sample calculation, configuration photographs and data tables of the emissions are included.

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation

The field strength is calculated by adding the reading on the Spectrum Analyzer to the factors associated with preamplifiers (if any), antennas, cables, pulse desensitization and average factors (when specified limit is in average and measurements are made with peak detectors). A sample calculation is included below.

$$FS = RA + AF + CF - AG + PD + AV$$

where FS = Field Strength in dB $\mu$ V/m

RA = Receiver Amplitude (including preamplifier) in dB $\mu$ V

CF = Cable Attenuation Factor in dB

AF = Antenna Factor in dB

AG = Amplifier Gain in dB

PD = Pulse Desensitization in dB

AV = Average Factor in -dB

In the radiated emission table which follows, the reading shown on the data table may reflect the preamplifier gain. An example of the calculations, where the reading does not reflect the preamplifier gain, follows:

$$FS = RA + AF + CF - AG + PD + AV$$

## INTERTEK TESTING SERVICES

---

### 3.1 Field Strength Calculation (cont'd)

#### Example

Assume a receiver reading of 62.0 dB $\mu$ V is obtained. The antenna factor of 7.4 dB and cable factor of 1.6 dB is added. The amplifier gain of 29 dB is subtracted. The pulse desensitization factor of the spectrum analyzer was 0 dB, and the resultant average factor was -10 dB. The net field strength for comparison to the appropriate emission limit is 32 dB $\mu$ V/m. This value in dB $\mu$ V/m was converted to its corresponding level in  $\mu$ V/m.

$$RA = 62.0 \text{ dB}\mu\text{V}$$

$$AF = 7.4 \text{ dB}$$

$$CF = 1.6 \text{ dB}$$

$$AG = 29.0 \text{ dB}$$

$$PD = 0 \text{ dB}$$

$$AV = -10 \text{ dB}$$

$$FS = 62 + 7.4 + 1.6 - 29 + 0 + (-10) = 32 \text{ dB}\mu\text{V/m}$$

$$\text{Level in } \mu\text{V/m} = \text{Common Antilogarithm } [(32 \text{ dB}\mu\text{V/m})/20] = 39.8 \mu\text{V/m}$$

## INTERTEK TESTING SERVICES

---

### 3.2 Radiated Emission Configuration Photograph

Worst Case Radiated Emission  
at  
9760.180 MHz

For electronic filing, the worst case radiated emission configuration photograph is saved with filename: radiated photos.doc.

## INTERTEK TESTING SERVICES


---

### 3.3 Radiated Emission Data

The data on the following page lists the significant emission frequencies, the limit and the margin of compliance. Numbers with a minus sign are below the limit.

Judgement: Passed by 4.0 dB

#### **TEST PERSONNEL:**



---

*Signature*

Ben W. K. Ho, Compliance Engineer  
*Typed/Printed Name*

March 14, 2006  
*Date*

---

## INTERTEK TESTING SERVICES

---

Applicant: Soehnle-Waagen GmbH & Co. KG  
Model: Soehnle BB COMFORT F5

Date of Test: January 25, 2006

Table 1

### Radiated Emissions

| Polarization | Frequency (MHz) | Reading (dB $\mu$ V) | Antenna Factor (dB) | Pre-Amp Gain (dB) | Net at 3m (dB $\mu$ V/m) | Limit at 3m (dB $\mu$ V/m) | Margin (dB) |
|--------------|-----------------|----------------------|---------------------|-------------------|--------------------------|----------------------------|-------------|
| H            | 2440.000        | 92.8                 | 29.4                | 34                | 88.2                     | 94.0                       | -5.8        |
| V            | 4880.080        | 46.5                 | 34.9                | 34                | 47.4                     | 54.0                       | -6.6        |
| V            | 7230.140        | 42.9                 | 37.9                | 34                | 46.8                     | 54.0                       | -7.2        |
| V            | 9760.180        | 43.6                 | 40.4                | 34                | 50.0                     | 54.0                       | -4.0        |
| V            | 12220.000       | 42.4                 | 40.5                | 34                | 48.9                     | 54.0                       | -5.1        |

- Notes:
1. Peak Detector Data unless otherwise stated.
  2. All measurements were made at 3 meter. Harmonic emissions not detected at the 3-meter distance were measured at 0.3-meter and an inverse proportional extrapolation was performed to compare the signal level to the 3-meter limit. No other harmonic emissions than those reported were detected at a test distance of 0.3-meter.
  3. Negative value in the margin column shows emission below limit.
  4. Horn antenna is used for the emission over 1000MHz.

Test Engineer: Ben W. K. Ho

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 4**

### **EQUIPMENT PHOTOGRAPHS**

## INTERTEK TESTING SERVICES

---

### 4.0 Equipment Photographs

For electronic filing, the photographs of the tested EUT are saved with filename: external photos.doc & internal photos.doc.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 5**

### **PRODUCT LABELLING**

## INTERTEK TESTING SERVICES

---

### 5.0 **Product Labelling**

For electronic filing, the FCC ID label artwork and the label location are saved with filename: label.pdf.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 6**

### **TECHNICAL SPECIFICATIONS**

## INTERTEK TESTING SERVICES

---

### 6.0 Technical Specifications

For electronic filing, the block diagram and schematics of the tested EUT are saved with filename: block.pdf and circuit.pdf respectively.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 7**

### **INSTRUCTION MANUAL**

## INTERTEK TESTING SERVICES

---

### 7.0 Instruction Manual

For electronic filing, a preliminary copy of the Instruction Manual is saved with filename: manual.pdf.

This manual will be provided to the end-user with each unit sold/leased in the United States.

## **INTERTEK TESTING SERVICES**

---

### **EXHIBIT 8**

### **MISCELLANEOUS INFORMATION**

## INTERTEK TESTING SERVICES

---

### 8.0 Miscellaneous Information

This miscellaneous information includes details of the measured bandwidth, the test procedure and calculation of factors such as pulse desensitization and averaging factor.

## INTERTEK TESTING SERVICES

---

### 8.1 Bandwidth Plot

For electronic filing, the plot shows the fundamental emission when modulated is saved with filename: bw.pdf. From the plot, the field strength of any emissions appearing between the band edges and up to 10 kHz above and below the band edges are attenuated at least 50dB below the level of the modulated carrier. It fulfil the requirement of 15.249(c).

## INTERTEK TESTING SERVICES

---

### 8.2 Discussion of Pulse Desensitization

The determination of pulse desensitivity was made in accordance with Hewlett Packard Application Note 150-2, *Spectrum Analysis ... Pulsed RF*.

## INTERTEK TESTING SERVICES

---

### 8.3 Emissions Test Procedures

The following is a description of the test procedure used by Intertek Testing Services in the measurements of transmitters operating under Part 15, Subpart C rules.

The test set-up and procedures described below are designed to meet the requirements of ANSI C63.4 - 2003.

The transmitting equipment under test (EUT) is placed on a wooden turntable which is four feet in diameter and approximately one meter in height above the ground plane. During the radiated emissions test, the turntable is rotated and any cables leaving the EUT are manipulated to find the configuration resulting in maximum emissions. The EUT is adjusted through all three orthogonal axes to obtain maximum emission levels. The antenna height and polarization are varied during the testing to search for maximum signal levels. The height of the antenna is varied from one to four meters.

Detector function for radiated emissions is in peak mode. Average readings, when required, are taken by measuring the duty cycle of the equipment under test and subtracting the corresponding amount in dB from the measured peak readings.

The frequency range scanned is from the lowest radio frequency signal generated in the device which is greater than 9 kHz to the tenth harmonic of the highest fundamental frequency or 40 GHz, whichever is lower. For line conducted emissions, the range scanned is 150 kHz to 30 MHz.

## INTERTEK TESTING SERVICES

---

### 8.3 Emissions Test Procedures (cont'd)

The EUT is warmed up for 15 minutes prior to the test.

AC power to the unit is varied from 85% to 115% nominal and variation in the fundamental emission field strength is recorded. If battery powered, a new, fully charged battery is used.

Conducted measurements are made as described in ANSI C63.4 - 2003.

The IF bandwidth used for measurement of radiated signal strength was 100 kHz or greater when frequency is below 1000 MHz. Where pulsed transmissions of short enough pulse duration warrant, a greater bandwidth is selected according to the recommendations of Hewlett Packard Application Note 150-2. A discussion of whether pulse desensitivity is applicable to this unit is included in this report (See Exhibit 8.2). Above 1000 MHz, a resolution bandwidth of 1 MHz is used.

Transmitter measurements are normally conducted at a measurement distance of three meters. However, to assure low enough noise floor in the forbidden bands and above 1 GHz, signals are acquired at a distance of one meter or less. All measurements are extrapolated to three meters using inverse scaling, unless otherwise reported. Measurements taken at a closer distance are so marked.