

RF Exposure Report

(Part 0: SAR Char Evaluation)

APPLICANT : Zebra Technologies Corporation
EQUIPMENT : Enterprise Mobile
BRAND NAME : ZEBRA
MODEL NAME : EM45A2
FCC ID : UZ7EM45A2
STANDARD : FCC 47 CFR PART 2 (2.1093)

We, Sporton International Inc. (Kunshan), would like to declare that the tested sample has been evaluated in accordance with the test procedures given in 47 CFR Part 2.1093 and FCC KDB and has been in compliance with the applicable technical standards.

The test results in this report apply exclusively to the tested model / sample. Without written approval of Sporton International Inc. (Kunshan), the test report shall not be reproduced except in full.



Approved by: Si Zhang

Sporton International Inc. (Kunshan)

No. 1098, Pengxi North Road, Kunshan Economic Development Zone Jiangsu Province 215300
People's Republic of China



Table of Contents

1. Introduction	4
2. Product Description	5
3. SAR Characterization.....	6
3.1 SAR design target and uncertainty.....	6
3.2 SAR Char Table	7



History of this test report

Report No.	Version	Description	Issued Date
FA460505D	01	Initial issue of report	Sep. 06, 2024



1. Introduction

The RF exposure limit is defined based on time-averaged RF exposure. The product implements Qualcomm Smart Transmit feature which controls the instantaneous transmitting power for WWAN transmitter to ensure the product in compliance with RF exposure limit over a defined time window. To control and manage transmitting power in real time and to ensure at all times the time-averaged RF exposure is compliant to the regulation requirement. Smart Transmit cannot operate without SAR characterization at the device level, beforehand.

This report describes the procedures for the SAR char generation, and the parameters obtained from SAR characterization (referred to as SAR char, respectively) will be used as input for Smart Transmit. Both SAR char will be entered via the Embedded File System (EFS) version 16 to enable the Smart Transmit GEN1 Feature.

Terminologies in this report

P_{limit}	The time-averaged RF power which corresponds to SAR_design_target.
P_{max}	Maximum target power level
SAR_design_target:	The design target for SAR compliance. It should be less than regulatory power density limit to account for all device design related uncertainty.
SAR char	P_{limit} for all the technologies/bands for all applicable DSI



2. Product Description

Product Feature & Specification	
Equipment Name	Enterprise Mobile
Brand Name	ZEBRA
Model Name	EM45A2
FCC ID	UZ7EM45A2
Wireless Technology and Frequency Range	WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 14: 788 MHz ~ 798 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 25: 1850 MHz ~ 1915 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 30: 2305 MHz ~ 2315 MHz LTE Band 38: 2570 MHz ~ 2620 MHz LTE Band 41: 2496 MHz ~ 2690 MHz LTE Band 48: 3550 MHz ~ 3700 MHz LTE Band 66: 1710 MHz ~ 1780 MHz LTE Band 71: 663 MHz ~ 698 MHz 5G NR n2 : 1850 MHz ~ 1910 MHz 5G NR n5 : 824 MHz ~ 849 MHz 5G NR n7 : 2500 MHz ~ 2570 MHz 5G NR n12 : 699 MHz ~ 716 MHz 5G NR n13 : 777 MHz ~ 787 MHz 5G NR n14 : 788 MHz ~ 798 MHz 5G NR n25 : 1850 MHz ~ 1915 MHz 5G NR n26 : 814 MHz ~ 849 MHz 5G NR n30 : 2305 MHz ~ 2315 MHz 5G NR n38 : 2570 MHz ~ 2620 MHz 5G NR n41 : 2496 MHz ~ 2690 MHz 5G NR n48 : 3550 MHz ~ 3700 MHz 5G NR n66 : 1710 MHz ~ 1780 MHz 5G NR n71 : 663 MHz ~ 698 MHz 5G NR n77: 3450 MHz ~ 3980 MHz 5G NR n78: 3450 MHz ~ 3800 MHz WLAN 2.4GHz Band: 2412 MHz ~ 2462 MHz WLAN 5.2GHz Band: 5180 MHz ~ 5240 MHz WLAN 5.3GHz Band: 5260 MHz ~ 5320 MHz WLAN 5.5GHz Band: 5500 MHz ~ 5720 MHz WLAN 5.8GHz Band: 5745 MHz ~ 5825 MHz WLAN 6GHz U-NII 5: 5925 MHz ~ 6425 MHz WLAN 6GHz U-NII 6: 6425 MHz ~ 6525 MHz WLAN 6GHz U-NII 7: 6525 MHz ~ 6875 MHz WLAN 6GHz U-NII 8: 6875 MHz ~ 7125 MHz Bluetooth: 2402 MHz ~ 2480 MHz NFC : 13.56 MHz RFID : 902.75 MHz ~ 927.25 MHz
Mode	RMC/AMR 12.2Kbps HSDPA HSUPA DC-HSDPA HSPA+ (16QAM uplink is supported) LTE: QPSK, 16QAM, 64QAM, 256QAM 5G NR: DFT-s-OFDM/CP-OFDM, Pi/2 BPSK/QPSK/16QAM/64QAM/256QAM WLAN 2.4GHz 802.11b/g/n HT20 WLAN 2.4GHz 802.11ac VHT20 WLAN 2.4GHz 802.11ax HE20 WLAN 5GHz 802.11a/n HT20/HT40 WLAN 5GHz 802.11ac VHT20/VHT40/VHT80/VHT160 WLAN 5GHz 802.11ax HE20/HE40/HE80/HE160 WLAN 6GHz 802.11a/ax HE20/HE40/HE80/HE160 Bluetooth BR/EDR/LE NFC: ASK RFID : ASK

3. SAR Characterization

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

3.1 SAR design target and uncertainty

SAR design Target :

Exposure Condition	Measure Distance	SAR (W/kg)	
		RFID Off	RFID On
Body Worn (1g)	15 mm	0.87	0.64
Hotspot (1g)	10 mm	0.87	0.64
Head (1g)	touch&tilt 15deg	0.87	
Extremity (10g)	0 mm	2.46	1.59

Uncertainty:

Item	Uncertainty dB (k=2)
Total uncertainty	1.0

To account for total uncertainty, SAR_design_target should be determined as:

$$SAR_{design_target} < SAR_{regulatory_limit} \times 10^{\frac{-total\ uncertainty}{10}}$$

3.2 SAR Char Table

SAR char must be generated to cover all radio configurations and usage scenarios that the wireless device supports for operating at 6 GHz or below. It will then be used as input for Smart Transmit to control and manage RF exposure for $f < 6$ GHz.

<P_{limit} for supported technologies and bands (P_{limit} in EFS file)>

Band	Antenna	Head DSI 2	Hotspot DSI 1 RFID OFF	Hotspot DSI 4 RFID ON	Body-Worn& Extremity DSI 0 RFID OFF	Body-Worn& Extremity DSI 5 RFID ON	Pmax*
WCDMA II	Ant 2	18.6	20.7	19.2	22.2	20.7	24.0
WCDMA IV	Ant 2	18.4	21.9	20.4	22.2	21.2	24.0
WCDMA V	Ant 0	21.7	24.8	23.5	24.8	23.5	24.0
WCDMA V	Ant 1			23.5		23.5	23.0
LTE Band 2	Ant 5	23.4	22.2	20.7	23.4	21.9	24.0
LTE Band 25(2)	Ant 2	18.6	20.7	19.2	22.2	20.7	24.0
LTE Band 66(4)	Ant 2	17.9	21.1	19.6	22.6	21.1	24.0
LTE Band 66(4)	Ant 5	24.0	22.0	20.5	24.0	22.5	24.0
LTE Band 26(5)	Ant 0	21.4	24.0	22.6	24.0	23.5	24.0
LTE Band 26(5)	Ant 1			22.6		23.5	23.0
LTE Band 7	Ant 3	15.9	18.4	16.9	19.9	18.4	23.0
LTE Band 12(17)	Ant 0	21.7	26.0	24.0	26.0	24.0	24.0
LTE Band 12(17)	Ant 1			24.0		24.0	23.0
LTE Band 13	Ant 0	21.4	25.6	24.0	25.6	24.0	24.0
LTE Band 13	Ant 1			24.0		24.0	23.0
LTE Band 14	Ant 0	21.4	24.9	23.4	24.9	24.0	24.0
LTE Band 14	Ant 1			23.4		24.0	23.0
LTE Band 30	Ant 3	15.2	19.4	17.9	19.4	17.4	24.0
LTE Band 71	Ant 0	21.9	24.7	23.0	24.7	23.0	23.0
LTE Band 71	Ant 1			23.0		23.0	22.5
LTE Band 41(38)	Ant 3	15.7	18.3	16.8	19.8	17.8	21.0
LTE Band 41 HPUE	Ant 3	15.7	18.3	16.8	19.8	17.8	22.4
LTE Band 48	Ant 4	15.2	20.0	19.5	20.0	19.5	20.0
FR1 n26(5)	Ant 0	21	24.1	22.6	24.1	22.6	24.0
FR1 n26(5)	Ant 1			22.6		22.6	23.0
FR1 n7	Ant 3	16.4	17.7	16.2	20.8	18.8	23.0
FR1 n12	Ant 0	21.4	24.5	23.4	24.5	23.4	24.0
FR1 n12	Ant 1			23.4		23.4	23.0
FR1 n13	Ant 0	21.4	24.2	23.4	24.2	23.4	24.0
FR1 n13	Ant 1			23.4		23.4	23.0
FR1 n14	Ant 0	21.4	24.2	23.4	24.2	23.4	24.0
FR1 n14	Ant 1			23.4		23.4	23.0
FR1 n25(2)	Ant 2	18.6	20.7	19.2	22.2	20.2	24.0
FR1 n25	Ant 5	23.4	22.7	21.2	23.4	21.9	24.0
FR1 n30	Ant 3	15.2	19.6	18.6	19.7	17.7	24.0
FR1 n66	Ant 2	18.7	21.1	19.6	22.6	21.6	24.0
FR1 n66	Ant 5	24.0	23.2	21.5	24.0	23.0	24.0
FR1 n71	Ant 0	21.4	24.7	23.4	24.7	23.0	23.0
FR1 n71	Ant 1			23.4		23.0	23.0
FR1 n41(38)	Ant 3	16.1	17.9	16.4	19.8	17.8	23.0
FR1 n41 HPUE	Ant 3	16.1	17.9	16.4	19.8	17.8	26.0
FR1 n41	Ant 0	16.3	21.0	19.5	21.0	19.5	23.0
FR1 n41 HPUE	Ant 0	16.3	21.0	19.5	21.0	19.5	25.0
FR1 n41	Ant 5	19.4	20.4	18.9	19.4	17.4	22.0
FR1 n41 HPUE	Ant 5	19.4	20.4	18.9	19.4	17.4	24.0

FR1 n41	Ant 6	19.3	19.1	17.3	19.3	17.3	22.0
FR1 n41 HPUE	Ant 6	19.3	19.1	17.3	19.3	17.3	24.0
FR1 n48	Ant 4	14.9	21.3	19.8	21.3	19.8	22.0
FR1 n77(78) Part 27O&27Q&96 PC3	Ant 4	14.4	22.2	20.7	22.2	20.7	23.0
FR1 n77(78) Part 27O&27Q PC2	Ant 4	14.4	22.2	20.7	22.2	20.7	26.0
FR1 n77(78) Part 27O PC3	Ant 2	15.6	22.6	21.1	22.6	20.6	22.0
FR1 n77 Part 27O PC2	Ant 2	15.6	22.6	21.1	22.6	20.6	25.0
FR1 n78 Part 27O PC2	Ant 2	15.6	22.6	21.1	22.6	20.6	24.0
FR1 n77 Part 27Q PC3	Ant 2	15.6	22.6	21.1	22.6	20.6	22.0
FR1 n78 Part 27Q PC3	Ant 2	15.6	22.6	21.1	22.6	20.6	21.0
FR1 n77 Part 27Q PC2	Ant 2	15.6	22.6	21.1	22.6	20.6	24.0
FR1 n78 Part 27Q PC2	Ant 2	15.6	22.6	21.1	22.6	20.6	23.0
FR1 n77(78) Part 96 PC3	Ant 2	15.6	22.6	21.1	22.6	20.6	22.0
FR1 n77 Part 27O PC3	Ant 3	16.7	17.9	16.4	17.9	16.4	23.0
FR1 n78 Part 27O PC3	Ant 3	16.7	17.9	16.4	17.9	16.4	22.0
FR1 n77(78) Part 27O PC2	Ant 3	16.7	17.9	16.4	17.9	16.4	24.0
FR1 n77 Part 27Q PC3	Ant 3	16.7	17.9	16.4	17.9	16.4	22.0
FR1 n78 Part 27Q PC3	Ant 3	16.7	17.9	16.4	17.9	16.4	21.0
FR1 n77 Part 27Q PC2	Ant 3	16.7	17.9	16.4	17.9	16.4	24.0
FR1 n78 Part 27Q PC2	Ant 3	16.7	17.9	16.4	17.9	16.4	23.0
FR1 n77(78) Part 96 PC3	Ant 3	16.7	17.9	16.4	17.9	16.4	23.0
FR1 n77(78) Part 27O&27Q&96 PC3	Ant 6	19.1	20.3	18.8	19.1	17.1	22.0
FR1 n77(78) Part 27O&27Q PC2	Ant 6	19.1	20.3	18.8	19.1	17.1	25.0

Note: 1) * P_{max} is used for RF tune up procedure. The maximum allowed output power is equal to $P_{max} + 1.0$ dB device uncertainty.

2) **All P_{limit} power levels entered in the Table correspond to average power levels after accounting for duty cycle in the case TDD modulation schemes (for e.g., LTE TDD & NR TDD).

3) The max allowed output power is the $P_{limit} +$ device uncertainty, and if P_{limit} is higher than P_{max} , the device output power will be P_{max} instead.

4) When P-light sensor is used to detect the user who take the device close to head, or during the voice call is established and audio is actively routed through the earpiece receiver (earpiece is ON) while P-light sensor be detected Phone close to Head, therefore RFID is turned off. When the RFID is turned off, then WWAN ant1 cannot be transmitted. When the RFID is active, then WWAN ant1 can be transmitted.

5) The following table is duty cycle and factor used for calculating time average power.

FDD/TDD	Duty Cycle	Time average calculation factor(dB)
FDD LTE	100%	0.0
TDD LTE	63.30%	-2.0
TDD HPUE	43.30%	-3.6
NR FDD/TDD	100%	0.0
NR TDD HPUE	100%	0.0