

ET6x

Enterprise Tablet

DRAFT



ZEBRA

Quick Start Guide for Windows

2024/07/01

ZEBRA and the stylized Zebra head are trademarks of Zebra Technologies Corporation, registered in many jurisdictions worldwide. All other trademarks are the property of their respective owners. ©2024 Zebra Technologies Corporation and/or its affiliates. All rights reserved.

Information in this document is subject to change without notice. The software described in this document is furnished under a license agreement or nondisclosure agreement. The software may be used or copied only in accordance with the terms of those agreements.

For further information regarding legal and proprietary statements, please go to:

SOFTWARE: zebra.com/informationpolicy.

COPYRIGHTS: zebra.com/copyright.

PATENTS: ip.zebra.com.

WARRANTY: zebra.com/warranty.

END USER LICENSE AGREEMENT: zebra.com/eula.

Terms of Use

Proprietary Statement

This manual contains proprietary information of Zebra Technologies Corporation and its subsidiaries ("Zebra Technologies"). It is intended solely for the information and use of parties operating and maintaining the equipment described herein. Such proprietary information may not be used, reproduced, or disclosed to any other parties for any other purpose without the express, written permission of Zebra Technologies.

Product Improvements

Continuous improvement of products is a policy of Zebra Technologies. All specifications and designs are subject to change without notice.

Liability Disclaimer

Zebra Technologies takes steps to ensure that its published Engineering specifications and manuals are correct; however, errors do occur. Zebra Technologies reserves the right to correct any such errors and disclaims liability resulting therefrom.

Limitation of Liability

In no event shall Zebra Technologies or anyone else involved in the creation, production, or delivery of the accompanying product (including hardware and software) be liable for any damages whatsoever (including, without limitation, consequential damages including loss of business profits, business interruption, or loss of business information) arising out of the use of, the results of use of, or inability to use such product, even if Zebra Technologies has been advised of the possibility of such damages. Some jurisdictions do not allow the exclusion or limitation of incidental or consequential damages, so the above limitation or exclusion may not apply to you.

Features

This section lists the features of the ET60 and ET65 tablets.



NOTE: Some features may not be available on all configurations.

Figure 1 Front View





Table 1 Front View

Number	Item	Description
1	Front microphone	Use for voice communications or audio recordings.
2	Front camera	Use for video conferencing.
3	Light sensor	Determines ambient light for controlling display backlight intensity.
4	Access door	Secure door for accessing USB ports (two USB-A and one USB-C).
5	Touch screen	Displays all information needed to operate the device.
6	Dock alignment slot	Assists in aligning the tablet with the dock.
7	Speakers	Provides audio output.
8	Dock USB connector	Provides USB communication through the dock.
9	Charging indicator	Indicates power state and battery charging status while charging and application-generated notifications.
10	Keyboard/Shoulder strap mount slots	Provides alignment and mounting of keyboard and shoulder strap clips.
11	Power button	Turns the display on and off. Press and release to turn on the device. Press and hold to restart the device or power it off.
12	Volume up button	Increases the audio volume.

Table 1 Front View (Continued)

Number	Item	Description
13	Volume down button	Decreases the audio volume.
14	Keyboard interface connector	Provides power and communication with the keyboard.
15	P3 button	Programmable button (PTT - default).
16	Kensington security slot	Provides mounting a security cable to prevent theft or unauthorized use of the tablet.
17	P2 button	Programmable button (Home - default).
18	P1 button	Programmable button (Back - default).
19	Dock Power / Antenna connector	Provides power and antenna connection through the dock.

Figure 2 Right Side USB Ports**Table 2** USB Ports

Number	Item	Description
1	Stylus holder	It provides a place for holding an optional stylus.
2	USB-C port	Provides communication with accessories such as scanners.
3	USB-A port	Provides communication with a host computer and charging.



Figure 3 Left USB Ports

Table 3 USB Ports

Number	Item	Description
1	USB-C port	Provides communication with accessories such as scanners.
2	Scan button	Initiates barcode data capture when a scan-enabled application is active.

Figure 4 Back View

Number	Item	Description
2	NFC antenna	Use to read NFC cards.
1	Stylus mount	Provides mounting for a stylus tether.
3	Accessory mount point locations	Indicates mounting location points on polymer film for accessory captive screws. CAUTION: Do not remove the polymer film.
6	Scanner exit window	Provides data capture using the imager.
4	Rear camera	Autofocus camera that takes photos, captures barcode data, and reads OCR data.
5	Rear camera LED flash	Provides illumination for the camera.
7	Communication expansion port	Provides USB communication and power to an accessory.

10	Dock alignment slot	Assists in aligning the tablet with the dock.
13	Dock locking mechanism	Secures the tablet in a dock.
8	Battery release latches	Releases the battery.
9	Battery Blank Battery Pack	Provides power to the tablet. Provides water and dust sealing when used in fixed mount installation when a battery is not required.

Repair or Replacement

For purchasing a new battery for repair and replacement a battery, go to [Request a Repair](#).

Repair and replacement services of ET60/65 for 3 to 5 years from the date of sale can be purchased from [One Care Support Services](#)

Setting Up the Device

Set up the device before using it for the first time.



NOTE: The ET6x with a battery ships in Ship Mode to prevent discharging during shipment and storage. To remove the tablet from Ship Mode, place the tablet in a powered Vehicle Dock, connect power with a USB cable, or press the power button.

To start using the device for the first time:

1. Install a nano SIM card (optional for ET65 only).
2. Install the battery.
3. Charge the device.

Installing the nano SIM Card

The nano SIM card is required for cellular data connectivity.




NOTE: Only use a nano SIM card.




NOTE: For proper electrostatic discharge (ESD) precautions to avoid damaging the SIM card. Proper ESD precautions include, but are not limited to, working on an ESD mat and ensuring that the user is properly grounded.


1. Slide the battery release latches toward the sides of the tablet.
The battery ejects slightly.




2. Lift the battery out of the tablet.



3. Using a T4 Torx screwdriver, remove four screws securing the SIM cover to the tablet.



4. Open the SIM holder.




5. Place the SIM card face down.




6. Close the SIM door.



7. Using a T4 Torx screwdriver, secure the SIM cover to the tablet using the four screws.



8. Insert the battery, bottom first, into the battery compartment at the back of the device.



9. Press the battery down into the compartment until the release latches snap into place.


Installing the Battery

This section describes how to install the battery into the tablet.



NOTE: User modification of the device, particularly in the battery well, such as labels, asset tags, engravings, stickers, etc., may compromise the intended performance of the device or accessories. Performance levels such as sealing (Ingress Protection (IP)), impact performance (drop and tumble), functionality, temperature resistance, etc. could be affected. DO NOT put any labels, asset tags, engravings, stickers, etc. in the battery well.

1. Insert the battery, bottom first, into the battery compartment at the back of the device.



2. Press the battery down into the compartment until the release latches snap into place.

Class 1/Division 2 Compliant Tablet

ET6x devices that support Class 1/Division 2 requirements can be used in hazardous areas as long as the electronic parts are securely covered. A hazardous area is a location that has a higher risk of explosion and/or fire than a normal industrial area. This is due to the properties of the materials handled or stored there.




CAUTION: The ET6x comes with screws to secure the battery access and USB ports. Ensure that you install the screws before entering a hazardous area.



NOTE: Only the ET6x tablet or the ET6x tablet with the attached ET6x Keyboard can be used in hazardous locations.

1. Align two M2x3 Philips head screws with the battery release latches.


Figure 5 Secure battery latches



2. Using a Philips screwdriver, secure the screws to the latches.
3. Torque the screws to 2.5 kg-cm (2.2 lbf-in).

4. Align one M2x3 Philips head screw with the access door.

Figure 6 Secure access door



5. Using a Philips screwdriver, secure the screw to the access door.
6. Torque the screw to 2.5 kg-cm (2.2 lbf-in).

Device Charging

Before using the tablet for the first time, connect it to an external power source to charge the battery.



NOTE: Battery-free tablets do not require charging.

Keep the tablet connected to the external power source until fully charged. The Charging Indicator LED turns green when the tablet is fully charged. You may use the tablet while it is charging.

To charge the main battery, connect the charging accessory to the appropriate power source.

Insert the device into the dock or attach the USB charger. The device turns on and begins charging. The Charging/Notification LED blinks amber while charging, then turns solid green when fully charged.

The standard battery charges from 4% to 80% in approximately 2.5 hours. The extended battery charges from 4% to 80% in 5.5 hours. To achieve optimal charging results, use only Zebra charging accessories and batteries. Charge batteries at room temperature with the device in sleep mode.

Charging Accessories

Use one of the following accessories to charge the tablet and spare batteries.

Table 4 Charging Accessories

Accessory	Part Number	Description
USB-C to AC Adapter	PWR-BGA15V45W-UC2-WW	Provides tablet charging only. Requires country-specific AC line cord.

Table 4 Charging Accessories (Continued)

Accessory	Part Number	Description
2-slot Battery Charger	SAC-ET6X-2SCHG-01	Charges up to two standard or extended batteries. Requires power supply, DC line cord, and country-specific AC line cord.

Charging Indicators

Charge the battery before using the device.

Table 5 Charging Indicators

LED	Indication
Off	Power is not supplied to the device.
Solid orange	The device is charging.
Solid red	The device is charging, but the battery is at the end of its useful life.
Solid green	The device is fully charged.
Solid Blue	A Battery-free tablet is connected to external power.

Charging Temperature

Charge batteries in ambient temperatures.

Charge batteries in temperatures from 0°C to 40°C (32°F to 104°F). The device always performs battery charging in a safe and intelligent manner. At higher temperatures (e.g. approximately +37°C (+98°F)), the device may, for small periods of time, alternately enable and disable battery charging to keep the battery at acceptable temperatures. The device indicates when charging is disabled due to abnormal temperatures via its LED.

Spare Battery Charging

The Spare Battery Charging LED on the cup indicates the status of the spare battery charging. The standard battery charges from 4% to 80% in 2.5 hours. The extended battery charges from 4% to 80% in 5.5 hours.

To achieve optimal fast charging results, use only Zebra charging accessories and batteries.

Table 6 Spare Battery LED Charging Indicators

Indication	Description
Solid Amber	The spare battery is charging.
Solid Green	The spare battery charging is complete.
Solid Red	The spare battery is charging, and the battery is at the end of its useful life. Charging is complete, and the battery is at the end of its useful life.

Table 6 Spare Battery LED Charging Indicators (Continued)


Indication	Description
Fast Blinking Red (2 blinks/second)	Error in charging; check the placement of the spare battery and battery at the end of its useful life.
Off	No spare battery in the slot. The spare battery is not placed in the slot correctly. The charger is not powered.

USB-C to AC Adapter

The USB-C to AC Adapter provides power to the tablet.




NOTE: Ensure that you follow the guidelines for battery safety described in the ET6x Product Reference Guide.



2-Slot Battery Charger

Use the 2-slot Battery Charger to charge up to two standard or extended batteries.

Figure 7 2-Slot Battery Charger



1	Battery Charge LED
2	Battery slot
3	Power LED
4	USB-C port

The USB-C port is a service connector only for firmware upgrades and is not intended for power charging.

See [Spare Battery Charging](#) on page 12 for more information.

Using the Camera


Use the front or rear camera to take a photo or record a video.



NOTE: If using the front camera, move the front camera privacy switch to the open position.

To take a photo or record a video:

1. Open the Camera application.
2. Point the rear camera at an object.
3. Touch the on-screen shutter button to take a photo or record a video.



Reading NFC Cards

The tablet supports reading NFC cards. The NFC antenna is located on the back of the tablet under the NFC logo.

With an NFC-enabled application open, bring the NFC card toward the antenna. Depending upon the application, an audio or visual indication indicates a successful reading of the card.

Scanning with the Internal Scanner

Use the internal imager to capture barcode data.

1. Ensure that an app is open on the device and a text field is in focus (text cursor in the text field).
2. Point the exit window of the device at a barcode.
3. Press and hold the scan button.

The aiming dot with illumination turns on to assist in aiming.

4. Ensure the barcode is within the area formed by the aiming pattern. The aiming dot is used for increased visibility in bright lighting conditions.

A beep sounds, by default, to indicate the barcode was decoded successfully.

5. The captured data appears in the text field.
- 6.


Scanning with Camera

Use the camera to capture barcode data.



NOTE: To read a barcode, a scan-enabled app is required. The device contains the DataWedge app that allows the user to enable the scanner to decode barcode data and display the barcode content.

1. Ensure that an app is open on the device, and a text field is in focus (text cursor in the text field).
2. Point the camera window at a barcode.
3. Press and hold the scan button. By default, a preview window appears on the screen.



4. Move the device until the barcode is visible on the screen.
5. A beep sounds, by default, to indicate the barcode is decoded successfully.
6. The captured data appears in the text field.

DRAFT