**Z-Wave Specifications** 

Z-Wave SW Serial API Z-Wave Protocol Release 4.25

Basic Device Class Portable Controller

RF Data Rate 9.6kbps / 40kbps

RF Frequency EU 9.6kbps: 868.42 MHz

40kbps: 868.40 MHz

US 9.6kbps: 908.42 MHz

40kbps: 908.40 MHz

AU 9.6kbps: 921.42 MHz

40kbps: 921.40 MHz

Modulation Frequency Shift Key

ing (FSK)

Frequency deviation Center frequency

± 20kHz

Signal coding 9.6kbps: Manchester

Encoded 40kbps: NRZ

RF filter SAW Filter

US: Center frequency = 908.0 MHz, BW = 20MHz EU: Center frequency = 868.0 MHz, BW = 20MHz AU: Center frequency = 923.5 MHz, BW = 9MHz

**Electrical Specifications** 

USB Voltage -0.3 to 5.5V

**Physical Specifications** 

Operating Temperature 0° to 50°C
Storage Temperature -40°C to +85°C
Humidity 5 to 90% N/C
Dimensions 82mm (L)

25.2mm (W) 10.5 mm (H)

Colour Glossy White

Shipping Weight TBA

**Regulatory Approvals** 

Conformity to product standards for safety + EMC:

US: FCC Part 15

EU: R&TTE Directive 1999/5/EC, EN 300 220-

3/2000

ANZ: AS/ANZ 4268+A1+A2

**Declaration of conformity** 

CE (EU)

2002/95/EG (RoHs) 2002/96/EC (WEEE) 1999/5/EC (RTTE)

C-Tick

**Z-Wave Certified** 

**Test Reports** 

All test reports and approval certificates are available from Empower Controls on request. All test reports and approval certificates are made in the name of

Empower Controls Limited.

**Ordering Information** 

300ZWUS-W USB Interface, Z-Wave, US frequency 300ZWEU-W USB Interface, Z-Wave, EU frequency 300ZWAU-W USB Interface, Z-Wave, AU frequency



Copyright © 2008 Empower Controls Ltd. All rights reserved. The information in this document is subject to change without notice. Empower Controls Ltd assumes no responsibility for any errors that may appear in this document. Specific product names may be trademarks or registered trademarks and are the property of their respective companies.

**Empower Controls Ltd** (1182350)

Hong Kong: Unit F 28/F Tower 1, 2 Kwun Tsing Road, Tuen Mun New Territories, Hong Kong SAR. Tel +852 630 85726 Malaysia: F-3-2 Palmyra Bangsar, 9 Jalan Medang Tanduk, Bukit Bandaraya, 59100, Kuala Lumpur. Tel +6012 383 3070

www.empower-controls.com