

## Wireless finger optics mouse specification explanation

1, Resolution:	1000DPI
2, Wireless frequency:	2.4G MHz
3. Working distance:	15 meter
4, Build-in lithium battery:	3.7V 230mA
5, Charging Times:	2 hours
6, Continue Using Time:	14 hours
7, Standby time:	170days
8, Dimension:	60*40*38mm(Genius mouse) 72*17*8mm(receiver)
9, Net weight :	30g(Genius mouse) 18g(receiver)
10, interface:	USB 1.0 OR2.0
11, Operating System:	WINDOWS95/98/2000/XP/NT/VISTA

### Features :

**Healthful**--- Ergonomical design - restores natural movement to your forearm and wrist to reduce the repetitive strain injuries effectively

**Save effort**--- Small motion of the finger mouse within 5~8cm distance allows the cursor moves on full screen easily

**Convenient**--- Except reflective glass, it works on almost any surface such as wooden table, laptop itself, clothes and even your hands.

**Compact design** --- Stylish and space saving, easy carrying and operation. Multi-tasking function allows users to write or type when operating the USB Finger Mouse at the same time

**be handled easily** --- Multi-function: The finger mouse could be also as a wireless presenter for presentation, training, seminar etc.

**Economical** --- High quality internal lithium battery could be recharged for several hundred times, no extra battery cost required.

### Operating manual:

#### Start to use:

- 1, Insert the index finger into the suitable ring enclosed in the package, and adjust your finger position until you feel comfortable. Use your thumb to control the 'Right Button', 'Left Button' and 'Scroll Wheel'.
2. Press down the left and right key for 5 seconds to turn on the finger mouse.

3, Plug the receiver into the USB port of computer. Press the small button on the receiver, the LED indicator on receiver start flashing rapidly, then using the ball pen tip to press the synchronize button inside the small hole on finger mouse at same time, the LED on the receiver turns on without flashing, the sync is completed.

### **Stand by time:**

**1, Power Management Feature:** automatically shuts off unit if left idle for 5 minutes & press the left or right key for awaking the device.

**2, Power on & power off:** Press the left & right key for 5 seconds simultaneously to shut off the device. presses down the left & right key for five seconds to turn on the device.

### **Battery charging:**

1, Connect the finger mouse to the computer with USB cable for recharging the battery inside the finger mouse.

2, The wireless finger mouse can be used as a wired optical mouse while charging.

### **Package Contents::**

- 1, Wireless mouse x1
- 2, Index finger rings: 3pcs in different sizes
- 3, Receiver x1
- 4, USB cable x 1
- 5. Instruction sheet x1

### **FCC Statement**

1. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) This device must accept any interference received, including interference that may cause undesired operation.

2. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.